

ةدقعل نم ةديعل ةدقعل لوخد ليجست TL1 رماو لالخ نم ةيلحمل

تايوتحمل

ةمدقمل

[TL1 رماو لالخ نم ةيلحمل ةدقعل نم ةديعل ةدقعل لوخد ليجست](#)

ةمدقمل

ةدقعل نم اهيلي لوصول ةلباق ةديعل ةدقعل لوخد ليجست ةقيرط دننتمس م اذه فصي TL1 ةطساوب ةيلحمل.

لالخ نم ةيلحمل ةدقعل نم ةديعل ةدقعل لوخد ليجست TL1 رماو

ةدحو لمعت مل اذا، ةرواحمل لوصول ةلباق ةدقعل نم ةديعل ةدقعل لوخد ليجست نع ثحبل ي TL1 ةقيرط كيدل يقبت ي، Cisco (CTC) نم لقنل ي ف مكحتل.

يتل ةيلحمل ةدقعل نم ةديعل ةدقعل ل لوخدل ليجست ةيفي ةقيرطال هذه فرصت يه تاوطل او اهيلي لوخدل ليجست مت:

ةلباق ةديعل ةدقعل تنك اذا امم ققحت و ةدقعل ل لوخدل ليجست ب مق 1. ةوطخل اهيلي لوصول نكمي و (DCC/GCC/OSI). لاثم ل ليلبس يل، ةانق ي ربع اهيلي لوصول لاصلال رابتخا قيرط نع ةرشابم.

```
10.105.142.206 |
WARNING
This system is restricted to authorized users for business purposes. Unauthorized
access is a violation of the law. This service may be monitored for administrative
and security reasons. By proceeding, you consent to this monitoring.

ATTENTION!!!
This shell is intended for QUALIFIED PERSONNEL ONLY. Customer Use of
this shell is not recommended OR supported by the Technical Assistance
Center. Inappropriate use of shell Commands can have a Negative AND
Service Affecting impact on your network. Please consult the User
Documentation for appropriate troubleshooting procedures.

To exit without logging in, enter Control-D at the login prompt.
To exit after logging in, type "logout" at the prompt.

Login: CISCO15
Password:XXXXXX

To discontinue logging in, type control-d or wait 60 seconds.
After logging in, type 'enablec' to enable abort key (control-c).

-> enablec
value = 3 = 0x3
-> acNodes
===== AlrmC Nodes =====
ind Val NodeName IP Addr Cri Maj Min N-A N-R Vwire ProdField VirtWrProdNm VirtwireProdEnum MsgVer
0 Yes 206 10.105.142.206 3 0 2 8 1 xxxx ONS15454 1 400 local node
1 Yes wxc-207 10.105.142.207 0 1 5 6 0 xxxx ONS15454 1 400 remote nodes
2 Yes 197 10.105.142.197 3 2 10 10 5 xxxx ONS15454 1 400

-> acNodes
===== AlrmC Nodes =====
```

ind	Val	NodeName	IP Addr	Cri	Maj	Min	N-A	N-R	Vwire	ProdField	VirtWrProdNm
0	Yes	206	10.105.142.206	3	0	2	8	1	xxxx	ONS15454	1 400
1	Yes	WXC-207	10.105.142.207	0	1	5	6	0	xxxx	ONS15454	1 400
2	Yes	197	10.105.142.197	3	2	11	11	5	xxxx	ONS15454	1 400

ةؤغايصلل هذه مادختساب ةيحلحالم ةدقعلال في TL1 ربع لوخدلاليجستب مق 2. ةوطخلال

10.105.142.206 (1)

```
ACT-USER::CISCO15:123::*****;
```

```
206 2000-12-15 23:43:21
123 COMPLD
"CISCO15:2000-12-15 23-42-43,2000-12-15 23-15-04,0"
```

logged in local node

```
206 2000-12-15 23:43:21
A 0 REPT EVT SESSION
"206:NO,"
/* TL1 Agent Copyright (c) 1999-2007 Cisco Systems, Inc.
```

WARNING
This system is restricted to authorized users for business purposes. Unauthorized access is a violation of the law. This service may be monitored for administrative and security reasons. By proceeding, you consent to this monitoring.

User CISCO15 logged in from 64.103.228.115 */

```
;RTRV-ALM-ALL:::123;
```

```
206 2000-12-15 23:43:38
M 123 COMPLD
"SLOT-11,EQPT:MN,EQPT,NSA,12-04,03-26-24,NEND,NA:"Equipment Failure",TCC"
"LINEWL-17-4-RX-1530.33,OCH:CR,LOS-P,SA,12-09,02-55-16,NEND,NA:"Incoming Payload Signal Absent",40-SMR1-C
"LINEWL-17-4-RX-1531.90,OCH:CR,LOS-P,SA,12-09,02-57-20,NEND,NA:"Incoming Payload Signal Absent",40-SMR1-C
"LINE-17-5-TX,OTS:CR,OPWR-LFAIL,SA,12-09,02-55-19,NEND,NA:"Optical Power Failure Low",40-SMR1-C"
"LINE-17-1-TX,OTS:MN,APC-OUT-OF-RANGE,NSA,12-15,22-55-33,NEND,NA:"APC Cannot Set Value Due To Range Limits",40-SMR1-C"
```

ةؤغايصلل:

مءارءالءمدختسم:[:<TID>]:<uid>:<CTAG>::<pid>;

```
ACT-USER::CISCO15:123::*****;
```

```
206 2000-12-15 23:43:21
M 123 COMPLD
"CISCO15:2000-12-15 23-42-43,2000-12-15 23-15-04,0"
;
```

```
206 2000-12-15 23:43:21
A 0 REPT EVT SESSION
"206:NO,"
/* TL1 Agent Copyright (c) 1999-2007 Cisco Systems, Inc.
```

WARNING
This system is restricted to authorized users for business purposes. Unauthorized access is a violation of the law. This service may be monitored for administrative and security reasons. By proceeding, you consent to this monitoring.

User CISCO15 logged in from 64.103.228.115 */

```
;RTRV-ALM-ALL:::123;
```

```
206 2000-12-15 23:47:04
M 123 COMPLD
"SLOT-11,EQPT:MN,EQPT,NSA,12-04,03-26-24,NEND,NA:"Equipment Failure",TCC"
"LINEWL-17-4-RX-1530.33,OCH:CR,LOS-P,SA,12-09,02-55-16,NEND,NA:"Incoming Payload Signal Absent",40-SMR1-C"
```

```
"LINEWL-17-4-RX-1531.90,OCH:CR,LOS-P,SA,12-09,02-57-20,NEND,NA:\\"Incoming Payload Signal Absent\"," ,40-SMR1-C"
```

```
"LINE-17-5-TX,OTS:CR,OPWR-LFAIL,SA,12-09,02-55-19,NEND,NA:\\"Optical Power Failure Low\"," ,40-SMR1-C"
```

```
"LINE-17-1-TX,OTS:MN,APC-OUT-OF-RANGE,NSA,12-15,22-55-33,NEND,NA:\\"APC Cannot Set Value Due To Range Limits\"," ,40-SMR1-C"
```

ةدي عبل اة دق ع لل ACT-User لو خ د ليج س ت و TID ري ي غ ت ب مق ،ة غ ا ي ص ل ل ا ل خ ن م 3 ة و ط خ ل ل م سا ي ا ، TID ة م ي ق م ا د خ ت س ا ب ج ي ، ي ر خ ا ل ر م ا و ا ل ل ة ب س ن ل ا ب . ا ه ي ل ل ل و خ د ل ل ا ل ي ج س ت د ي ر ت ي ت ل ل ا ة د ي ع ب ل ا ة د ق ع ل ل .

```
> ACT-USER:WXC-207:CISCO15:123::*****; Change the TID value with the "node name".Here it is "WXC-207"
```

```
WXC-207 2004-06-03 18:50:20
123 COMPLD
"CISCO15:2004-06-03 18-23-24,2004-06-03 16-35-48,0"
logged in remote node "WXC-207" from node "206"
```

```
WXC-207 2004-06-03 18:50:20
A 0 REPT EVT SESSION
"WXC-207:NO,"
/* TL1 Agent Copyright (c) 1999-2007 Cisco Systems, Inc.
```

```
WARNING
This system is restricted to authorized users for business purposes. Unauthorized
access is a violation of the law. This service may be monitored for administrative
and security reasons. By proceeding, you consent to this monitoring.
```

```
User CISCO15 logged in from 10.105.142.206 */ confirmation message for login from remote node
```

```
;RTRV-ALM-ALL:123;
206 2000-12-15 23:47:04
M 123 COMPLD
"SLOT-11,EQPT:MN,EQPT,NSA,12-04,03-26-24,NEND,NA:\\"Equipment Failure\","TCC"
"LINEWL-17-4-RX-1530.33,OCH:CR,LOS-P,SA,12-09,02-55-16,NEND,NA:\\"Incoming Payload Signal Absent\"," ,40-SMR1-C
"LINEWL-17-4-RX-1531.90,OCH:CR,LOS-P,SA,12-09,02-57-20,NEND,NA:\\"Incoming Payload Signal Absent\"," ,40-SMR1-C
"LINE-17-5-TX,OTS:CR,OPWR-LFAIL,SA,12-09,02-55-19,NEND,NA:\\"Optical Power Failure Low\"," ,40-SMR1-C
"LINE-17-1-TX,OTS:MN,APC-OUT-OF-RANGE,NSA,12-15,22-55-33,NEND,NA:\\"APC Cannot Set Value Due To Range Limits
\"," ,40-SMR1-C"
```

```
> RTRV-ALM-ALL:WXC-207::123; Insert correct TID value to query for particular node
```

```
WXC-207 2004-06-03 18:50:54
M 123 COMPLD
"SLOT-11,EQPT:MN,PROTNA,NSA,05-21,21-55-10,NEND,NA:\\"Protection Unit Not Available\","TCC"
"BITS-1,BITS:MN,LOS,NSA,05-21,21-55-25,NEND,RCV:\\"Loss Of Signal\",""
"BITS-2,BITS:MN,LOS,NSA,05-21,21-55-25,NEND,RCV:\\"Loss Of Signal\",""
"SYNC-NE,SYNCR:MJ,SYNCPRI,SA,05-21,21-55-25,NEND,NA:\\"Primary Synchronization Reference Failure\",""
"SYNC-NE,SYNCR:MN,SYNCRSEC,NSA,05-21,21-55-25,NEND,NA:\\"Secondary Synchronization Reference Failure\",""
"PWR-A,EQPT:MN,BAT-FAIL,NSA,05-21,21-55-18,NEND,NA:\\"Battery Failure\",""
;
```

```
> ACT-USER:WXC-207:CISCO15:123::*****;
```

```
WXC-207 2004-06-03 18:50:20
M 123 COMPLD
"CISCO15:2004-06-03 18-23-24,2004-06-03 16-35-48,0"
;
```

```
WXC-207 2004-06-03 18:50:20
A 0 REPT EVT SESSION
"WXC-207:NO,"
/* TL1 Agent Copyright (c) 1999-2007 Cisco Systems, Inc.
```

```
WARNING
This system is restricted to authorized users for business purposes. Unauthorized
access is a violation of the law. This service may be monitored for administrative
and security reasons. By proceeding, you consent to this monitoring.
```

```
User CISCO15 logged in from 10.105.142.206 */
```

ل ع ة د ق ع ل ل م سا ي ا ، ة ل ص ل ل ا ت ا ذ TID م ي ق ل ا خ د ا ك م ز ل ي ، ل ا ث م ل ا ي ف ح ض و م و ه ا م ك ي ر خ ا ل ر م ا و ا ل ل ا ة ي ة WXC-207:

```
> RTRV-ALM-ALL:WXC-207::123;
```

WXC-207 2004-06-03 18:50:54

M 123 COMPLD

"SLOT-11,EQPT:MN,PROTNA,NSA,05-21,21-55-10,NEND,NA:\\"Protection Unit Not Available\\",TCC"

"BITS-1,BITS:MN,LOS,NSA,05-21,21-55-25,NEND,RCV:\\"Loss Of Signal\\","

"BITS-2,BITS:MN,LOS,NSA,05-21,21-55-25,NEND,RCV:\\"Loss Of Signal\\","

"SYNC-NE,SYNCN:MJ,SYNCPRI,SA,05-21,21-55-25,NEND,NA:\\"Primary Synchronization Reference Failure\\","

"SYNC-NE,SYNCN:MN,SYNCSEC,NSA,05-21,21-55-25,NEND,NA:\\"Secondary Synchronization Reference Failure\\","

"PWR-A,EQPT:MN,BAT-FAIL,NSA,05-21,21-55-18,NEND,NA:\\"Battery Failure\\","

;

ةلصتم ىرخأ ةدقع ىف لىقننلا كىنكى ةديعبلا ةدقعلال لىل كىل وخذ لىجست ةلأح ىف ىتح
ةىللحملا دقعلال TID لثم اغراف هئاقبإو ةديعبلا طاقنلل TID رىغىو

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل