



Network Element Defaults for Release 9.3

Last Updated: May 25, 2011, OL-25208-01



Note

The terms “Unidirectional Path Switched Ring” and “UPSR” may appear in Cisco literature. These terms do not refer to using Cisco ONS 15xxx products in a unidirectional path switched ring configuration. Rather, these terms, as well as “Path Protected Mesh Network” and “PPMN”, refer generally to Cisco's path protection feature, which may be used in any topological network configuration. Cisco does not recommend using its path protection feature in any particular topological network configuration.

This document describes the factory-configured (default) network element (NE) settings for the Cisco ONS 15454, Cisco ONS 15454 M2, and Cisco ONS 15454 M6 platforms. It includes descriptions of card, node, and Cisco Transport Controller (CTC) default settings. To import, export, or edit the settings, see the chapter “Maintain the Node” in the *Cisco ONS 15454 DWDM Configuration Guide*. Cards supported by this platform that are not listed in this document are not supported by user-configurable NE defaults settings.



Note

Unless otherwise specified, in this document “ONS 15454” refers to both ANSI (ONS 15454 SONET) and ETSI (ONS 15454 SDH) shelf assemblies.

Network Element Defaults Description

The NE defaults are preinstalled on each Cisco ONS 15454 TCC2 and TCC2P, TCC3, TNC and TSC cards. Cisco also ships a file named 15454-defaults.txt (ANSI shelves) or 15454SDH-defaults.txt (ETSI shelves) on the CTC software CD in case you want to import the defaults onto existing TCC2/TCC2P/TCC3/TNC/TSC cards. The NE defaults include card-level, CTC, and node-level defaults.



Note

The TCC2/TCC2P/TCC3 cards are supported only on the Cisco ONS 15454 platform. The TNC/TSC cards are supported on the Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Manual card provisioning overrides default settings. Manual changes are those made using procedures in the chapters “Provision Transponder and Muxponder Cards” and “Change DWDM Card Settings” in the *Cisco ONS 15454 DWDM Configuration Guide*. If you use the CTC Defaults editor (on the node view Provisioning > Defaults tabs) or import a new defaults file, any changes to card or port settings that result only affect cards that are installed or preprovisioned after the defaults have changed.

Changes made manually to most node-level default settings override the current settings, whether default or provisioned. If you change node-level default settings, either by using the Defaults editor or by importing a new defaults file, the new defaults reprovision the node immediately for all settings except those relating to protection (1+1 bidirectional switching, 1+1 reversion time, 1+1 revertive, Bidirectional Line Switched Ring [BLSR] or multiplex section-shared protection ring [MS-SPRing] reversion time, BLSR/MS-SPRing ring revertive, BLSR/MS-SPRing span reversion time, BLSR/MS-SPRing span revertive, y cable revertive or reversion time, splitter revertive or reversion time). Settings relating to protection apply to subsequent provisioning.



Note

Changing some node-level provisioning through NE defaults can cause CTC disconnection or a reboot of the node in order for the provisioning to take effect. Before you change a default, check in the Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) and be prepared for the occurrence of any side effects listed for that default.

ANSI Platform Defaults

The following sections give the NE defaults for the ONS 15454 ANSI platform. To see defaults for the ONS 15454 ETSI platform, see the “[ETSI Platform Defaults](#)” section on page 612.

ANSI Card Defaults

The tables in this section list the default settings for each DWDM, Transponder (TXP), Muxponder (MXP), or Ethernet card. Cisco provides several types of user-configurable defaults for Cisco ONS 15454 DWDM, TXP, MXP, and Ethernet cards. Types of card defaults can be broadly grouped by function, as outlined in the following subsections. For information about individual card settings, see the chapters “Provision Transponder and Muxponder Cards” and “Change DWDM Card Settings” in the *Cisco ONS 15454 DWDM Configuration Guide*.



Note

When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.



Note

The tables in this section list the default settings for each DWDM, TXP, and MXP card. For all other cards, including electrical, optical, Ethernet, and Fibre Channel, see the *Cisco ONS 15454 Reference Manual* or the *Cisco ONS 15454 SDH Reference Manual*.

The following types of defaults are defined for DWDM, TXP, MXP, and Ethernet cards.

ANSI Configuration Defaults

Most card-level and port-level configuration defaults correspond to settings found in the CTC card-level Provisioning tabs.


Note

The full set of Automatic Laser Shutdown (ALS) configuration defaults can be found in the CTC card-level Maintenance > ALS tab for supported cards. ALS defaults are supported for OSCM, OSC-CSM, OPT-BST, OPT-BST-L, ADM-10G, GE_XP, 10GE_XP, TXP, MXP, OTU2-XP, and PSM cards. For information on how ALS card settings achieve network level optical safety, see the chapters “Setup Optical Service Channel Cards”, “Optical Amplifier Cards”, or “Provision Transponder and Muxponder Cards” in the *Cisco ONS 15454 DWDM Configuration Guide*.

Configuration defaults that are reachable from the CTC card-level Provisioning tabs (except as noted) include the following types of options (arranged by CTC subtab):

- Line—(ADM-10G, GE_XP, 10GE_XP, TXP and MXP cards) Line-level configuration settings, including SONET, Wavelength Trunk, Trunk, Client, Distance Extension, and Enhanced FC/FICON ISL settings.


Note

Some line configuration tabs, including Client, Distance Extension, and Enhanced FC/FICON ISL settings tabs, only appear in the card-level Provisioning > Line tab after a pluggable port module (PPM) is provisioned to a fibre channel payload type (port rate) for the particular card.

- OTN—(ADM-10G, GE_XP, 10GE_XP, MXP-2.5G-10E, MXP-2_5G-10G, MXP-MR-10DME, TXP-MR-10E, TXP-MR-10G, TXP-MR-2.5G, and TXPP-MR-2.5G cards) Optical transport network (OTN) line configuration settings.
- Card—(See listed settings for applicable cards)
 - Card mode—MXPP-MR-2.5G and MXP-MR-2.5G (ESCON, FC_GE, or MIXED), GE_XP (20GE MXP, 10GE MXP, or L2 over DWDM) , and 10GE_XP (10GE TXP or L2 over DWDM)
 - Port range-level mode settings—MXP-MR-10DME cards only
 - Termination mode—TXP-MR-10E, MXP-2.5G-10E, MXP-2.5G-10G, TXPP_MR_2.5G, TXP_MR_10G, and TXP_MR_2.5G cards
 - AIS squelch settings—TXP-MR-10E and MXP-2.5G-10E cards
- ALS (card-level Maintenance > ALS tab)—(OSC-CSM, OSCM, OPT-BST, OPT-BST-L, ADM-10G, GE_XP, 10GE_XP, TXP, MXP, and PSM cards) ALS configuration defaults.


Note

For further information about supported features on each card, see the chapters “Setup Optical Service Channel Cards”, “Optical Amplifier Cards”, or “Provision Transponder and Muxponder Cards” in the *Cisco ONS 15454 DWDM Configuration Guide*.

ANSI Threshold Defaults

Threshold default settings define the default cumulative values (thresholds) beyond which a threshold crossing alert (TCA) will be raised, making it possible to monitor the network and detect errors early.

Card threshold default settings are provided as follows:

- PM thresholds—(OSCM, OSC-CSM, OTU2-XP, TXP, and MXP cards) Expressed in counts or seconds; includes line and SONET thresholds.
- Optical thresholds—(ADM-10G, GE_XP, 10GE_XP, OTU2-XP, TXP, and MXP cards) Expressed in percentages or dBm; includes client and trunk optical thresholds.
- OTN FEC thresholds (ADM-10G, GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts; includes enhanced, standard, 1G Ethernet, 1G Fibre channel, 1G FICON, OC-3, OC-12, OC-48, 2G FICON, and 2G Fibre channel thresholds.
- OTN G.709 thresholds (ADM-10G, GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts or seconds; includes ITU-T G.709 PM and SM thresholds.

Threshold defaults are defined for near end and/or far end, at 15-minute and one-day intervals.

Thresholds are further broken down by type, such as Multiplex Section, Regeneration Section, VC LO, MS, RS, or Path, for performance monitoring (PM) thresholds, and TCA (warning) or Alarm for physical thresholds. PM threshold types define the layer to which the threshold applies. Physical threshold types define the level of response expected when the threshold is crossed.



Note For full descriptions of the thresholds you can set for each card, see “[Monitor Performance](#)”.



Note When LOS, LOS-P, or LOF alarms occur on transponder and muxponder trunks, ITU-T G.709 SONET/SDH TCAs are suppressed. For details, see “[Alarm and TCA Monitoring and Management](#)”.



Note For additional information regarding PM parameter threshold defaults as defined by Telcordia specifications, refer to Telcordia GR-820-CORE and GR-253-CORE.

ANSI Defaults by Card

In the tables that follow, card defaults are defined by the default name, its factory-configured value, and the domain of allowable values that you can assign to it.



Note When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.



Note Some default values, such as certain thresholds, are interdependent. Before changing a value, review the domain for that default and any other related defaults for potential dependencies.

ANSI ADM-10G Card Default Settings

[Table 1](#) lists the ADM-10G card default settings.



Note ADM-10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 1 ANSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.config.interlink.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.interlink.ppmPortAssignment	UNASSIGNED	UNASSIGNED; Internal Link
ADM-10G.config.oc12.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc12.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.oc12.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc12.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc12.line.PJStsMon#	0 (STS #)	0 - 12
ADM-10G.config.oc12.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc12.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc12.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc12.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc12.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.oc3.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc3.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.oc3.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc3.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc3.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc3.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc3.line.PJStsMon#	0 (STS #)	0 - 3
ADM-10G.config.oc3.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc3.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc3.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.oc48.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc48.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.oc48.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc48.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc48.line.PJStsMon#	0 (STS #)	0 - 48
ADM-10G.config.oc48.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc48.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc48.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc48.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc48.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.ppmSlotAssignment	UNASSIGN ED	UNASSIGNED; PPM (1 Port)
ADM-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
ADM-10G.config.trunk.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.trunk.PJStsMon#	0 (STS #)	0 - 192
ADM-10G.config.trunk.ppmPortAssignment	OC192	UNASSIGNED; OC192
ADM-10G.etherPortConfig.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.etherPortConfig.AutoNegotiation	1000 Mbps	Auto; 1000 Mbps
ADM-10G.etherPortConfig.MTU	Jumbo	1548; Jumbo
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
ADM-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
ADM-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.CV	75 (B3 count)	0 - 2160000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.SES	3 (seconds)	0 - 900

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJCPGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJCPDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700
ADM-10G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
ADM-10G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
ADM-10G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc3.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
ADM-10G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc3.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
ADM-10G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
ADM-10G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.ES	200 (seconds)	0 - 86400

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts1.farend.1day.ES	100 (seconds)	0 - 86400

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
ADM-10G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
ADM-10G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
ADM-10G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc48.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc48.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
ADM-10G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc48.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc48.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
ADM-10G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
ADM-10G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJCPGEN	5760 (count)	0 - 691200000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJCPGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJCPDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJCPGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJCPDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.CV	75 (B3 count)	0 - 2160000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJCPDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.SES	3 (seconds)	0 - 900

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
ADM-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
ADM-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
ADM-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.trunk.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
ADM-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.trunk.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
ADM-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
ADM-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.PPJCPGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.PPJCPDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.PPJCPGEN	60 (count)	0 - 7200000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.CV	750 (B3 count)	0 - 207360000

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.FC	40 (count)	0 - 6912

Table 1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000

ANSI 40G-MXP-C Card Default Settings

Table 2 lists the 40G-MXP-C card default settings.

**Note**

40G-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.client.AisSquelchMode	Squelch	Ais; Squelch
40G-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC192; Transparent when ppmPortAssignment UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40G-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40G-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40G-MXP-C.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
40G-MXP-C.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
40G-MXP-C.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
40G-MXP-C.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
40G-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-MXP-C.config.wis.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.wis.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40k.m.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40k.m.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40k.m.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alafrm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alafrm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alafrm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alafrm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alafrm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1d ay.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.ala rm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.ala rm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.ala rm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.ala rm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.ala rm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15 min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15 min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15 min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15 min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15 min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1da y.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1da y.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1da y.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1da y.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1da y.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alar m.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alar m.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alar m.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alar m.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alar m.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1d ay .HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1d ay .HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1d ay .HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1d ay .LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1d ay .LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.ala rm .HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.ala rm .HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.ala rm .HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.ala rm .LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.ala rm .LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 5min .HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 5min .HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 5min .HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 5min .LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 5min .LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1 day .HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.al.arm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.al.arm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.al.arm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15.min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15.min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15.min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15.min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15.min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1d/ay.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1d/ay.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1d/ay.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1d/ay.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1d/ay.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.al/arm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.al/arm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.al/arm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.al/arm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.al/arm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15/min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15/min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighRxPower	2.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowTxPower	-10.7 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.ir.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.ir.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.ir.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.ir.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.oc192.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.oc192.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.oc192.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe c.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfe.c.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.pmthresholds.client.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-MXP-C.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-MXP-C.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.15min.CV	75 (B3 count)	0 - 2160000

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.sts192c.nearend.15min.ES	60 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.sts192c.nearend.15min.SES	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.15min.UAS	10 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.1day.CV	750 (B3 count)	0 - 207360000
40G-MXP-C.pmthresholds.sts192c.nearend.1day.ES	600 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.sts192c.nearend.1day.SES	7 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.wis.line.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.wis.line.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.line.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.wis.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.wis.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.wis.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.wis.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-MXP-C.pmthresholds.wis.section.nearend.15min.ES	500 (seconds)	0 - 900
	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-MXP-C.pmthresholds.wis.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI 40G-TXP-C Card Default Settings

Table 4 lists the 40G-TXP-C card default settings.

**Note**

40G-TXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.config.client.AisSquelchMode	Squelch	Ais; Squelch
40G-TXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-TXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-TXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-TXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-TXP-C.config.client.TerminationMode	Transparent	Transparent; Section; Line when mrPortAssignment UNASSIGNED; OC768; Transparent when mrPortAssignment UNASSIGNED; OC768; 40G Ethernet LAN Phy; OTU3
40G-TXP-C.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED; OC768; 40G Ethernet LAN Phy; OTU3
40G-TXP-C.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
40G-TXP-C.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
40G-TXP-C.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
40G-TXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-TXP-C.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.oc768.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.oc768.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.oc768.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.oc768.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-TXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-TXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-TXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-TXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-TXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-TXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-TXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-TXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-TXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-TXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-TXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.pmthresholds.client.line.farend.15min.CV	340160 (B2 count)	0 - 8850600
40G-TXP-C.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.farend.1day.CV	3401600 (B2 count)	0 - 849657600
40G-TXP-C.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.line.nearend.15min.CV	340160 (B2 count)	0 - 8850600
40G-TXP-C.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
40G-TXP-C.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.line.nearend.1day.CV	3401600 (B2 count)	0 - 849657600
40G-TXP-C.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-TXP-C.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-TXP-C.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.farend.15min.CV	340160 (B2 count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.line.farend.1day.CV	3401600 (B2 count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.nearend.15min.CV	340160 (B2 count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
40G-TXP-C.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900

Table 3 ANSI 40G-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-TXP-C.pmthresholds.trunk.line.nearend.1day.CV	3401600 (B2 count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-TXP-C.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-TXP-C.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI 40E-MXP-C Card Default Settings

Table 4 lists the 40E-MXP-C card default settings.



Note 40E-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40E-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40E-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40E-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC192; Transparent when ppmPortAssignment UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40E-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40E-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40E-MXP-C.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
40E-MXP-C.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
40E-MXP-C.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
40E-MXP-C.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
40E-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40E-MXP-C.config.wis.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.config.wis.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighLas erBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighLa serBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighLas erBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighRxPower	2.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowTxPower	-10.7 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.ir.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.ir.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.ir.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.ir.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192 lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192 lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192 lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192 lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192 lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192 lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192 lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192 mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.oc192.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.oc192.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.oc192.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15m.in.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15m.in.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15m.in.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15m.in.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15m.in.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarms.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarms.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarms.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarms.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarms.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarms.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarms.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarms.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarms.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.otn.fe thresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-MXP-C.otn.fe thresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-MXP-C.otn.fe thresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-MXP-C.otn.fe thresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-MXP-C.otn.fe thresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40E-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40E-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40E-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.pmthresholds.client.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40E-MXP-C.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.farend.1day.CV	850400 (B2 count)	0 - 849657600

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40E-MXP-C.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40E-MXP-C.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40E-MXP-C.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40E-MXP-C.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.sts192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
40E-MXP-C.pmthresholds.sts192c.nearend.15min.ES	60 (seconds)	0 - 900
40E-MXP-C.pmthresholds.sts192c.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.pmthresholds.sts192c.nearend.15min.SES	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.sts192c.nearend.15min.UAS	10 (seconds)	0 - 900

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.sts192c.nearend.1day.CV	750 (B3 count)	0 - 207360000
40E-MXP-C.pmthresholds.sts192c.nearend.1day.ES	600 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.sts192c.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.pmthresholds.sts192c.nearend.1day.SES	7 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.sts192c.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40E-MXP-C.pmthresholds.wis.line.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.pmthresholds.wis.line.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.farend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
40E-MXP-C.pmthresholds.wis.line.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.pmthresholds.wis.line.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.farend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40E-MXP-C.pmthresholds.wis.line.nearend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.pmthresholds.wis.line.nearend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40E-MXP-C.pmthresholds.wis.line.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.pmthresholds.wis.line.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40E-MXP-C.pmthresholds.wis.section.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.section.nearend.15min.SEFS	500 (seconds)	0 - 900

Table 4 ANSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.wis.section.nearend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40E-MXP-C.pmthresholds.wis.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI 40E-TXP-C Card Default Settings

Table 5 lists the 40E-TXP-C card default settings.



Note 40E-TXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-TXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40E-TXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40E-TXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40E-TXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40E-TXP-C.config.client.TerminationMode	Transparent	Transparent; Section; Line when mrPortAssignment UNASSIGNED; OC768; Transparent when mrPortAssignment UNASSIGNED; OC768; 40G Ethernet LAN Phy; OTU3

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED; OC768; 40G Ethernet LAN Phy; OTU3
40E-TXP-C.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
40E-TXP-C.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
40E-TXP-C.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
40E-TXP-C.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
40E-TXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-TXP-C.config.trunk.Overclock	OFF	OFF; ON
40E-TXP-C.config.trunk.SDBER(only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.config.trunk.SFBER(only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	1.00E-04	1E-3; 1E-4; 1E-5
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.oc768.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.oc768.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-TXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-TXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-TXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-TXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-TXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-TXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-TXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-TXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.BBE	100000 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40E-TXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40E-TXP-C.otn.otnLines.G709OTN	Enable	Enable
40E-TXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.pmthresholds.client.line.farend.15min.CV	340160 (B2 count)	0 - 8850600
40E-TXP-C.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.line.farend.1day.CV	3401600 (B2 count)	0 - 849657600
40E-TXP-C.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.line.nearend.15min.CV	340160 (B2 count)	0 - 8850600
40E-TXP-C.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.pmthresholds.client.line.nearend.1day.CV	3401600 (B2 count)	0 - 849657600
40E-TXP-C.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40E-TXP-C.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40E-TXP-C.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.farend.15min.CV	340160 (B2 count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.farend.1day.CV	3401600 (B2 count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.nearend.15min.CV	340160 (B2 count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.line.nearend.1day.CV	3401600 (B2 count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912

Table 5 ANSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40E-TXP-C.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40E-TXP-C.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Table 6 lists the 40-WXC-C, 40-WSS-C, and 80-WXC-C card default settings.



Note 40-WXC-C, 40-WSS-C, and 80-WXC-C cards are supported on the Cisco ONS 15454 and Cisco ONS 15454 M6 platforms.

Table 6 ANSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Default Name	Default Value	Default Domain
WXC-80.config.card.WavelengthDrift	Enable	Disable; Enable
WXC-40.config.card.WavelengthDrift	Enable	Disable; Enable
WSS-40.config.card.WavelengthDrift	Enable	Disable; Enable

ANSI MXP_2.5G_10E Card Default Settings

Table 7 lists the MXP_2.5G_10E card default settings.



Note MXP_2.5G_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 7 ANSI MXP_2.5G_10E Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
MXP-2_5G-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-2_5G-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-2_5G-10E.config.client.TerminationMode	Transparent	Transparent; Section
MXP-2_5G-10E.config.client.ppmPortAssignment	OC48	UNASSIGNED; OC48
MXP-2_5G-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-2_5G-10E.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10E.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10E.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10E.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.15min.HighRxPower	-9 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.15min.HighTxPower	9 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.1day.HighRxPower	-9 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.1day.HighTxPower	9 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.alarm.HighRxPower	-6.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.alarm.LowTxPower	-4.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lrl.2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.otnLines.AsyncSynchMapping	ODU Multiplex	ODU Multiplex
MXP-2_5G-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced
MXP-2_5G-10E.otn.otnLines.G709OTN	Enable	Enable
MXP-2_5G-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400

Table 7 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI MXP_2.5G_10G Card Default Settings

Table 8 lists the MXP_2.5G_10G card default settings.



Note MXP_2.5G_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 8 ANSI MXP_2.5G_10G Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-2_5G-10G.config.client.TerminationMode	Transparent	Transparent; Line
MXP-2_5G-10G.config.client.ppmPortAssignment	OC48	UNASSIGNED; OC48
MXP-2_5G-10G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-2_5G-10G.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10G.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10G.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10G.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
MXP-2_5G-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
MXP-2_5G-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 8 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI MXP_MR_2.5G Card Default Settings

[Table 9](#) lists the MXP_MR_2.5G card default settings.



Note MXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 9 ANSI MXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.card.Mode	FC_GE	FC_GE; MIXED; ESCON
MXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE_GE; FC1G ISL; FC2G ISL; FICON1G ISL; FICON2G ISL when // .card.Mode FC_GE; UNASSIGNED; ONE_GE; ESCON; FC1G ISL; FICON1G ISL when // .card.Mode MIXED; UNASSIGNED; ESCON when // .card.Mode ESCON
MXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16; 32; 48 .. 1200
MXP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148; 2152; 2156; 2160; 2164; 2168; 2172
MXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.trunk.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-MR-2_5G.config.trunk.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-2_5G.config.trunk.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-MR-2_5G.config.trunk.sonet.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900

Table 9 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI MXPP_MR_2.5G Card Default Settings

Table 10 lists the MXPP_MR_2.5G card default settings.



Note MXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 10 ANSI MXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.card.Mode	FC_GE	FC_GE; MIXED; ESCON
MXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE_GE; FC1G ISL; FC2G ISL; FICON1G ISL; FICON2G ISL when //card.Mode FC_GE; UNASSIGNED; ONE_GE; ESCON; FC1G ISL; FICON1G ISL when //card.Mode MIXED; UNASSIGNED; ESCON when //card.Mode ESCON
MXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXPP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXPP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16; 32; 48 .. 1200
MXPP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148; 2152; 2156; 2160; 2164; 2168; 2172
MXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXPP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400

Table 10 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Table 11 lists the MXP_MR_10DME_C and MXP_MR_10DME_L card default settings.



Note MXP_MR_10DME_C and MXP_MR_10DME_L cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.card.Mode	Port 1-8: FC_GE_ISC	Port 1-8: FC_GE_ISC; Port 1-4: FC_GE_ISC; Port 5-8: FC4G; Port 1-4: FC4G; Port 5-8: FC_GE_ISC; Port 1-8: FC4G
MXP-MR-10DME.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-MR-10DME.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-MR-10DME.config.client.ppmPortAssignment	UNASSIGN ED	UNASSIGNED; ONE-GE; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC3 PEER 1G; ISC3 PEER 2G when //.card.Mode Port 1-8: FC_GE_ISC; UNASSIGNED; FC4G_PORT when //.card.Mode Port 1-8: FC4G; UNASSIGNED; ONE-GE; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; FC4G; ISC3 PEER 1G; ISC3 PEER 2G when //.card.Mode Port 1-4: FC_GE_ISC; Port 5-8: FC4G; Port 1-4: FC4G; Port 5-8: FC_GE_ISC

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-MR-10DME.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXP-MR-10DME.config.fc.distanceExtension.Fastswitch	FALSE	TRUE; FALSE
MXP-MR-10DME.config.trunk.AINSSoakTime	08:00 (hours:mins) .. 48:00	00:00; 00:15; 00:30 .. 48:00
MXP-MR-10DME.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-MR-10DME.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-10DME.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-MR-10DME.config.trunk.SendDoNotUse	FALSE	FALSE; TRUE
MXP-MR-10DME.config.trunk.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.otnLines.AsyncSynchMapping	Synch Mapping	Synch Mapping
MXP-MR-10DME.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-MR-10DME.otn.otnLines.G709OTN	Enable	Disable; Enable
MXP-MR-10DME.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72

Table 11 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI SMR Card Default Settings

Table 12 lists the SMR card default settings.



Note 40-SMR1-C and 40-SMR2-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

ANSI TNC Card Default Settings**Table 12 ANSI SMR Card Default Settings**

Default Name	Default Value	Default Domain
SMR1-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR1-40.config.card.WavelengthDrift	Disable	Disable; Enable
SMR2-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR2-40.config.card.WavelengthDrift	Disable	Disable; Enable

Table 13 lists the TNC card default settings.



Note TNC cards are supported only on the Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TNC.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
TNC.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
TNC.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TNC.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
TNC.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TNC.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912
TNC.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
TNC.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
TNC.opticalthresholds.oc3.ulh.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.alarm.LowRxPower	-45.5 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.ulh.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.1day.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.ulh.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.15min.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.alarm.LowRxPower	-36.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.opticalthresholds.oc3.lr2.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.oc3.lr2.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.oc3.lr2.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.LowRxPower	-45.5 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.opticalthresholds.fastethernet.ulh.1day.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.15min.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.alarm.LowRxPower	-36.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.opticalthresholds.fastethernet.lx.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.1day.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.15min.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 13 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.opticalthresholds.1gethernet.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.config.oc3.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.ge.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart

ANSI TXP_MR_10E Card Default Settings

Table 14 lists the TXP_MR_10E card default settings.



Note TXP_MR_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 14 ANSI TXP_MR_10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
TXP-MR-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
TXP-MR-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; SONET (including 10G Ethernet WAN Phy); Transparent when ppmPortAssignment 10G Ethernet LAN Phy; 10G Fiber Channel
TXP-MR-10E.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SONET (including 10G Ethernet WAN Phy); 10G Ethernet LAN Phy; 10G Fiber Channel
TXP-MR-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-10E.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	6.0; 6.1; 6.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
TXP-MR-10E.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.LowTxPower	0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lrl.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.p111.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p111.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.p111.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p111.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.p111.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p111.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p111.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighRxPower	-1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighTxPower	5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.LowRxPower	-11 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.LowTxPower	-12 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighRxPower	1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighTxPower	1 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.LowRxPower	-13 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.LowTxPower	-8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72

Table 14 *ANSI TXP_MR_10E Card Default Settings (continued)*

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.otnLines.AsyncSynchMapping	Synch Mapping	Asynch mapping; Synch Mapping
TXP-MR-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10E.otn.otnLines.G709OTN	Enable	Disable; Enable
TXP-MR-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.pmthresholds.client.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.1day.CV	850400 (B2 count)	0 - 849657600

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10E.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 14 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI TXP_MR_10G Card Default Settings

Table 15 lists the TXP_MR_10G card default settings.



Note TXP_MR_10G cards are supported only on the Cisco ONS 15454 platform.

Table 15 ANSI TXP_MR_10G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED, SONET (including 10G Ethernet WAN Phy), 10G Ethernet LAN Phy
TXP-MR-10G.config.client.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.client.SFBER	1.00E-04	1E-3, 1E-4, 1E-5
TXP-MR-10G.config.client.TerminationMode	Transparent	Transparent, Line when mrPortAssignment UNASSIGNED, SONET (including 10G Ethernet WAN Phy); Transparent when mrPortAssignment 10G Ethernet LAN Phy
TXP-MR-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.trunk.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.trunk.SFBER	1.00E-04	1E-3, 1E-4, 1E-5
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.feethresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10G.otn.feethresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10G.otn.feethresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10G.otn.feethresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-10G.otn.otnLines.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900

Table 15 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI TXP_MR_2.5G Card Default Settings

Table 16 lists the TXP_MR_2.5G card default settings.



Note TXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 16 ANSI TXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC3; OC12; OC48; Transparent when ppmPortAssignment OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000 sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000 sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12 lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lrl.2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc12.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc12.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.oc12.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc12.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc3.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc3.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.fecthresholds.oc3.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc3.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc48.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc48.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.oc48.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc48.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable; Enable

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400

Table 16 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI TXPP_MR_2.5G Card Default Settings

Table 17 lists the TXPP_MR_2.5G card default settings.

**Note**

TXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 17 ANSI TXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXPP-MR-2_5G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXPP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC3; OC12; OC48; Transparent when ppmPortAssignment OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGN ED	UNASSIGNED; OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGN ED	UNASSIGNED; PPM (1 Port)
TXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXPP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000 lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lrl.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc12.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc12.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc12.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc12.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc3.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc3.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc3.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc3.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc48.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc48.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc48.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc48.1day.UncorrectableWords	96 (count)	0 - 453570969600

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
TXPP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable; Enable
TXPP-MR-2_5G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900

Table 17 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI GE_XP Card Default Settings

Table 18 lists the GE_XP card default settings.



Note GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 18 ANSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.config.card.Mode	10GE MXP	20GE MXP; 10GE MXP; L2 over DWDM
XP-GE.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-GE.config.client.CommittedBurstSize	4K	4K; 8K; 16K .. 16M

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.client.DS1.LineCoding	B8ZS	B8ZS; AMI
XP-GE.config.client.DS1.LineLength	266-399 ft	0-133 ft; 133-266 ft; 266-399 ft; 399-533 ft; 533-655 ft
XP-GE.config.client.DS1.LineType	ESF	ESF; Unframed
XP-GE.config.client.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.client.FlowControl	OFF	OFF; ON
XP-GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.client.Speed	Auto	10 Mbps; 100 Mbps; 1000 Mbps; Auto
XP-GE.config.client.cEtherType	8100 (Hex)	Free form field
XP-GE.config.client.macLearningState	OFF	OFF; ON
XP-GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-GE.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE-GE; FE
XP-GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-GE.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.config.trunk.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.trunk.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.trunk.FlowControl	OFF	OFF; ON
XP-GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.macLearningState	OFF	OFF; ON
XP-GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighRxPower	-5.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighTxPower	-5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowRxPower	-30.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowTxPower	-17.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowRxPower	-33.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowTxPower	-21.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900

Table 18 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

ANSI 10GE_XP Card Default Settings

Table 19 lists the 10GE_XP card default settings.



Note 10GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 19 ANSI 10GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-10GE.config.card.Mode	10GE TXP	10GE TXP; L2 over DWDM
XP-10GE.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-10GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-10GE.config.client.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-10GE.config.client.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.client.FlowControl	OFF	OFF; ON
XP-10GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.client.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.client.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.macLearningState	OFF	OFF; ON
XP-10GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-10GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-10GE.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-10GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-10GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-10GE.config.trunk.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-10GE.config.trunk.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.trunk.FlowControl	OFF	OFF; ON
XP-10GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.macLearningState	OFF	OFF; ON
XP-10GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-10GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 86722769387520 0
XP-10GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 86722769387520 0
XP-10GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table 19 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-10GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-10GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

ANSI OSCM Card Default Settings

Table 20 lists the OSCM card default settings.

**Note**

OSCM cards are supported only on the Cisco ONS 15454 platform.

Table 20 ANSI OSCM Card Default Settings

Default Name	Default Value	Default Domain
OSCM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSCM.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
OSCM.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
OSCM.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
OSCM.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912

Table 20 ANSI OSCM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSCM.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
OSCM.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
OSCM.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
OSCM.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
OSCM.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
OSCM.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
OSCM.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI OSC-CSM Card Default Settings

Table 21 lists the OSC-CSM card default settings.


Note

OSC-CSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 21 ANSI OSC-CSM Card Default Settings

Default Name	Default Value	Default Domain
OSC_CSM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSC_CSM.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
OSC_CSM.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
OSC_CSM.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200

Table 21 ANSI OSC-CSM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSC_CSM.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912
OSC_CSM.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
OSC_CSM.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
OSC_CSM.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
OSC_CSM.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
OSC_CSM.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
OSC_CSM.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
OSC_CSM.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI OTU2-XP Card Default Settings

Table 25 lists the OTU2-XP card default settings.



Note OTU2-XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.



Note NE default values for flow control and client distance parameters do not exist.

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.config.port.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
OTU2-XP.config.port.AisSquelchMode	Squelch	Ais; Squelch

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.config.port.OduTransparency	Cisco Extended Use	Transparent Standard Use; Cisco Extended Use
OTU2-XP.config.port.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.config.port.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
OTU2-XP.config.port.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; SONET (including 10G Ethernet WAN Phy); IB_5G; Transparent when ppmPortAssignment 10G Ethernet LAN Phy; 10G Fiber Channel
OTU2-XP.config.port.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SONET (including 10G Ethernet WAN Phy); 10G Ethernet LAN Phy; 10G Fiber Channel; IB_5G
OTU2-XP.config.port.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disablefec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfe.c.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15m.in.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15m.in.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alar m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alar m.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alar m.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alar m.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alar m.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alar.m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alar.m.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alar.m.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alar.m.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alar.m.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disable dfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standar dfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr.disabledfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr.disabledfec.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr.disabledfec.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfe c.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfe c.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfe.c.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15m.in.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15m.in.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15m.in.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15m.in.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15m.in.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
OTU2-XP.otn.otnLines.G709OTN	Enable	Disable; Enable
OTU2-XP.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.pmthresholds.sts192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
OTU2-XP.pmthresholds.sts192c.nearend.15min.ES	60 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.sts192c.nearend.15min.SES	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.15min.UAS	10 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.1day.CV	750 (B3 count)	0 - 207360000
OTU2-XP.pmthresholds.sts192c.nearend.1day.ES	600 (seconds)	0 - 86400
OTU2-XP.pmthresholds.sts192c.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.sts192c.nearend.1day.SES	7 (seconds)	0 - 86400
OTU2-XP.pmthresholds.sts192c.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900

Table 22 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

ANSI PSM Card Default Settings

Table 25 lists the PSM card default settings.



Note PSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 23 ANSI Amplifier Card Default Settings

Default Name	Default Value	Default Domain
PSM.config.card.AlsMode	Disabled	Disabled, Auto Restart

ANSI EDFA Card Default Settings

Table 25 lists the OPT-EDFA-17 card default settings.



Note EDFA cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 24 ANSI EDFA Card Default Settings

Default Name	Default Value	Default Domain
OPT-EDFA-17.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
OPT-EDFA-24.config.card.AlsMode	Auto Restart	Disabled; Auto Restart

ANSI Amplifier Card Default Settings

[Table 25](#) lists the OPT-BST, OPT-BST-L, OPT-AMP-C, and OPT-AMP-17-C card default settings.



Note The OPT-BST-L card is supported only on the Cisco ONS 15454 platform. The OPT-BST and OPT-AMP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 25 *ANSI Amplifier Card Default Settings*

Default Name	Default Value	Default Domain
OPT-AMP-17-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-AMP-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST-L.config.card.AlsMode	Auto Restart	Disabled, Auto Restart

ANSI Node Default Settings

[Table 26 on page 591](#) lists the node-level default settings for the Cisco ONS 15454. Cisco provides the following types of user-configurable defaults for each Cisco ONS 15454 node:



Note The node default settings described in this section are supported on the Cisco ONS 15454, Cisco ONS 15454 M6, Cisco ONS 15454 M2 platforms, unless noted otherwise.

- Circuit settings—Set the administrative state and path protection circuit defaults, and whether to have circuits send a payload defect indication condition (PDIP).
- General settings—Set general node management defaults, including whether to use Daylight Savings Time (DST), whether to insert Alarm Indication Signal VT (AIS-V) in each VT when the carrying STS crosses the signal degrade (SD) path bit error rate (BER) threshold, the IP address of the Network Time Protocol/Simple Network Time Protocol (NTP/SNTP) server to be used, the time zone where the node is located, the SD path BER value, the defaults description, whether to raise a condition on an empty card slot, whether automatic autonomous Transcation Language One (TL1) reporting of PM data is enabled for cross-connect paths on the node, whether or not to allow ports to be disabled when they are providing services (when the default is set to FALSE users must remove or disable the services first, then put the ports out of service), and whether to report loopback conditions on Out-of-Service, Maintenance (OOS-MT) state ports.
- Link Management Protocol settings—Set link management protocol data link type, traffic engineering link, and general settings.
- Power Monitor settings—Set default voltage thresholds for the node.
- Network settings—Set whether to prevent display of node IP addresses in CTC (applicable for all users except Superusers); default gateway node type; whether to raise an alarm when the backplane LAN cable is disconnected; and whether to display the IP address in the LCD in an editable mode (in which you can change the IP address directly from LCD screen), to display the IP address on the LCD as read-only, or to suppress display of the IP on the LCD entirely.

- OSI settings—Set the Open System Interconnection (OSI) main setup, generic routing encapsulation (GRE) tunnel, link access protocol on the D channel (LAP-D), the router subnet, and the TID address resolution protocol (TARP) settings.
- 1+1 and Optimized 1+1 protection settings—Set whether or not protected circuits have bidirectional switching, are revertive, and what the reversion time is; set optimized 1+1 detection, recovery, and verify guard timer values.

**Note**

Optimized 1+1 supports three timers that ensure the correct state of the cards at key points in card communication. A verification guard timer is used when a Force is issued, to ensure that the far end has a chance to respond. A detection guard timer is used to ensure the presence of an SF/SD condition before switching away from a card. A recover guard timer ensures the absence of SF/SD prior to switching to a card. You can change the default number of seconds before these timers expire by changing the NE default for the corresponding timer to a value within its domain of allowable values.

- BLSR protection settings—Set whether BLSR-protected circuits are revertive, and what the reversion time is, at both the ring and span levels.
- Y Cable protection settings—Set whether Y-cable protected circuits are revertive, and what the reversion time is.
- Splitter protection settings—Set whether splitter protected circuits are revertive, and what the reversion time is.
- Legal Disclaimer—Set the legal disclaimer that warns users at the login screen about the possible legal or contractual ramifications of accessing equipment, systems, or networks without authorization.
- Security Grant Permissions—Set default user security levels for activating/reverting software, PM data clearing, database restoring, and retrieving audit logs.
- Security DataComm settings—Set default security settings for TCC Ethernet IP address and IP netmask, and CTC backplane IP suppression; set secure mode on and secure mode locked (for TCC2P cards only).
- Security Access settings—Set default security settings for LAN access, shell access, serial craft access, element management system (EMS) access (including Internet Inter-Object Request Broker Protocol [IIOP] listener port number), TL1 access, and Simple Network Management Protocol (SNMP) access.
- Security RADIUS settings—Set default RADIUS server settings for the accounting port number and the authentication port number, and whether to enable the node as a final authenticator.
- Security Policy settings—Set the allowable failed logins before lockout, idle user timeout for each user level, optional lockout duration or manual unlock enabled, password reuse and change frequency policies, number of characters difference that is required between the old and new password, password aging by security level, enforced single concurrent session per user, and option to disable inactive user after a set inactivity period.
- Security Password settings—Set when passwords can be changed, how many characters they must differ by, whether or not password reuse is allowed, and whether a password change is required on first login to a new account; set password aging enforcement and user-level specific aging and warning periods; set how many consecutive identical characters are allowed in a password, maximum password length, minimum password length, minimum number and combination of nonalphabetical characters required, and whether or not to allow a password that is a reversal of the login ID associated with the password.

- BITS Timing settings—Set the AIS threshold, Admin synchronization status messaging (SSM), coding, facility type, framing, state, and line build-out (LBO) settings for building integrated timing supply 1 (BITS-1) and BITS2 timing.
- General Timing settings—Set the mode (External, Line, or Mixed), quality of reserved (RES) timing (the rule that defines the order of clock quality from lowest to highest), revertive, reversion time, and SSM message set for node timing.

**Note**

Any node level defaults changed using the **Provisioning > Defaults** tab, changes existing node level provisioning. Although this is service affecting, it depends on the type of defaults changed, for example, general, and all timing and security attributes. The “Changing default values for some node level attributes overrides the current provisioning.” message is displayed. The Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) explains the effect of changing the default values. However, when the card level defaults are changed using the **Provisioning > Defaults** tab, existing card provisioning remains unaffected.

**Note**

For more information about each individual node setting, see the chapter “Manage the Node” in the *Cisco ONS 15454 DWDM Configuration Guide*.

Table 26 *ANSI Node Default Settings*

Default Name	Default Value	Default Domain
NODE.circuits.SendPDIP	TRUE	TRUE, FALSE
NODE.circuits.State	IS,AINS	IS, OOS,DSBLD, OOS,MT, IS,AINS
NODE.circuits.upsr.AllowUprsOverOnePlusOne	FALSE	TRUE, FALSE
NODE.circuits.upsr.ProvisionWorkingGoAndReturnOnPrimaryPath	TRUE	TRUE, FALSE
NODE.circuits.upsr.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.circuits.upsr.Revertive	FALSE	TRUE, FALSE
NODE.circuits.upsr.STS_SDBER	1.00E-06	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.circuits.upsr.STS_SFBER	1.00E-04	1E-3, 1E-4, 1E-5
NODE.circuits.upsr.SwitchOnPDIP	FALSE	TRUE, FALSE
NODE.circuits.upsr.VT_SDBER	1.00E-05	1E-5, 1E-6, 1E-7, 1E-8
NODE.circuits.upsr.VT_SFBER	1.00E-03	1E-3, 1E-4, 1E-5
NODE.general.AllowServiceAffectingPortChangeToDisabled	TRUE	FALSE, TRUE
NODE.general.AutoPM (only Cisco ONS 15454)	FALSE	FALSE, TRUE
NODE.general.BackupNtpSntpServer	0.0.0.0	IP Address
NODE.general.DefaultsDescription	Factory Defaults	Free form field

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.general.InsertAISVOnSDP	FALSE	TRUE, FALSE
NODE.general.NtpSntpServer	0.0.0.0	IP Address
NODE.general.RaiseConditionOnEmptySlot	FALSE	TRUE, FALSE
NODE.general.ReportLoopbackConditionsOnOOS-MTPorts	FALSE	FALSE, TRUE
NODE.general.SDPBER	1.00E-06	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.general.TimeZone	(GMT-08:00) Pacific Time (US & Canada), Tijuana	(For applicable time zones, see Table 27 on page 609 .)
NODE.general.UseDST	TRUE	TRUE, FALSE
NODE.lmp.controlChannel.AdminState	OOS,DSBLD	IS, OOS,DSBLD
NODE.lmp.controlChannel.HelloDeadInterval	12000 (ms)	maximum_of(20 00,MinHelloDea dInterval,produ ct_of(HelloInterv al,3)), maximum_of(20 00,MinHelloDea dInterval,produ ct_of(HelloInterv al,3)) + 1, maximum_of(20 00,MinHelloDea dInterval,produ ct_of(HelloInterv al,3)) + 2 .. minimum_of(20 000,MaxHelloD eadInterval)
NODE.lmp.controlChannel.HelloInterval	500 (ms)	maximum_of(30 0,MinHelloInter val), maximum_of(30 0,MinHelloInter val) + 1, maximum_of(30 0,MinHelloInter val) + 2 .. minimum_of(50 00,MaxHelloInt erval,quotient_o f(HelloDeadInte rval,3))

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.general.mvAirFilterBasedFanEnable (only Cisco ONS 15454 M6)	FALSE	TRUE, FALSE
NODE.lmp.controlChannel.MaxHelloDeadInterval	20000 (ms)	maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)), maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 1, maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 2 .. 20000
NODE.lmp.controlChannel.MaxHelloInterval	2000 (ms)	maximum_of(300>HelloInterval), maximum_of(300>HelloInterval) + 1, maximum_of(300>HelloInterval) + 2 .. minimum_of(500,difference_of(MaxHelloDeadInterval,1))
NODE.lmp.controlChannel.MinHelloDeadInterval	2000 (ms)	maximum_of(200,sum_of(MinHelloInterval,1)), maximum_of(200,sum_of(MinHelloInterval,1)) + 1, maximum_of(200,sum_of(MinHelloInterval,1)) + 2 .. minimum_of(2000>HelloDeadInterval)

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.MinHelloInterval	300 (ms)	300, 301, 302 .. minimum_of(5000,HelloInterval,difference_of(MinHelloDeadline,1))
NODE.lmp.dataLink.Type	Port	Port, Component
NODE.lmp.general.Allowed	TRUE	FALSE, TRUE
NODE.lmp.general.Enabled	FALSE	FALSE, TRUE when Allowed TRUE; FALSE when Allowed FALSE
NODE.lmp.general.LMP-WDM	TRUE	FALSE, TRUE
NODE.lmp.general.Role	OLS	PEER, OLS
NODE.lmp.teLink.AdminState	OOS,DSBLD	IS, OOS,DSBLD
NODE.lmp.teLink.DWDM	TRUE	FALSE, TRUE
NODE.lmp.teLink.MuxCapability	Lambda Switch	Packet Switch - Level 1, Packet Switch - Level 2, Packet Switch - Level 3, Packet Switch - Level 4, Layer 2 Switch, TDM Cross-connect, Lambda Switch, Fiber Switch
NODE.network.general.AlarmMissingBackplaneLAN	FALSE	TRUE, FALSE
NODE.network.general.CtcIpDisplaySuppression	FALSE	TRUE, FALSE
NODE.network.general.GatewaySettings	None	LeaveAsIs, None, ENE, GNE, ProxyOnlyNode
NODE.network.general.LcdSetting	Allow Configuration	Allow Configuration, Display Only, Suppress Display
NODE.osi.greTunnel.OspfCost	110	110 - 65535
NODE.osi.greTunnel.SubnetMask	24 (bits)	8, 9, 10 .. 32
NODE.osi.lapd.Mode	AITS	AITS, UITS

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.osi.lapd.MTU	512	512, 513, 514 .. 1500
NODE.osi.lapd.Role	Network	Network, User
NODE.osi.lapd.T200	200 (ms)	200, 300, 400 .. 20000
NODE.osi.lapd.T203	10000 (ms)	4000, 4100, 4200 .. 120000
NODE.osi.mainSetup.L1L2LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.L1LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.NodeRoutingMode	Intermediate System Level 1	End System, Intermediate System Level 1, Intermediate System Level 1/Level 2
NODE.osi.subnet.DISPriority	63	1, 2, 3 .. 127
NODE.osi.subnet.ESH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.GCCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.IIH	3 (sec)	1, 2, 3 .. 600
NODE.osi.subnet.ISH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.LANISISCost	20	1, 2, 3 .. 63
NODE.osi.subnet.LDCCISISCost	40	1, 2, 3 .. 63
NODE.osi.subnet.OSCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.SDCCISISCost	60	1, 2, 3 .. 63
NODE.osi.tarp.L1DataCache	TRUE	FALSE, TRUE
NODE.osi.tarp.L2DataCache	FALSE	FALSE, TRUE
NODE.osi.tarp.LANStormSuppression	TRUE	FALSE, TRUE
NODE.osi.tarp.LDB	TRUE	FALSE, TRUE
NODE.osi.tarp.LDBEntry	5 (min)	1 - 10
NODE.osi.tarp.LDBFlush	5 (min)	0 - 1440
NODE.osi.tarp.PDUsL1Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsL2Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsOrigination	TRUE	FALSE, TRUE
NODE.osi.tarp.T1Timer	15 (sec)	0 - 3600
NODE.osi.tarp.T2Timer	25 (sec)	0 - 3600
NODE.osi.tarp.T3Timer	40 (sec)	0 - 3600
NODE.osi.tarp.T4Timer	20 (sec)	0 - 3600

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.osi.tarp.Type4PDUDelay	0 (sec)	0 - 255
NODE.powerMonitor.EHIBATVG	-56.5 (Vdc)	-54.0, -54.5, -55.0, -55.5, -56.0, -56.5
NODE.powerMonitor.ELWBATVG	-40.5 (Vdc)	-40.5, -41.0, -41.5, -42.0, -42.5, -43.0, -43.5, -44.0
NODE.powerMonitor.HIBATVG	-54.0 (Vdc)	-44.0, -44.5, -45.0 .. -56.5
NODE.powerMonitor.LWBATVG	-44.0 (Vdc)	-40.5, -41.0, -41.5 .. -54.0
NODE.protection.1+1.BidirectionalSwitching	FALSE	TRUE, FALSE
NODE.protection.1+1.DetectionGuardTimer	1 (seconds)	0, 0.05, 0.1, 0.5, 1, 2, 3, 4, 5
NODE.protection.1+1.RecoveryGuardTimer	1 (seconds)	0, 0.05, 0.1 .. 10
NODE.protection.1+1.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.1+1.Revertive	FALSE	TRUE, FALSE
NODE.protection.1+1.VerifyGuardTimer	0.5 (seconds)	0.5, 1
NODE.protection.blsr.RingReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.blsr.RingRevertive	TRUE	TRUE, FALSE
NODE.protection.blsr.SpanReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.blsr.SpanRevertive	TRUE	TRUE, FALSE
NODE.protection.splitter.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.splitter.Revertive	FALSE	TRUE, FALSE
NODE.protection.yable.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.yable.Revertive	FALSE	TRUE, FALSE
NODE.security.dataComm.CtcBackplaneIpDisplaySuppression	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.DefaultTCCEthernetIP	10.0.0.1	IP Address
NODE.security.dataComm.DefaultTCCEthernetIPNetmask	24 (bits)	8, 9, 10 .. 32
NODE.security.dataComm.isSecureModeSupportedOnControlCard	TRUE	FALSE, TRUE

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.dataComm.LcdBackplaneIpSetting (Cisco ONS 15454)	NOT SUPPORTED	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.LcdBackplaneIpSetting (Cisco ONS 15454 M6)	Display Only	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.SecureModeLocked	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.SecureModeOn (May reboot node)	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.emsAccess.AccessState	NonSecure	NonSecure, Secure
NODE.security.emsAccess.IIOPListenerPort (May reboot node)	57790 (port #)	0 - 65535
NODE.security.grantPermission.ActivateRevertSoftware	Superuser	Provisioning, Superuser
NODE.security.grantPermission.PMClearingPrivilege	Provisioning	Provisioning, Superuser
NODE.security.grantPermission.RestoreDB	Superuser	Provisioning, Superuser
NODE.security.grantPermission.RetrieveAuditLog	Superuser	Provisioning, Superuser
NODE.security.idleUserTimeout.Maintenance	01:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.idleUserTimeout.Provisioning	00:30 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Retrieve	00:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Superuser	00:15 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.lanAccess.LANAccess (May disconnect CTC from node)	Front & Backplane	No LAN Access, Front Only, Backplane Only, Front & Backplane
NODE.security.lanAccess.LANAccess (only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	Front Craft & EMS	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.RestoreTimeout	5 (minutes)	0 - 60
NODE.security.legalDisclaimer.LoginWarningMessage	<html><center>WARNING</center>This system is restricted to authorized users for business purposes. Unauthorized access is a violation of the law. This service may be monitored for administrative and security reasons. By proceeding, you consent to this monitoring.	Free form field
NODE.security.other.DisableInactiveUser	FALSE	FALSE, TRUE

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.other.InactiveDuration	45 (days)	1, 2, 3 .. 99 when nothing TRUE; 45 when nothing FALSE
NODE.security.other.SingleSessionPerUser	FALSE	TRUE, FALSE
NODE.security.passwordAging.EnforcePasswordAging	FALSE	TRUE, FALSE
NODE.security.passwordAging.maintenance.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.maintenance.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.provisioning.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.provisioning.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.retrieve.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.retrieve.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.superuser.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.superuser.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordChange.CannotChangeNewPassword	FALSE	TRUE, FALSE
NODE.security.passwordChange.CannotChangeNewPasswordForNDays	20 (days)	20 - 95
NODE.security.passwordChange.NewPasswordMustDifferFromOldByNCharacters	1 (characters)	1 - 5
NODE.security.passwordChange.PreventReusingLastNPasswords	1 (times)	1 - 10
NODE.security.passwordChange.RequirePasswordChangeOnFirstLoginToNewAccount	FALSE	TRUE, FALSE
NODE.security.passwordComplexity.IdenticalConsecutiveCharactersAllowed	3 or more	0-2, 3 or more
NODE.security.passwordComplexity.MaximumLength	20	20, 80
NODE.security.passwordComplexity.MinimumLength	6	6, 8, 10, 12
NODE.security.passwordComplexity.MinimumRequiredCharacters	1 num, 1 letter & 1 TL1 special	1 num, 1 letter & 1 TL1 special, 1 num, 1 letter & 1 special, 2 each of any 2 of num, upper, lower & TL1 special, 2 each of any 2 of num, upper, lower & special
NODE.security.passwordComplexity.ReverseUserIdAllowed	TRUE	TRUE, FALSE
NODE.security.pseudoIOSAccess.AccessState	NonSecure	Disabled; NonSecure; Secure
NODE.security.pseudoIOSAccess.Port	65000	1024 - 65535
NODE.security.pseudoIOSAccess.SecurePort	64000	1024 - 65535
NODE.security.radiusServer.AccountingPort	1813 (port)	0 - 32767
NODE.security.radiusServer.AuthenticationPort	1812 (port)	0 - 32767

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.radiusServer.EnableNodeAsFinalAuthenticator	TRUE	FALSE, TRUE
NODE.security.serialCraftAccess.EnableCraftPort	TRUE	TRUE, FALSE
NODE.security.shellAccess.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.shellAccess.EnableShellPassword	FALSE	TRUE, FALSE
NODE.security.shellAccess.TelnetPort	23	23 - 9999
NODE.security.snmpAccess.AccessState	NonSecure	Disabled, NonSecure
NODE.security.tl1Access.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.userLockout.FailedLoginsAllowedBeforeLockout	5 (times)	0 - 10
NODE.security.userLockout.LockoutDuration	00:30 (mins:secs)	00:00, 00:05, 00:10 .. 10:00
NODE.security.userLockout.ManualUnlockBySuperuser	FALSE	TRUE, FALSE
NODE.software.AllowDelayedUpgrades	FALSE	FALSE, TRUE
NODE.software.DefaultDelayedUpgrades	FALSE	FALSE, TRUE when AllowDelayedU pgrades TRUE; FALSE when AllowDelayedU pgrades FALSE
NODE.timing.bits-1.AdminSSMIn	STU	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.AIThreshold	SMC	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A
NODE.timing.bits-1.Coding	B8ZS	B8ZS, AMI when FacilityType DS1; HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-1.CodingOut	B8ZS	B8ZS, AMI when FacilityTypeOut DS1; HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.FacilityType	DS1	DS1, 64kHz+8kHz when //.general.TimingStandard SONET; E1, 64kHz+8kHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-1.FacilityTypeOut	DS1	DS1, 6MHz when //.general.TimingStandard SONET; E1, 6MHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-1.Framing	ESF	ESF, D4 when FacilityType DS1; FAS+CRC, FAS+CAS, FAS+CAS+CR C, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.FramingOut	ESF	ESF, D4 when FacilityTypeOut DS1; FAS+CRC, FAS+CAS, FAS+CAS+CR C, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; N/A when FacilityTypeOut 6MHz
NODE.timing.bits-1.LBO	0-133	0-133, 134-266, 267-399, 400-533, 534-655
NODE.timing.bits-1.SaBit	N/A	N/A when FacilityType DS1; 4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-1.State	OOS,DSBLD	IS, OOS,DSBLD
NODE.timing.bits-1.StateOut	OOS,DSBLD	IS, OOS,DSBLD

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.AdminSSMIn	STU	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A
NODE.timing.bits-2.AISThreshold (only Cisco ONS 15454)	ST3	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.AISThreshold (only Cisco ONS 15454 M6)	SMC	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A
NODE.timing.bits-2.Coding	B8ZS	B8ZS, AMI when FacilityType DS1; HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-2.CodingOut	B8ZS	B8ZS, AMI when FacilityTypeOut DS1; HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.FacilityType	DS1	DS1, 64kHz+8kHz when //.general.TimingStandard SONET; E1, 64kHz+8kHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-2.FacilityTypeOut	DS1	DS1, 6MHz when //.general.TimingStandard SONET; E1, 6MHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-2.Framing	ESF	ESF, D4 when FacilityType DS1; FAS+CRC, FAS+CAS, FAS+CAS+CR C, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.FramingOut	ESF	ESF, D4 when FacilityTypeOut DS1; FAS+CRC, FAS+CAS, FAS+CAS+CR C, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; N/A when FacilityTypeOut 6MHz
NODE.timing.bits-2.LBO	0-133	0-133, 134-266, 267-399, 400-533, 534-655
NODE.timing.bits-2.SaBit	N/A	N/A when FacilityType DS1; 4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-2.State	OOS,DSBLD	IS, OOS,DSBLD
NODE.timing.bits-2.State (only Cisco ONS 15454 M6)	IS	IS, OOS,DSBLD
NODE.timing.bits-2.StateOut (only Cisco ONS 15454 M6)	IS	IS, OOS,DSBLD
NODE.timing.bits-2.StateOut	OOS,DSBLD	IS, OOS,DSBLD
NODE.timing.general.Mode	Line	External, Line, Mixed

Table 26 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.general.QualityOfRES	RES=DUS	PRS<RES, STU<RES<PRS , ST2<RES<STU, ST3<RES<ST2, SMC<RES<ST3 , ST4<RES<SMC , RES<ST4, RES=DUS when SSMMessagSet Generation 1; PRS<RES, STU<RES<PRS , ST2<RES<STU, TNC<RES<ST2 , ST3E<RES<TN C, ST3<RES<ST3 E, SMC<RES<ST3 , ST4<RES<SMC , RES<ST4, RES=DUS when SSMMessagSet Generation 2; N/A when SSMMessagSet N/A
NODE.timing.general.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.timing.general.Revertive	TRUE	TRUE, FALSE
NODE.timing.general.SSMMessagSet	Generation 1	Generation 1, Generation 2 when TimingStandard SONET; N/A when TimingStandard SDH
NODE.timing.general.TimingStandard	SONET	SONET, SDH

Time Zones

Table 27 lists the time zones that apply for node time zone defaults. Time zones in the table are ordered by their relative relationships to Greenwich Mean Time (GMT), and the default values are displayed in the correct format for valid default input.

Table 27 Time Zones

Time Zone (GMT +/- Hours)	Default Value
GMT-11:00	(GMT-11:00) Midway Islands, Samoa
GMT-10:00	(GMT-10:00) Hawaiian Islands, Tahiti
GMT-09:00	(GMT-09:00) Anchorage - Alaska
GMT-08:00	(GMT-08:00) Pacific Time (US & Canada), Tijuana
GMT-07:00	(GMT-07:00) Mountain Time (US & Canada)
GMT-07:00	(GMT-07:00) Phoenix - Arizona
GMT-06:00	(GMT-06:00) Central Time (US & Canada)
GMT-06:00	(GMT-06:00) Mexico City
GMT-06:00	(GMT-06:00) Costa Rica, Managua, San Salvador
GMT-06:00	(GMT-06:00) Saskatchewan
GMT-05:00	(GMT-05:00) Bogota, Lima, Quito
GMT-05:00	(GMT-05:00) Eastern Time (US & Canada)
GMT-05:00	(GMT-05:00) Havana
GMT-05:00	(GMT-05:00) Indiana (US)
GMT-04:00	(GMT-04:00) Asuncion
GMT-04:00	(GMT-04:00) Caracas, La Paz, San Juan
GMT-04:00	(GMT-04:00) Atlantic Time (Canada), Halifax, Saint John, Charlottetown
GMT-04:00	(GMT-04:00) Santiago
GMT-04:00	(GMT-04:00) Thule (Qaanaaq)
GMT-03:30	(GMT-03:30) St. John's - Newfoundland
GMT-03:00	(GMT-03:00) Brasilia, Rio de Janeiro, Sao Paulo
GMT-03:00	(GMT-03:00) Buenos Aires, Georgetown
GMT-03:00	(GMT-03:00) Godthab (Nuuk) - Greenland
GMT-02:00	(GMT-02:00) Mid-Atlantic
GMT-01:00	(GMT-01:00) Azores, Scoresbysund
GMT-01:00	(GMT-01:00) Praia - Cape Verde
GMT 00:00	(GMT 00:00) Casablanca, Reykjavik, Monrovia
GMT	(GMT) Greenwich Mean Time
GMT 00:00	(GMT 00:00) Dublin, Edinburgh, London, Lisbon
GMT+01:00	(GMT+01:00) Amsterdam, Berlin, Rome, Stockholm, Paris
GMT+01:00	(GMT+01:00) Belgrade, Bratislava, Budapest, Ljubljana, Prague
GMT+01:00	(GMT+01:00) Brussels, Copenhagen, Madrid, Vienna

Table 27 Time Zones (continued)

Time Zone (GMT +/- Hours)	Default Value
GMT+01:00	(GMT+01:00) Sarajevo, Skopje, Sofija, Vilnius, Warsaw, Zagreb
GMT+01:00	(GMT+01:00) West Central Africa, Algiers, Lagos, Luanda
GMT+01:00	(GMT+01:00) Windhoek (Namibia)
GMT+02:00	(GMT+02:00) Al Jizah, Alexandria, Cairo
GMT+02:00	(GMT+02:00) Amman
GMT+02:00	(GMT+02:00) Athens, Bucharest, Istanbul
GMT+02:00	(GMT+02:00) Beirut
GMT+02:00	(GMT+02:00) Cape Town, Harare, Johannesburg, Pretoria
GMT+02:00	(GMT+02:00) Jerusalem
GMT+02:00	(GMT+02:00) Kaliningrad, Minsk
GMT+03:00	(GMT+03:00) Aden, Antananarivo, Khartoum, Nairobi
GMT+03:00	(GMT+03:00) Baghdad
GMT+03:00	(GMT+03:00) Kuwait, Riyadh
GMT+03:00	(GMT+03:00) Moscow, St. Petersburg, Novgorod
GMT+03:30	(GMT+03:30) Tehran
GMT+04:00	(GMT+04:00) Abu Dhabi, Mauritius, Muscat
GMT+04:00	(GMT+04:00) Aqtau, T'bilisi
GMT+04:00	(GMT+04:00) Baku
GMT+04:00	(GMT+04:00) Yerevan, Samara
GMT+04:30	(GMT+04:30) Kabul
GMT+05:00	(GMT+05:00) Chelyabinsk, Prem, Yekaterinburg, Ufa
GMT+05:00	(GMT+05:00) Islamabad, Karachi, Tashkent
GMT+05:30	(GMT+05:30) Calcutta, Mumbai, New Delhi, Chennai
GMT+05:45	(GMT+05:45) Kathmandu
GMT+06:00	(GMT+06:00) Almaty
GMT+06:00	(GMT+06:00) Colombo, Dhaka, Astana
GMT+06:00	(GMT+06:00) Novosibirsk, Omsk
GMT+06:30	(GMT+06:30) Cocos, Rangoon
GMT+07:00	(GMT+07:00) Bangkok, Hanoi, Jakarta
GMT+07:00	(GMT+07:00) Krasnoyarsk, Norilsk, Novokuznetsk
GMT+08:00	(GMT+08:00) Irkutsk, Ulaan Bataar
GMT+08:00	(GMT+08:00) Beijing, Shanghai, Hong Kong, Urumqi
GMT+08:00	(GMT+08:00) Perth
GMT+08:00	(GMT+08:00) Singapore, Manila, Taipei, Kuala Lumpur
GMT+09:00	(GMT+09:00) Chita, Yakutsk
GMT+09:00	(GMT+09:00) Osaka, Sapporo, Tokyo

Table 27 Time Zones (continued)

Time Zone (GMT +/- Hours)	Default Value
GMT+09:00	(GMT+09:00) Palau, Pyongyang, Seoul
GMT+09:30	(GMT+09:30) Adelaide, Broken Hill
GMT+09:30	(GMT+09:30) Darwin
GMT+10:00	(GMT+10:00) Brisbane, Port Moresby, Guam
GMT+10:00	(GMT+10:00) Canberra, Melbourne, Sydney
GMT+10:00	(GMT+10:00) Hobart
GMT+10:00	(GMT+10:00) Khabarovsk, Vladivostok
GMT+10:30	(GMT+10:30) Lord Howe Island
GMT+11:00	(GMT+11:00) Honiara, Magadan, Solomon Islands
GMT+11:00	(GMT+11:00) Noumea - New Caledonia
GMT+11:30	(GMT+11:30) Kingston - Norfolk Island
GMT+12:00	(GMT+12:00) Andyra, Kamchatka
GMT+12:00	(GMT+12:00) Auckland, Wellington
GMT+12:00	(GMT+12:00) Marshall Islands, Eniwetok
GMT+12:00	(GMT+12:00) Suva - Fiji
GMT+12:45	(GMT+12:45) Chatham Island
GMT+13:00	(GMT+13:00) Nuku'alofa - Tonga
GMT+13:00	(GMT+13:00) Rawaki, Phoenix Islands
GMT+14:00	(GMT+14:00) Line Islands, Kiritimati - Kiribati

CTC Default Settings

Table 28 on page 612 lists the CTC-level default settings for the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6. Cisco provides the following user-configurable defaults for CTC:

- Automatic Routing—Set circuit creation with the Route Automatically check box selected by default.
- Network Circuit Automatic Routing Overridable—Set by default whether or not a user creating circuits can change (override) the Automatic Circuit Routing setting (also provisionable as a default) in the CTC Circuit Routing Preferences area. When this default is set to TRUE it enables users to change whether or not Route Automatically is selected in the check box. When this default is set to FALSE it ensures that users cannot change the Route Automatically setting while creating circuits in CTC.



Note

When the Route Automatically check box is not selectable (and is not checked) during circuit creation, the following automatic routing suboptions are also unavailable: Using Required Nodes/Spans, Review Route Before Creation, and VT-DS3 Mapped Conversion.

- Create TL1-like—Set whether to create only TL1-like circuits; that is, instruct the node to create only cross-connects, allowing the resulting circuits to be in an upgradable state.
- Local domain creation and viewing—Set whether domains that users create and view persist globally (all CTC sessions), or only locally (within the current CTC session).
- Network Map—Set the default network map (which country's map is displayed in CTC network view).

Table 28 **CTC Default Settings**

Default Name	Default Value	Default Domain
CTC.circuits.CreateLikeTL1	FALSE	TRUE, FALSE
CTC.circuits.RouteAutomatically	TRUE	TRUE, FALSE
CTC.circuits.RouteAutomaticallyDefaultOverridable	TRUE	TRUE, FALSE
CTC.network.Map	United States	-none-, Germany, Japan, Netherlands, South Korea, United Kingdom, United States

ETSI Platform Defaults

The following sections give the NE defaults for the ONS 15454 ETSI platform. To see defaults for the ONS 15454 ANSI platform, see the “[ANSI Platform Defaults](#)” section on page 2.

ETSI Card Defaults

The tables in this section list the default settings for each DWDM, Transponder (TXP), Muxponder (MXP), or Ethernet card. Cisco provides several types of user-configurable defaults for Cisco ONS 15454 DWDM, TXP, MXP, and Ethernet cards. Types of card defaults can be broadly grouped by function, as outlined in the following subsections. For information about individual card settings, see the chapters “Provision Transponder and Muxponder Cards” and “Change DWDM Card Settings” in the *Cisco ONS 15454 DWDM Configuration Guide*.



Note When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.



Note The tables in this section list the default settings for each DWDM, TXP, and MXP card. For all other cards, including electrical, optical, Ethernet, and Fibre Channel, see the *Cisco ONS 15454 Reference Manual* or the *Cisco ONS 15454 SDH Reference Manual*.

The following types of defaults are defined for DWDM, TXP, MXP, and Ethernet cards.

ETSI Configuration Defaults

Most card and port-level configuration defaults correspond to settings found in the CTC card-level Provisioning tabs.

**Note**

The full set of Automatic Laser Shutdown (ALS) configuration defaults can be found in the CTC card-level Maintenance > ALS tab for supported cards. ALS defaults are supported for OSCM, OSC-CSM, OPT-BST, OPT-BST-L, GE_XP, 10GE_XP, TXP, and MXP cards. For information on how ALS card settings achieve network level optical safety, see the chapters “Setup Optical Service Channel Cards”, “Optical Amplifier Cards”, or “Provision Transponder and Muxponder Cards” in the *Cisco ONS 15454 DWDM Configuration Guide*.

Configuration defaults that are reachable from the CTC card-level Provisioning tabs (except as noted) include the following types of options (arranged by CTC subtab):

- Line—(GE_XP, 10GE_XP, TXP and MXP cards) Line-level configuration settings, including SONET, Wavelength Trunk, Trunk, Client, Distance Extension, and Enhanced FC/FICON ISL settings.

**Note**

Some line configuration tabs, including Client, Distance Extension, and Enhanced FC/FICON ISL settings tabs, only appear in the card-level Provisioning > Line tab after a pluggable port module (PPM) is provisioned to a fibre channel payload type (port rate) for the particular card.

- OTN—(GE_XP, 10GE_XP, MXP-2.5G-10E, MXP-2_5G-10G, MXP-MR-10DME, TXP-MR-10E, TXP-MR-10G, TXP-MR-2.5G, and TXPP-MR-2.5G cards) Optical transport network (OTN) line configuration settings.
- Card—(See listed settings for applicable cards)
 - Card mode—MXPP-MR-2.5G and MXP-MR-2.5G (ESCON, FC_GE, or MIXED), GE_XP (20GE MXP, 10GE MXP, or L2 over DWDM) , and 10GE_XP (10GE TXP or L2 over DWDM)
 - Port range-level mode settings—MXP-MR-10DME cards only
 - Termination mode—TXP-MR-10E, MXP-2.5G-10E, MXP-2.5G-10G, TXPP_MR_2.5G, TXP_MR_10G, and TXP_MR_2.5G cards
 - AIS squelch settings—TXP-MR-10E and MXP-2.5G-10E cards
- ALS (card-level Maintenance > ALS tab)—(OSC-CSM, OSCM, OPT-BST, OPT-BST-L, GE_XP, 10GE_XP, TXP, and MXP cards) ALS configuration defaults.

**Note**

For further information about supported features on each card, see the chapters “Setup Optical Service Channel Cards”, “Optical Amplifier Cards”, or “Provision Transponder and Muxponder Cards” in the *Cisco ONS 15454 DWDM Configuration Guide*.

ETSI Threshold Defaults

Threshold default settings define the default cumulative values (thresholds) beyond which a threshold crossing alert (TCA) will be raised, making it possible to monitor the network and detect errors early.

Card threshold default settings are provided as follows:

- PM thresholds—(OSCM, OSC-CSM, TXP and MXP cards) Expressed in counts or seconds; includes line and SDH thresholds.
- Optical thresholds—(GE_XP, 10GE_XP, TXP, and MXP cards) Expressed in percentages or dBm; includes client and trunk optical thresholds.

- OTN FEC thresholds (GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts; includes enhanced, standard, 1G Ethernet, 1G Fibre channel, 1G FICON, STM-1, STM-4, STM-16, 2G FICON, and 2G Fibre channel thresholds.
- OTN G.709 thresholds (GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts or seconds; includes ITU-T G.709 PM and SM thresholds.

Threshold defaults are defined for near end and/or far end, at 15-minute and one-day intervals. Thresholds are further broken down by type, such as Multiplex Section, Regeneration Section, VC LO, MS, RS, or Path, for performance monitoring (PM) thresholds, and TCA (warning) or Alarm for physical thresholds. PM threshold types define the layer to which the threshold applies. Physical threshold types define the level of response expected when the threshold is crossed.



Note For full descriptions of the thresholds you can set for each card, see “[Monitor Performance](#)”.



Note In R7.0.1, when LOS, LOS-P, or LOF alarms occur on TXP and MXP trunks, certain TCAs are suppressed. For details, see “[Alarm and TCA Monitoring and Management](#)”.



Note For additional information regarding PM parameter threshold defaults as defined by Telcordia specifications, refer to Telcordia GR-820-CORE and GR-253-CORE.

ETSI Defaults by Card

In the tables that follow, card defaults are defined by the default name, its factory-configured value, and the domain of allowable values that you can assign to it.



Note Some default values, such as certain thresholds, are interdependent. Before changing a value, review the domain for that default and any other related defaults for potential dependencies.

ETSI ADM-10G Card Default Settings

[Table 29](#) lists the ADM-10G card default settings.



Note ADM-10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.config.interlink.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.interlink.ppmPortAssignment	UNASSIGNED	UNASSIGNED; Internal Link
ADM-10G.config.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
ADM-10G.config.stm1.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm1.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm1.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm1.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.stm1.line.PJVC4Mon#	0 (VC4 #)	0 - 1
ADM-10G.config.stm1.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm1.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.stm1.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm1.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm1.vc4.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.stm16.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm16.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm16.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm16.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.stm16.line.PJVC4Mon#	0 (VC4 #)	0 - 16
ADM-10G.config.stm16.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm16.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.config.stm16.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm16.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm16_vc4.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.stm4.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm4.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm4.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm4.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.stm4.line.PJVC4Mon#	0 (VC4 #)	0 - 4
ADM-10G.config.stm4.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm4.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.stm4.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm4.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm4_vc4.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
ADM-10G.config.trunk.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.trunk.PJVC4Mon#	0 (VC4 #)	0 - 64
ADM-10G.config.trunk.ppmPortAssignment	STM64	UNASSIGNED; STM64
ADM-10G.etherPortConfig.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.etherPortConfig.AutoNegotiation	1000 Mbps	Auto; 1000 Mbps
ADM-10G.etherPortConfig.MTU	Jumbo	1548; Jumbo
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alar.m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alar.m.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alar.m.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alar.m.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alar.m.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200

Table 29 *ETSI ADM-10G Card Default Settings*

Default Name	Default Value	Default Domain
ADM-10G.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
ADM-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
ADM-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm1.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 53049600
ADM-10G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm1.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.15min.BBE	25 (count)	0 - 2159100

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm1.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm1.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm1.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.PPJJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.PPJJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm1.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 138600
ADM-10G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
ADM-10G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm16.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm16.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm16.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm16.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.farend.15min.UAS	10 (seconds)	0 - 900

Table 29 *ETSI ADM-10G Card Default Settings*

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm16.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm16.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm16.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm16.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2151900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.1day.BBE	100000 (count)	0 - 206582400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm4.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm4.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm4.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm4.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm4.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.farend.1day.SES	7 (seconds)	0 - 86400

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm4.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm4.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.PPJJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.PPJJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm4.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 553500
ADM-10G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 553500
ADM-10G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.rs.nearend.1day.BBE	100000 (count)	0 - 53136000
ADM-10G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
ADM-10G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600

Table 29 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.trunk.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.trunk.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.trunk.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.trunk.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.trunk.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.ES	12 (seconds)	0 - 900

Table 29 *ETSI ADM-10G Card Default Settings*

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.PPJJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.PPJJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.trunk.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.PPJJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.PPJJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
ADM-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
ADM-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
ADM-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
ADM-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI 40G-TXP-C Card Default Settings

Table 30 lists the 40G-TXP-C card default settings.



Note 40G-TXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.config.client.AisSquelchMode	Squelch	Ais; Squelch
40G-TXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-TXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-TXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-TXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-TXP-C.config.client.SendDoNotUse	FALSE	TRUE; FALSE
40G-TXP-C.config.client.SyncMsgIn	TRUE	FALSE; TRUE
40G-TXP-C.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when mrPortAssignment UNASSIGNED; STM256; Transparent when mrPortAssignment UNASSIGNED; STM256; 40G Ethernet; OTU3
40G-TXP-C.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED; STM256; 40G Ethernet; OTU3
40G-TXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-TXP-C.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.40gEthernet.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.stm256.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.opticalthresholds.client.stm256.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.client.stm256.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.client.stm256.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-TXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-TXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-TXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-TXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-TXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-TXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-TXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-TXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-TXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-TXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-TXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-TXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-TXP-C.pmthresholds.client.ms.farend.15min.BBE	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.client.ms.farend.15min.EB	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.farend.1day.BBE	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.client.ms.farend.1day.EB	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.ms.nearend.15min.BBE	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.client.ms.nearend.15min.EB	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.ms.nearend.1day.BBE	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.client.ms.nearend.1day.EB	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
40G-TXP-C.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
40G-TXP-C.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40G-TXP-C.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.farend.15min.BBE	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.ms.farend.15min.EB	340160 (count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.farend.1day.BBE	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.ms.farend.1day.EB	3401600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
40G-TXP-C.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.ms.nearend.1day.BBE	212600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.ms.nearend.1day.EB	212600 (count)	0 - 849657600
40G-TXP-C.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
40G-TXP-C.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40G-TXP-C.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-TXP-C.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200

Table 30 ETSI 40G-TXP-C Card Default Settings

40G-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-TXP-C.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40G-TXP-C.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-TXP-C.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI 40G-MXP-C Card Default Settings

Table 31 lists the 40G-MXP-C card default settings.



Note 40G-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.client.AisSquelchMode	Squelch	Ais; Squelch
40G-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.client.SendDoNotUse	FALSE	TRUE; FALSE
40G-MXP-C.config.client.SyncMsgIn	TRUE	FALSE; TRUE
40G-MXP-C.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; STM64; Transparent when ppmPortAssignment UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel

Table 31 *ETSI 40G-MXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40G-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40G-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40G-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-MXP-C.config.wis.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.wis.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.11.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.11.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.11.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.11.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.11.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighLaser Bias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.11.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.12.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.15min.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.1day.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighRxPower	2.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowTxPower	-10.7 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.11.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.11.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.11.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.11.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.11.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.11.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.11.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.11.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.11.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.11.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.12.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.12.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.12.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.12.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ll.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ll.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ll.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.11.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.11.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.11.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.11.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.11.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.11.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.11.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.11.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.11.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.11.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.11.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.11.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.12.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.12.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.12.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.12.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.12.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.12.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.12.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.12.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.12.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.12.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.12.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64 lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64 lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64 lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64 lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64 mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64 mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64 mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 31 *ETSI 40G-MXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.client.ms.farend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.nearend.15min.EB	85040 (count)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.nearend.1day.EB	850400 (count)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40G-MXP-C.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40G-MXP-C.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.15min.BBE	25 (count)	0 - 2159100
40G-MXP-C.pmthresholds.path.nearend.15min.EB	15 (count)	0 - 7200000

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.path.nearend.15min.ES	12 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.15min.SES	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.15min.UAS	10 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.1day.BBE	250 (count)	0 - 207273600
40G-MXP-C.pmthresholds.path.nearend.1day.EB	125 (count)	0 - 691200000
40G-MXP-C.pmthresholds.path.nearend.1day.ES	100 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.1day.SES	7 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.wis.ms.farend.15min.EB	85040 (count)	0 - 8850600
40G-MXP-C.pmthresholds.wis.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.farend.1day.EB	850400 (count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.EB	85040 (count)	0 - 8850600
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.EB	850400 (count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.SES	500 (seconds)	0 - 900

Table 31 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI 40E-MXP-C Card Default Settings

Table 32 lists the 40E-MXP-C card default settings.



Note 40E-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-MXP-C.config.client.AisSquelchMode	Squelch	Ais; Squelch
40E-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40E-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40E-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40E-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40E-MXP-C.config.client.SendDoNotUse	FALSE	TRUE; FALSE
40E-MXP-C.config.client.SyncMsgIn	TRUE	FALSE; TRUE

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; STM64; Transparent when ppmPortAssignment UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40E-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40E-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40E-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40E-MXP-C.config.wis.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.config.wis.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd m40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.cwd.m40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwd.m.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 *ETSI 40E-MXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.i1.1d ay.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.1d ay.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.1d ay.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.1d ay.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i1.1d ay.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i1.alarm. HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.alarm. HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.alarm. HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i1.alarm. LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i1.alarm. LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i2.15 min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.15 min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.15 min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.15 min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.11.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.11.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.lrlalarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.allarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.allarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.c wdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.c wdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.c wdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.c wdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.c wdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d wdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.d.wdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.e.r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i 2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i r1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i r1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i r1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i r1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i r1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.i.r1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.1.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 *ETSI 40E-MXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.s.m.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.10gfibrechannel.z.r.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.z.r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.10gfibrechannel.z.r.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.10gfibrechannel.z.r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.15min.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.m.m.1day.LowTxPower	-14.2 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighRxPower	2.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.mm.alarm.LowTxPower	-10.7 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.l1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.l1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.l1.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.l1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.l1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.l1.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.l1.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.11.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.12.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.12.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.12.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.12.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.12.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.12.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.12.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.12.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.12.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.12.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.12.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.12.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.12.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.alarms.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.alarms.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.alarms.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.dwdm.alarms.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.dwdm.alarms.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.ll.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.ll.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.11.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.11.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.11.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.11.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.11.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.11.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.11.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.11.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.11.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.11.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.11.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.11.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.11.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.12.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.l2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.l2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.l2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.l2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.l2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.client.stm64.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-MXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-MXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-MXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-MXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-MXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.BB E	10000 (count)	0 - 8850600
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.SE S	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.15min.U AS	500 (seconds)	0 - 900
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40E-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40E-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40E-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-MXP-C.pmthresholds.client.ms.farend.15min.BB E	85040 (seconds)	0 - 8850600
40E-MXP-C.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
40E-MXP-C.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.ms.farend.15min.UA S	3 (seconds)	0 - 900

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.client.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40E-MXP-C.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
40E-MXP-C.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
	85040 (seconds)	0 - 8850600
40E-MXP-C.pmthresholds.client.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
40E-MXP-C.pmthresholds.client.ms.nearend.15min.EB	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.ms.nearend.15min.ES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.ms.nearend.15min.SES	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.ms.nearend.15min.UAS	850400 (seconds)	0 - 849657600
40E-MXP-C.pmthresholds.client.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
40E-MXP-C.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600
40E-MXP-C.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40E-MXP-C.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.client.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40E-MXP-C.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.path.nearend.15min.BBE	25 (count)	0 - 2159100
40E-MXP-C.pmthresholds.path.nearend.15min.EB	15 (count)	0 - 7200000
40E-MXP-C.pmthresholds.path.nearend.15min.ES	12 (seconds)	0 - 900
40E-MXP-C.pmthresholds.path.nearend.15min.SES	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.path.nearend.15min.UAS	10 (seconds)	0 - 900
40E-MXP-C.pmthresholds.path.nearend.1day.BBE	250 (count)	0 - 207273600
40E-MXP-C.pmthresholds.path.nearend.1day.EB	125 (count)	0 - 691200000
40E-MXP-C.pmthresholds.path.nearend.1day.ES	100 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.path.nearend.1day.SES	7 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.path.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.farend.15min.BBE	85040 (seconds)	0 - 8850600
40E-MXP-C.pmthresholds.wis.ms.farend.15min.EB	85040 (count)	0 - 8850600
40E-MXP-C.pmthresholds.wis.ms.farend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.farend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.farend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40E-MXP-C.pmthresholds.wis.ms.farend.1day.EB	850400 (count)	0 - 849657600
40E-MXP-C.pmthresholds.wis.ms.farend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.farend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.nearend.15min.BBE	85040 (seconds)	0 - 8850600
40E-MXP-C.pmthresholds.wis.ms.nearend.15min.EB	85040 (count)	0 - 8850600
40E-MXP-C.pmthresholds.wis.ms.nearend.15min.ES	87 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.nearend.15min.SES	1 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.ms.nearend.1day.BBE	850400 (seconds)	0 - 849657600
40E-MXP-C.pmthresholds.wis.ms.nearend.1day.EB	850400 (count)	0 - 849657600
40E-MXP-C.pmthresholds.wis.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600

Table 32 ETSI 40E-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-MXP-C.pmthresholds.wis.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40E-MXP-C.pmthresholds.wis.rs.nearend.15min.ES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.rs.nearend.15min.SES	500 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40E-MXP-C.pmthresholds.wis.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600
40E-MXP-C.pmthresholds.wis.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40E-MXP-C.pmthresholds.wis.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-MXP-C.pmthresholds.wis.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI 40E-TXP-C Card Default Settings

Table 33 lists the 40E-TXP-C card default settings.

**Note**

40E-TXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-TXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40E-TXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40E-TXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40E-TXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40E-TXP-C.config.client.SendDoNotUse	FALSE	TRUE; FALSE
40E-TXP-C.config.client.SyncMsgIn	TRUE	FALSE; TRUE

Table 33 *ETSI 40E-TXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40E-TXP-C.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when mrPortAssignment UNASSIGNED; STM256; Transparent when mrPortAssignment UNASSIGNED; STM256; 40G Ethernet; OTU3
40E-TXP-C.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED; STM256; 40G Ethernet; OTU3
40E-TXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40E-TXP-C.config.trunk.Overclock	OFF	OFF; ON
40E-TXP-C.config.trunk.SDBER(only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.config.trunk.SFBER(only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	1.00E-04	1E-3; 1E-4; 1E-5
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.40gethernet.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 33 *ETSI 40E-TXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.otu3.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.15min.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.1day.LowRxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighRxPower	5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.client.stm256.vsr.alarm.LowRxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.client.stm256.vsr.alarm.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 33 *ETSI 40E-TXP-C Card Default Settings*

Default Name	Default Value	Default Domain
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40E-TXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40E-TXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-TXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-TXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-TXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-TXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40E-TXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40E-TXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40E-TXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40E-TXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40E-TXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40E-TXP-C.otn.otnLines.G709OTN	Enable	Enable
40E-TXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40E-TXP-C.pmthresholds.client.ms.farend.15min.BBE	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.client.ms.farend.15min.EB	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.ms.farend.1day.BBE	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.client.ms.farend.1day.EB	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.ms.nearend.15min.BBE	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.client.ms.nearend.15min.EB	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.ms.nearend.1day.BBE	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.client.ms.nearend.1day.EB	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
40E-TXP-C.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40E-TXP-C.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
40E-TXP-C.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40E-TXP-C.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.ms.farend.15min.BBE	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.ms.farend.15min.EB	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.farend.1day.BBE	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.ms.farend.1day.EB	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.ms.nearend.15min.BBE	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.ms.nearend.15min.EB	340160 (count)	0 - 8850600
40E-TXP-C.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.ms.nearend.1day.BBE	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.ms.nearend.1day.EB	3401600 (count)	0 - 849657600
40E-TXP-C.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400

Table 33 ETSI 40E-TXP-C Card Default Settings

Default Name	Default Value	Default Domain
40E-TXP-C.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
40E-TXP-C.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
40E-TXP-C.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40E-TXP-C.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
40E-TXP-C.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
40E-TXP-C.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40E-TXP-C.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Table 34 lists the 40-WXC-C, 40-WSS-C, and 80-WXC-C card default settings.



Note 40-WXC-C, 40-WSS-C, and 80-WXC-C cards are supported on the Cisco ONS 15454 and Cisco ONS 15454 M6 platforms.

Table 34 ETSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Default Name	Default Value	Default Domain
WXC-80.config.card.WavelengthDrift	Disable	Disable; Enable
WXC-40.config.card.WavelengthDrift	Disable	Disable; Enable
WSS-40.config.card.WavelengthDrift	Disable	Disable; Enable

ETSI MS-ISC-100T Card Default Settings

Table 35 lists the MS-ISC-100T card default settings.



Note MS-ISC-100T cards are supported only on the Cisco ONS 15454 platform.

Table 35 MS-ISC-100T Card Default Settings

Default Name	Default Value	Default Domain
MS-ISC-100T.config.PreServiceAlarmSuppression	TRUE	TRUE, FALSE
MS-ISC-100T.config.SoakTime	00:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MS-ISC-100T.config.card.Mode	HDLC	HDLC, GFP-F, RPR 802.17
MS-ISC-100T.ios.consolePortAccess	TRUE	TRUE, FALSE

Table 35 MS-ISC-100T Card Default Settings

Default Name	Default Value	Default Domain
MS-ISC-100T.ios.radiusServerAccess	FALSE	TRUE, FALSE

ETSI MXP_2.5G_10E Card Default Settings

Table 36 lists the MXP_2.5G_10E card default settings.



Note MXP_2.5G_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 36 ETSI MXP_2.5G_10E Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10E.config.client.AisSquelchMode	Squelch	Ais, Squelch
MXP-2_5G-10E.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-2_5G-10E.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10E.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-2_5G-10E.config.client.SendDoNotUse	FALSE	TRUE, FALSE
MXP-2_5G-10E.config.client.SyncMsgIn	TRUE	FALSE, TRUE
MXP-2_5G-10E.config.client.TerminationMode	Transparent	Transparent, Regeneration Section
MXP-2_5G-10E.config.client.ppmPortAssignment	STM16	UNASSIGNED, STM16
MXP-2_5G-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-2_5G-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10E.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.11.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.11.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.11.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.11.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.11.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.11.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.11.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.12.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.12.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.12.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.12.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.12.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.12.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.12.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.13.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.13.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.13.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.13.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.13.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.13.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.otnLines.AsyncSynchMapping	ODU Multiplex	ODU Multiplex
MXP-2_5G-10E.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced
MXP-2_5G-10E.otn.otnLines.G709OTN	Enable	Enable

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table 36 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI MXP_2.5G_10G Card Default Settings

Table 37 lists the MXP_2.5G_10G card default settings.



Note MXP_2.5G_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 37 ETSI MXP_2.5G_10G Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-2_5G-10G.config.client.SendDoNotUse	FALSE	TRUE, FALSE
MXP-2_5G-10G.config.client.SyncMsgIn	TRUE	FALSE, TRUE
MXP-2_5G-10G.config.client.TerminationMode	Transparent	Transparent, Multiplex Section
MXP-2_5G-10G.config.client.ppmPortAssignment	STM16	UNASSIGNED, STM16
MXP-2_5G-10G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.11.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.11.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.11.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.11.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.11.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.11.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.11.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.12.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.12.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.12.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.12.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.12.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.12.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-2_5G-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
MXP-2_5G-10G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.EB	212600 (count)	0 - 212371200

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600

Table 37 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI MXP_MR_2.5G Card Default Settings

Table 38 lists the MXP_MR_2.5G card default settings.



Note MXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 38 ETSI MXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.card.Mode	FC_GE	FC_GE, MIXED, ESCON
MXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, ONE_GE, FC1G ISL, FC2G ISL, FICON1G ISL, FICON2G ISL when //.card.Mode FC_GE; UNASSIGNED, ONE_GE, ESCON, FC1G ISL, FICON1G ISL when //.card.Mode MIXED; UNASSIGNED, ESCON when //.card.Mode ESCON
MXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16, 32, 48 .. 1200
MXP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148, 2152, 2156, 2160, 2164, 2168, 2172
MXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-MR-2_5G.config.trunk.SendDoNotUse	FALSE	TRUE, FALSE
MXP-MR-2_5G.config.trunk.SyncMsgIn	TRUE	FALSE, TRUE
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.BBE	212600 (count)	0 - 212371200

Table 38 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI MXPP_MR_2.5G Card Default Settings

Table 39 lists the MXPP_MR_2.5G card default settings.



Note MXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 39 ETSI MXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.card.Mode	FC_GE	FC_GE, MIXED, ESCON
MXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, ONE_Ge, FC1G ISL, FC2G ISL, FICON1G ISL, FICON2G ISL when //card.Mode FC_Ge; UNASSIGNED, ONE_Ge, ESCON, FC1G ISL, FICON1G ISL when //card.Mode MIXED; UNASSIGNED, ESCON when //card.Mode ESCON
MXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXPP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXPP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16, 32, 48 .. 1200
MXPP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148, 2152, 2156, 2160, 2164, 2168, 2172

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXPP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 39 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.BBE	212600 (count)	0 - 212371200

Table 39 *ETSI MXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Table 40 lists the MXP_MR_10DME_C and MXP_MR_10DME_L card default settings.

**Note**

MXP_MR_10DME_C and MXP_MR_10DME_L cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.card.Mode	Port 1-8: FC_GE_ISC	Port 1-8: FC_GE_ISC, Port 1-4: FC_GE_ISC, Port 5-8: FC4G, Port 1-4: FC4G, Port 5-8: FC_GE_ISC, Port 1-8: FC4G
MXP-MR-10DME.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.client.ppmPortAssignment	UNASSIGNED ED	UNASSIGNED, ONE-GE, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC3 PEER 1G, ISC3 PEER 2G when //.card.Mode Port 1-8: FC_GE_ISC; UNASSIGNED, FC4G_PORT when //.card.Mode Port 1-8: FC4G; UNASSIGNED, ONE-GE, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, FC4G, ISC3 PEER 1G, ISC3 PEER 2G when //.card.Mode Port 1-4: FC_GE_ISC, Port 5-8: FC4G, Port 1-4: FC4G, Port 5-8: FC_GE_ISC
MXP-MR-10DME.config.client.ppmSlotAssignment	UNASSIGNED ED	UNASSIGNED, PPM (1 Port)
MXP-MR-10DME.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXP-MR-10DME.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-MR-10DME.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-MR-10DME.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-MR-10DME.config.trunk.SendDoNotUse	FALSE	FALSE, TRUE
MXP-MR-10DME.config.trunk.SyncMsgIn	TRUE	FALSE, TRUE
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 40 *ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)*

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.otnLines.AsyncSynchMapping	Synch Mapping	Synch Mapping
MXP-MR-10DME.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-MR-10DME.otn.otnLines.G709OTN	Enable	Disable, Enable
MXP-MR-10DME.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table 40 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI OTU2-XP Card Default Settings

Table 41 lists the OTU2-XP card default settings.



Note OTU2-XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.



Note NE default values for flow control and client distance parameters do not exist.

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.config.port.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
OTU2-XP.config.port.AisSquelchMode	Squelch	Ais; Squelch
OTU2-XP.config.port.OduTransparency	Cisco Extended Use	Transparent Standard Use; Cisco Extended Use
OTU2-XP.config.port.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.config.port.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
OTU2-XP.config.port.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; SDH; IB_5G; Transparent when ppmPortAssignment 10G Ethernet; 10G Fiber Channel
OTU2-XP.config.port.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SDH; 10G Ethernet; 10G Fiber Channel; IB_5G
OTU2-XP.config.port.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disable dfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhanc edfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.a larm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alar.m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alar.m.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alar.m.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alar.m.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alar.m.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15m.in.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15m.in.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15m.in.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15m.in.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15m.in.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.alar.m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.alar.m.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.alar.m.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.alar.m.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.11.disabledfec.alar.m.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.12.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.12.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.12.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarmin.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarmin.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarmin.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarmin.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarmin.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alar.m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alar.m.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alar.m.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alar.m.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alar.m.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhance dfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standard fec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ll1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.11.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.12.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600

Table 41 *ETSI OTU2-XP Card Default Settings*

Default Name	Default Value	Default Domain
OTU2-XP.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
OTU2-XP.otn.otnLines.G709OTN	Enable	Disable; Enable
OTU2-XP.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.pmthresholds.path.nearend.15min.BBE	25 (count)	0 - 2159100
OTU2-XP.pmthresholds.path.nearend.15min.EB	15 (count)	0 - 7200000
OTU2-XP.pmthresholds.path.nearend.15min.ES	12 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.15min.SES	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.15min.UAS	10 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.1day.BBE	250 (count)	0 - 207273600
OTU2-XP.pmthresholds.path.nearend.1day.EB	125 (count)	0 - 691200000
OTU2-XP.pmthresholds.path.nearend.1day.ES	100 (seconds)	0 - 86400
OTU2-XP.pmthresholds.path.nearend.1day.SES	7 (seconds)	0 - 86400

Table 41 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.path.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI SMR Card Default Settings

Table 42 lists the SMR card default settings.



Note 40-SMR1-C and 40-SMR2-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 42 ETSI SMR Card Default Settings

Default Name	Default Value	Default Name
SMR1-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR1-40.config.card.WavelengthDrift	Disable	Disable; Enable
SMR2-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR2-40.config.card.WavelengthDrift	Disable	Disable; Enable

ETSI TNC Card Default Settings

Table 43 lists the TNC card default settings.



Note TNC cards are supported on the Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 43 ETSI TNC Card Default Settings

Default Name	Default Value	Default Domain
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.ge.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.stm1.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.opticalthresholds.1gethernet.cwdm.15min.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.15min.HighRxPower	-9.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.15min.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.15min.LowRxPower	-29.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.15min.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.1day.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighRxPower	-9.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.LowRxPower	-29.0	-40.0; -39.9; -39.8 .. HighRxPower

Table 43 ETSI TNC Card Default Settings (continued)

Default Name	Default Value	Default Domain
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.opticalthresholds.1gethernet.cwdm.1day.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighRxPower	-6.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighTxPower	8.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowRxPower	-32.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowTxPower	-3.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.15min.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.15min.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.15min.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.15min.LowRxPower	-34.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.15min.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.1day.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.1day.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.LowRxPower	-34.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.1day.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.alarm.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighRxPower	-4.5	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighTxPower	7.5	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.LowRxPower	-36.5	-40.0; -39.9; -39.8 .. HighRxPower

Table 43 ETSI TNC Card Default Settings (continued)

Default Name	Default Value	Default Domain
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.opticalthresholds.fastethernet.lx.alarm.LowTxPower	-2.5	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.15min.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.LowRxPower	-43.0	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.15min.LowTxPower	-5.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.1day.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.LowRxPower	-43.0	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.1day.LowTxPower	-5.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighRxPower	-4.5	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighTxPower	7.5	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.LowRxPower	-45.5	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.LowTxPower	-1.5	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.12.15min.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.stm1.12.15min.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.12.15min.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.12.15min.LowRxPower	-34.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.stm1.12.15min.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.12.1day.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0

Table 43 ETSI TNC Card Default Settings (continued)

Default Name	Default Value	Default Domain
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.opticalthresholds.stm1.l2.1day.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.l2.1day.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.l2.1day.LowRxPower	-34.0	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.stm1.l2.1day.LowTxPower	-6.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.l2.alarm.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.stm1.l2.alarm.HighRxPower	-4.5	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.l2.alarm.HighTxPower	7.5	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.l2.alarm.LowRxPower	-36.5	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.stm1.l2.alarm.LowTxPower	-2.5	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.ulh.15min.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.stm1.ulh.15min.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.15min.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.15min.LowRxPower	-43.0	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.stm1.ulh.15min.LowTxPower	-5.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.ulh.1day.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.stm1.ulh.1day.HighRxPower	-7.0	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.1day.HighTxPower	11.0	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.1day.LowRxPower	-43.0	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.stm1.ulh.1day.LowTxPower	-5.0	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.stm1.ulh.alarm.HighLaserBias	98.0	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.stm1.ulh.alarm.HighRxPower	-4.5	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.alarm.HighTxPower	7.5	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.stm1.ulh.alarm.LowRxPower	-45.5	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.stm1.ulh.alarm.LowTxPower	-1.5	-40.0; -39.9; -39.8 .. HighTxPower
TNC.pmtthresholds.ms.farend.15min.BBE	1312	0 - 137700
TNC.pmtthresholds.ms.farend.15min.EB	1312	0 - 900
TNC.pmtthresholds.ms.farend.15min.ES	87	0 - 72
TNC.pmtthresholds.ms.farend.15min.SES	1	0 - 900

Table 43 ETSI TNC Card Default Settings (continued)

Default Name	Default Value	Default Domain
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.pmthresholds.ms.farend.15min.UAS	3	0 - 900
TNC.pmthresholds.ms.farend.1day.BBE	13120	0 - 13219200
TNC.pmthresholds.ms.farend.1day.EB	13120	0 - 86400
TNC.pmthresholds.ms.farend.1day.ES	864	0 - 6912
TNC.pmthresholds.ms.farend.1day.SES	4	0 - 86400
TNC.pmthresholds.ms.farend.1day.UAS	10	0 - 86400
TNC.pmthresholds.ms.nearend.15min.BBE	1312	0 - 137700
TNC.pmthresholds.ms.nearend.15min.EB	1312	0 - 900
TNC.pmthresholds.ms.nearend.15min.ES	87	0 - 72
TNC.pmthresholds.ms.nearend.15min.SES	1	0 - 900
TNC.pmthresholds.ms.nearend.15min.UAS	3	0 - 900
TNC.pmthresholds.ms.nearend.1day.BBE	13120	0 - 13219200
TNC.pmthresholds.ms.nearend.1day.EB	13120	0 - 86400
TNC.pmthresholds.ms.nearend.1day.ES	864	0 - 6912
TNC.pmthresholds.ms.nearend.1day.SES	4	0 - 86400
TNC.pmthresholds.ms.nearend.1day.UAS	10	0 - 86400
TNC.pmthresholds.rs.nearend.15min.BBE	10000	0 - 138600
TNC.pmthresholds.rs.nearend.15min.EB	10000	0 - 900
TNC.pmthresholds.rs.nearend.15min.ES	500	0 - 900
TNC.pmthresholds.rs.nearend.15min.OFS	500	0 - 900
TNC.pmthresholds.rs.nearend.15min.SES	500	0 - 13305600
TNC.pmthresholds.rs.nearend.15min.UAS	3	0 - 86400
TNC.pmthresholds.rs.nearend.1day.BBE	100000	0 - 86400
TNC.pmthresholds.rs.nearend.1day.EB	100000	0 - 86400
TNC.pmthresholds.rs.nearend.1day.ES	5000	0 - 6912
TNC.pmthresholds.rs.nearend.1day.OFS	5000	0 - 86400
TNC.pmthresholds.rs.nearend.1day.SES	5000	0 - 86400
TNC.pmthresholds.rs.nearend.1day.UAS	10	0 - 86400

ETSI TXP-MR-10E Card Default Settings

Table 44 lists the TXP-MR-10E card default settings.

**Note**

TXP-MR-10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
TXP-MR-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
TXP-MR-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.config.client.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; SDH; IB_5G; Transparent when ppmPortAssignment 10G Ethernet; 10G Fiber Channel
TXP-MR-10E.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SDH; 10G Ethernet; 10G Fiber Channel; IB_5G
TXP-MR-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	6.0; 6.1; 6.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
TXP-MR-10E.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.11.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.11.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.11.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.11.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.11.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.12.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.12.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.12.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.12.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.12.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.12.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.12.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.13.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.15.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.15.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.15.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.15.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.15.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.p111.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p111.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p111.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias		
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.otnLines.AsynchSynchMapping	Synch Mapping	Asynch mapping; Synch Mapping
TXP-MR-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10E.otn.otnLines.G709OTN	Enable	Disable; Enable
TXP-MR-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.pmthresholds.client.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 764899200

Table 44 ETSI TXP-MR-10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200

Table 44 *ETSI TXP-MR-10E Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI TXP_MR_10G Card Default Settings

Table 45 lists the TXP_MR_10G card default settings.



Note TXP_MR_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 45 *ETSI TXP_MR_10G Card Default Settings*

Default Name	Default Value	Default Domain
TXP-MR-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 300
TXP-MR-10G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-10G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when mrPortAssignment UNASSIGNED, SDH; Transparent when mrPortAssignment 10G Ethernet
TXP-MR-10G.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED, SDH, 10G Ethernet

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 45 *ETSI TXP_MR_10G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.feethresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10G.otn.feethresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10G.otn.feethresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10G.otn.feethresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-10G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.pmthresholds.client.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.client.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table 45 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI TXP_MR_2.5G Card Default Settings

Table 46 lists the TXP_MR_2.5G card default settings.



Note TXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 46 ETSI TXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when ppmPortAssignment UNASSIGNED, STM1, STM4, STM16; Transparent when ppmPortAssignment STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
TXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.11.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.15min.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.11.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.11.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.1day.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.11.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.11.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.I1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.12.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.12.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.12.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.12.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm1.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm1.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm1.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm1.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm16.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm16.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm16.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm16.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm4.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm4.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm4.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm4.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-2_5G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.BBE	10000 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.BBE	10000 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.BBE	10000 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400

Table 46 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI TXPP_MR_2.5G Card Default Settings

Table 47 lists the TXPP_MR_2.5G card default settings.



Note TXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 47 ETSI TXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when ppmPortAssignment UNASSIGNED, STM1, STM4, STM16; Transparent when ppmPortAssignment STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
TXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 *ETSI TXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 *ETSI TXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lrl.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 *ETSI TXPP_MR_2.5G Card Default Settings (continued)*

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.11.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.12.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.11.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.12.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.11.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.12.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm1.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm1.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.stm1.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm1.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm16.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm16.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.stm16.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm16.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm4.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm4.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.fecthresholds.stm4.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm4.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXPP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXPP-MR-2_5G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.BBE	10000 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.BBE	10000 (count)	0 - 212371200

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900

Table 47 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.BBE	10000 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI GE_XP Card Default Settings

Table 48 lists the GE_XP card default settings.



Note GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.config.card.Mode	10GE MXP	20GE MXP; 10GE MXP; L2 over DWDM
XP-GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.client.E1.LineCoding	HDB3	HDB3; AMI
XP-GE.config.client.E1.LineType	Framed	Unframed; Framed
XP-GE.config.client.FlowControl	OFF	OFF; ON
XP-GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.client.Speed	Auto	10 Mbps; 100 Mbps; 1000 Mbps; Auto

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.config.client.cEtherType	8100 (Hex)	0 - 65535
XP-GE.config.client.macLearningState	OFF	OFF; ON
XP-GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-GE.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE-GE; FE
XP-GE.config.client.sEtherType	8100 (Hex)	0 - 65535
XP-GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN; DSCP
XP-GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.trunk.FlowControl	OFF	OFF; ON
XP-GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-GE.config.trunk.cEtherType	8100 (Hex)	0 - 65535
XP-GE.config.trunk.macLearningState	OFF	OFF; ON
XP-GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-GE.config.trunk.sEtherType	8100 (Hex)	0 - 65535
XP-GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN; DSCP
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighRxPower	-5.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighTxPower	-5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowRxPower	-30.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowTxPower	-17.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowRxPower	-33.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowTxPower	-21.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable

Table 48 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

ETSI 10GE_XP Card Default Settings

Table 49 lists the 10GE_XP card default settings.



Note 10GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 49 ETSI 10GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-10GE.config.card.Mode	10GE TXP	10GE TXP; L2 over DWDM
XP-10GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-10GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-10GE.config.client.FlowControl	OFF	OFF; ON
XP-10GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.client.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.client.cEtherType	8100 (Hex)	0 - 65535
XP-10GE.config.client.macLearningState	OFF	OFF; ON
XP-10GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-10GE.config.client.sEtherType	8100 (Hex)	0 - 65535
XP-10GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN; DSCP
XP-10GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-10GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-10GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.config.trunk.FlowControl	OFF	OFF; ON
XP-10GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.trunk.cEtherType	8100 (Hex)	0 - 65535
XP-10GE.config.trunk.macLearningState	OFF	OFF; ON
XP-10GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-10GE.config.trunk.sEtherType	8100 (Hex)	0 - 65535
XP-10GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN; DSCP
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhance dfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standar dfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1 5min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alar m.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alar m.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15 min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15 min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15 min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15 min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15 min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1da y.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1da y.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1da y.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1da y.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1da y.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alar m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alar m.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alar m.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alar m.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alar m.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15mi n.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15mi n.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15mi n.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15mi n.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15mi n.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day .HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day .HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day .HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day .LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day .LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alar m.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alar m.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alar m.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alar m.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alar m.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min .HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min .HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min .HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min .LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min .LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day. HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day. HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day. HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day. LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day. LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table 49 ETSI 10GE_XP Card Default Settings (*continued*)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72

Table 49 ETSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-10GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-10GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

ETSI OSCM Card Default Settings

Table 50 lists the OSCM card default settings.



Note OSCM cards are supported only on the Cisco ONS 15454 platform.

Table 50 *ETSI OSCM Card Default Settings*

Default Name	Default Value	Default Domain
OSCM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSCM.pmthresholds.ms.farend.15min.BBE	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.farend.15min.EB	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.farend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.1day.BBE	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.farend.1day.EB	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.farend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.ms.farend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.15min.BBE	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.nearend.15min.EB	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.nearend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.nearend.1day.EB	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.15min.BBE	10000 (count)	0 - 138600
OSCM.pmthresholds.rs.nearend.15min.EB	10000 (count)	0 - 138600
OSCM.pmthresholds.rs.nearend.15min.ES	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.OFS	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.SES	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
OSCM.pmthresholds.rs.nearend.1day.EB	100000 (count)	0 - 13305600
OSCM.pmthresholds.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.1day.OFS	5000 (seconds)	0 - 86400

Table 50 ETSI OSCM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSCM.pmthresholds.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI OSC-CSM Card Default Settings

Table 51 lists the OSC-CSM card default settings.



Note OSC-CSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 51 ETSI OSC-CSM Card Default Settings

Default Name	Default Value	Default Domain
OSC_CSM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSC_CSM.pmthresholds.ms.farend.15min.BBE	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.farend.15min.EB	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.farend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.1day.BBE	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.farend.1day.EB	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.farend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.farend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.15min.BBE	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.nearend.15min.EB	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.nearend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.nearend.1day.EB	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.15min.BBE	10000 (count)	0 - 138600
OSC_CSM.pmthresholds.rs.nearend.15min.EB	10000 (count)	0 - 138600
OSC_CSM.pmthresholds.rs.nearend.15min.ES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.15min.OFS	500 (seconds)	0 - 900

Table 51 ETSI OSC-CSM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSC_CSM.pmthresholds.rs.nearend.15min.SES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
OSC_CSM.pmthresholds.rs.nearend.1day.EB	100000 (count)	0 - 13305600
OSC_CSM.pmthresholds.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.1day.OFS	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

ETSI Amplifier Card Default Settings

Table 52 lists the OPT-BST, OPT-AMP-17-C, and OPT-BST-L card default settings.



Note The OPT-BST-L card is supported only on the Cisco ONS 15454 platform. The OPT-BST and OPT-AMP cards are supported on the Cisco ONS 15454 , Cisco ONS 15454 M2, and Cisco ONS 15454 M6 platforms.

Table 52 ETSI Amplifier Card Default Settings

Default Name	Default Value	Default Domain
OPT-AMP-17-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST-L.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST.config.card.AlsMode	Auto Restart	Disabled, Auto Restart

ETSI EDFA Card Default Settings

Table 25 lists the OPT-EDFA-17 card default settings.



Note EDFA cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table 53 ETSI EDFA Card Default Settings

Default Name	Default Value	Default Domain
OPT-EDFA-17.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
OPT-EDFA-24.config.card.AlsMode	Auto Restart	Disabled; Auto Restart

ETSI Node Default Settings

[Table 54 on page 1185](#) lists the Cisco ONS 15454 node-level default settings for the ETSI shelf assembly. Cisco provides the following types of user-configurable defaults for each Cisco ONS 15454 node:



The node default settings described in this section are supported on the Cisco ONS 15454, Cisco ONS 15454 M6, Cisco ONS 15454 M2 platforms, unless noted otherwise.

- Circuit settings—Set the administrative state, subnetwork connection protection (SNCP) circuit threshold levels for signal degradation and failure, SNCP reversion time, and whether SNCP circuits are revertive by default.
- General settings—Set general node management defaults, including whether to use Daylight Savings Time (DST), the IP address of the NTP/SNTP server to be used, the time zone where the node is located, the SD path BER value, whether automatic autonomous TL1 reporting of PM data is enabled for cross-connect paths on the node, whether or not to allow ports to be disabled when they are providing services (when the default is set to FALSE users must remove or disable the services first, then put the ports out of service), and the defaults description.
- Link Management Protocol settings—Set link management protocol data link type, traffic engineering link, and general settings.
- Power Monitor settings—Set default voltage thresholds for the node.
- Network settings—Set whether to prevent display of node IP addresses in CTC (applicable for all users except Superusers); default gateway node type; whether to raise an alarm when the backplane LAN cable is disconnected; and whether to display the IP address in the LCD in an editable mode (in which you can change the IP address directly from LCD screen), to display the IP address on the LCD as read-only, or to suppress display of the IP on the LCD entirely.
- OSI settings—Set the Open System Interconnection (OSI) main setup, generic routing encapsulation (GRE) tunnel default, the link access protocol on the D channel (LAP-D), the router subnet, and the TID address resolution protocol (TARP) settings.
- Linear Multiplex Section Protection (LMSP) settings—Set whether or not protected circuits have bidirectional switching, are revertive, and what the reversion time is.
- MS-SPRing protection settings—Set whether MS-SPRing-protected circuits are revertive, and what the reversion time is, at both the ring and span levels.
- Y Cable protection settings—Set whether Y-cable protected circuits are revertive, and what the reversion time is.
- Splitter protection settings—Set whether splitter protected circuits are revertive, and what the reversion time is.
- Legal Disclaimer—Set the legal disclaimer that warns users at the login screen about the possible legal or contractual ramifications of accessing equipment, systems, or networks without authorization.
- Security Grant Permissions—Set default user security levels for activating/reverting software, PM data clearing, database restoring, and retrieving audit logs.
- Security DataComm settings—Set default security settings for TCC Ethernet IP address and IP netmask, and CTC backplane IP suppression; set secure mode on and secure mode locked (for TCC2P cards only).

- Security Access settings—Set default security settings for LAN access, shell access, serial craft access, element management system (EMS) access (including Internet Inter-Object Request Broker Protocol [IIOP] listener port number), TL1 access, and SNMP access.
- Security RADIUS settings—Set default RADIUS server settings for the accounting port number and the authentication port number, and whether to enable the node as a final authenticator.
- Security Policy settings—Set the allowable failed logins before lockout, idle user timeout for each user level, optional lockout duration or manual unlock enabled, password reuse and change frequency policies, number of characters difference that is required between the old and new password, password aging by security level, enforced single concurrent session per user, and option to disable inactive user after a set inactivity period.
- Security Password settings—Set when passwords can be changed, how many characters they must differ by, whether or not password reuse is allowed, and whether a password change is required on first login to a new account; set password aging enforcement and user-level specific aging and warning periods; set how many consecutive identical characters are allowed in a password, maximum password length, minimum password length, minimum number and combination of nonalphabetical characters required, and whether or not to allow a password that is a reversal of the login ID associated with the password.
- BITS Timing settings—Set the AIS threshold, Admin synchronization status messaging (SSM), coding, facility type, framing, state, and Sa bit (the overhead bit that will carry the SSM) for building integrated timing supply 1 (BITS-1) and BITS2 timing.
- General Timing settings—Set the mode (External, Line, or Mixed), revertive, and reversion time.

**Note**

Any node level defaults changed using the **Provisioning > Defaults** tab, changes existing node level provisioning. Although this is service affecting, it depends on the type of defaults changed, for example, general, and all timing and security attributes. The “Changing default values for some node level attributes overrides the current provisioning.” message is displayed. The Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) explains the effect of changing the default values. However, when the card level defaults are changed using the **Provisioning > Defaults** tab, existing card provisioning remains unaffected.

**Note**

For more information about each individual node setting, see the chapter “Manage the Node” in the *Cisco ONS 15454 DWDM Configuration Guide*.

**Note**

For information about the CTC-level default settings for the Cisco ONS 15454, see the [CTC Default Settings, page 611](#).

Table 54 ETSI Node Default Settings

Default Name	Default Value	Default Domain
NODE.circuits.State	unlocked, automaticInService	unlocked, locked, disabled, locked, maintenance, unlocked, automaticInService
NODE.circuits.sncp.HO_SDBER	1E-6	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.circuits.sncp.HO_SFBER	1E-4	1E-3, 1E-4, 1E-5
NODE.circuits.sncp.LO_SDBER	1E-6	1E-5, 1E-6, 1E-7, 1E-8
NODE.circuits.sncp.LO_SFBER	1E-4	1E-3, 1E-4, 1E-5
NODE.circuits.sncp.ProvisionWorkingGoAndReturnOnPrimaryPath	FALSE	TRUE, FALSE
NODE.circuits.sncp.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.circuits.sncp.Revertive	FALSE	TRUE, FALSE
NODE.general.AllowServiceAffectingPortChangeToDisabled	TRUE	FALSE, TRUE
NODE.general.AutoPM (only Cisco ONS 15454)	FALSE	FALSE, TRUE
NODE.general.BackupNtpSntpServer (only Cisco ONS 15454)	0.0.0.0	IP Address
NODE.general.DefaultsDescription	Factory Defaults	Free form field
NODE.general.NtpSntpServer	0.0.0.0	IP Address
NODE.general.ReportLoopbackConditionsOnLocked,MaintenancePorts	FALSE	FALSE, TRUE
NODE.general.TimeZone	(GMT-08:00) Pacific Time (US & Canada), Tijuana	(For applicable time zones, see Table 27 on page 609.)
NODE.general.UseDST	TRUE	TRUE, FALSE
NODE.general.mvAirFilterBasedFanEnable (only Cisco ONS 15454 M6)	FALSE	TRUE, FALSE
NODE.lmp.controlChannel.AdminState	locked, disabled	unlocked, locked, disabled

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.HelloDeadInterval	12000 (ms)	maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)), maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 1, maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 2 .. minimum_of(20000,MaxHelloDeadInterval)
NODE.lmp.controlChannel.HelloInterval	500 (ms)	maximum_of(300,MinHelloInterval), maximum_of(300,MinHelloInterval) + 1, maximum_of(300,MinHelloInterval) + 2 .. minimum_of(500,MaxHelloInterval,quotient_of(HelloDeadInterval,3))
NODE.lmp.controlChannel.MaxHelloDeadInterval	20000 (ms)	maximum_of(2000>HelloDeadInterval,sum_of(MaxHelloInterval,1)), maximum_of(2000>HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 1, maximum_of(2000>HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 2 .. 20000

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.MaxHelloInterval	2000 (ms)	maximum_of(300,HelloInterval), maximum_of(300,HelloInterval) + 1, maximum_of(300,HelloInterval) + 2 .. minimum_of(5000,difference_of(MaxHelloDeadInterval,1))
NODE.lmp.controlChannel.MinHelloDeadInterval	2000 (ms)	maximum_of(2000,sum_of(MinHelloInterval,1)), maximum_of(2000,sum_of(MinHelloInterval,1)) + 1, maximum_of(2000,sum_of(MinHelloInterval,1)) + 2 .. minimum_of(20000>HelloDeadInterval)
NODE.lmp.controlChannel.MinHelloInterval	300 (ms)	300, 301, 302 .. minimum_of(5000>HelloInterval, difference_of(MinHelloDeadInterval,1))
NODE.lmp.dataLink.Type	Port	Port, Component
NODE.lmp.general.Allowed	TRUE	FALSE, TRUE
NODE.lmp.general.Enabled	FALSE	FALSE, TRUE when Allowed TRUE; FALSE when Allowed FALSE
NODE.lmp.general.LMP-WDM	TRUE	FALSE, TRUE
NODE.lmp.general.Role	OLS	PEER, OLS
NODE.lmp.teLink.AdminState	locked, disabled	unlocked, locked, disabled
NODE.lmp.teLink.DWDM	TRUE	FALSE, TRUE

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.teLink.MuxCapability	Lambda Switch	Packet Switch - Level 1, Packet Switch - Level 2, Packet Switch - Level 3, Packet Switch - Level 4, Layer 2 Switch, TDM Cross-connect, Lambda Switch, Fiber Switch
NODE.network.general.AlarmMissingBackplaneLAN	FALSE	TRUE, FALSE
NODE.network.general.CtcIpDisplaySuppression	FALSE	TRUE, FALSE
NODE.network.general.GatewaySettings (only Cisco ONS 15454 and Cisco ONS 15454)	None	LeaveAsIs, None, ENE, GNE, ProxyOnlyNode
NODE.network.general.GatewaySettings (only Cisco ONS 15454 M2)	GNE	LeaveAsIs, None, ENE, GNE, ProxyOnlyNode
NODE.network.general.LcdSetting	Allow Configuration	Allow Configuration, Display Only, Suppress Display
NODE.osi.greTunnel.OspfCost	110	110 - 65535
NODE.osi.greTunnel.SubnetMask	24 (bits)	8, 9, 10 .. 32
NODE.osi.lapd.MTU	512	512, 513, 514 .. 1500
NODE.osi.lapd.Mode	AITS	AITS, UITS
NODE.osi.lapd.Role	Network	Network, User
NODE.osi.lapd.T200	200 (ms)	200, 300, 400 .. 20000
NODE.osi.lapd.T203	10000 (ms)	4000, 4100, 4200 .. 120000
NODE.osi.mainSetup.L1L2LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.L1LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.NodeRoutingMode	Intermediate System Level 1	End System, Intermediate System Level 1, Intermediate System Level 1/Level 2

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.osi.subnet.DISPriority	63	1, 2, 3 .. 127
NODE.osi.subnet.ESH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.GCCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.IIH	3 (sec)	1, 2, 3 .. 600
NODE.osi.subnet.ISH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.LANISISCost	20	1, 2, 3 .. 63
NODE.osi.subnet.LDCCISISCost	40	1, 2, 3 .. 63
NODE.osi.subnet.OSCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.SDCCISISCost	60	1, 2, 3 .. 63
NODE.osi.tarp.L1DataCache	TRUE	FALSE, TRUE
NODE.osi.tarp.L2DataCache	FALSE	FALSE, TRUE
NODE.osi.tarp.LANStormSuppression	TRUE	FALSE, TRUE
NODE.osi.tarp.LDB	TRUE	FALSE, TRUE
NODE.osi.tarp.LDBEntry	5 (min)	1 - 10
NODE.osi.tarp.LDBFlush	5 (min)	0 - 1440
NODE.osi.tarp.PDUsL1Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsL2Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsOrigination	TRUE	FALSE, TRUE
NODE.osi.tarp.T1Timer	15 (sec)	0 - 3600
NODE.osi.tarp.T2Timer	25 (sec)	0 - 3600
NODE.osi.tarp.T3Timer	40 (sec)	0 - 3600
NODE.osi.tarp.T4Timer	20 (sec)	0 - 3600
NODE.osi.tarp.Type4PDUDelay	0 (sec)	0 - 255
NODE.powerMonitor.EHIBATVG_48V (only Cisco 15454)	-56.5 (Vdc)	-40.5, -41.0, -41.5 .. -57.0
NODE.powerMonitor.EHIBATVG_60V (only Cisco 15454)	-72.0	-50.0, -50.5, -51.0 .. -72.0
NODE.powerMonitor.ELWBATVG_60V(only Cisco 15454)	-50.5 (Vdc)	-50.0, -50.5, -51.0 .. -72.0
NODE.powerMonitor.HIBATVG_48V(only Cisco 15454)	-40.5 (Vdc)	-40.5, -41.0, -41.5 .. -56.5
NODE.powerMonitor.EHIBATVG (only Cisco 15454 M6)	-56.5 (Vdc)	-40.5, -41.0, -41.5 .. -57.0
NODE.powerMonitor.ELWBATVG (only Cisco 15454 M6)	-40.5 (Vdc)	-40.5, -41.0, -41.5 .. -56.5
NODE.powerMonitor.HIBATVG (only Cisco 15454 M6)	-54.0 (Vdc)	-50.0, -50.5, -51.0 .. -72.0

Table 54 *ETSI Node Default Settings (continued)*

Default Name	Default Value	Default Domain
NODE.powerMonitor.LWBATVG (only Cisco 15454 M6)	-44.0 (Vdc)	-40.5, -41.0, -41.5 .. -56.5
NODE.protection.lmsp.BidirectionalSwitching	FALSE	TRUE, FALSE
NODE.protection.lmsp.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.lmsp.Revertive	FALSE	TRUE, FALSE
NODE.protection.msspr.RingReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.msspr.RingRevertive	TRUE	TRUE, FALSE
NODE.protection.msspr.SpanReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.msspr.SpanRevertive	TRUE	TRUE, FALSE
NODE.protection.splitter.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.splitter.Revertive	FALSE	TRUE, FALSE
NODE.protection.yable.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.yable.Revertive	FALSE	TRUE, FALSE
NODE.security.dataComm.CtcBackplaneIpDisplaySuppression (only Cisco ONS 15454)	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.CtcBackplaneIpDisplaySuppression (only Cisco ONS 15454 M6)	TRUE	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.DefaultTCCEthernetIP	10.0.0.1	IP Address
NODE.security.dataComm.DefaultTCCEthernetIPNetmask	24 (bits)	8, 9, 10 .. 32
NODE.security.dataComm.LcdBackplaneIpSetting (only Cisco ONS 15454)	NOT SUPPORTED	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.dataComm.LcdBackplaneIpSetting (only Cisco ONS 15454 M6)	Display Only	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.SecureModeLocked (only Cisco ONS 15454)	NOT SUPPORTED	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE
NODE.security.dataComm.SecureModeLocked (only Cisco ONS 15454 M6)	FALSE	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE
NODE.security.dataComm.SecureModeOn (May reboot node) (only Cisco ONS 15454)	NOT SUPPORTED	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE

Table 54 *ETSI Node Default Settings (continued)*

Default Name	Default Value	Default Domain
NODE.security.dataComm.SecureModeOn (only Cisco ONS 15454 M6)	FALSE	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE
NODE.security.dataComm.isSecureModeSupportedOnControlCard	TRUE	FALSE, TRUE
NODE.security.emsAccess.AccessState	NonSecure	NonSecure, Secure
NODE.security.emsAccess.IIOPListenerPort (May reboot node)	57790 (port #)	0 - 65535
NODE.security.grantPermission.ActivateRevertSoftware	Superuser	Provisioning, Superuser
NODE.security.grantPermission.PMClearingPrivilege	Provisioning	Provisioning, Superuser
NODE.security.grantPermission.RestoreDB	Superuser	Provisioning, Superuser
NODE.security.grantPermission.RetrieveAuditLog	Superuser	Provisioning, Superuser
NODE.security.idleUserTimeout.Maintenance	01:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Provisioning	00:30 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Retrieve	00:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Superuser	00:15 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.lanAccess.LANAccess (May disconnect CTC from node) only Cisco ONS 15454)	Front & Backplane	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.LANAccess (only Cisco ONS 15454 M2)	Front & EMS	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.LANAccess (only Cisco ONS 15454 M6)	Front Craft & EMS	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.RestoreTimeout	5 (minutes)	0 - 60

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.CableType	120 ohm	75 ohm, 120 ohm
NODE.timing.bits-2.CableType	120 ohm	75 ohm, 120 ohm
NODE.security.legalDisclaimer.LoginWarningMessage	<html><center>WARNING</center>This system is restricted to authorized users for business purposes. Unauthorized access is a violation of the law. This service may be monitored for administrative and security reasons. By proceeding, you consent to this monitoring.	Free form field
NODE.security.other.DisableInactiveUser	FALSE	FALSE, TRUE
NODE.security.other.InactiveDuration	45 (days)	1, 2, 3 .. 99 when nothing TRUE; 45 when nothing FALSE
NODE.security.other.PreventInactiveSuperuserDisable	FALSE	TRUE, FALSE
NODE.security.other.SingleSessionPerUser	FALSE	TRUE, FALSE
NODE.security.passwordAging.EnforcePasswordAging	FALSE	TRUE, FALSE
NODE.security.passwordAging.maintenance.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.maintenance.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.provisioning.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.provisioning.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.retrieve.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.retrieve.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.superuser.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.superuser.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordChange.CannotChangeNewPassword	FALSE	TRUE, FALSE

Table 54 *ETSI Node Default Settings (continued)*

Default Name	Default Value	Default Domain
NODE.security.passwordChange.CannotChangeNewPasswordForNDays	20 (days)	20 - 95
NODE.security.passwordChange.NewPasswordMustDifferFromOldByNCharacters	1 (characters)	1 - 5
NODE.security.passwordChange.PreventReusingLastNPasswords	1 (times)	1 - 10
NODE.security.passwordChange.RequirePasswordChangeOnFirstLoginToNewAccount	FALSE	TRUE, FALSE
NODE.security.passwordComplexity.IdenticalConsecutiveCharactersAllowed	3 or more	0-2, 3 or more
NODE.security.passwordComplexity.MaximumLength	20	20, 80
NODE.security.passwordComplexity.MinimumLength	6	6, 8, 10, 12
NODE.security.passwordComplexity.MinimumRequiredCharacters	1 num, 1 letter & 1 TL1 special	1 num, 1 letter & 1 TL1 special, 1 num, 1 letter & 1 special, 2 each of any 2 of num, upper, lower & TL1 special, 2 each of any 2 of num, upper, lower & special
NODE.security.passwordComplexity.ReverseUserIdAllowed	TRUE	TRUE, FALSE
NODE.security.radiusServer.AccountingPort	1813 (port)	0 - 32767
NODE.security.radiusServer.AuthenticationPort	1812 (port)	0 - 32767
NODE.security.radiusServer.EnableNodeAsFinalAuthenticator	TRUE	FALSE, TRUE
NODE.security.serialCraftAccess.EnableCraftPort	TRUE	TRUE, FALSE
NODE.security.shellAccess.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.shellAccess.EnableShellPassword	FALSE	TRUE, FALSE
NODE.security.shellAccess.TelnetPort	23	23 - 9999
NODE.security.snmpAccess.AccessState	NonSecure	Disabled, NonSecure
NODE.security.tl1Access.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.userLockout.FailedLoginsAllowedBeforeLockout	5 (times)	0 - 10
NODE.security.userLockout.LockoutDuration	00:30 (mins:secs)	00:00, 00:05, 00:10 .. 10:00
NODE.security.userLockout.ManualUnlockBySuperuser	FALSE	TRUE, FALSE
NODE.software.AllowDelayedUpgrades	FALSE	FALSE, TRUE

Table 54 ETSI Node Default Settings (continued)

Default Name		Default Value	Default Domain
NODE.software.DefaultDelayedUpgrades		FALSE	FALSE, TRUE when AllowDelayedU pgrades TRUE; FALSE when AllowDelayedU pgrades FALSE
NODE.timing.bits-1.AISThreshold	DUS		G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-1.AdminSSMIn	STU		G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-1.Coding	HDB3		HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-1.CodingOut	HDB3		HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-1.FacilityType	E1		E1, 64kHz+8kHz, 2MHz
NODE.timing.bits-1.FacilityTypeOut	E1		E1, 6MHz, 2MHz

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.Framing	FAS+CAS+C RC	FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed, Unframed - 2Mhz when FacilityType 64kHz+8kHz
NODE.timing.bits-1.FramingOut	FAS+CAS+C RC	FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed, Unframed - 2Mhz when FacilityTypeOut 6MHz
NODE.timing.bits-1.SaBit	4	4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-1.State	unlocked	unlocked, locked, disabled
NODE.timing.bits-1.StateOut	unlocked	unlocked, locked, disabled

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.AISThreshold	DUS	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-2.AdminSSMIn	STU	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-2.Coding	HDB3	HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-2.CodingOut	HDB3	HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-2.FacilityType	E1	E1, 64kHz+8kHz, 2MHz
NODE.timing.bits-2.FacilityTypeOut	E1	E1, 6MHz, 2MHz

Table 54 *ETSI Node Default Settings (continued)*

Default Name	Default Value	Default Domain
NODE.timing.bits-2.Framing	FAS+CAS+C RC	FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed, Unframed - 2Mhz when FacilityType 64kHz+8kHz
NODE.timing.bits-2.FramingOut	FAS+CAS+C RC	FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC , FAS, Unframed, Unframed - 2Mhz when FacilityTypeOut 6MHz
NODE.timing.bits-2.SaBit	4	4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-2.State	unlocked	unlocked, locked, disabled
NODE.timing.bits-2.StateOut	unlocked	unlocked, locked, disabled

Table 54 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.general.Mode	External	External, Line, Mixed
NODE.timing.general.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.timing.general.Revertive	FALSE	TRUE, FALSE

