



Restrictions and Limitations

- IPsec is not supported in Cisco IOS XE Everest 16.6.1 release.
- In-Service Software Upgrade (ISSU) is not supported in the Cisco IOS XE Everest 16.6.1 release.
- The **ip cef accounting** command is *not* supported on the router.
- Crash may be observed on the router when:
 - EoMPLS, CEM, ATM and IMA Pseudowire Redundancy (PW-redundancy) configurations exist while switchover and fail-back of the pseudowires are being triggered, and the **show platform hardware pp active pw eompls** command is executed.
- Configuration sync does *not* happen on the Standby RSP when the active RSP has Cisco Software Licensing configured, and the standby RSP has Smart Licensing configured on the router. If the active RSP has Smart Licensing configured, the state of the standby RSP is undetermined. The state could be pending or authorized as the sync between the RSP modules is not performed.
- Evaluation mode feature licenses may not be available to use after disabling, and enabling the smart licensing on the ASR 903 RSP2 module. A reload of the router is required.
- Ingress counters are not incremented for packets of the below format on the RSP3 module for the 10 Gigabit Ethernet interfaces, 100 Gigabit Ethernet interfaces, and 40 Gigabit Ethernet interfaces:

Packet Format

MAC header---->Vlan header---->Length/Type

When these packets are received on the RSP3 module, the packets are not dropped, but the counters are not incremented.

- ISSU is not supported between a Cisco IOS XE 3S Release and the Cisco IOS XE Everest 16.6.1.
- The following table lists the traffic flow information:

Table 1: Permissible Traffic Rate on RSP3

Packets (in bytes)	Supported Traffic Flow Line Rate
64	< 70%
90	< 90%
95	< 95%

Packets (in bytes)	Supported Traffic Flow Line Rate
>100	100%

- Effective with Cisco IOS XE Everest 16.6.1, the Port-channel (PoCH) scale is reduced to 24 from 48 for Cisco ASR 900 RSP3 module.



Note The PoCH scale for Cisco ASR 907 routers is 48.
