



MPLS OAM Commands

This module describes Multiprotocol Label Switching (MPLS) label switched path (LSP) verification commands. These commands provide a means to detect and diagnose data plane failures and are the first set of commands in the MPLS Operations, Administration, and Maintenance (OAM) solution.

For detailed information about MPLS concepts, configuration tasks, and examples, see .

- [clear mpls oam counters, on page 2](#)
- [echo disable-vendor-extension, on page 3](#)
- [echo revision, on page 4](#)
- [mpls oam, on page 5](#)
- [ping mpls ipv4, on page 6](#)
- [ping pseudowire \(AToM\), on page 11](#)
- [ping mpls traffic-eng tunnel-mte \(P2MP\), on page 15](#)
- [ping mpls mldp \(P2MP\), on page 22](#)
- [ping mpls mldp \(MP2MP\), on page 28](#)
- [show mpls oam, on page 34](#)
- [show mpls oam database, on page 36](#)
- [traceroute mpls ipv4, on page 37](#)
- [traceroute mpls multipath, on page 40](#)
- [traceroute mpls traffic-eng tunnel-mte \(P2MP\), on page 44](#)
- [traceroute mpls mldp \(P2MP\), on page 48](#)
- [traceroute mpls mldp \(MP2MP\), on page 53](#)

clear mpls oam counters

To clear MPLS OAM counters, use the **clear mpls oam counters** command in XR EXEC mode.

clear mpls oam counters {**global** | **interface** [*{type interface-path-id}*] | **packet**}

Syntax Description		
global		Clears global counters.
interface		Clears counters on a specified interface.
<i>type</i>		Interface type. For more information, use the question mark (?) online help function.
<i>interface-path-id</i>		Physical interface or virtual interface.
	Note	Use the show interfaces command to see a list of all interfaces currently configured on the router.
		For more information about the syntax for the router, use the question mark (?) online help function.
packet		Clears global packet counters.

Command Default No default behavior or values

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	mpls-te	execute
	mpls-ldp	execute
	mpls-static	execute

Examples

The following example shows how to clear all global MPLS OAM counters:

```
RP/0/RP0/CPU0:router# clear mpls oam counters global
```

echo disable-vendor-extension

To disable sending the vendor extension type length and value (TLV) in the echo request, use the **echo disable-vendor extension** command in MPLS OAM configuration mode. To return to the default behavior, use the **no** form of this command.

echo disable-vendor-extension

Syntax Description This command has no arguments or keywords.

Command Default The default value is 4.

Command Modes MPLS OAM configuration mode

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operations
	mpls-te	read, write
	mpls-ldp	read, write
	mpls-static	read, write

Examples

The following example shows how to disable inclusion of the vendor extensions TLV in the echo requests:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# mpls oam
RP/0/RP0/CPU0:router(config-oam)# echo disable-vendor-extension
```

echo revision

To set the echo packet revision, use the **echo revision** command in MPLS OAM configuration mode. To return to the default behavior, use the **no** form of this command.

echo revision {1 | 2 | 3 | 4 }

Syntax Description	1 2 3 4
	Draft revision number: <ul style="list-style-type: none"> • 1: draft-ietf-mpls-lsp-ping-03 (initial) • 2: draft-ietf-mpls-lsp-ping-03 (rev 1) • 3: draft-ietf-mpls-lsp-ping-03 (rev 2) • 4: draft-ietf-mpls-lsp-ping-09 (initial)

Command Default The default echo revision is 4 (in draft 9).

Command Modes MPLS OAM configuration mode

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operations
	mpls-te	read, write
	mpls-ldp	read, write
	mpls-static	read, write

Examples

The following example shows how to set the echo packet default revision:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# mpls oam
RP/0/RP0/CPU0:router(config-oam)# echo revision 1
```

mpls oam

To enable MPLS OAM LSP verification, use the **mpls oam** command in XR Config mode. To return to the default behavior, use the **no** form of this command.

mpls oam

Syntax Description

This command has no arguments or keywords.

Command Default

By default, MPLS OAM functionality is disabled.

Command Modes

Command History

Release	Modification
Release 5.2.1	This command was introduced.

Usage Guidelines

The **mpls oam** command and OAM functionality is described in the IETF LSP ping draft.

Task ID

Task ID	Operations
mpls-te	read, write
mpls-ldp	read, write
mpls-static	read, write

Examples

The following example shows how to enable MPLS OAM:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# mpls oam
RP/0/RP0/CPU0:router(config-oam)#
```

ping mpls ipv4

To check MPLS host reachability and network connectivity by specifying the destination type as a Label Distribution Protocol (LDP) IPv4 address, use the **ping mpls ipv4** command in XR EXEC mode.

```
ping mpls ipv4 address/mask [destination start-address end-address increment] [dsmap] [exp exp-bits] [force-explicit-null] [interval min-send-delay] [output { interface type interface-path-id | [nexthop nexthop-iaddress] | [nexthop nexthop-address] } ] [pad pattern] [repeat count] [reply { dscp dscp-value | reply mode { ipv4 | no-reply | router-alert } | reply pad-tlv } ] [revision version] [size packet-size] [source source-address] [sweep min value max value increment] [timeout timeout] [ttl value] [verbose]
```

Syntax Description	<i>address/mask</i>	Address prefix of the target and number of bits in the target address network mask.
	destination <i>start address end address address increment</i>	(Optional) Specifies a network 127/8 address to be used as the destination address in the echo request packet. <i>start address</i> Start of the network address. <i>end address</i> Start of the ending network address. <i>address increment</i> Incremental value of the network address, which is expressed as a decimal number value or IP address.
	dsmap	(Optional) Indicates that a downstream mapping (DSMAP) type length and value should be included in the LSP echo request.
	exp <i>exp-bits</i>	(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
	force-explicit-null	(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.
	interval <i>min-send-delay</i>	(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.
	output interface	(Optional) Specifies the output interface where echo request packets are sent.

<i>type</i>	Interface type. For more information, use the question mark (?) online help function.
<i>interface-path-id</i>	Physical interface or virtual interface. Note Use the show interfaces command to see a list of all interfaces currently configured on the router. For more information, use the question mark (?) online help function.
nexthop	(Optional) Specifies the nextop as an IP address.
<i>nexthop-iaddress</i>	(Optional) IP address for the next hop.
pad pattern	(Optional) Specifies the pad pattern for an echo request.
repeat count	(Optional) Specifies the number of times to resend a packet. Range is 1 to 2147483647. Default is 5.
reply dscp dscp-value	Specifies the differentiated service codepoint value for an MPLS echo reply.
reply mode [ipv4 router-alert no-reply]	Specifies the reply mode for the echo request packet. no-reply Do not reply ipv4 Reply with an IPv4 UDP packet (this is the default) router-alert Reply with an IPv4 UDP packet with the IP router alert set
reply pad-tlv	Indicates that a pad TLV should be included.
revision version	(Optional) Specifies the Cisco extension TLV versioning field: <ul style="list-style-type: none"> • 1 draft-ietf-mpls-lsp-ping-03 (initial) • 2 draft-ietf-mpls-lsp-ping-03 (rev 1) • 3 draft-ietf-mpls-lsp-ping-03 (rev 2) • 4 draft-ietf-mpls-lsp-ping-09 (initial)
size packet size	(Optional) Specifies the packet size or number of bytes in each MPLS echo request packet. Range is 100 to 17986. Default is 100.

source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.
sweep <i>min value max value interval</i>	(Optional) Specifies a range of sizes for the echo packets sent. min value Minimum or start size for an echo packet (range is 100 to 17986) max value Maximum or end size for an echo packet (range is 100 to 17986) interval Number used to increment an echo packet size (range is 1 to 8993)
timeout <i>timeout</i>	(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.
ttl <i>value</i>	(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255).
verbose	(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp bits*: 0
interval *min-send-delay*: 0
repeat *count* : 5
reply-mode: IPv4
timeout *timeout* : 2

Command Modes

XR EXEC

Command History

Release	Modification
Release 5.2.1	This command was introduced.

Usage Guidelines

The **output interface** keyword specifies the output interface on which the MPLS echo request packets are sent. If the specified output interface is not part of the LSP, the packets are not transmitted.

In cases where the sweep keyword is used, values larger than the outgoing interface's MTU are not transmitted.

The **ping** command sends an echo request packet to an address, and then awaits a reply. Ping output can help you evaluate path-to-host reliability, delays over the path, and whether the host can be reached or is functioning.



Note The **ping mpls** command is not supported on optical LSPs. If an optical LSP is encountered along the LSP's path, it is treated as a physical interface.

For detailed configuration information about the MPLS **ping** command, see *System Monitoring Configuration Guide*.

Task ID	Task ID	Operations
	mpls-te	read, write
	mpls-ldp	read, write

Examples

The following example shows the destination type as a label distribution protocol (LDP) prefix and specifies a range of sizes for the echo packets sent:

```
RP/0/RP0/CPU0:router# ping mpls ipv4 140.140.140.140/32 verbose sweep 100 200 15 repeat 1

Sending 1, [100..200]-byte MPLS Echos to 140.140.140.140/32,
timeout is 2 seconds, send interval is 0 msec:

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0

Type escape sequence to abort.
! size 100, reply addr 196.100.1.26, return code 3
! size 115, reply addr 196.100.1.26, return code 3
! size 130, reply addr 196.100.1.26, return code 3
! size 145, reply addr 196.100.1.26, return code 3
! size 160, reply addr 196.100.1.26, return code 3
! size 175, reply addr 196.100.1.26, return code 3
! size 190, reply addr 196.100.1.26, return code 3

Success rate is 100 percent (7/7), round-trip min/avg/max = 5/6/8 ms
```

The following example shows the destination type as a label distribution protocol (LDP) prefix and specifies FEC type as generic and verbose option:

```
RP/0/RP0/CPU0:router# ping mpls ipv4 11.11.11.11/32 fec-type generic output interface
gigabitEthernet 0/0/0/3
nexthop 172.40.103.2 verbose

Sending 5, 100-byte MPLS Echos to 11.11.11.11/32,
timeout is 2 seconds, send interval is 0 msec:

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
```

```
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,  
'P' - no rx intf label prot, 'p' - premature termination of LSP,  
'R' - transit router, 'I' - unknown upstream index,  
'X' - unknown return code, 'x' - return code 0
```

Type escape sequence to abort.

```
!      size 100, reply addr 11.101.11.11, return code 3  
!      size 100, reply addr 11.101.11.11, return code 3  
!      size 100, reply addr 11.101.11.11, return code 3  
!      size 100, reply addr 11.101.11.11, return code 3  
!      size 100, reply addr 11.101.11.11, return code 3
```

Success rate is 100 percent (5/5), round-trip min/avg/max = 3/4/6 ms

ping pseudowire (AToM)

To verify connectivity between provider edge (PE) LSRs in an Any Transport over MPLS (AToM) setup, use the **ping pseudowire** command in XR EXEC mode.

```
ping [mpls] pseudowire { remote-PE-address pw-id | fec-129 { aii-type1 | aii-type2 } vpls-id
{ ipv4-address:nn as-number:nn } target router-id } [ exp exp-bits ] [ interval min-send-delay
] [ pad pattern ] [ repeat count ] [ reply { dscp dscp-value | reply mode { ipv4 | no-reply
| router-alert | control-channel } | reply pad-tlv } ] [ size packet-size ] [ source source-address
] [ sweep min-value max-value increment ] [ timeout timeout ] [ ttl value ] [verbose]
```

Syntax Description		
mpls		(Optional) Verifies the Labeled Switch Path (LSP).
<i>remote-PE address</i>		IP address of the remote PE LSR.
<i>pw-id</i>		Pseudowire ID that identifies the pseudowire in which MPLS connectivity is being verified. The pseudowire is used to send the echo request packets. The range is from 1 to 4294967295.
fec-129		Specifies FEC 129 pseudowire.
aii-type1		Specifies the type 1 attachment individual identifier.
aii-type2		Specifies the type 2 attachment individual identifier.
vpls-id		Specifies that the VPLS identifier should be included.
<i>ipv4-address:nn</i>		Specifies the VPLS identifier as an IPv4 address followed by the index value. The index value range is 0 to 4294967295.
<i>as-number:nn</i>		Specifies the VPLS identifier as an autonomous system (AS) identifier followed by the index value. The index value range is 0 to 4294967295. The AS identifier value range is 1 to 65535.
target		Specifies that the target end address of the pseudowire should be included.
<i>router-id</i>		Specifies the IPv4 address that is the L2VPN router identifier of the target.
exp <i>exp-bits</i>		(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
interval <i>min-send-delay</i>		(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.
pad <i>pattern</i>		(Optional) Specifies the pad pattern for an echo request.
repeat <i>count</i>		(Optional) Specifies the number of times to resend a packet. Range is 1 to 2147483647. Default is 5.

reply dscp <i>dscp-value</i>	(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.
reply mode { ipv4 router-alert no-reply control-channel }	(Optional) Specifies the reply mode for the echo request packet. no-reply Do not reply ipv4 Reply with an IPv4 UDP packet (the default) router-alert Reply with an IPv4 UDP packet with the IP router alert set control-channel Force the use of a VCCV control channel. Reply using an application for a defined control channel. This applies only to pseudowires in which VCCV is used in the reply path. This is the default choice for pseudowire ping.
reply pad-tlv	(Optional) Indicates that a reply pad TLV should be included.
size <i>packet-size</i>	(Optional) Specifies the packet size or number of bytes in each MPLS echo request packet. Range is 100 to 17986. Default is 100.
source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.
sweep <i>min-value max-value interval</i>	Specifies a range of sizes for the echo packets sent. min-value Minimum or start size for an echo packet (range is 100 to 17986) max-value Maximum or end size for an echo packet(range is 100 to 17986) interval Number used to increment an echo packet size(range is 1 to 8993)
timeout <i>timeout</i>	(Optional) Specifies the timeout interval in seconds. Range is 0 to 3600. Default is 2 seconds.
ttl <i>value</i>	(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255).

verbose (Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp bits*: 0
interval *min-send-delay*: 0
repeat *count*: 5
reply-mode: IPv4
timeout *timeout* : 2

Command Modes EXEC

Command History

Release	Modification
Release 5.2.1	This command was introduced.
Release 5.3.2	The pseudowire FEC129 AII-type 1 is supported.

Usage Guidelines In cases in which the **sweep** keyword is used, values larger than the outgoing interface's MTU are not transmitted.

The **ping** command sends an echo request packet to an address, and then awaits a reply. Ping output can help you evaluate path-to-host reliability, delays over the path, and whether the host can be reached or is functioning.



Note The **ping mpls** command is not supported on optical LSPs. If an optical LSP is encountered along the LSP's path, it is treated as a physical interface.

AToM VCCV allows the sending of control packets inband of an AToM pseudowire (PW) from the originating provider edge (PE) router. The transmission is intercepted at the destination PE router, instead of being forwarded to the customer edge (CE) router. This lets you use MPLS LSP ping to test the pseudowire section of AToM virtual circuits (VCs).

The no interactive version of the **ping pseudowire (AToM)** command is supported.

The control word setting is either enabled along the entire path between the Terminating-Provider Edge (T-PE) or it is completely disabled. If the control word configuration is enabled on one segment and disabled on another segment, the multisegment pseudowire does not come up.

Task ID

Task ID	Operations
mpls-te	read, write
mpls-ldp	read, write

Examples

The following example shows how the **ping mpls pseudowire** command is used to verify PE to PE connectivity in which the remote PE address is 150.150.150.150. Only one echo request packet is sent and the remote PE is to answer using IPv4 instead of the control channel.

```
RP/0/RP0/CPU0:router# ping mpls pseudowire 150.150.150.150 21 repeat 1 reply mode ipv4
```

```
  Sending 1, 100-byte MPLS Echos to 150.150.150.150 VC: 21,  
    timeout is 2 seconds, send interval is 0 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,  
       'L' - labeled output interface, 'B' - unlabeled output interface,  
       'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,  
       'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,  
       'P' - no rx intf label prot, 'p' - premature termination of LSP,  
       'R' - transit router, 'I' - unknown upstream index,  
       'X' - unknown return code, 'x' - return code 0
```

```
Type escape sequence to abort.
```

```
!  
Success rate is 100 percent (1/1), round-trip min/avg/max = 23/23/23 ms
```

ping mpls traffic-eng tunnel-mte (P2MP)

To specify the destination type as a Point-to-Multipoint (P2MP) for MPLS-TE tunnel and tunnel interface, use the **ping mpls traffic-eng tunnel-mte** command in XR EXEC mode.

```
ping mpls traffic-eng tunnel-mte tunnel-ID [ddmap { destination start-address end-address
increment }] [responder-id ipv4-address] [exp exp-bits] [interval min-send-delay] [
jitter jitter-value] [lsp { active | reopt }] [pad pattern] [repeat count] [reply { dscp
dscp-value | mode { ipv4 | no-reply | router-alert } | pad-tlv }] [size packet-size] [source
source-address] [sweep min-value max-value increment] [timeout timeout] [ttl value]
[verbose]
```

Syntax Description		
tunnel-mte <i>tunnel-ID</i>		Specifies the destination type as an MPLS traffic engineering (TE) P2MP tunnel and the tunnel interface number. The range for the tunnel interface number is 0 to 65535.
ddmap		(Optional) Indicates that a downstream detailed mapping TLV should be included in the LSP echo request.
destination <i>start-address end-address increment</i>		Specifies a network 127/8 address to be used as the destination address in the echo request packet. <i>start-address</i> Start of the network address. <i>end-address</i> End of the network address. <i>address increment</i> Incremental value of the network address, which is expressed as a decimal number value or IP address.
responder-id <i>ipv4-address</i>		(Optional) Specifies the responder IPv4 address.
exp <i>exp-bits</i>		(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
interval <i>min-send-delay</i>		(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.

jitter <i>jitter-value</i>	(Optional) Specifies a jitter value, in milliseconds. Range is 0 to 2147483647. Default is 200.
pad <i>pattern</i>	(Optional) Specifies the pad pattern for an echo request.
repeat <i>count</i>	(Optional) Specifies the number of times to resend a packet. Range is 1 to 2147483647. Default is 5.
reply dscp <i>dscp-value</i>	(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.
mode [ipv4 router-alert no-reply]	(Optional) Specifies the reply mode for the echo request packet. no-reply Do not reply ipv4 Reply with an IPv4 UDP packet (this is the default) router-alert Reply with an IPv4 UDP packet with the IP router alert set
reply pad-tlv	(Optional) Indicates that a pad TLV should be included.
size <i>packet-size</i>	(Optional) Specifies the packet size or number of bytes in each MPLS echo request packet. Range is 100 to 17986. Default is 100.
source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.

sweep <i>min-value max-value interval</i>	(Optional) Specifies a range of sizes for the echo packets sent. <i>min-value</i> Minimum or start size for an echo packet (range is 100 to 17986) <i>max-value</i> Maximum or end size for an echo packet(range is 100 to 17986) <i>interval</i> Number used to increment an echo packet size(range is 1 to 8993)
timeout <i>timeout</i>	(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.
ttl <i>value</i>	(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255). Default is 255.
verbose	(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp-bits*: 0
interval *min-send-delay*: 0
repeat *count*: 5
reply-mode: IPv4
timeout *timeout* : 2
lsp: active

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Usage Guidelines To ping for LSP reoptimization, ensure that the reoptimization timer for the tunnel is running by using the **show mpls traffic-eng tunnels reoptimized within-last** command.

Task ID	Task ID	Operation
	basic-services	execute

Task ID	Operation
mpls-te or mpls-ldp	read

Example

The following example shows how to check connectivity by using the **ping mpls traffic-eng tunnel-mte** command with the **jitter** keyword:

```
RP/0/RP0/CPU0:router# ping mpls traffic-eng tunnel-mte 10 jitter 300

Mon Apr 12 12:13:00.630 EST

Sending 1, 100-byte MPLS Echos to tunnel-mte10,
    timeout is 2.3 seconds, send interval is 0 msec, jitter value is 300 msec:

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
       'L' - labeled output interface, 'B' - unlabeled output interface,
       'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
       'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
       'P' - no rx intf label prot, 'p' - premature termination of LSP,
       'R' - transit router, 'I' - unknown upstream index,
       'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

Request #1
! reply addr 192.168.222.2
! reply addr 192.168.140.2
! reply addr 192.168.170.1

Success rate is 100 percent (3 received replies/3 expected replies),
    round-trip min/avg/max = 148/191/256 ms
```

The following example shows how to check connectivity by using the **ping mpls traffic-eng tunnel-mte** command with the **ddmap** keyword:

```
RP/0/RP0/CPU0:router# ping traffic-eng tunnel-mte 10 ddmap

Mon Apr 12 12:13:34.365 EST

Sending 1, 100-byte MPLS Echos to tunnel-mte10,
    timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
       'L' - labeled output interface, 'B' - unlabeled output interface,
       'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
       'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
       'P' - no rx intf label prot, 'p' - premature termination of LSP,
       'R' - transit router, 'I' - unknown upstream index,
       'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

Request #1
! reply addr 192.168.222.2
! reply addr 192.168.140.2
! reply addr 192.168.170.1

Success rate is 100 percent (3 received replies/3 expected replies),
```

round-trip min/avg/max = 105/178/237 ms

The following example shows how to identify the LSP ID tunnel information by using the **show mpls traffic-eng tunnels p2mp** command, and then using the **lsp id** keyword with the **ping mpls traffic-eng tunnel-mte** command.

```
RP/0/RP0/CPU0:router# show mpls traffic-eng tunnels p2mp 10

Mon Apr 12 12:13:55.075 EST
Signalling Summary:
    LSP Tunnels Process: running
    RSVP Process: running
    Forwarding: enabled
    Periodic reoptimization: every 3600 seconds, next in 654 seconds
    Periodic FRR Promotion: every 300 seconds, next in 70 seconds
    Auto-bw enabled tunnels: 0 (disabled)

Name: tunnel-mte10
Status:
  Admin: up Oper: up (Up for 12w4d)

Config Parameters:
  Bandwidth: 0 kbps (CT0) Priority: 7 7 Affinity: 0x0/0xffff
  Metric Type: TE (default)
  Fast Reroute: Not Enabled, Protection Desired: None
  Record Route: Not Enabled

Destination summary: (3 up, 0 down, 0 disabled) Affinity: 0x0/0xffff
Auto-bw: disabled
Destination: 11.0.0.1
  State: Up for 12w4d
  Path options:
    path-option 1 dynamic [active]
Destination: 12.0.0.1
  State: Up for 12w4d
  Path options:
    path-option 1 dynamic [active]
Destination: 13.0.0.1
  State: Up for 12w4d
  Path options:
    path-option 1 dynamic [active]

History:
  Reopt. LSP:
    Last Failure:
      LSP not signalled, identical to the [CURRENT] LSP
      Date/Time: Thu Jan 14 02:49:22 EST 2010 [12w4d ago]

Current LSP:
  lsp-id: 10002 p2mp-id: 10 tun-id: 10 src: 10.0.0.1 extid: 10.0.0.1
  LSP up for: 12w4d
  Reroute Pending: No
  Inuse Bandwidth: 0 kbps (CT0)
  Number of S2Ls: 3 connected, 0 signaling proceeding, 0 down

S2L Sub LSP: Destination 11.0.0.1 Signaling Status: connected
  S2L up for: 12w4d
  Sub Group ID: 1 Sub Group Originator ID: 10.0.0.1
  Path option path-option 1 dynamic (path weight 1)
  Path info (OSPF 1 area 0)
    192.168.222.2
    11.0.0.1
```

```
S2L Sub LSP: Destination 12.0.0.1 Signaling Status: connected
S2L up for: 12w4d
Sub Group ID: 2 Sub Group Originator ID: 10.0.0.1
Path option path-option 1 dynamic (path weight 2)
Path info (OSPF 1 area 0)
  192.168.222.2
  192.168.140.3
  192.168.140.2
  12.0.0.1
```

```
S2L Sub LSP: Destination 13.0.0.1 Signaling Status: connected
S2L up for: 12w4d
Sub Group ID: 3 Sub Group Originator ID: 10.0.0.1
Path option path-option 1 dynamic (path weight 2)
Path info (OSPF 1 area 0)
  192.168.222.2
  192.168.170.3
  192.168.170.1
  13.0.0.1
```

```
Reoptimized LSP (Install Timer Remaining 0 Seconds):
```

```
None
```

```
Cleaned LSP (Cleanup Timer Remaining 0 Seconds):
```

```
None
```

```
Displayed 1 (of 16) heads, 0 (of 0) midpoints, 0 (of 0) tails
```

```
Displayed 1 up, 0 down, 0 recovering, 0 recovered heads
```

```
RP/0/RP0/CPU0:router# ping mpls traffic-eng tunnel-mte 10 lsp id 10002
```

```
Mon Apr 12 12:14:04.532 EST
```

```
Sending 1, 100-byte MPLS Echos to tunnel-mte10,
  timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

```
Type escape sequence to abort.
```

```
Request #1
! reply addr 192.168.222.2
! reply addr 192.168.170.1
! reply addr 192.168.140.2
```

```
Success rate is 100 percent (3 received replies/3 expected replies),
  round-trip min/avg/max = 128/153/167 ms
```

The following example shows how to use the **ping mpls traffic-eng tunnel-mte** command to check connectivity with a router's host address 13.0.0.1:

```
RP/0/RP0/CPU0:router# ping mpls traffic-eng tunnel-mte 10 egress 13.0.0.1
```

```
Mon Apr 12 12:15:34.205 EST
```

```
Sending 1, 100-byte MPLS Echos to tunnel-mte10,
  timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
 'L' - labeled output interface, 'B' - unlabeled output interface,
 'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
 'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
 'P' - no rx intf label prot, 'p' - premature termination of LSP,
 'R' - transit router, 'I' - unknown upstream index,
 'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

Request #1
 ! reply addr 192.168.170.1

Success rate is 100 percent (1 received reply/1 expected reply),
 round-trip min/avg/max = 179/179/179 ms

Related Commands

Command	Description
show mpls traffic-eng tunnels	Displays information about MPLS-TE tunnels.

ping mpls mldp (P2MP)

To check data plane and control plane of MPLS for the Point-to-Multipoint (P2MP) label switch path, use the **ping mpls mldp p2mp** command in XR EXEC mode.

```
ping mpls mldp p2mp root-address {IPv4 source-ipv4-address group-ipv4-address | IPv6
source-ipv6-address group-ipv6-address | vpn4 AS-number [source-ipv4-address group-ipv4-address] |
vpn6 AS-number [source-ipv6-address group-ipv6-address] | mdt oui:vpn-index mdt-number | global-id
lsp-id} [options]
```

Syntax Description		
mldp		Verifies the ping capability for multicast label distribution protocol (mldp).
p2mp		Indicates the Point-to-Multipoint (P2MP) label switch path.
<i>root-address</i>		Specifies the root address.
IPv4 <i>ipv4-address</i>		Defines IPv4 opaque encoding.
IPv6 <i>ipv6-address</i>		Defines IPv6 opaque encoding.
vpn4 <i>AS-number</i> [<i>source-ipv4-address group-ipv4-address</i>]		Defines VPNv4 opaque encoding.
vpn6 <i>AS-number</i> [<i>source-ipv6-address group-ipv6-address</i>]		Defines VPNv6 opaque encoding.
mdt <i>oui:vpn-index mdt number</i>		Defines VPN ID opaque encoding. Range of 3-byte OUI is 0 to 16777215. Range of <i>mdt-number</i> is 0 to 4294967295.
global-id <i>isp-id</i>		Defines 4 byte global LSP ID opaque encoding.
<i>source-address</i>		Specifies the source address of target multicast address.
<i>group-address</i>		Specifies the target address of target multicast address.
<i>AS-number</i>		Specifies the Autonomous system number as follows: <ul style="list-style-type: none"> • 4-byte AS-number with asdot (X.Y) : aa.bb:cc format (for example, 11.22:33) • 2-byte AS-number or 4-byte AS-number: aa:bb format (for example, 11:22) • IPv4 address and index:aa.bb.cc.dd:ee format (for example, 11.22.33.44:55)

options

Specifies a set of various options:

ddmap

(Optional) Indicates that a downstream detailed mapping TLV (ddmap) should be included in the LSP echo request.

destination

(Optional) Specifies a network 127/8 address to be used as the destination address in the echo request packet.

start-address: Start of the network address.

end-address: End of the network address.

address increment: Incremental value of the network address, which is expressed as a decimal number value or IP address.

expexp-bits

(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.

flags

fec: (Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.

no-ttl: (Optional) Specifies not to add TTL expired flag in echo request.

force-explicit-null

(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.

interval *min-send-delay*

(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.

jitter

(Optional) Specifies a jitter value for a corresponding echo request, in milliseconds. Range is 0 to 2147483647. Default is 200.

pad *pattern*

(Optional) Specifies the pad pattern for an echo request.

repeat *count*

(Optional) Specifies the number of times to resend a packet. Range is 1 to 2147483647. Default is 5.

reply dscp dscp-value

(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.

mode [ipv4 | router-alert]

(Optional) Specifies the reply mode for the echo request packet.

ipv4

Reply with an IPv4 UDP packet (this is the default)

router-alert

Reply with an IPv4 UDP packet with the IP router alert set

responder-id ipv4-address

(Optional) Adds responder identifier into corresponding echo request.

sizepacket size

(Optional) Specifies the packet size or number of bytes in each MPLS echo request packet. Range is 100 to 17986. Default is 100.

source ipv4-address

(Optional) Specifies the source address used in the echo request packet.

sweep

(Optional)

timeout timeout

(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.

ttl

(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255). Default is 255.

verbose

(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default No default behavior or values

Command Modes	XR EXEC
----------------------	---------

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operation
	basic-services	execute
	mpls-te	read
	mpls-ldp	read

The following examples show how to check connectivity for P2MP by using the **ping mpls mldp p2mp** command.

```
RP/0/RP0/CPU0:router#ping mpls mldp p2mp 192.168.0.1 ipv4 2.2.2.2 232.1.1.1
```

```
Sending 1, 100-byte MPLS Echos to mldp p2mp 192.168.0.1 ipv4 (2.2.2.2, 232.1.1.1),
  timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
Request #1
! reply addr 11.11.11.3
! reply addr 12.12.12.4
```

```
Round-trip min/avg/max = 17/27/38 ms
```

```
RP/0/RP0/CPU0:router#ping mpls mldp p2mp 192.168.0.1 ipv4 2.2.2.2 232.1.1.1 ddmapped ttl 1
```

```
Sending 1, 100-byte MPLS Echos to mldp p2mp 192.168.0.1 ipv4 (2.2.2.2, 232.1.1.1),
  timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
Request #1
d reply addr 10.10.10.2
 [L] DDMAP 0: 11.11.11.3 11.11.11.3 MRU 1500 [Labels: 16016 Exp: 0]
 [L] DDMAP 1: 12.12.12.4 12.12.12.4 MRU 1500 [Labels: 16016 Exp: 0]
```

This table describes the significant fields shown in the display:

Opaque Type	Opaque Value	Supported Multicast Application	Signaling
IPv4	S, G	PIM-SSM transit of IPv4	In-Band
IPv6	S, G	PIM-SSM transit of IPv6	In-Band
MDT	VPN-ID, MDT#	mVPN Default-MDT (MDT# = 0) mVPN Data-MDT (MDT# > 0)	In-Band
Global ID	4 byte value	BGP Assigned LSPs	Out-of-Band
VPNv4	(S,G), VPN-ID	VPNv4	In-Band
VPNv6	(S,G), VPN-ID	VPNv6	In-Band

Related Commands

Command	Description
ping mpls mldp (MP2MP), on page 28	Verifies data plane and control plane for the Multipoint-to-Multipoint (MP2MP) label switch path.
traceroute mpls mldp (P2MP), on page 48	Verifies hop-by-hop fault localization and path tracing for the point-to-multipoint path.
traceroute mpls mldp (MP2MP), on page 53	Verifies hop-by-hop fault localization and path tracing for the multipoint-to-multipoint path.

ping mpls mldp (MP2MP)

To check data plane and control plane of MPLS for the Multipoint-to-Multipoint (MP2MP) label switch path, use the **ping mpls mldp mp2mp** command in XR EXEC mode.

```
ping mpls mldp mp2mp root-address {IPv4 source-ipv4-address group-ipv4-address | IPv6
source-ipv6-address group-ipv6-address | vpn4 AS-number [source-ipv4-address group-ipv4-address] |
vpn6 AS-number [source-ipv6-address group-ipv6-address] | mdt oui:vpn-index mdt-number | global-id
lsp-id} [options]
```

Syntax Description

mldp	Verifies the ping capability for multicast label distribution protocol (mldp).
mp2mp	Indicates the Multipoint-to-Multipoint (MP2MP) label switch path.
<i>root-address</i>	Specifies the root address.
IPv4 <i>ipv4-address</i>	Defines IPv4 opaque encoding.
IPv6 <i>ipv6-address</i>	Defines IPv6 opaque encoding.
vpn4 <i>AS-number</i> [<i>source-ipv4-address group-ipv4-address</i>]	Defines VPNv4 opaque encoding.
vpn6 <i>AS-number</i> [<i>source-ipv6-address group-ipv6-address</i>]	Defines VPNv6 opaque encoding.
mdt <i>oui:vpn-index mdt number</i>	Defines VPN ID opaque encoding. Range of 3-byte OUI is 0 to 16777215. Range of <i>mdt-number</i> is 0 to 4294967295.
global-id <i>lsp-id</i>	Defines 4 byte global LSP ID opaque encoding.
<i>source-address</i>	Specifies the source address of target multicast address.
<i>group-address</i>	Specifies the target address of target multicast address.
<i>AS-number</i>	Specifies the Autonomous system number as follows: <ul style="list-style-type: none"> • 4-byte AS-number with asdot (X.Y) : aa.bb.cc format (for example, 11.22:33) • 2-byte AS-number or 4-byte AS-number: aa:bb format (for example, 11:22) • IPv4 address and index:aa.bb.cc.dd:ee format (for example, 11.22.33.44:55)

options

Specifies a set of various options:

ddmap

(Optional) Indicates that a downstream detailed mapping TLV (ddmap) should be included in the LSP echo request.

destination

(Optional) Specifies a network 127/8 address to be used as the destination address in the echo request packet.

start-address: Start of the network address.

end-address: End of the network address.

address increment: Incremental value of the network address, which is expressed as a decimal number value or IP address.

expexp-bits

(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.

flags

fec: (Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.

no-ttl: (Optional) Specifies not to add TTL expired flag in echo request.

force-explicit-null

(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.

interval *min-send-delay*

(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.

jitter

(Optional) Specifies a jitter value for a corresponding echo request, in milliseconds. Range is 0 to 2147483647. Default is 200.

pad *pattern*

(Optional) Specifies the pad pattern for an echo request.

repeat *count*

(Optional) Specifies the number of times to resend a packet. Range is 1 to 2147483647. Default is 5.

reply dscp dscp-value

(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.

mode [ipv4 | router-alert]

(Optional) Specifies the reply mode for the echo request packet.

ipv4

Reply with an IPv4 UDP packet (this is the default)

router-alert

Reply with an IPv4 UDP packet with the IP router alert set

responder-id ipv4-address

(Optional) Adds responder identifier into corresponding echo request.

sizepacket size

(Optional) Specifies the packet size or number of bytes in each MPLS echo request packet. Range is 100 to 17986. Default is 100.

source ipv4-address

(Optional) Specifies the source address used in the echo request packet.

sweep

(Optional)

timeout timeout

(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.

ttl

(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255). Default is 255.

verbose

(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default No default behavior or values

Command Modes	XR EXEC
----------------------	---------

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operation
	basic-services	execute
	mpls-te	read
	mpls-ldp	read

The following example shows how to check connectivity by using the **ping mpls mldp** command when a root address is present.

```
RP/0/RP0/CPU0:router#ping mpls mldp mp2mp 192.168.0.1 global-id 1
Mon Jul 11 15:35:50.294 JST
```

```
Sending 1, 100-byte MPLS Echos to mldp mp2mp 192.168.0.1 global-id 1,
    timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
        'L' - labeled output interface, 'B' - unlabeled output interface,
        'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
        'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
        'P' - no rx intf label prot, 'p' - premature termination of LSP,
        'R' - transit router, 'I' - unknown upstream index,
        'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
Request #1
! reply addr 10.10.10.2
! reply addr 12.12.12.4
! reply addr 11.11.11.3
```

```
Round-trip min/avg/max = 72/112/135 ms
```

```
RP/0/RP0/CPU0:router#ping mpls mldp mp2mp 192.168.0.1 global-id 1 responder-id 11.11.11.3
Mon Jul 11 15:36:16.038 JST
```

```
Sending 1, 100-byte MPLS Echos to mldp mp2mp 192.168.0.1 global-id 1,
    timeout is 2.2 seconds, send interval is 0 msec, jitter value is 200 msec:
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
        'L' - labeled output interface, 'B' - unlabeled output interface,
        'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
        'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
        'P' - no rx intf label prot, 'p' - premature termination of LSP,
        'R' - transit router, 'I' - unknown upstream index,
        'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
Request #1
```



```
! reply addr 11.11.11.3
```

```
Round-trip min/avg/max = 163/163/163 ms
```

This table describes the significant fields shown in the display:

Opaque Type	Opaque Value	Supported Multicast Application	Signaling
IPv4	S, G	PIM-SSM transit of IPv4	In-Band
IPv6	S, G	PIM-SSM transit of IPv6	In-Band
MDT	VPN-ID, MDT#	mVPN Default-MDT (MDT# = 0) mVPN Data-MDT (MDT# > 0)	In-Band
Global ID	4 byte value	BGP Assigned LSPs	Out-of-Band
VPNv4	(S,G), VPN-ID	VPNv4	In-Band
VPNv6	(S,G), VPN-ID	VPNv6	In-Band

Related Commands

Command	Description
ping mpls mldp (P2MP), on page 22	Verifies data plane and control plane for the point-to-multipoint (P2MP) label switch path.
traceroute mpls mldp (P2MP), on page 48	Verifies hop-by-hop fault localization and path tracing for the point-to-multipoint path.
traceroute mpls mldp (MP2MP), on page 53	Verifies hop-by-hop fault localization and path tracing for the multipoint-to-multipoint path.

show mpls oam

To display MPLS OAM information, use the **show mpls oam** command in XR EXEC mode.

show mpls oam {**client** | **counters** {**global** | **packet**} | **interface** *type interface-path-id*}

Syntax Description

client	Displays clients registered with LSPV server.
counters global	Displays LSP verification global counters.
counters packet	Displays LSP verification packet counters.
counters interface	Displays LSP verification information for a specific interface.
<i>type</i>	Interface type. For more information, use the question mark (?) online help function.
<i>interface-path-id</i>	Physical interface or virtual interface.
Note	Use the show interfaces command to see a list of all interfaces currently configured on the router.
	For more information about the syntax for the router, use the question mark (?) online help function.

Command Default

No default behavior or values

Command Modes

XR EXEC

Command History

Release	Modification
Release 5.2.1	This command was introduced.

Task ID

Task ID	Operations
mpls-te	read
mpls-ldp	read
mpls-static	read

Examples

The following example shows how to display MPLS OAM client information:

```
RP/0/RP0/CPU0:router# show mpls oam client

Client Process: l2vpn_mgr Node: 0/0/SP Pid: 418014
Client Process: te_control Node: 0/0/SP Pid: 639227
```

This table describes the significant fields shown in the display.

Table 1: show mpls oam client Command Field Descriptions

Field	Description
Client Process	Process of client.

show mpls oam database

To display MPLS OAM database information, use the **show mpls oam database** command in XR EXEC mode.

show mpls oam database {**replies** | **requests** | **tt-requests**} [**detail**] [**handle** *handle-value*]

Syntax Description	
replies	Displays replies database.
requests	Displays request database
tt-requests	Displays tree trace request database
detail	(Optional) Displays displayed information.
handle	(Optional) Displays handle information.
<i>handle-value</i>	Generic handle value. Range is from 0 to 4294967295.

Command Default No default behavior or values

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operations
	mpls-te	read
	mpls-ldp	read
	mpls-static	read

Examples

The following example shows how to display detailed MPLS OAM database information:

```
RP/0/RP0/CPU0:router# show mpls oam database request detail
```

traceroute mpls ipv4

To learn the routes that packets follow when traveling to their Label Distribution Protocol (LDP) IPv4 destination, use the **traceroute mpls** command in XR EXEC mode.

```
traceroute mpls ipv4 address/mask [ destination start-address end-address address-increment ] [ exp exp-bits ] [ flags fec ] [ force-explicit-null ] [ output { interface type interface-path-id } ] [ nexthop nexthop-address ] | [ nexthop nexthop-address ] } } ] [ reply { dscp dscp-value | reply mode { ipv4 | router-alert } } ] [ revision version ] [ source source-address ] [ timeout timeout ] [ ttl value ] [ verbose ] [ fec-type { bgp | generic | ldp } ]
```

Syntax Description

<i>address/mask</i>	Specifies the destination type as a label distribution protocol (LDP) prefix. Address prefix of the target and number of bits in the target address network mask.
destination <i>start-address end-address address-increment</i>	Specifies a network 127 address to be used as the destination address in the echo request packet. start address Start of the network address. end address End of the network address. address increment Incremental value of the network address.
exp <i>exp-bits</i>	(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
flags fec	(Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.
force-explicit-null	(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.
output interface	(Optional) Specifies the output interface in which echo request packets are sent.
<i>type</i>	Interface type. For more information, use the question mark (?) online help function.
<i>interface-path-id</i>	Physical interface or virtual interface. Note Use the show interfaces command to see a list of all interfaces currently configured on the router. For more information, use the question mark (?) online help function.
nexthop	(Optional) Specifies the IP address for the next hop.

<i>nexthop-address</i>	(Optional) IP address for the next hop.
reply dscp <i>dscp-value</i>	(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.
reply mode { ipv4 router-alert }	(Optional) Specifies the reply mode for the echo request packet. ipv4 Reply with IPv4 UDP packet (this is the default) router-alert Reply with IPv4 UDP packet with router alert
revision <i>version</i>	(Optional) Specifies the Cisco extension TLV versioning field: <ul style="list-style-type: none"> • 1 draft-ietf-mpls-lsp-ping-03 (initial) • 2 draft-ietf-mpls-lsp-ping-03 (rev 1) • 3 draft-ietf-mpls-lsp-ping-03 (rev 2) • 4 draft-ietf-mpls-lsp-ping-09 (initial)
source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.
timeout <i>timeout</i>	(Optional) Specifies the timeout interval, in seconds. Range is from 0 to 3600. Default is 2.
ttl <i>value</i>	(Optional) Specifies the maximum number of hops (range is 1 to 255).
verbose	(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp-bits*: 0
reply mode: IPv4
timeout *timeout*: 2

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Usage Guidelines



Note The **traceroute mpls** command is not supported on optical LSPs. If an optical LSP is encountered along the LSPs path, it is treated as a physical interface.

For detailed configuration information about MPLS LSP trace operations, see .

Task ID	Task ID	Operations
	mpls-te	read, write
	mpls-ldp	read, write

Examples

The following example shows how to trace a destination:

```
RP/0/RP0/CPU0:router# traceroute mpls ipv4 140.140.140.140/32  
destination 127.0.0.10 127.0.0.15.1
```

Tracing MPLS Label Switched Path to 140.140.140.140/32, timeout is 2 seconds

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,  
'L' - labeled output interface, 'B' - unlabeled output interface,  
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,  
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,  
'P' - no rx intf label prot, 'p' - premature termination of LSP,  
'R' - transit router, 'I' - unknown upstream index,  
'X' - unknown return code, 'x' - return code 0
```

Type escape sequence to abort.

Destination address 127.0.0.10

```
0 196.100.1.41 MRU 4470 [Labels: 19 Exp: 0]  
L 1 196.100.1.42 MRU 4470 [Labels: 86 Exp: 0] 360 ms  
2 196.100.1.50 MRU 4470 [Labels: implicit-null Exp: 0] 8 ms  
! 3 196.100.1.18 9 ms
```

The following example shows how to trace a destination with FEC type specified as generic and verbose option:

```
RP/0/RP0/CPU0:router# traceroute mpls ipv4 11.11.11.11/32 fec-type generic output interface  
gigabitEthernet 0/0/0/3  
nexthop 172.40.103.2 verbose
```

Tracing MPLS Label Switched Path to 11.11.11.11/32, timeout is 2 seconds

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,  
'L' - labeled output interface, 'B' - unlabeled output interface,  
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,  
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,  
'P' - no rx intf label prot, 'p' - premature termination of LSP,  
'R' - transit router, 'I' - unknown upstream index,  
'X' - unknown return code, 'x' - return code 0
```

Type escape sequence to abort.

```
0 172.40.103.1 172.40.103.2 MRU 1500 [Labels: 16038 Exp: 0]  
L 1 172.40.103.2 173.101.103.1 MRU 1500 [Labels: 16037 Exp: 0] 6 ms, ret code 8  
L 2 173.101.103.1 11.101.11.11 MRU 1500 [Labels: implicit-null Exp: 0] 4 ms, ret code 8  
! 3 11.101.11.11 6 ms, ret code 3
```

tracertoute mpls multipath

To discover all possible paths of an LSP between the ingress and egress routers, use the **tracertoute mpls multipath** command in XR EXEC mode.

```
tracertoute mpls multipath ipv4 address/mask [destination start-address end-address address-increment]
[exp exp-bits] [flags fec] [force-explicit-null] [hashkey ipv4 bitmap bit-size] [interval min-send-delay]
[output interface type interface-path-id] [nexthop nexthop-address] [reply {dscp dscp-value | reply
mode{ipv4 | router-alert}}] [retry-count count] [revision version] [source source-address] [timeout
timeout] [ttl value] [verbose] [fec-type {bgp | generic | ldp}]
```

Syntax Description	
ipv4	Specifies the destination type as a Label Distribution Protocol (LDP) IPv4 address.
<i>address/mask</i>	Address prefix of the target and number of bits in the target address network mask.
destination <i>start-address end-address address-increment</i>	(Optional) Specifies a network 127 address to be used as the destination address in the echo request packet. start-address Start of the network address. end-address End of the network address. address-increment Incremental value of the network address.
exp <i>exp-bits</i>	(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
flags fec	(Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.
force-explicit-null	(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.
hashkey ipv4 bitmap <i>bit-size</i>	(Optional) Allows user control of the hash key/multipath settings. Range is 0 to 256. The default is 32.
interval <i>min-send-delay</i>	(Optional) Specifies a send interval, in milliseconds, between requests. Range is 0 to 3600000. Default is 0.
output interface	(Optional) Specifies the output interface where echo request packets are sent.
<i>type</i>	Interface type. For more information, use the question mark (?) online help function.

<i>interface-path-id</i>	Physical interface or virtual interface. Note Use the show interfaces command to see a list of all interfaces currently configured on the router. For more information, use the question mark (?) online help function.
nexthop	(Optional) Specifies the IP address for the next hop.
<i>nexthop-address</i>	(Optional) IP address for the next hop.
reply dscp <i>dscp-value</i>	(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.
reply mode [ipv4 router-alert]	(Optional) Specifies the reply mode for the echo request packet. ipv4 Reply with IPv4 UDP packet (this is the default) router-alert Reply with IPv4 UDP packet with router alert
retry-count <i>count</i>	(Optional) Specifies the number of retry attempts during multipath LSP traceroute. A retry is attempted if an outstanding echo request <ul style="list-style-type: none"> times out waiting for the corresponding echo reply. fails to find a valid destination address set to exercise a specific outgoing path. Range is 0 to 10. Default is 3.
revision <i>version</i>	(Optional) Specifies the Cisco extension TLV versioning field: <ul style="list-style-type: none"> 1 draft-ietf-mpls-lsp-ping-03 (initial) 2 draft-ietf-mpls-lsp-ping-03 (rev 1) 3 draft-ietf-mpls-lsp-ping-03 (rev 2) 4 draft-ietf-mpls-lsp-ping-09 (initial)
source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.
timeout <i>timeout</i>	(Optional) Specifies the timeout interval, in seconds. Range is from 0 to 3600. Default is 2.
ttl <i>value</i>	(Optional) Specifies the maximum number of hops (range is 1 to 255).
verbose	(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp-bits* : 0
hashkey **ipv4** **bitmap** *bit-size*: 4
interval *min-send-delay*: 0
reply mode: IPv4
retry-count: 3

timeout *timeout* : 2

Command Modes EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Usage Guidelines The **hashkey ipv4 bitmap** keyword and *bit-size* value control how many addresses are encoded in the DSMAP multipath field. Larger values allow more coverage of equal cost multiple paths throughout the network, but with more processing at the head, mid, and tail routers.

Task ID	Task ID	Operations
	mpls-te	read, write
	mpls-ldp	read, write

Examples

The following example shows how to specify the destination type as an LDP IPv4 prefix:

```
RP/0/RP0/CPU0:router# traceroute mpls multi ipv4 140.140.140.140/32 verbose
force-explicit-null

Starting LSP Path Discovery for 140.140.140.140/32

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0

Type escape sequence to abort.

LL!
Path 0 found,
output interface POS0/2/0/3 source 196.100.1.61 destination 127.0.0.1
0 196.100.1.61 196.100.1.62 MRU 4470 [Labels: 18/explicit-null Exp: 0/0] multipaths 0
L 1 196.100.1.62 196.100.1.10 MRU 4470 [Labels: 17/explicit-null Exp: 0/0] ret code 8
multipaths 1
L 2 196.100.1.10 196.100.1.18 MRU 4470 [Labels: implicit-null/explicit-null Exp: 0/0] ret
code 8 multipaths 1
! 3 196.100.1.1018, ret code 3 multipaths 0
LL!
Path 1 found,
output interface GigabitEthernet0/3/0/0 source 196.100.1.5 destination 127.0.0.1
0 196.100.1.5 196.100.1.37 6 MRU 1500 [Labels: 18/explicit-null Exp: 0/0] multipaths 0
L 1 196.100.1.6 196.100.1.10 MRU 4470 [Labels: 17/explicit-null Exp: 0/0] ret code 8
multipaths 1
L 2 10196.0100.21.5 1010 196.0100.21.10 18 MRU 4470 [Labels: implicit-null/explicit-null
Exp: 0/0] ret code 8 multipaths 1
! 3 10196.0100.21.1018, ret code 3 multipaths 0
```

```

Paths (found/broken/unexplored) (2/0/0)
Echo Request (sent/fail) (6/0)
Echo Reply (received/timeout) (6/0)
Total Time Elapsed 80 ms

```

The following example shows how to specify the FEC type as LDP with verbose option:

```

RP/0/RP0/CPU0:router# traceroute mpls multipath ipv4 11.11.11.11/32 fec-type ldp output
interface gigabitEthernet 0/0/0/3
nexthop 172.40.103.2 verbose

```

```

Starting LSP Path Discovery for 11.11.11.11/32

```

```

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0

```

Type escape sequence to abort.

```

LL!
Path 0 found,
  output interface GigabitEthernet0/0/0/3 nexthop 172.40.103.2
  source 172.40.103.1 destination 127.0.0.0
    0 172.40.103.1 172.40.103.2 MRU 1500 [Labels: 16038 Exp: 0] multipaths 0
L 1 172.40.103.2 173.101.103.1 MRU 1500 [Labels: 16037 Exp: 0] ret code 8 multipaths 1
L 2 173.101.103.1 11.101.11.11 MRU 1500 [Labels: implicit-null Exp: 0] ret code 8 multipaths
  1
! 3 11.101.11.11, ret code 3 multipaths 0

Paths (found/broken/unexplored) (1/0/0)
Echo Request (sent/fail) (3/0)
Echo Reply (received/timeout) (3/0)
Total Time Elapsed 21 ms

```

traceroute mpls traffic-eng tunnel-mte (P2MP)

To specify the destination type as an MPLS traffic engineering (TE) tunnel for point-to-multipoint connection, use the **traceroute mpls traffic-eng tunnel-mte** command in XR EXEC mode.

```
traceroute mpls traffic-eng tunnel-mte tunnel-ID [destination start-address end-address
address-increment increment-mask] [responder-id ipv4-address][exp exp-bits] [flags fec] [jitter
jitter-value] [reply {dscp dscp-value | mode {ipv4 | router-alert}}] [source source-address]
[timeout timeout] [ttl value] [verbose]
```

Syntax Description	
tunnel-mte	Specifies the MPLS-TE P2MP tunnel type.
<i>tunnel-ID</i>	Tunnel interface.
destination <i>start-address end-address address-increment increment-mask</i>	(Optional) Specifies a network 127 address to be used as the destination address in the echo request packet. <i>start-address</i> Start of the network address. <i>end-address</i> End of the network address. <i>address-increment</i> Incremental value of the network address. <i>increment-mask</i> Incremental mask of the network address.
responder-id <i>ipv4-address</i>	(Optional) Specifies the responder-id IPv4 address.
exp <i>exp-bits</i>	(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.
flags fec	(Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.
jitter <i>jitter-value</i>	(Optional) Specifies the jitter value. Range is 0 to 2147483647.
reply dscp <i>dscp-value</i>	(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.

reply-mode [ipv4 router-alert]	(Optional) Specifies the reply mode for the echo request packet. ipv4 Reply with IPv4 UDP packet. (This is the default.) router-alert Reply with IPv4 UDP packet with router alert
source <i>source-address</i>	(Optional) Specifies the source address used in the echo request packet.
timeout <i>timeout</i>	(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.
ttl <i>value</i>	(Optional) Specifies the maximum number of hops. Range is 1 to 255. Default is 30.
verbose	(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default

exp *exp-bits* : 0
reply-mode: IPv4
timeout *timeout* : 2
ttl: 30

Command Modes

XR EXEC

Command History

Release	Modification
Release 5.2.1	This command was introduced.

Task ID

Task ID	Operation
mpls-te	read
mpls-ldp	read

Example

The following example shows how to specify the maximum number of hops for the trace route to traverse by using the **ttl** keyword:

```
RP/0/RP0/CPU0:router# traceroute mpls traffic-eng tunnel-mte 10 ttl 4
```

```
Mon Apr 12 12:16:50.095 EST
```

```
Tracing MPLS MTE Label Switched Path on tunnel-mte10, timeout is 2.2 seconds
```

```

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

! 1 192.168.222.2 186 ms [Estimated Role: Bud]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]

! 2 192.168.222.2 115 ms [Estimated Role: Bud]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 2 192.168.140.2 213 ms [Estimated Role: Egress]
! 2 192.168.170.1 254 ms [Estimated Role: Egress]

! 3 192.168.222.2 108 ms [Estimated Role: Bud]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 3 192.168.170.1 164 ms [Estimated Role: Egress]
! 3 192.168.140.2 199 ms [Estimated Role: Egress]

! 4 192.168.170.1 198 ms [Estimated Role: Egress]
! 4 192.168.222.2 206 ms [Estimated Role: Bud]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 4 192.168.140.2 266 ms [Estimated Role: Egress]

```

The following example shows how to specify the egress host address by using the **egress** keyword:

```

RP/0/RP0/CPU0:router# traceroute mpls traffic-eng tunnel-mte 10 egress 13.0.0.1

Mon Apr 12 12:18:01.994 EST

Tracing MPLS MTE Label Switched Path on tunnel-mte10, timeout is 2.2 seconds

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

d 1 192.168.222.2 113 ms [Estimated Role: Branch]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]

d 2 192.168.222.2 118 ms [Estimated Role: Branch]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 2 192.168.170.1 244 ms [Estimated Role: Egress]

d 3 192.168.222.2 141 ms [Estimated Role: Branch]
    [L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
    [L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 3 192.168.170.1 204 ms [Estimated Role: Egress]

d 4 192.168.222.2 110 ms [Estimated Role: Branch]

```

```

[L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
[L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 4 192.168.170.1 174 ms [Estimated Role: Egress]

```

The following example shows how to specify the egress host address, the maximum number of hops, and jitter in the tunnel:

```

RP/0/RP0/CPU0:router# traceroute mpls traffic-eng tunnel-mte 10 egress 13.0.0.1 ttl 4 jitter 500

```

```

Mon Apr 12 12:19:00.292 EST

```

```

Tracing MPLS MTE Label Switched Path on tunnel-mte10, timeout is 2.5 seconds

```

```

Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

```

```

Type escape sequence to abort.

```

```

d 1 192.168.222.2 238 ms [Estimated Role: Branch]
[L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
[L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]

d 2 192.168.222.2 188 ms [Estimated Role: Branch]
[L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
[L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 2 192.168.170.1 290 ms [Estimated Role: Egress]

d 3 192.168.222.2 115 ms [Estimated Role: Branch]
[L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
[L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 3 192.168.170.1 428 ms [Estimated Role: Egress]

d 4 192.168.222.2 127 ms [Estimated Role: Branch]
[L] DDMAP 0: 192.168.140.2 192.168.140.2 MRU 1500 [Labels: 16001 Exp: 0]
[L] DDMAP 1: 192.168.170.1 192.168.170.1 MRU 1500 [Labels: 16000 Exp: 0]
! 4 192.168.170.1 327 ms [Estimated Role: Egress]

```

Related Commands

Command	Description
show mpls traffic-eng tunnels	Displays information about MPLS-TE tunnels.
ping mpls traffic-eng tunnel-te (P2P)	Displays information about MPLS-TE tunnel for a point-to-point connection.

tracertoute mpls mldp (P2MP)

To verify hop-by-hop fault localization and path tracing for the point-to-multipoint path, use the **tracertoute mpls mldp p2mp** command in XR EXEC mode.

```
tracertoute mpls mldp p2mp root-address {IPv4 source-ipv4-address group-ipv4-address | IPv6
source-ipv6-address group-ipv6-address | vpn4 AS-number [source-ipv4-address group-ipv4-address] |
vpn6 AS-number [source-ipv6-address group-ipv6-address] | mdt oui:vpn-index mdt-number | global-id
lsp-id} [options]
```

Syntax Description		
mldp		Verifies the ping capability for multicast label distribution protocol (mldp).
p2mp		Indicates the Point-to-Multipoint (P2MP) label switch path.
<i>root-address</i>		Specifies the root address.
IPv4 <i>ipv4-address</i>		Defines IPv4 opaque encoding.
IPv6 <i>ipv6-address</i>		Defines IPv6 opaque encoding.
vpn4 <i>AS-number</i> [<i>source-ipv4-address group-ipv4-address</i>]		Defines VPNv4 opaque encoding.
vpn6 <i>AS-number</i> [<i>source-ipv6-address group-ipv6-address</i>]		Defines VPNv6 opaque encoding.
mdt <i>oui:vpn-index mdt number</i>		Defines VPN ID opaque encoding. Range of 3-byte OUI is 0 to 16777215. Range of <i>mdt-number</i> is 0 to 4294967295.
global-id <i>lsp-id</i>		Defines 4 byte global LSP ID opaque encoding.
<i>source-address</i>		Specifies the source address of target multicast address.
<i>group-address</i>		Specifies the target address of target multicast address.
<i>AS-number</i>		Specifies the Autonomous system number as follows: <ul style="list-style-type: none"> • 4-byte AS-number with asdot (X.Y) : aa.bb:cc format (for example, 11.22:33) • 2-byte AS-number or 4-byte AS-number: aa:bb format (for example, 11:22) • IPv4 address and index:aa.bb.cc.dd:ee format (for example, 11.22.33.44:55)

options

Specifies a set of various options:

destination

(Optional) Specifies a network 127/8 address to be used as the destination address in the echo request packet.

start-address: Start of the network address.

end-address: End of the network address.

address increment: Incremental value of the network address, which is expressed as a decimal number value or IP address.

expexp-bits

(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.

flags

fec: (Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.

no-ttl: (Optional) Specifies not to add TTL expired flag in echo request.

force-explicit-null

(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.

jitter

(Optional) Specifies a jitter value for a corresponding echo request, in milliseconds. Range is 0 to 2147483647. Default is 200.

reply dscp dscp-value

(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.

mode [ipv4 | router-alert]

(Optional) Specifies the reply mode for the echo request packet.

ipv4

Reply with an IPv4 UDP packet (this is the default)

router-alert

Reply with an IPv4 UDP packet with the IP

router alert set

responder-id *ipv4-address*

(Optional) Adds responder identifier into corresponding echo request.

source *ipv4-address*

(Optional) Specifies the source address used in the echo request packet.

timeout *timeout*

(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.

ttl

(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255). Default is 255.

verbose

(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default No default behavior or values

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operation
	basic-services	execute
	mpls-te or mpls-ldp	read

The following examples show how to verify path tracing for P2MP by using the **traceroute mpls mldp p2mp** command.

```
RP/0/RP0/CPU0:router#traceroute mpls mldp p2mp 192.168.0.1 ipv4 2.2.2.2 232.1.1.1 ttl 4
Mon Jul 11 15:36:42.299 JST
```

```
Tracing MPLS Label Switched Path to mldp p2mp 192.168.0.1 ipv4 (2.2.2.2, 232.1.1.1),
timeout is 2.2 seconds, jitter value is 200 msec
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
```

```
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
d 1 10.10.10.2 54 ms [Estimated Role: Branch]
  [L] DDMAP 0: 11.11.11.3 11.11.11.3 MRU 1500 [Labels: 16016 Exp: 0]
  [L] DDMAP 1: 12.12.12.4 12.12.12.4 MRU 1500 [Labels: 16016 Exp: 0]

! 2 11.11.11.3 47 ms [Estimated Role: Egress]
! 2 12.12.12.4 68 ms [Estimated Role: Egress]
. 3 *
. 4 *
```

```
RP/0/RP0/CPU0:router#tracroute mpls mldp p2mp 192.168.0.1 ipv4 2.2.2.2 232.1.1.1 ttl 4
jitter 300
Mon Jul 11 15:37:18.976 JST
```

```
Tracing MPLS Label Switched Path to mldp p2mp 192.168.0.1 ipv4 (2.2.2.2, 232.1.1.1),
  timeout is 2.3 seconds, jitter value is 300 msec
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP
```

Type escape sequence to abort.

```
d 1 10.10.10.2 77 ms [Estimated Role: Branch]
  [L] DDMAP 0: 11.11.11.3 11.11.11.3 MRU 1500 [Labels: 16016 Exp: 0]
  [L] DDMAP 1: 12.12.12.4 12.12.12.4 MRU 1500 [Labels: 16016 Exp: 0]

! 2 12.12.12.4 15 ms [Estimated Role: Egress]
! 2 11.11.11.3 114 ms [Estimated Role: Egress]
. 3 *
. 4 *
```

Related Commands

Command	Description
ping mpls mldp (P2MP), on page 22	Verifies data plane and control plane for the point-to-multipoint (P2MP) label switch path.
tracroute mpls mldp (MP2MP), on page 53	Verifies hop-by-hop fault localization and path tracing for the multipoint-to-multipoint path.

traceroute mpls mldp (MP2MP)

To verify hop-by-hop fault localization and path tracing for the multipoint-to-multipoint path (MP2MP), use the **traceroute mpls mldp mp2mp** command in XR EXEC mode.

```
traceroute mpls mldp mp2mp root-address {IPv4 source-ipv4-address group-ipv4-address | IPv6
source-ipv6-address group-ipv6-address | vpn4 AS-number [source-ipv4-address group-ipv4-address] |
vpn6 AS-number [source-ipv6-address group-ipv6-address] | mdt oui:vpn-index mdt-number | global-id
lsp-id} [options]
```

Syntax	Description
mldp	Verifies the ping capability for multicast label distribution protocol (mldp).
mp2mp	Indicates the Multipoint-to-Multipoint (MP2MP) label switch path.
<i>root-address</i>	Specifies the root address.
IPv4 <i>ipv4-address</i>	Defines IPv4 opaque encoding.
IPv6 <i>ipv6-address</i>	Defines IPv6 opaque encoding.
vpn4 <i>AS-number</i> [<i>source-ipv4-address group-ipv4-address</i>]	Defines VPNv4 opaque encoding.
vpn6 <i>AS-number</i> [<i>source-ipv6-address group-ipv6-address</i>]	Defines VPNv6 opaque encoding.
mdt <i>oui:vpn-index mdt number</i>	Defines VPN ID opaque encoding. Range of 3-byte OUI is 0 to 16777215. Range of <i>mdt-number</i> is 0 to 4294967295.
global-id <i>lsp-id</i>	Defines 4 byte global LSP ID opaque encoding.
<i>source-address</i>	Specifies the source address of target multicast address.
<i>group-address</i>	Specifies the target address of target multicast address.
<i>AS-number</i>	Specifies the Autonomous system number as follows: <ul style="list-style-type: none"> • 4-byte AS-number with asdot (X.Y) : aa.bb.cc format (for example, 11.22:33) • 2-byte AS-number or 4-byte AS-number: aa.bb format (for example, 11:22) • IPv4 address and index:aa.bb.cc.dd:ee format (for example, 11.22.33.44:55)

options

Specifies a set of various options:

destination

(Optional) Specifies a network 127/8 address to be used as the destination address in the echo request packet.

start-address: Start of the network address.

end-address: End of the network address.

address increment: Incremental value of the network address, which is expressed as a decimal number value or IP address.

expexp-bits

(Optional) Specifies the MPLS experimental field value in the MPLS header for echo replies. Range is 0 to 7. Default is 0.

flags

fec: (Optional) Specifies that forwarding equivalent class (FEC) stack checking is to be performed at transit routers.

no-ttl: (Optional) Specifies not to add TTL expired flag in echo request.

force-explicit-null

(Optional) Forces an unsolicited explicit null label to be added to the MPLS label stack and allows LSP ping to be used to detect LSP breakages at the penultimate hop.

jitter

(Optional) Specifies a jitter value for a corresponding echo request, in milliseconds. Range is 0 to 2147483647. Default is 200.

reply dscp-value

(Optional) Specifies the differentiated service codepoint value for an MPLS echo reply.

mode [ipv4 | router-alert]

(Optional) Specifies the reply mode for the echo request packet.

ipv4

Reply with an IPv4 UDP packet (this is the default)

router-alert

Reply with an IPv4 UDP packet with the IP

router alert set

responder-id *ipv4-address*

(Optional) Adds responder identifier into corresponding echo request.

source *ipv4-address*

(Optional) Specifies the source address used in the echo request packet.

timeout *timeout*

(Optional) Specifies the timeout interval, in seconds. Range is 0 to 3600. Default is 2.

ttl

(Optional) Specifies the TTL value to be used in the MPLS labels (range is 1 to 255). Default is 255.

verbose

(Optional) Enables verbose output information, including MPLS echo reply, sender address of the packet, and return codes.

Command Default `ttl255 jitter200`

Command Modes XR EXEC

Command History	Release	Modification
	Release 5.2.1	This command was introduced.

Task ID	Task ID	Operation
	basic-services	execute
	mpls-te or mpls-ldp	read

The following examples show how to verify path tracing for MP2MP by using the **traceroute mpls mldp mp2mp** command.

```
RP/0/RP0/CPU0:router#traceroute mpls mldp mp2mp 192.168.0.1 global-id 1 ttl 4
```

```
Tracing MPLS Label Switched Path to mldp mp2mp 192.168.0.1 global-id 1,
  timeout is 2.2 seconds, jitter value is 200 msec
```

```
Codes: '!' - success, 'Q' - request not sent, '.' - timeout,
'L' - labeled output interface, 'B' - unlabeled output interface,
'D' - DS Map mismatch, 'F' - no FEC mapping, 'f' - FEC mismatch,
'M' - malformed request, 'm' - unsupported tlvs, 'N' - no rx label,
'P' - no rx intf label prot, 'p' - premature termination of LSP,
'R' - transit router, 'I' - unknown upstream index,
```


'X' - unknown return code, 'x' - return code 0, 'd' - DDMAP

Type escape sequence to abort.

```
! 1 10.10.10.2 41 ms [Estimated Role: Bud]
  [L] DDMAP 0: 11.11.11.3 11.11.11.3 MRU 1500 [Labels: 16020 Exp: 0]
  [L] DDMAP 1: 12.12.12.4 12.12.12.4 MRU 1500 [Labels: 16020 Exp: 0]

! 2 11.11.11.3 16 ms [Estimated Role: Egress]
! 2 12.12.12.4 17 ms [Estimated Role: Egress]
. 3 *
. 4 *
```

Related Commands

Command	Description
ping mpls mldp (MP2MP), on page 28	Verifies data plane and control plane for the multipoint-to-multipoint (MP2MP) label switch path.
traceroute mpls mldp (P2MP), on page 48	Verifies hop-by-hop fault localization and path tracing for the point-to-multipoint path.

