



Cisco MDS 9000 Software Upgrade and Downgrade Guide, Release 8.x

First Published: May 4, 2017

Updated: August 18, 2023

This document describes how to upgrade or downgrade the Cisco MDS NX-OS software for Cisco MDS 9000 Series Multilayer Switches.



Note

The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

This guide includes the following sections:

- [Introduction, page 3](#)
- [Supported Components, page 3](#)
- [Determining the Software Version, page 4](#)
- [Installing Cisco MDS NX-OS Release 8.x Software on a Cisco MDS Switch, page 6](#)
- [Supported Nondisruptive Upgrade Paths for Cisco MDS NX-OS Releases, page 14](#)
- [Supported FICON Upgrade Paths for Cisco MDS NX-OS Releases, page 26](#)
- [Upgrading Cisco MDS NX-OS Release 8.x on an Existing Cisco MDS Switch, page 28](#)
- [Moving From an NPE Image to a non-NPE Image and Vice Versa, page 47](#)
- [Supported Downgrade Paths for Cisco MDS NX-OS Releases, page 51](#)
- [Supported FICON Downgrade Paths for Cisco MDS NX-OS Releases, page 59](#)
- [Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.x, page 62](#)
- [Related Documentation, page 75](#)
- [Obtaining Documentation and Submitting a Service Request, page 76](#)

Table 1 **Change History**

Date	Description
August 18, 2023	Updated FICON ISSU and ISSD paths.
February 19, 2022	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(2d).
August 26, 2021	Added ISSD guideline for OBFL TxWait.
May 18, 2021	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(2c) and Cisco MDS NX-OS Release 8.5(1).
March 4, 2021	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.5(1).
November 26, 2020	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(2b).
July 1, 2020	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(2a).
May 4, 2020	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(2).
December 12, 2019	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Release 8.4(1a).
August 29, 2019	Updated the nondisruptive ISSU and ISSD paths for the Cisco MDS NX-OS Releases 8.3(2), 8.3(1), 8.2(2), 8.2(1), and 8.1(1b).
June 22, 2019	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.4(1).
December 17, 2018	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.3(2).
October 22, 2018	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.1(1b).
July 13, 2018	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.3(1).
March 9, 2018	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.2(2).
February 28, 2018	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.1(1a).
September 28, 2017	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.2(1).
May 04, 2017	Added guidelines for upgrading to Cisco MDS NX-OS Release 8.1(1).

Introduction

The Cisco MDS 9000 Series of Multilayer Directors and Fabric Switches provide best-in-class high availability, scalability, security, and management, allowing you to deploy high-performance storage area networks. Layering a rich set of intelligent features onto a high-performance switch fabric, the Cisco MDS 9000 Series addresses the stringent requirements of large data center storage environments: high availability, security, scalability, ease of management, and seamless integration of new technologies.

About Software Images

Cisco MDS switch is shipped with the Cisco MDS NX-OS operating system for the Cisco MDS 9000 Series Multilayer Directors and Fabric Switches. The Cisco MDS NX-OS software consists of two images: the kickstart image and the system image.

- To select the kickstart image, use the KICKSTART variable.
- To select the system image, use the SYSTEM variable.

The images and variables are important factors in any install procedure. Specify the variable and the respective image to upgrade or downgrade your switch. You do not always need both the kickstart and system images for installing the operating system.

**Note**

Do not rename the standard image filenames.

**Note**

To download a new Cisco MDS 9000 Series software, including Cisco NX-OS and Cisco DCNM management software, go to the Storage Networking Software download website at <http://www.cisco.com/cisco/software/navigator.html>

Release notes are sometimes updated with the new information on restrictions and caveats. Refer to the following website for the most recent version of the [Cisco MDS 9000 Series Release Notes](#).

Dependent Factors for Software Installation

The software image install procedure depends on the following factors:

- Software images — The kickstart and system image files reside in directories or folders that can be accessed from the Cisco MDS 9000 Series Multilayer switch prompt.
- Image version — Each image file has a version.
- Flash disks on the switch — The bootflash: resides on the supervisor module, and the CompactFlash disk is inserted into the slot0: device.
- Supervisor modules — Either single or dual supervisor modules are present.

Supported Components

For information on supported software and hardware components, see the [Cisco MDS 9000 Series Compatibility Matrix](#).

Determining the Software Version

To determine the version of the Cisco MDS NX-OS software that is currently running on a Cisco MDS 9000 switch using the CLI, log in to the switch and run the **show version** command in privileged EXEC mode.

To determine the version of the Cisco MDS NX-OS software currently running on a Cisco MDS 9000 switch using Cisco DCNM for SAN, click the **Switches** tab in the **Information** pane, locate the relevant switch using the corresponding IP address, logical name, or worldwide name (WWN), and check its version in the **Release** column.

Downloading Software

The Cisco MDS NX-OS software is designed for mission-critical high-availability environments. To realize the benefits of nondisruptive upgrade on the Cisco MDS 9700 Series Multilayer Directors, we recommend that you install dual supervisor modules.



Note

All the CLI session examples that are provided in this document are intended only for reference. The actual switch output differs based on your switch model.

To download the latest Cisco MDS NX-OS software, access the Software Center at:

<http://www.cisco.com/cisco/software/navigator.html?a=a&i=rpm>

Use the **show incompatibility-all system bootflash:system image filename** command to determine which features are incompatible with the destination upgrade release.

```
switch(config)# show incompatibility-all system bootflash:m9700-sf4ek9-mz.8.4.1.bin
```

```
Checking incompatible configuration(s):
No incompatible configurations
```

```
Checking dynamic incompatibilities:
No incompatible configurations
```

To request a copy of the source code under the terms of either GPL (General Public License) or LGPL (Lesser General Public License), email mds-software-disclosure@cisco.com.

Selecting the Software Image for a Cisco MDS Switch

Table 2 lists the system and kickstart image that you can use for a Cisco MDS switch.

Table 2 Software Images for Cisco MDS Switches

Cisco MDS Switch	Naming Convention
Cisco MDS 9396T	Filenames begin with m9300-s2ek9
Cisco MDS 9148T	Filenames begin with m9148-s6ek9
Cisco MDS 9132T	Filenames begin with m9100-s6ek9
Cisco MDS 9148S	Filenames begin with m9100-s5ek9
Cisco MDS 9220i	Filenames begin with m9220-s7ek9

Table 2 Software Images for Cisco MDS Switches (continued)

Cisco MDS Switch	Naming Convention
Cisco MDS 9250i	Filenames begin with m9250-s5ek9
Cisco MDS 9396S	Filenames begin with m9300-s1ek9
Cisco MDS 9718, 9710, and 9706	Filenames begin with m9700-sf3ek9 ¹ Filenames begin with m9700-sf4ek9 ²

1. The m9700-sf3ek9 filename images are supported only on Cisco MDS 9700 Series Supervisor-1 Module on Cisco MDS 9710 and 9706 Director Switches, and Cisco MDS 9700 Series Supervisor-1E Module on Cisco MDS 9718 Director Switches.
2. The m9700-sf4ek9 filename images are supported only on Cisco MDS 9700 Series Supervisor-4 Module on Cisco MDS 9710 and 9706 Director Switches.

No Payload Encryption Software Images

No payload encryption (NPE) images are available with the Cisco MDS NX-OS Release 8.5(1) software. The NPE images are intended for countries that have import restrictions on products that encrypt payload data.

To differentiate an NPE image from a standard software image, the letters *npe* are included in the image name as follows:

- m9100-s6ek9-kickstart-mz-npe.8.5.1.bin
- m9100-s6ek9-mz-npe.8.5.1.bin
- m9100-s6ek9-kickstart-mz-npe.8.5.1.bin
- m9100-s6ek9-mz-npe.8.5.1.bin
- m9100-s5ek9-kickstart-mz-npe.8.5.1.bin
- m9100-s5ek9-mz-npe.8.5.1.bin
- m9148-s6ek9-kickstart-mz-npe.8.5.1.bin
- m9148-s6ek9-mz-npe.8.5.1.bin
- m9300-s2ek9-kickstart-mz-npe.8.5.1.bin
- m9300-s2ek9-mz-npe.8.5.1.bin
- m9220-s7ek9-kickstart-mz-npe.8.5.1.bin
- m9220-s7ek9-mz-npe.8.5.1.bin
- m9250-s5ek9-kickstart-mz-npe.8.5.1.bin
- m9250-s5ek9-mz-npe.8.5.1.bin
- m9300-s1ek9-kickstart-mz-npe.8.5.1.bin
- m9300-s1ek9-mz-npe.8.5.1.bin
- m9700-sf3ek9-kickstart-mz-npe.8.5.1.bin
- m9700-sf3ek9-mz-npe.8.5.1.bin
- m9700-sf4ek9-kickstart-mz-npe.8.5.1.bin
- m9700-sf4ek9-mz-npe.8.5.1.bin

**Note**

When downloading software, ensure that you select the correct software image for your Cisco MDS 9000 Series Multilayer switch. Nondisruptive software upgrades or downgrades between NPE images and non-NPE images are not supported.

Installing Cisco MDS NX-OS Release 8.x Software on a Cisco MDS Switch

To install the latest Cisco MDS NX-OS Release 8.x software images on a new Cisco MDS 9000 Series Multilayer switch, perform the following steps:

Step 1 Log in to Cisco.com and click **Log In** at the top of the page. Enter your Cisco username and password.

**Note**

Use your registered Cisco username and password to access the links provided in this document.

Step 2 Verify the following physical connections for the new Cisco MDS 9000 Series Multilayer switch:

- The console port is physically connected to a computer terminal (or terminal server).
- The management 10/100/1000 Ethernet port (mgmt0) is connected to an external hub, switch, or a router.

For more information about physical connections, see the [Cisco MDS 9000 Series Hardware Installation guides](#).

**Note**

On switches with dual supervisor modules, both the supervisor modules must have Ethernet connections on the management interfaces (mgmt 0) to maintain connectivity when switchovers occur during upgrades and downgrades.

**Note**

If the management 10/100/1000 Ethernet port (mgmt0) interface of the Cisco MDS 9700 Series Multilayer Directors has a preconfigured “/0” IPv6 address that cannot be removed, use the **write erase boot** command to clear the complete configuration of the device and reload the device using the **reload** command. Perform this process before commissioning the device into production, because this process is disruptive to the user traffic if it is applied to the active supervisor of a system. Ensure that there is an active console connection to the supervisor, because this process removes the IPv4 address of the mgmt0 interface.

**Tip**

Save the host ID information for future use, for example, to enable licensed features. The host ID information is provided in the Proof of Purchase document that accompanies the switch.

Step 3 Verify that the default console port parameters listed below are identical to the parameters of the computer terminal (or terminal server) attached to the switch console port:

- 9600 baud
- 8 data bits

- 1 stop bit
- No parity

See the “Configuring Terminal Settings and Sessions” chapter in the [Cisco MDS 9000 Series NX-OS Fundamentals Configuration Guide](#).

- Step 4** Power up the Cisco MDS 9000 Series Multilayer switch. The switch boots up automatically after powering on the switch.
- Step 5** Obtain the IP address, subnet mask, and default gateway information that is required for the Cisco MDS 9000 Series Multilayer switch to communicate over the supervisor module Ethernet interface. This information is required to configure and manage the switch.

See the “Using the Cisco NX-OS Setup Utility” chapter in the [Cisco MDS 9000 Series NX-OS Fundamentals Configuration Guide](#).

- Step 6** Complete the System Admin Account Setup process.
If you create a short, easy-to-decipher password, your password will be rejected. Configure a strong password, as shown in the sample configuration. Passwords are case-sensitive. Explicitly create a password that meets the requirements that are listed in the “Characteristics of Strong Passwords” section in the “Configuring Users and Common Roles” chapter in the [Cisco MDS 9000 Series NX-OS Security Configuration Guide](#).



Note You can change the default password during the initial setup process. All Cisco MDS 9000 Series Multilayer switches have the network administrator as the default user (admin) with a default password (admin). You cannot change the default user.

```
---- System Admin Account Setup ----

Do you want to enforce secure password standard (yes/no) [y]: no

Enter the password for "admin":

Confirm the password for "admin":
```

- Step 7** Enter **yes** to when prompted, to set up a mode and assign the information that is obtained in Step 5.
See the “Using the Cisco NX-OS Setup Utility” chapter in the [Cisco MDS 9000 Series NX-OS Fundamentals Configuration Guide](#).



Note Press **Ctrl-C** at prompts to skip the remaining configuration options and proceed with what is configured until that point.



Tip If you do not want to answer a previously configured question, or if you want to skip answers to any questions, press **Enter**. If a default answer is not available (for example, a switch name), the switch uses the previously configured settings and moves to the next question.

The CLI configuration step (using factory defaults) is as follows:

```
---- Basic System Configuration Dialog ----

This setup utility will guide you through the basic configuration of
the system. Setup configures only enough connectivity for management
of the system.
```

Press Enter incase you want to skip any dialog. Use ctrl-c at anytime to skip remaining dialogs.

Would you like to enter the basic configuration dialog (yes/no): **yes**

By default, two roles exist in all the switches:

- Network operator (network-operator) — Has permission to view only the configuration. The operator cannot make any configuration changes.
- Network administrator (network-admin) — Has permission to execute all commands and make configuration changes. The administrator can also create and customize up to 64 additional roles. One of these 64 additional roles can be configured during the initial setup process.

Create another login account (yes/no) [n]: **yes**



Note While configuring your initial setup, you can create an additional user account (if you are in the network-admin role) besides the administrator's account. The username must contain only non-numeric characters. See the "Configuring User Accounts" section in the "Configuring Users and Common Roles" chapter in the *Cisco MDS 9000 Series NX-OS Security Configuration Guide*.

Enter the user login ID: *test*

Enter the password for "test":

Confirm the password for "test":

Enter the user role [network-operator]:



Note If you use SNMPv3, do not configure the SNMPv2 community string. Refer to the "Configuring SMNP" chapter in the *Cisco MDS 9000 Series NX-OS System Management Configuration Guide*.

Configure read-only SNMP community string (yes/no) [n]: **yes**

SNMP community string: *admin*



Note The switch name is limited to 32 alphanumeric characters.

Enter the switch name: *switch*

Continue with Out-of-band (mgmt0) management configuration? [yes/no]: **yes**



Note IPv6 is supported in Cisco MDS NX-OS Release 4.1(x) and later. However, the setup script supports only IPv4 for the management interface. For information about configuring IPv6 in the management interface, see the *Cisco MDS 9000 Series NX-OS IP Services Configuration Guide* or the *IP Services Configuration Guide, Cisco DCNM for SAN*.

Mgmt0 IPv4 address: *ip_address*

Mgmt0 IPv4 netmask: *subnet_mask*

Configure the default gateway? (yes/no) [y]: **yes**

IPv4 address of the default gateway : 10.104.122.1

Configure advanced IP options? (yes/no) [n]: **yes**

Continue with In-band (vsan1) management configuration? (yes/no) [n]: **yes**

Enable IP routing? (yes/no) [n]: **yes**

Configure static route? (yes/no) [n]: **n**



Note Ensure that you have configured the IP route, IP default network address, and IP default gateway address to enable the SNMP access. If IP routing is enabled, the switch uses the IP route and the default network IP address. If IP routing is disabled, the switch uses the default gateway IP address.

Configure the default-network: (yes/no) [y]: **yes**



Note The default network address is Destination prefix: *dest_prefix* provided in Mgmt0 IPv4 netmask: *subnet_mask*.

Default network IPv4 address: *dest_prefix*

Configure the DNS IPv4 address? (yes/no) [y]: **yes**

DNS IP address: *name_server_ip_address*

Configure the default domain name? (yes/no) [n]: **yes**

Default domain name: *domain_name*

Enable the ssh service? (yes/no) [y]:

Type of ssh key you would like to generate (dsa/rsa) [rsa]:

Number of rsa key bits <1024-4096> [1024]:

Enable the telnet service? (yes/no) [n]: **y**

Configure congestion/no_credit drop for fc interfaces? (yes/no) [y]: **n**

Enable the http-server? (yes/no) [y]:

Configure clock? (yes/no) [n]:

Configure timezone? (yes/no) [n]: **yes**

Enter timezone config [PST/MST/CST/EST] :**PST**

Enter Hrs offset from UTC [-23:+23] :

Enter Minutes offset from UTC [0-59] :+23

Configure summertime? (yes/no) [n]: **yes**

summer-time config :PDT 2 sunday march 02:00 1 sunday november 02:00 59

Configure NTP server? (yes/no) [n]: **yes**

NTP server IP address: *ntp_server_IP_address*

Configure default switchport interface state (shut/noshut) [shut]: **shut**



Note The mgmt0 interface is not shut down at this point. Only the Fibre Channel, iSCSI, FCIP, and Gigabit Ethernet interfaces are shut down.

Configure default switchport trunk mode (on/off/auto) [on]: **on**

Configure default switchport port mode F (yes/no) [n]: **yes**

Configure default zone policy (permit/deny) [deny]: **deny**

Enable full zoneset distribution (yes/no) [n]: **yes**

Configure default zone mode (basic/enhanced) [basic]: **basic**

See the “Configuring and Managing Zones” chapter in the [Cisco MDS 9000 Series NX-OS Fabric Configuration Guide](#).

The following configuration is applied:

```
username admin password admin_pass role network-admin
username user_name password user_pass role network-admin
snmp-server community snmp_community role
switchname switch
interface mgmt0
  ip address ip_address subnet_mask
  no shutdown
ip routing
ip route dest_prefix dest_mask dest_address
ip default-network dest_prefix
ip default-gateway default_gateway
ip name-server name_server
ip domain-name domain_name
telnet server disable
ssh key rsa 2048 force
ssh server enable
ntp server ipaddr ntp_server
system default switchport shutdown
system default switchport trunk mode on
system default switchport mode F
system default port-channel auto-create
zone default-zone permit vsan 1-4093
zoneset distribute full vsan 1-4093
system default zone mode enhanced
```

Would you like to edit the configuration? (yes/no) [n]: **no**

Would you like to edit the configuration? (yes/no) [n]: **no**

Use this configuration and save it? (yes/no) [y]: **yes**



Caution If you do not save the configuration at this point, your changes will not be updated the next time the switch is rebooted. Type **yes** in order to save the new configuration. This process ensures that the kickstart and system boot images are also automatically configured.



Tip Up to this point, you can only configure the switch using the CLI. Post this point, continue to configure the switch using either the CLI or the Cisco DCNM application. For more information on using the Cisco DCNM application to configure a switch, see the [Cisco DCNM Fundamentals Configuration Guide](#).

```
Would you like to save the running-config to startup-config? (yes/no) [n]: y
```

```
[#####] 100%
Copy complete.
```

If you continue to use the CLI, the login prompt is automatically displayed on your terminal:

Step 8 Log in to the switch using the new username and password.

Step 9 Verify that the required licenses are installed in the switch using the **show license** command.



Note The switch is initially shipped with the required licenses installed in the system. However, the initial license file does not cover unlicensed features that may be used during the grace period. For more information on licensing, see the [Cisco MDS 9000 Series NX-OS Licensing Guide](#).

The following example shows the CLI output for a valid license:

```
switch# show license
license.lic:
SERVER this_host ANY
VENDOR cisco
INCREMENT ENTERPRISE_PKG cisco 1.0 permanent uncounted \
  VENDOR_STRING=MDS HOSTID=VDH=REG070201 \
  NOTICE="<LicFileID>ent_ips_main_fm.lic</LicFileID><LicLineID>0</LicLineI
D> \
  <PAK>dummyPak</PAK>" SIGN=FB454F0A0D40
INCREMENT MAINFRAME_PKG cisco 1.0 permanent uncounted \
  VENDOR_STRING=MDS HOSTID=VDH=REG070201 \
  NOTICE="<LicFileID>ent_ips_main_fm.lic</LicFileID><LicLineID>1</LicLineI
D> \
  <PAK>dummyPak</PAK>" SIGN=0DAE1B086D9E
INCREMENT SAN_EXTN_OVER_IP cisco 1.0 permanent 7 VENDOR_STRING=MDS \
  HOSTID=VDH=REG070201 \
  NOTICE="<LicFileID>ent_ips_main_fm.lic</LicFileID><LicLineID>2</LicLineI
D> \
  <PAK>dummyPak</PAK>" SIGN=D336330C76A6
INCREMENT FM_SERVER_PKG cisco 1.0 permanent uncounted \
  VENDOR_STRING=MDS HOSTID=VDH=REG070201 \
  NOTICE="<LicFileID>ent_ips_main_fm.lic</LicFileID><LicLineID>3</LicLineI
D> \
  <PAK>dummyPak</PAK>" SIGN=AEAEA04629E8
```

Step 10 Verify that the switch is running the latest Cisco MDS NX-OS Release 8.x software, depending on which version you have installed, by using the **show version** command:

```
switch# show version

Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Documents:
http://www.cisco.com/en/US/products/ps9372/tsd_products_support_series_home.html
Copyright (c) 2002-2019, Cisco Systems, Inc. All rights reserved.
The copyrights to certain works contained in this software are
owned by other third parties and used and distributed under
```

license. Certain components of this software are licensed under the GNU General Public License (GPL) version 2.0 or the GNU Lesser General Public License (LGPL) Version 2.1. A copy of each such license is available at <http://www.opensource.org/licenses/gpl-2.0.php> and <http://www.opensource.org/licenses/lgpl-2.1.php>

```
Software
BIOS: version 3.2.0
kickstart: version 8.4(1) [build 8.4(1)]
system: version 8.4(1) [build 8.4(1)]
BIOS compile time: 09/27/2018
kickstart image file is: bootflash:///m9700-sf4ek9-kickstart-mz.8.4.1.bin
kickstart compile time: 5/31/2019 12:00:00 [03/20/2019 12:14:26]

system image file is: bootflash:///m9700-sf4ek9-mz.8.4.1.bin
system compile time: 5/31/2019 12:00:00 [03/20/2019 13:49:56]
```

```
Hardware
cisco MDS 9710 (10 Slot) Chassis ("Supervisor Module-3")
Intel(R) Xeon(R) CPU with 8167260 kB of memory.
Processor Board ID JAE17050AU2
```

```
Device name: switch
bootflash: 3915776 kB
slot0: 0 kB (expansion flash)
```

```
Kernel uptime is 0 day(s), 0 hour(s), 48 minute(s), 25 second(s)
```

```
Last reset
Reason: Unknown
System version: 8.4(1)
Service:
```

```
plugin
Core Plugin, Ethernet Plugin
3:22 PM
```

If the latest Cisco MDS NX-OS Release 8.x software version is displayed, you can continue configuring the switch using one of the following options:

- Configure other Cisco MDS NX-OS features using the CLI. For more information about this, see [Cisco MDS 9000 NX-OS and SAN-OS Configuration guides](#).
- Use Cisco DCNM-SAN to configure your switch. For more information, see the [Cisco DCNM for SAN Configuration guides](#).

If the latest Cisco MDS NX-OS Release 8.x software is not displayed, continue upgrading or downgrading the switch, as required, to install the correct version.

Step 11 Verify the status of the modules on the switch, using the **show module** command.

```
switch# show module
```

Mod	Ports	Module-Type	Model	Status
1	48	4/8/16/32 Gbps Advanced FC Module	DS-X9648-1536K9	ok
2	48	4/8/16/32 Gbps Advanced FC Module	DS-X9648-1536K9	ok
3	48	2/4/8/10/16 Gbps Advanced FC Module	DS-X9448-768K9	ok
4	48	4/8/16/32 Gbps Advanced FC Module	DS-X9648-1536K9	ok
5	0	Supervisor Module-4	DS-X97-SF4-K9	active *
6	0	Supervisor Module-4	DS-X97-SF4-K9	ha-standby

```

7    48    2/4/8/10/16 Gbps Advanced FC Module DS-X9448-768K9    ok
8    48    1/10 Gbps Ethernet Module                DS-X9848-480K9    ok
10   34    1/10/40G IPS,2/4/8/10/16G FC Module DS-X9334-K9      ok

```

```

Mod  Sw              Hw
---  -
1    8.4 (1)          1.0
2    8.4 (1)          1.0
3    8.4 (1)          2.0
4    8.4 (1)          1.0
5    8.4 (1)          1.0
6    8.4 (1)          1.4
7    8.4 (1)          2.0
8    8.4 (1)          1.1
10   8.4 (1)          1.0

```

```

Mod  MAC-Address(es)                Serial-Num
---  -
1    2c-31-24-50-59-d4 to 2c-31-24-50-5a-08 JAE205202WW
2    00-b8-b3-ee-03-38 to 00-b8-b3-ee-03-6c JAE223403BK
3    00-d6-fe-b0-4b-88 to 00-d6-fe-b0-4b-8b JAE223003C1
4    00-76-86-be-41-79 to 00-76-86-be-41-ad JAE2039020M
5    00-2f-5c-fc-81-dc to 00-2f-5c-fc-81-ef JAE22490XKR
6    70-18-a7-7e-f8-94 to 70-18-a7-7e-f8-a7 JAE22440CB0
7    3c-0e-23-c4-9c-84 to 3c-0e-23-c4-9c-87 JAE18030477
8    0c-68-03-29-90-4c to 0c-68-03-29-90-7f JAE173000Q4
10   00-8e-73-39-81-50 to 00-8e-73-39-81-5f JAE200504DK

```

```

Mod  Online Diag Status
---  -
1    Pass
2    Pass
3    Pass
4    Pass
5    Pass
6    Pass
7    Pass
8    Pass
10   Pass

```

```

Xbar  Ports  Module-Type                Model                Status
---  -
1    0      Fabric Module 3            DS-X9710-FAB3       ok
2    0      Fabric Module 3            DS-X9710-FAB3       ok
3    0      Fabric Module 3            DS-X9710-FAB3       ok
4    0      Fabric Module 3            DS-X9710-FAB3       ok

```

```

Xbar  Sw              Hw
---  -
1    NA              1.1
2    NA              1.1
3    NA              1.1
4    NA              1.1

```

```

Xbar  MAC-Address(es)                Serial-Num
---  -
1    NA              JAE222305V6
2    NA              JAE222305VA
3    NA              JAE22170963
4    NA              JAE2217096Z

```

Supported Nondisruptive Upgrade Paths for Cisco MDS NX-OS Releases

This section provides information on nondisruptive upgrade paths that are supported for Cisco MDS NX-OS software Release 8.x. It includes the following topics:

- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.5\(1\)](#), page 14
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2f\)](#), page 15
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2e\)](#), page 16
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2f\)](#), page 15
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2c\)](#), page 17
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2b\)](#), page 17
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2a\)](#), page 18
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2\)](#), page 19
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(1a\)](#), page 19
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(1\)](#), page 20
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3\(2\)](#), page 20
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3\(1\)](#), page 21
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2\(2\)](#), page 21
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2\(1\)](#), page 22
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1\(1b\)](#), page 23
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1\(1a\)](#), page 24
- [Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1\(1\)](#), page 25

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.5(1)



Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.5(1).

Table 3 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.5(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.1(1) until 8.4(2b)	Upgrade directly to MDS NX-OS Release 8.5(1)
8.4(2c) ¹	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(2b) 2. Upgrade to MDS NX-OS Release 8.5(1)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.5(1)

Table 3 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.5(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
6.2(29) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b), Release 8.4(2), Release 8.4(2a), or Release 8.4(2b) 2. Upgrade to MDS NX-OS Release 8.5(1)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.5(1)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.5(1)

1. Upgrading from Cisco MDS NX-OS Release 8.4(2c) directly to Cisco MDS NX-OS Release 8.5(1) is not supported. To perform this upgrade, set the boot variables and reload the switch - this process is disruptive. To upgrade nondisruptively, first downgrade from Cisco MDS NX-OS Release 8.4(2c) to an earlier release and from there upgrade to Cisco MDS NX-OS Release 8.5(1). For more information, see [CSCvx99164](#).

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2f)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2f).

Table 4 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2f)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(2f)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2f)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2f)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2f)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2f)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2e).

Table 5 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(2e)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2e)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2e)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2e)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2e)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2d)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2d).

Table 6 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2d)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases except 8.5(1) ¹	Upgrade directly to MDS NX-OS Release 8.4(2d)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2d)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2d)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2d)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2d)

1. If the SAN Analytics feature is enabled, then disable the SAN Analytics feature using the no feature analytics command before upgrading from Cisco MDS NX-OS 8.2(x) or Cisco MDS NX-OS 8.3(x) to Cisco MDS NX-OS Release 8.4(2) or later. However, you can upgrade from Cisco MDS NX-OS Release 8.4(1) and above releases to Cisco MDS NX-OS Release 9.2(1) or later without disabling the feature.

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2c).

Table 7 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases except 8.5(1) ¹	Upgrade directly to MDS NX-OS Release 8.4(2c)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2c)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2c)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2c)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2c)

1. If the SAN Analytics feature is enabled, then disable the SAN Analytics feature using the no feature analytics command before upgrading from Cisco MDS NX-OS 8.2(x) or Cisco MDS NX-OS 8.3(x) to Cisco MDS NX-OS Release 8.4(2) or later. However, you can upgrade from Cisco MDS NX-OS Release 8.4(1) and above releases to Cisco MDS NX-OS Release 9.2(1) or later without disabling the feature.

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2b)



Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2b).

Table 8 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2b)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(2b)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2b)

Table 8 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2b)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2b)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2b)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2b)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2a)


Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2a).

Table 9 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2a)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(2a)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2a)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2a)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2a)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2a)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2)


Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(2).

Table 10 *Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2)*

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(2)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2)
6.2(29) and above releases	Upgrade directly to MDS NX-OS Release 8.4(2)
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(1a)


Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(1a).

Table 11 *Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(1a)*

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(1a)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(1a)
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(1a)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(1a)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(1)


Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS Release 8.2(x) to Cisco MDS NX-OS Release 8.4(1).

Table 12 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.4(1)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(1)
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(1)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(1)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3(2)


Note

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS 8.2(x) to Cisco MDS NX-OS Release 8.3(2).


Note

When upgrading to Cisco MDS NX-OS Release 8.3(2) from release 8.3(1), any remote logging servers that are configured will be lost after the upgrade. After the upgrade is complete, reconfigure the remote logging server(s) using the **logging server** {*host-name* | *ipv4-address* | *ipv6-address*} command. For more information, see [CSCvn07339](#).

Table 13 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3(2)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.3(2)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.3(2)

Table 13 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3(2)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.3(2)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.3(2)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3(1)



Note If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading from Cisco MDS NX-OS 8.2(x) to Cisco MDS NX-OS Release 8.3(1).



Note Cisco MDS 9718 Multilayer Director Switches are not supported on Cisco MDS NX-OS Release 8.3(1).

Table 14 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.3(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.3(1)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.3(1)
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.3(1)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.3(1)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2(2)



Note Prior to upgrading any Cisco MDS 9706 and Cisco MDS 9710 switches to Cisco MDS NX-OS Release 8.2(2), the switches should be checked if they are affected by [CSCvf99665](#). This defect manifests as a corrupt IPv6 address with a zero length mask (/0) on the mgmt0 interface. The actual IPv6 address itself is not important but if it has a /0 mask then it is invalid. This invalid IPv6 address cannot be removed by normal configuration. Refer to the following example:

```
show interface mgmt0
mgmt0 is up
```

```
Internet address is 1.2.3.4/24
...
::148.173.170.255/0
fe80::2e31:24ff:fe51:b834/64
```

If a switch is found to be affected, there are specific steps that must be taken after upgrading to Cisco MDS NX-OS Release 8.2(2). For information on these specific steps, see the **Resolution Summary** section in [CSCvf99665](#).

**Note**

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before upgrading to Cisco MDS NX-OS Release 8.2(2).

Table 15 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2(2)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.2(2)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.2(2)
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.2(2)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.2(2)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2(1)

**Note**

Before upgrading any Cisco MDS 9706 and Cisco MDS 9710 switches to Cisco MDS NX-OS Release 8.2(1), the switches should be checked if they are affected by [CSCvf99665](#).

This defect manifests as a corrupt IPv6 address with a zero length mask (/0) on the mgmt0 interface. The actual IPv6 address itself is not important but if it has a /0 mask then it is invalid. This invalid IPv6 address cannot be removed by normal configuration. Refer to the following example:

```
show interface mgmt0
mgmt0 is up
Internet address is 1.2.3.4/24
...
::148.173.170.255/0
fe80::2e31:24ff:fe51:b834/64
```

If a switch is found to be affected, there are specific steps that must be taken after upgrading to Cisco MDS NX-OS Release 8.2(1). For information on these specific steps, see the **Resolution Summary** section in [CSCvf99665](#).

**Note**

Upgrading to Cisco MDS NX-OS Release 8.2(1) on a device with the **esp-aes-xcbc-mac** algorithm is not supported. In such a scenario, we recommend that you first change the algorithm, and then upgrade to Cisco MDS NX-OS Release 8.2(1).

**Note**

We recommend that you delete existing IP ACLs on the management interface before upgrading to Cisco MDS NX-OS Release 8.2(1). You can reconfigure the IP ACLs after the upgrade is complete. For more information, see [CSCvh30932](#).

Table 16 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.2(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.2(1)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.2(1)
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.2(1)
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.2(1)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1b)

**Note**

Before upgrading any Cisco MDS 9706 and Cisco MDS 9710 switches to Cisco MDS NX-OS Release 8.1(1b), the switches should be checked if they are affected by [CSCvf99665](#).

This defect manifests as a corrupt IPv6 address with a zero length mask (/0) on the mgmt0 interface. The actual IPv6 address itself is not important but if it has a /0 mask then it is invalid. This invalid IPv6 address cannot be removed by normal configuration. Refer to the following example:

```
show interface mgmt0
mgmt0 is up
Internet address is 1.2.3.4/24
...
::148.173.170.255/0
fe80::2e31:24ff:fe51:b834/64
```

If a switch is found to be affected, there are specific steps that must be taken after upgrading to Cisco MDS NX-OS Release 8.1(1b). For information on these specific steps, see the **Resolution Summary** section in [CSCvf99665](#).

**Note**

The Cisco MDS 9700 HVDC PSU (DS-CHV-3.5KW) is not supported in this release. When upgrading a device equipped with these units from any Cisco MDS NX-OS 6.x release do not use this release.

Table 17 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1b)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.1(1b)
All 7.3(x) releases	Upgrade directly to MDS NX-OS Release 8.1(1b)
6.2(13a) and above releases	Upgrade directly to MDS NX-OS Release 8.1(1b)
All 6.2(x) releases before 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1b)

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1a)



Note

Before upgrading any Cisco MDS 9706 and Cisco MDS 9710 switches to Cisco MDS NX-OS Release 8.2(2), the switches should be checked if they are affected by [CSCvf99665](#).

This defect manifests as a corrupt IPv6 address with a zero length mask (/0) on the mgmt0 interface. The actual IPv6 address itself is not important but if it has a /0 mask then it is invalid. This invalid IPv6 address cannot be removed by normal configuration. Refer to the following example:

```
show interface mgmt0
mgmt0 is up
Internet address is 1.2.3.4/24
...
::148.173.170.255/0
fe80::2e31:24ff:fe51:b834/64
```

If a switch is found to be affected, there are specific steps that must be taken after upgrading to Cisco MDS NX-OS Release 8.1(1a). For information on these specific steps, see the **Resolution Summary** section in [CSCvf99665](#).



Note

The Cisco MDS 9700 HVDC PSU (DS-CHV-3.5KW) is not supported in this release. When upgrading a device equipped with these units from any Cisco MDS NX-OS 6.x release do not use this release.

Table 18 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1a)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x releases	Upgrade directly to MDS NX-OS Release 8.1(1a)
All 7.3(x) releases	Upgrade directly to MDS NX-OS Release 8.1(1a)
6.2(21) ¹	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(23) 2. Upgrade to MDS NX-OS Release 8.1(1a)²

Table 18 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1a)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
All 6.2(13a) and above releases except 6.2(21)	Upgrade directly to MDS NX-OS Release 8.1(1a) ²
All 6.2(x) releases before 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1a)²

1. Upgrading specifically from MDS NX-OS Release 6.2(21) to MDS NX-OS Release 8.1(1a) is disruptive. For more information, see [CSCvj40760](#).

2. The Cisco MDS 9700 HVDC PSU (DS-CHV-3.5KW) is not supported in this release. Such devices must be upgraded directly to Cisco MDS NX-OS Release 8.2(x) or later via a disruptive reload.

Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1)



Note

Before upgrading the Cisco MDS 9706 and Cisco MDS 9710 switches to Cisco MDS NX-OS Release 8.1(1), ensure that they are not affected by [CSCvg05230](#). This defect manifests as a corrupt IPv6 address and mask on the mgmt0 interface. An affected switch cannot be upgraded or downgraded while running the Cisco MDS NX-OS Release 8.1(1). Because this issue cannot be resolved through normal methods, we recommend that you contact the Cisco TAC for help in purging the IPv6 NVRAM fields nondisruptively. This process is simpler if performed before upgrading to Cisco MDS NX-OS Release 8.1(1). For more information, including how to determine if a switch is affected, see [CSCvg05230](#) and [CSCvf99665](#).



Note

We recommend that you delete existing IP ACLs on the management interface before upgrading to Cisco MDS NX-OS Release 8.1(1). You can reconfigure the IP ACLs after the upgrade is complete. For more information, see [CSCvh30932](#).



Note

The Cisco MDS 9700 HVDC PSU (DS-CHV-3.5KW) is not supported in this release. When upgrading a device equipped with these units from any Cisco MDS NX-OS 6.x release do not use this release.

Table 19 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 7.3(x) releases	Upgrade directly to MDS NX-OS Release 8.1(1)
6.2(13a) and above releases	Upgrade directly to MDS NX-OS Release 8.1(1)
All 6.2(x) releases before 6.2(13a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 6.2(13a) 2. Upgrade to MDS NX-OS Release 8.1(1)

Supported FICON Upgrade Paths for Cisco MDS NX-OS Releases

This section provides information on FICON upgrade paths that are supported for Cisco MDS NX-OS software Release 8.x. It includes the following topics:

- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2e\), page 27](#)
- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2c\), page 27](#)
- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2b\), page 27](#)
- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4\(2b\), page 27](#)
- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1\(1b\), page 28](#)
- [FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1\(1a\), page 28](#)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

Table 20 FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
All 8.x FICON releases	Upgrade directly to MDS NX-OS Release 8.4(2e)
6.2(11e)	<ol style="list-style-type: none"> 1. Upgrade to MDS NX-OS Release 8.1(1a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(1c)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

Table 21 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.4(1a) and 8.4(2b)	Upgrade directly to MDS NX-OS Release 8.4(2c)
8.1(1b)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) 2. Upgrade to MDS NX-OS Release 8.4(2c)
8.1(1a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) 2. Upgrade to MDS NX-OS Release 8.4(2c)
6.2(11e)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(1a) or 8.4(2b) 4. Upgrade to MDS NX-OS Release 8.4(2c)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2b)

Table 22 Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2b)

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.1(1b) and 8.4(1a)	Upgrade directly to MDS NX-OS Release 8.4(2b)
8.1(1a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(2b)
6.2(11e)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(2b)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(1a)

Table 23 *Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.4(2f)*

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.1(1b)	Upgrade directly to MDS NX-OS Release 8.4(1a)
8.1(1a)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.4(1a)
6.2(11e)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1a) 2. Upgrade to MDS NX-OS Release 8.1(1b) 3. Upgrade to MDS NX-OS Release 8.4(1a)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1b)

Table 24 *FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1b)*

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.1(1b)	Upgrade directly to MDS NX-OS Release 8.4(2f)
6.2(11e)	<ol style="list-style-type: none"> 1. Upgrade directly to MDS NX-OS Release 8.1(1b) 2. Upgrade to MDS NX-OS Release 8.1(1b)

FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1a)

Table 25 *FICON Nondisruptive Upgrade Paths to Cisco MDS NX-OS Release 8.1(1a)*

Current Release	Nondisruptive Upgrade Path and Ordered Upgrade Steps
NX-OS:	
8.1(1a)	Upgrade directly to MDS NX-OS Release 8.1(1a)
6.2(11e)	Upgrade directly to MDS NX-OS Release 8.1(1a)

Upgrading Cisco MDS NX-OS Release 8.x on an Existing Cisco MDS Switch

This section provides information on upgrading your Cisco MDS NX-OS software to Cisco MDS NX-OS Release 8.x. It includes the following topics:

- [Upgrading Guidelines, page 29](#)
- [Upgrade Process for a Cisco MDS 9700 Series Multilayer Director, page 29](#)
- [Upgrading to Cisco MDS NX-OS Release 8.x on a Cisco MDS 9700 Series Multilayer Director, page 29](#)

- [Upgrading to Cisco MDS NX-OS Release 8.x on a Cisco MDS Fabric Switch, page 39](#)

Upgrading Guidelines

- We recommend that you do not perform an In-Service Software Upgrade (ISSU) concurrently on switches that are connected via FCIP ISLs. Rather perform the ISSU on one switch and after the ISSU is complete perform the ISSU on the adjacent switch. However, you can perform ISSUs concurrently on switches that are connected via Fibre Channel ISLs.
- Smartoptics is supported from Cisco MDS NX-OS Release 8.2(1) or later releases and are not supported on Cisco MDS NX-OS Release 8.1(1b) or earlier releases. If you insert the smartoptics on a switch running an unsupported release and upgrade to a supported release version, the ports will be error disabled and the ports will only come up after removing and inserting the SFP back to their ports.
- To upgrade or downgrade to a Cisco MDS NX-OS release version, the same release version of the kickstart and system images in the **install all** command must be used.
- If you copy firmware using the SFTP or SCP clients after enabling the **feature scp-server** or **feature sftp-server** command on your switch, ensure that you close the SFTP or SCP connection using the **no feature scp-server** or **no feature sftp-server** command before performing ISSU. Otherwise, ISSU will be disruptive. To avoid this issue, we recommend that you transfer files to the switch using the **copy** command instead or using the DCNM client.

Upgrade Process for a Cisco MDS 9700 Series Multilayer Director

On a Cisco MDS 9700 Series Multilayer Director, the high-level process to upgrade to Cisco MDS NX-OS Release 8.x is as follows:

-
- Step 1** Upgrade to Cisco MDS NX-OS Release 8.x, as described in [“Upgrading to Cisco MDS NX-OS Release 8.x on a Cisco MDS 9700 Series Multilayer Director”](#) section on page 29.
 - Step 2** Install the Cisco MDS 48-port 16-Gbps Fibre Channel Switching module in the Cisco MDS 9700 chassis. For additional information, see the [Cisco MDS 9700 Series Hardware Installation Guide](#).
 - Step 3** Install the Cisco MDS 48-port 10-Gigabit Ethernet module in the Cisco MDS 9700 chassis. For additional information, see the [Cisco MDS 9700 Series Hardware Installation Guide](#).
 - Step 4** If needed, reload the switch.

Upgrading to Cisco MDS NX-OS Release 8.x on a Cisco MDS 9700 Series Multilayer Director



Note

Use the console connection for firmware upgrades. If you are upgrading through the management interface, you must have a working connection to both supervisors because this process causes a switchover and the current standby supervisor will be active after the upgrade.



Note

Cisco MDS 9718 Multilayer Director supports only Cisco MDS NX-OS Release 7.3(0)D1(1) and later.



Note When the **system auto-collect tech-support** command is enabled, there is a delay of 600 seconds for the standby switch to reload and become HA-Standby in Cisco MDS 9700 Series Multilayer Directors.

To upgrade your switch to use the latest Cisco MDS NX-OS software on your Cisco MDS 9700 Series Multilayer Directors, perform the following steps:

Step 1 Go to <http://www.cisco.com/> and click **Log In** at the top of the page. Enter your Cisco Systems username and password.



Note Unregistered Cisco.com users cannot access secure links that are provided in this document.

Step 2 Verify the following physical connections for the new Cisco MDS 9700 Series Multilayer switch:

- The console port is physically connected to a computer terminal (or terminal server).
- The management 10/100/1000 Ethernet port (mgmt0) is connected to an external hub, switch, or router.

To verify the physical connections, see the hardware installation guide for your product. For more information, see the *Cisco MDS 9710 Director Hardware Installation Guide*.

Step 3 Log in to the switch.

Step 4 Run the **copy running-config startup-config** command to store your current running configuration. You can also create a backup of your existing configuration in a file by running the **copy running-config bootflash:backup_config.txt** command. See the “Using the Cisco NX-OS Setup Utility” chapter in the *Cisco MDS 9000 Series NX-OS Fundamentals Configuration Guide*.

Step 5 Save a copy of the **show tech-support** command output of the switch. For more information, see <https://www.cisco.com/c/en/us/td/docs/dcn/whitepapers/how-to-collect-logs-cisco-mds.html#Theshowtechsupportcommand>.

Step 6 Verify that the requested license files installed in the switch are displayed, using the **show license usage** command.



Note The switch is initially shipped with the required licenses installed in the system. However, the initial license file does not cover the unlicensed features that may be used during the grace period. See the *Cisco MDS 9000 Series NX-OS Licensing Guide*. If no license is displayed at this point, perform [Step 7](#) and [Step 8](#) to install the required licenses. If the required licenses are displayed at this point, skip [Step 7](#) and [Step 8](#) and, move to [Step 9](#).

The following is a sample CLI output for a valid license:

```
switch# show license usage
Feature                               Ins  Lic  Status Expiry Date Comments
                                      Count
-----
FM_SERVER_PKG                         No   -   Unused          -
MAINFRAME_PKG                         No   -   Unused          -
ENTERPRISE_PKG                       Yes  -   Unused never    -
-----
```

Step 7 Install licenses, if necessary, to ensure that the required features are available on the switch. Perform the following steps:

- a. Use the **show license host-id** command to obtain the serial number of your switch. The host ID is also referred to as the switch serial number.

```
switch# show license host-id
License hostid: VDH=JAF1721AEQG
```



Tip Use the entire ID that appears after the colon (:). In this example, the host ID is VDH=JAF1721AEQG.

- b. Obtain your Claim Certificate or Proof of Purchase document. This document accompanies every Cisco MDS switch.
- c. Locate the Product Authorization Key (PAK) from the Claim Certificate or Proof of Purchase document.
- d. A URL is provided in the Claim Certificate or Proof of Purchase document for your product.
- e. Locate and access the specified URL that applies to your switch's and enter the switch serial number and PAK. The license key file is sent to you by email. The license key file is digitally signed to be used only on the switch for which it was requested. The requested features are also enabled after the Cisco MDS NX-OS software on the specified switch accesses the license key file.



Note Install the license file in the specified Cisco MDS 9000 Series Multilayer switch without modifying the key.

For more information on licensing, see the [Cisco MDS 9000 Series NX-OS Licensing Guide](#).

Step 8 Install the license key file when you receive it by email. Perform the following steps:

- a. Copy the license file to bootflash using TFTP or SCP.
- b. Install the license file by running the **install license** command on the active supervisor module, from the switch console.

```
switch# install license bootflash:license_file.lic
Installing license ..done
```



Note If you provide a target name for the license key file, the file is installed with the specified name. Otherwise, the filename specified in the license key file is used to install the license.

- c. Exit the switch console.

For more information on licensing, see the [Cisco MDS 9000 Series NX-OS Licensing Guide](#).

Step 9 Ensure that the required space is available in the bootflash: directory for the image files to be copied using the **dir bootflash:** command. Use the **delete bootflash:filename** command to remove unnecessary files.

```
switch# dir bootflash:

 4096   Nov 23 10:47:46 2018  .patch/
 68230  Dec 10 11:27:20 2018  backup_10_12_2018
 4096   Dec 12 10:23:54 2018  bootflash/
52692992 Aug 24 06:18:35 2018  diag-bz-npu-F26
82725888 Aug 24 06:18:24 2018  diag-sup3dc3-bz-F26.bin
1048576 Aug 24 05:47:10 2018  diag_test_file
```

```

34646 Jan 28 14:45:50 2019 ethpm_act_logs.log
270463 Jan 28 14:47:51 2019 ethpm_im_tech.log
30627 Jan 28 14:46:50 2019 ethpm_mts_details.log
73 Jan 28 14:46:50 2019 ethpm_syslogs.log
1935271 Jan 28 14:47:50 2019 ethpm_tech.log
12831 Dec 07 15:57:20 2018 log1
4096 Feb 07 13:13:47 2019 lost+found/
4421896 May 02 19:32:22 2019 m9700-sf4ek9-dplug-mz.8.4.1.bin
4421857 May 07 12:18:16 2019 m9700-sf4ek9-dplug-mz.8.4.1.bin
60380672 Apr 29 16:15:25 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
60380672 May 02 19:32:34 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
60380672 May 07 12:19:05 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
433279746 Apr 29 16:32:42 2019 m9700-sf4ek9-mz.8.4.1.bin
433304076 May 02 19:47:52 2019 m9700-sf4ek9-mz.8.4.1.bin
1548886 May 02 19:47:58 2019 m9700-sf4ek9-mz.8.4.1.tar.gz
433423429 May 07 12:33:27 2019 m9700-sf4ek9-mz.8.4.1.bin
1548937 May 07 12:33:35 2019 m9700-sf4ek9-mz.8.4.1.tar.gz
4096 Mar 26 09:54:14 2019 scripts/
1286622 Mar 21 15:53:25 2019 sysmgrconfig
11082 Aug 24 06:14:41 2018 temp.log

```

```

Usage for bootflash://sup-local
3213733888 bytes used
500277248 bytes free
3714011136 bytes total

```



Note Before downloading and installing Cisco MDS NX-OS software, verify that the release is supported by your Cisco MDS reseller. If you purchased support from a Cisco reseller, contact them directly for more information. Otherwise, contact Cisco Technical support: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.

Step 10 If you need more space on the active supervisor module bootflash, delete the files that are not required to make space available:

```

switch# delete bootflash: m9700-sf3ek9-kickstart-mz.8.3.1.bin
switch# delete bootflash: m9700-sf3ek9-mz.8.3.1.bin

```

Step 11 Verify that there is space available on the standby supervisor module bootflash on a Cisco MDS 9700 Series Multilayer switch:

```

switch# attach mod x (where x is the module number of the standby supervisor)
switch(standby)# dir bootflash:

```

```

4096 Nov 23 10:47:46 2018 .patch/
68230 Dec 10 11:27:20 2018 backup_10_12_2018
4096 Dec 12 10:23:54 2018 bootflash/
52692992 Aug 24 06:18:35 2018 diag-bz-npu-F26
82725888 Aug 24 06:18:24 2018 diag-sup3dc3-bz-F26.bin
1048576 Aug 24 05:47:10 2018 diag_test_file
34646 Jan 28 14:45:50 2019 ethpm_act_logs.log
270463 Jan 28 14:47:51 2019 ethpm_im_tech.log
30627 Jan 28 14:46:50 2019 ethpm_mts_details.log
73 Jan 28 14:46:50 2019 ethpm_syslogs.log
1935271 Jan 28 14:47:50 2019 ethpm_tech.log
12831 Dec 07 15:57:20 2018 log1
4096 Feb 07 13:13:47 2019 lost+found/
4421896 May 02 19:32:22 2019 m9700-sf4ek9-dplug-mz.8.4.1.bin
4421857 May 07 12:18:16 2019 m9700-sf4ek9-dplug-mz.8.4.1.bin
60380672 Apr 29 16:15:25 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
60380672 May 02 19:32:34 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
60380672 May 07 12:19:05 2019 m9700-sf4ek9-kickstart-mz.8.4.1.bin
433279746 Apr 29 16:32:42 2019 m9700-sf4ek9-mz.8.4.1.bin

```



```

433304076    May 02 19:47:52 2019  m9700-sf4ek9-mz.8.4.1.bin
1548886     May 02 19:47:58 2019  m9700-sf4ek9-mz.8.4.1.tar.gz
433423429   May 07 12:33:27 2019  m9700-sf4ek9-mz.8.4.1.bin
1548937     May 07 12:33:35 2019  m9700-sf4ek9-mz.8.4.1.tar.gz
4096        Mar 26 09:54:14 2019  scripts/
1286622     Mar 21 15:53:25 2019  sysmgrconfig
11082       Aug 24 06:14:41 2018  temp.log

```

```

Usage for bootflash://sup-local
3213733888 bytes used
500277248 bytes free
3714011136 bytes total
switch(standby)# exit (to return to the active supervisor)

```

- Step 12** If you need more space on the standby supervisor module bootflash on a Cisco MDS 9700 Series Multilayer switch, delete the files that are not required to make space available:

```

switch(standby)# delete bootflash: m9700-sf3ek9-kickstart-mz.8.3.1.bin
switch(standby)# delete bootflash: m9700-sf3ek9-mz.8.3.1.bin

```

- Step 13** Access the Software Download Center using this URL:

<http://www.cisco.com/cisco/software/navigator.html>

You are prompted to log in, use your Cisco username and password.

- Step 14** Select the required Cisco MDS NX-OS Release 8.x image file, depending on the release you are installing.

The Technical Support Encryption Software Export Distribution Authorization form is displayed.

- Step 15** Enter the relevant details in this form, to obtain authorization.

- Step 16** After obtaining the authorization, download the files to an FTP or TFTP server.



Note Ensure that you have configured an FTP or TFTP server where the files can be downloaded.

- Step 17** Copy the Cisco MDS NX-OS kickstart and system images from the FTP or TFTP server to the active supervisor module bootflash.

When you download an image file, change your TFTP environment's IP address or Domain Name System (DNS) name to the path where the files are located.

```

switch# copy tftp://tftpserver.cisco.com/MDS/m9700-sf4ek9-kickstart-mz.8.4.1.bin
bootflash:m9700-sf4ek9-kickstart-mz.8.4.1.bin
switch# copy tftp://tftpserver.cisco.com/MDS/m9700-sf4ek9-mz.8.4.1.bin
bootflash:m9700-sf4ek9-mz.8.4.1.bin

```

- Step 18** Verify that the switch is running the required software version, using the **show version** command:

```

switch# show version

```

```

Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Documents: http://www.cisco.com/en/US/products/ps9372/tsd_products_support_series_home.html
Copyright (c) 2002-2018, Cisco Systems, Inc. All rights reserved.
The copyrights to certain works contained in this software are
owned by other third parties and used and distributed under
license. Certain components of this software are licensed under
the GNU General Public License (GPL) version 2.0 or the GNU
Lesser General Public License (LGPL) Version 2.1. A copy of each
such license is available at

```

http://www.opensource.org/licenses/gpl-2.0.php and
 http://www.opensource.org/licenses/lgpl-2.1.php

```
Software
BIOS: version 3.2.0
kickstart: version 8.3(2)
system: version 8.3(2)
BIOS compile time: 09/27/2018
kickstart image file is: bootflash:///m9700-sf3ek9-kickstart-mz.8.3.2.bin
kickstart compile time: 11/30/2018 12:00:00 [11/30/2018 23:18:49]
system image file is: bootflash:///m9700-sf3ek9-mz.8.3.2.bin
system compile time: 11/30/2018 12:00:00 [12/01/2018 00:45:13]
```

```
Hardware
cisco MDS 9706 (6 Slot) Chassis ("Supervisor Module-3")
Intel(R) Xeon(R) CPU with 8167760 kB of memory.
Processor Board ID JAE17440HVW
```

```
Device name: sw-9706-213
bootflash: 3915776 kB
slot0: 0 kB (expansion flash)
```

Kernel uptime is 0 day(s), 0 hour(s), 57 minute(s), 19 second(s)

```
Last reset at 818200 usecs after Tue Dec 4 13:49:17 2018
Reason: Reset triggered due to
Switchover*****
```

Step 19 Verify that your switch is running compatible hardware. For more information, see the corresponding version of the [Cisco MDS 9000 Series Release Notes](#).

Step 20 Perform the upgrade by running the **install all** command.

The following example displays the result of the **install all** command if the system and kickstart files are specified locally. The example shows the command issued on a Cisco MDS 9700 Series Multilayer switch.

```
switch# install all kickstart m9700-sf4ek9-kickstart-mz.8.4.1.bin system
m9700-sf4ek9-mz.8.4.1.bin
Installer will perform compatibility check first. Please wait.

Verifying image bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin for boot variable
"kickstart".
[#####] 100% -- SUCCESS

Verifying image bootflash:/m9700-sf4ek9-mz.8.4.1.bin for boot variable "system".
[#####] 100% -- SUCCESS

Performing module support checks.
[#####] 100% -- SUCCESS

Verifying image type.
[#####] 100% -- SUCCESS

Extracting "lctsh" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Extracting "bios" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Extracting "lc2dce-mds" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS
```

```

Extracting "slc4xb" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Extracting "system" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Extracting "kickstart" version from image bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Extracting "slcf32" version from image bootflash:/m9700-sf4ek9-mz.8.4.1.bin
[#####] 100% -- SUCCESS

Notifying services about system upgrade.
[#####] 100% -- SUCCESS

```

Compatibility check is done:

Module	bootable	Impact	Install-type	Reason
2	yes	non-disruptive	rolling	
3	yes	non-disruptive	rolling	
4	yes	non-disruptive	rolling	
5	yes	non-disruptive	reset	
6	yes	non-disruptive	reset	
10	yes	non-disruptive	rolling	

Other miscellaneous information for installation:

```

Module info
-----
2 FC ports 1-24 are hitless, IPS 1-8 are hitful, and Intelligent Applications running are hitful

```

Images will be upgraded according to following table:

Module	Image	Running-Version (pri:alt)	New-Version	Upg-Required
2	lctsh	8.3(2)	8.4(1)	yes
2	bios	v4.2.14(03/30/2018):v4.2.14(03/30/2018)		no
3	lc2dce-mds	8.3(2)	8.4(1)	yes
3	bios	v2.0.32(12/16/13)	v2.0.32(12/16/13)	no
4	slc4xb	8.3(2)	8.4(1)	yes
4	bios	v1.10.21(11/26/12)	v1.10.21(11/26/12)	no
5	system	8.3(2)	8.4(1)	yes
5	kickstart	8.3(2)	8.4(1)	yes
5	bios	v3.1.0(02/27/2013)	v3.2.0(09/27/2018)	yes
6	system	8.3(2)	8.4(1)	yes
6	kickstart	8.3(2)	8.4(1)	yes
6	bios	v3.1.0(02/27/2013)	v3.2.0(09/27/2018)	yes
10	slcf32	8.3(2)	8.4(1)	yes
10	bios	v4.1.49(01/29/2017)	v4.1.49(01/29/2017)	no

Do you want to continue with the installation (y/n)? [n] **y**

Install is in progress, please wait.

Performing runtime checks.

```
[#####] 100% -- SUCCESS
```

Syncing image bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin to standby.

```
[#####] 100% -- SUCCESS
```

Syncing image bootflash:/m9700-sf4ek9-mz.8.4.1.bin to standby.

```
[#####] 100% -- SUCCESS

Setting boot variables.
[#####] 100% -- SUCCESS

Performing configuration copy.
[#####] 100% -- SUCCESS

Module 2: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS

Module 3: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS

Module 4: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS

Module 5: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS

Module 6: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS

Module 10: Upgrading bios/loader/bootrom/power-seq.
Warning: please do not remove or power off the module at this time.
[#####] 100% -- SUCCESS
2019 Mar 23 15:38:37 switch %PLATFORM-2-MOD_REMOVE: Module 6 removed (Serial number
JAE17480AL1)
2019 Mar 23 15:40:58 switch %USBHSD-STANDBY-2-MOUNT: logflash: online
2019 Mar 23 15:42:06 switch %PLATFORM-1-PFM_ALERT: Disabling ejector based shutdown on sup
in slot 6

Module 6: Waiting for module online.
-- SUCCESS
2019 Mar 23 15:42:30 switch %PLATFORM-1-PFM_ALERT: Enabling ejector based shutdown on sup
in slot 5

Notifying services about the switchover.
[#####] 100% -- SUCCESS

"Switching over onto standby".

>>>
>>>
>>>
NX7k SUP BIOS version ( 3.02 ) : Build - 03/23/2019 02:38:22
PM FPGA Version : 0x00000014
Power sequence microcode revision - 0x00000001 : card type - f10156EEA0
Booting Spi Flash : Primary
CPU Signature - 0x000106e4: Version - 0x000106e0
CPU - 1 : Cores - 4 : HTEn - 1 : HT - 2 : Features - 0xbfebfbff
FSB Clk - 532 Mhz : Freq - 2152 Mhz - 2128 Mhz
MicroCode Version : 0x00000005
Memory - 8192 MB : Frequency - 1067 MHZ
Loading Bootloader: Done
IO FPGA Version : 0x10001
PLX Version : 861910b5
Bios digital signature verification - Passed
```

```

Reset Reason Registers: 0x1 0x0
  Filesystem type is ext2fs, partition type 0x83

      GNU GRUB  version 0.97

Autobooting bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin bootflash:/m9700-
sf4ek9-mz.8.4.1.bin..
  Filesystem type is ext2fs, partition type 0x83
Booting kickstart image: bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin...
.....
.....
Kickstart digital signature verification Successful
Image verification OK

INIT: version 2
boot device node /dev/sda
obfl flash device node /dev/sdb
USB log flash  device not found ...
Checking obfl filesystem.
Checking all filesystems..r.r.r.R. done.
fdisk: cannot open /dev/hd-log: No such file or directory
No partition found for LOG
LOG partition is less than 1G, size found = 0
mounting Log 1
Starting mcelog daemon
cat: /var/log/log_flash_node: No such file or directory
Initializing the LOG flash
LOG Partitioning result code = 0
rrCreating logflash directories
Loading system software
/bootflash//m9700-sf3ek9-mz.8.4.1.bin read done
System image digital signature verification successful.
Uncompressing system image: bootflash:/m9700-sf4ek9-mz.8.4.1.bin Fri Mar 23 15:46:29 IST
2019
blogger: nothing to do.
C
..done Fri Mar 23 15:46:34 IST 2019
INIT: Entering runlevel: 3
Starting portmap daemon...
starting statd: done
starting 8 nfsd kernel threads: done
starting mountd: done
System is coming up ... Please wait ...
2019 Mar 23 15:48:10 switch %LICMGR-2-LOG_LIC_NO_LIC: No license(s) present for feature
ENTERPRISE_PKG. Application(s) shut down in 96 days.

>>>
>>>
NX7k SUP BIOS version ( 3.02 ) : Build - 03/23/2019 02:38:22
PM FPGA Version : 0x00000014
Power sequence microcode revision - 0x00000001 : card type - f10156EEA0
Booting Spi Flash : Primary
  CPU Signature - 0x000106e4: Version - 0x000106e0
  CPU - 1 : Cores - 4 : HTEn - 1 : HT - 2 : Features - 0xbfebfbff
  FSB Clk - 532 Mhz : Freq - 2153 Mhz - 2128 Mhz
  MicroCode Version : 0x00000005
  Memory - 8192 MB : Frequency - 1067 MHZ
  Loading Bootloader: Done
  IO FPGA Version   : 0x10001
  PLX Version       : 861910b5
Bios digital signature verification - Passed

```

```
Reset Reason Registers: 0x0 0x8
Filesystem type is ext2fs, partition type 0x83
```

```
GNU GRUB version 0.97
```

```
Autobooting bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin bootflash:/m9700-
sf3ek9-mz.8.4.1.bin..
Filesystem type is ext2fs, partition type 0x83
Booting kickstart image: bootflash:/m9700-sf4ek9-kickstart-mz.8.4.1.bin...
.....
.....
Kickstart digital signature verification Successful
Image verification OK
```

```
INIT: version 2
boot device node /dev/sda
obfl flash device node /dev/sdb
log flash device node /dev/sdc
Checking obfl filesystem.
Checking all filesystems..r.r.r..r done.
Mounting Log Dir /logflash
mounting Log 0
Starting mcelog daemon
reCreating logflash directories
Loading system software
/bootflash//m9700-sf4ek9-mz.8.4.1.bin read done
System image digital signature verification successful.
Uncompressing system image: bootflash:/m9700-sf4ek9-mz.8.4.1.bin Fri Mar 23 15:40:22 IST
2019
blogger: nothing to do.
C
..done Fri Mar 23 15:40:27 IST 2019
INIT: Entering runlevel: 3
Starting portmap daemon...
starting statd: done
starting 8 nfsd kernel threads: done
starting mountd: done
2019 Mar 23 15:40:58 switch %USBHSD-2-MOUNT: logflash: online
2019 Mar 23 15:41:12 switch %LICMGR-2-LOG_LIC_NO_LIC: No license(s) present for feature
ENTERPRISE_PKG. Application(s) shut down in 96 days.
```

Continuing with installation, please wait

```
Module 6: Waiting for module online.
-- SUCCESS
2019 Mar 23 15:42:35 switch %KERN-2-SYSTEM_MSG: [ 203.622504] Switchover started by
redundancy driver - kernel
2019 Mar 23 15:42:36 switch %SYSMGR-2-HASWITCHOVER_PRE_START: This supervisor is becoming
active (pre-start phase).
2019 Mar 23 15:42:36 switch %SYSMGR-2-HASWITCHOVER_START: Supervisor 6 is becoming active.
2019 Mar 23 15:42:36 switch %SYSMGR-2-SWITCHOVER_OVER: Switchover completed.
2019 Mar 23 15:42:37 switch %PLATFORM-1-PFM_ALERT: Disabling ejector based shutdown on sup
in slot 6
2019 Mar 23 15:42:41 switch %LICMGR-2-LOG_LIC_NO_LIC: No license(s) present for feature
ENTERPRISE_PKG. Application(s) shut down in 96 days.
2019 Mar 23 15:42:41 switch %LICMGR-2-LOG_LIC_NO_LIC: No license(s) present for feature
MAINFRAME_PKG. Application(s) shut down in 120 days.
2019 Mar 23 15:42:41 switch %LICMGR-2-LOG_LICAPP_NO_LIC: Application Fabric Binding
running without MAINFRAME_PKG license, shutdown in 120 days
2019 Mar 23 15:42:42 switch %CALLHOME-2-EVENT: LICENSE_ALERT
```

```

Module 2: Non-disruptive upgrading.
[#          ] 0%2019 Mar 23 15:49:27 switch %PLATFORM-1-PFM_ALERT: Enabling
ejector based shutdown on sup in slot 6
2019 Mar 23 15:52:05 switch %PMON-SLOT2-2-PMON_CRIT_INFO: Port Monitor Critical
Information: Config download success .
[#####] 100% -- SUCCESS

Module 3: Non-disruptive upgrading.
[#####] 100% -- SUCCESS

Module 4: Non-disruptive upgrading.
[#          ] 0%2019 Mar 23 15:57:44 switch %PMON-SLOT4-2-PMON_CRIT_INFO: Port
Monitor Critical Information: Config download success .
[#####] 100% -- SUCCESS

Module 10: Non-disruptive upgrading.
[#          ] 0%2019 Mar 23 16:00:00 switch %PMON-SLOT10-2-PMON_CRIT_INFO: Port
Monitor Critical Information: Config download success .
[#####] 100% -- SUCCESS

Install has been successful.
switch# You have now upgraded the Cisco NX-OS software in your switch.

```

Upgrading to Cisco MDS NX-OS Release 8.x on a Cisco MDS Fabric Switch

This section describes how to perform nondisruptive upgrades on the following Cisco MDS fabric switches:

- Cisco MDS 9132T Multilayer Fabric Switch
- Cisco MDS 9148T Multilayer Fabric Switch
- Cisco MDS 9148S Multilayer Fabric Switch
- Cisco MDS 9220i Multilayer Fabric Switch
- Cisco MDS 9250i Multiservice Fabric Switch
- Cisco MDS 9396S Multilayer Fabric Switch
- Cisco MDS 9396T Multilayer Fabric Switch

Guidelines and Limitations for a Nondisruptive Upgrade on a Cisco MDS Fabric Switch

Before attempting to upgrade software images on the fabric switches, follow these guidelines:

- During the upgrade, the fabric must be stable.
- Do not perform the following configuration activities during an upgrade:
 - Zoning changes
 - Telnet sessions
 - Schedule changes
 - Switch cabling
 - Addition or removal of physical devices
- Configure the Fabric Shortest Path First (FSPF) timers to the default value of 20 seconds.

- If Cisco Fabric Services commits are pending in the fabric, the upgrade is aborted.
- If a zone server merge is in progress, the upgrade is aborted.
- If the upgrade is aborted due to a service not being ready for an upgrade, you are prompted to enter the **show install all failure-reason** command to identify the reason.
- Use the Software Install wizard to check whether sufficient space is available in the system to load the new images. Depending on the available space, you must either terminate the upgrade or proceed with a disruptive upgrade.
- Prior to upgrade or downgrade, reset the switch's logging levels to the system defaults via the **no logging level all** configuration command. If this is not done, the upgrade or downgrade may be disruptive due to excessive logging causing control plane downtime exceeding 80 seconds. Before entering the **no logging level all** command, ensure that the switch's current logging configuration is saved. This will need to be restored after the upgrade or downgrade. Follow these steps:
 1. Enter the **show running-config | i "logging level"** command and save the output. These are the switch's current settings.
 2. Enter the **no logging level all** command in configuration mode.
 3. Perform upgrade or downgrade.
 4. Restore logging level configuration using the output that was saved from Step 1.
- When the installation is completed, the supervisor kickstart image, supervisor system image, module image, and the system BIOS are all updated.
- Nondisruptive upgrade on fabric switches disrupt the control plane for about 80 seconds. The software upgrade can be disruptive, if the upgrade process goes beyond the period it can be stopped gracefully, or if a failure occurs.
- If Virtual Router Redundancy Protocol (VRRP) is running on the mgmt0 interface, and the switch being upgraded is the master, a new master is selected. This situation cannot be avoided because the mgmt0 interface goes down when the control plane goes down.
- On the Cisco MDS 18/4-port Multiservice Module, upgrading the 4-Gigabit Ethernet ports for the hybrid Supervisor 18/4 module is disruptive.
- Perform the upgrade process by using the console port. This method enables you to log your session to a file (in case you need it later for troubleshooting). Telnet sessions are lost when the switch is rebooted. Therefore, if you want to view the process in its entirety, ensure that you use the console port.
- Before performing an upgrade, use the **show install all impact** command to view the effect of updating the system from the running image to another specified image.

To upgrade to Cisco MDS NX-OS Release 8.4(1) from an earlier 8.x release, on a Cisco MDS fabric switch, perform the following steps:

Step 1 Verify that the system image files for the upgrade are present on the active supervisor module bootflash:

```
switch# dir bootflash:
25863680 Sep 23 12:02:16 2017 m9250-s5ek9-kickstart-mz.8.2.1.bin
25864704 Sep 05 12:21:26 2018 m9250-s5ek9-kickstart-mz.8.2.1.bin
25869312 Apr 01 12:29:34 2018 m9250-s5ek9-kickstart-mz.8.2.2.bin
25869312 Apr 12 01:55:22 2018 m9250-s5ek9-kickstart-mz.8.2.2.bin
25947136 Nov 09 13:41:43 2018 m9250-s5ek9-kickstart-mz.8.3.1.bin
```



```
25970176   Jan 17 14:10:47 2019  m9250-s5ek9-kickstart-mz.8.3.2.bin
26126848   May 07 11:51:20 2019  m9250-s5ek9-kickstart-mz.8.4.1.bin
```

```
Usage for bootflash://sup-local
```

```
2838728704 bytes used
520916992 bytes free
3359645696 bytes total
```

- Step 2** If the software image file is not present, download it from an FTP or TFTP server to bootflash. You can obtain the software image file from the Cisco.com Software Download Center at <http://www.cisco.com/cisco/software/navigator.html>

```
switch# copy tftp://tftpserver.cisco.com/MDS/m9250-s5ek9-kickstart-mz.8.4.1.bin
bootflash:m9250-s5ek9-kickstart-mz.8.4.1.bin
switch# copy tftp://tftpserver.cisco.com/MDS/m9250-s5ek9-mz.8.4.1.bin
bootflash:m9250-s5ek9-mz.8.4.1.bin
```

- Step 3** Ensure that the required space is available on the switch:

```
switch# dir bootflash:
25863680   Sep 23 12:02:16 2017  m9250-s5ek9-kickstart-mz.8.2.1.bin
25864704   Sep 05 12:21:26 2018  m9250-s5ek9-kickstart-mz.8.2.1.bin
25869312   Apr 01 12:29:34 2018  m9250-s5ek9-kickstart-mz.8.2.2.bin
25869312   Apr 12 01:55:22 2018  m9250-s5ek9-kickstart-mz.8.2.2.bin
25947136   Nov 09 13:41:43 2018  m9250-s5ek9-kickstart-mz.8.3.1.bin
25970176   Jan 17 14:10:47 2019  m9250-s5ek9-kickstart-mz.8.3.2.bin
26126848   May 07 11:51:20 2019  m9250-s5ek9-kickstart-mz.8.4.1.bin
26126848   May 07 11:51:50 2019  m9250-s5ek9-mz.8.4.1.bin
```

```
Usage for bootflash://sup-local
```

```
120695976 bytes used
63863640 bytes free
184559616 bytes total
```

- Step 4** If you need more space on the switch, delete the files that are not required:

```
switch# delete bootflash: m9250-s5ek9-kickstart-mz.8.2.1.bin
switch# delete bootflash: m9250-s5ek9-kickstart-mz.8.2.1.bin
```

- Step 5** Save the configuration using the **copy running-config startup-config** command:

```
switch# copy running-config startup-config
```

You can also back up your existing configuration to a file, using the **copy running-config bootflash:backup_config.txt** command. You can add a date reference to the .txt filename to identify the file later.

- Step 6** Save a copy of the **show tech-support** command output of the switch. For more information, see <https://www.cisco.com/c/en/us/td/docs/dcn/whitepapers/how-to-collect-logs-cisco-mds.html#Theshowtechsupportcommand>.

- Step 7** Perform the upgrade by running the **install all** command:

```
switch# install all kickstart m9250-s5ek9-kickstart-mz.8.4.1.bin system
m9250-s5ek9-mz.8.4.1.bin
Installer will perform compatibility check first. Please wait.
Y
Verifying image bootflash:/m9250-s5ek9-kickstart-mz.8.4.1.bin for boot variable
"kickstart".
[#           ] 0%
[#####] 100% -- SUCCESS
```

Verifying image bootflash:/m9250-s5ek9-mz.8.4.1.bin for boot variable "system".
 [#####] 100% -- SUCCESS

Performing module support checks.
 [#####] 100% -- SUCCESS

Verifying image type.
 [#####] 100% -- SUCCESS

Extracting "system" version from image bootflash:/m9250-s5ek9-mz.8.4.1.bin
 [#####] 100% -- SUCCESS

Extracting "kickstart" version from image bootflash:/m9250-s5ek9-kickstart-mz.8.4.1.bin
 [#####] 100% -- SUCCESS

Extracting "bios" version from image bootflash:/m9250-s5ek9-mz.8.4.1.bin
 [#####] 100% -- SUCCESS

Performing Compact Flash and TCAM sanity test.
 [#####] 100% -- SUCCESS

Notifying services about system upgrade.
 [#####] 100% -- SUCCESS

Compatibility check is done:
 Module bootable Impact Install-type Reason

 1 yes non-disruptive reset

Other miscellaneous information for installation:
 Module info

 1 FC ports 1-40 and FCoE ports 1-8 are hitless, IPS 1-2 are hitful, and Intelligent Applications running are hitful

Images will be upgraded according to following table:

Module	Image	Running-Version	New-Version	Upg-Required
1	system	8.1(1)	8.4(1)	yes
1	kickstart	8.1(1)	8.4(1)	yes
1 bios	v2.1.17(01/08/14):v2.1.17(01/08/14)	v2.1.17(01/08/14)		no

Do you want to continue with the installation (y/n)? [n] **y**

Install is in progress, please wait.

Performing runtime checks.
 [#####] 100% -- SUCCESS

Notifying services about the upgrade.
 [#####] 100% -- SUCCESS

Setting boot variables.
 [#####] 100% -- SUCCESS

Performing configuration copy.
 [#####] 100% -- SUCCESS

Module 1: Refreshing compact flash and Upgrading bios/loader/bootrom/power-seq.
 Warning: please do not remove or power off the module at this time.
 [#####] 100% -- SUCCESS

Upgrade can no longer be aborted, any failure will result in a disruptive upgrade.

Freeing memory in the file system.
 [#####] 100% -- SUCCESS

Loading images into memory.
 [#####] 100% -- SUCCESS

Saving linecard runtime state.
 [#####] 100% -- SUCCESS

Saving supervisor runtime state.
 [#####] 100% -- SUCCESS

Saving mts state.
 [#####] 100% -- SUCCESS

Reloading the kernel to proceed with the upgrade.
 All telnet and ssh connections will now be temporarily terminated.

>> NX7--LC-loader-02.01.17 (June 8 2019 - 16:30:41), Build: 02.01.17

```

CPU0: 8572E, Version: 2.2, (0x80e80022)
Core: E500, Version: 3.0, (0x80210030)
Clock Configuration:
      CPU:1066.672 MHz, CCB:533.336 MHz,
      DDR:266.668 MHz (533.336 MT/s data rate), LBC:33.334 MHz
L1:   D-cache 32 kB enabled
      I-cache 32 kB enabled
Board: 9044, IOFPGA: 0x0000001A, SPROM: 0xAB
Boot flash : Primary
I2C:   ready
DRAM:  Initializing
DDR:  dimm type 10, registered 1
DDR:  dimm type 10, registered 1
      DDR: 4 GB
L2:   1024 KB enabled
Using default environment

In:   serial
Out:  serial
Err:  serial
Net:  INFO: Net boot mode = 1
      INFO: Net boot mode = 1
      INFO: Board will come up MGMT interface
      INFO: MAC address is: b8:38:61:4a:24:40
      eTSEC2 board phy 3
      INFO: Net boot mode = 1
      eTSEC2
IDE:  Bus 0: OK
      Device 0: Model: UGB30STC4000Z4-EBY-ASD Firm: FW100511 Ser#: UNIGEN3 30021309
              Type: Hard Disk
              Capacity: 3907.9 MB = 3.8 GB (8003520 x 512)

Booting image bootflash://m9250-s5ek9-kickstart-mz.8.4.1.bin
25968640 bytes read
NBI at 08000000 size 134217728

Booting image at addr 0x00800000 ...
    
```



```

Performing supervisor state verification.
[#####] 100% -- SUCCESS

Supervisor non-disruptive upgrade successful.

Install has been successful.

```

Step 8 Log in to the switch:

```

MDS Switch
x.x.x.x login: admin
Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Copyright (c) 2002-2014, Cisco Systems, Inc. All rights reserved.
The copyrights to certain works contained in this software are
owned by other third parties and used and distributed under
license. Certain components of this software are licensed under
the GNU General Public License (GPL) version 2.0 or the GNU
Lesser General Public License (LGPL) Version 2.1. A copy of each
such license is available at
http://www.opensource.org/licenses/gpl-2.0.php and
http://www.opensource.org/licenses/lgpl-2.1.php

```

Step 9 Run the **show version** command:

```

switch# show version

Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Documents: http://www.cisco.com/en/US/products/ps9372/tsd_products_support_series_home.html
Copyright (c) 2002-2019, Cisco Systems, Inc. All rights reserved.
The copyrights to certain works contained herein are owned by
other third parties and are used and distributed under license.
Some parts of this software are covered under the GNU Public
License. A copy of the license is available at
http://www.gnu.org/licenses/gpl.html.

Software
  BIOS:          version 2.1.17
  loader:        version N/A
  kickstart:     version 8.4(1) [build 8.4(1)]
  system:        version 8.4(1) [build 8.4(1)]
  BIOS compile time:      01/08/14
  kickstart image file is: bootflash:///m9250-s5ek9-kickstart-mz.8.4.1.bin
  kickstart compile time: 6/1/2019 23:00:00 [05/07/2019 04:18:10]
  system image file is:   bootflash:///m9250-s5ek9-mz.8.4.1.bin
  system compile time:    6/1/2019 23:00:00 [05/07/2019 07:09:57]

Hardware
  cisco MDS 9250i 40 FC 2 IPS 8 FCoE (2 RU) Chassis ("40FC+8FCoE+2IPS Supervisor
  ")
  Motorola, e500v2 with 4088636 kB of memory.
  Processor Board ID JAF1804AAFG

  Device name: MDS9250i
  bootflash: 4001760 kB

Kernel uptime is 0 day(s), 0 hour(s), 7 minute(s), 42 second(s)

Last reset at 288238 usecs after Thu May 9 11:40:56 2019
Reason: Reset due to upgrade

```

```

System version: 8.1(1)
Service:

plugin
  Core Plugin
    
```

Step 10 Verify the status of the modules on the switch, using the **show module** command:

```

switch# show module

Mod Ports Module-Type Model Status
-----
1 50 40FC+8FCoE+2IPS Supervisor DS-C9250I-K9-SUP active *

Mod Sw Hw World-Wide-Name(s) (WWN)
-----
1 8.4(1) 1.0 20:01:00:2a:6a:1b:64:d0 to 20:28:00:2a:6a:1b:64:d0

Mod MAC-Address(es) Serial-Num
-----
1 b8-38-61-4a-25-c0 to b8-38-61-4a-25-cf JAF1804AAFG
    
```

Step 11 To display the status of a nondisruptive upgrade on a fabric switch, use the **show install all status** command. The command output displays the status only after the switch has rebooted with the new image. All the actions preceding the reboot are not captured in this output because when you enter the **install all** command using a Telnet session, the session is disconnected when the switch reboots. When you reconnect to the switch through a Telnet session, the upgrade may already be complete, in which case, the output displays the status of the upgrade.

```

switch# show install all status

This is the log of last installation.

Continuing with installation process, please wait.
The login will be disabled until the installation is completed.

Status for linecard upgrade.
-- SUCCESS

Performing supervisor state verification.
-- SUCCESS

Install has been successful
    
```

Troubleshooting a Nondisruptive Upgrade on a Fabric Switch

When a nondisruptive upgrade begins, the system notifies all the services that an upgrade is about to start, and finds out whether the upgrade can proceed. If a service cannot allow the upgrade to proceed immediately, for example, if Fabric Shortest Path First (FSPF) timers are not configured to the default value, or a Cisco Fabric Services operation is in progress, the service terminates the upgrade. If such a situation occurs, you are prompted to enter the **show install all failure-reason** command to determine the reason why the upgrade cannot proceed.

```

Do you want to continue with the installation (y/n)? [n] y

Install is in progress, please wait.
    
```

```
Notifying services about the upgrade.
[# ] 0% -- FAIL. Return code 0x401E0066 (request timed out).
```

Please issue "show install all failure-reason" to find the cause of the failure.<---system prompt to enter the show all failure-reason command.

```
Install has failed. Return code 0x401E0066 (request timed out).
Please identify the cause of the failure, and try 'install all' again.
```

```
switch# show install all failure-reason
Service: "cfs" failed to respond within the given time period.
```

When the upgrade is in progress, if any failures occur, for example, if a save runtime state failure or module upgrade failure occurs, the switch is rebooted disruptively because the changes cannot be rolled back. In this case, the upgrade fails, but you are not prompted to enter the **show install all failure-reason** command because the command does not yield any useful information.

If you need additional information to determine why an upgrade is unsuccessful, you can obtain the details by using the **show tech-support** command output, and from the console output from the installation, if available.

Moving From an NPE Image to a non-NPE Image and Vice Versa

The following section describes how to upgrade from a no payload encryption (NPE) image to a non-NPE image and vice versa.



Note

- If the image file name includes *npe* text, the image is an NPE image. If the image file name does not include *npe* text, the image is a non-NPE image.
- If you are moving from using an NPE image to a non-NPE image, we recommend that you use the corresponding non-NPE Cisco MDS NX-OS release image and vice versa. If you are upgrading from one release of Cisco MDS NX-OS to a newer release, and as part of this activity, you are moving from using an NPE image to a non-NPE image, we recommended that you first upgrade the existing NPE Cisco MDS NX-OS release image and then upgrade to the respective non-NPE Cisco MDS NX-OS release image and vice versa.
- Use the console connection for firmware upgrades. Be aware that if you are upgrading through the management interface, you must have a working connection to both supervisors, as this process causes a switchover and the current standby supervisor will be active after the upgrade.

Step 1

Log in to Cisco.com to access the links provided in this document. To log in to Cisco.com, go to the URL <http://www.cisco.com/> and click **Log In** at the top of the page. Enter your Cisco Systems user name and password.



Note

Unregistered Cisco.com users cannot access the links provided in this document.

Step 2

Verify the following physical connections for the switch:

- The console port is physically connected to a computer terminal (or terminal server).
- The management 10/100/1000 Ethernet port (mgmt0) is connected to an external hub, switch, or router.
- On switches with dual supervisor modules, both supervisor modules must have the management 10/100/1000 Ethernet ports (mgmt0) connected to an external hub, switch, or router.

These procedures are specified in the hardware installation guide for the required product.

Step 3 Log in to the switch.

Step 4 Issue the **copy running-config startup-config** command to store your current running configuration. You can also create a backup of your existing configuration to a file by issuing the **copy running-config bootflash:backup_config.txt** command.

Step 5 Verify that the requested license files installed in the switch are displayed in response to the **show license usage** command.



Note The switch is initially shipped with the required licenses installed in the system; however, the initial license file will not cover unlicensed features that may be used during the grace period. If no license is displayed at this point, perform Step 6 and Step 7 to install the required licenses. If the required licenses are displayed at this point, skip Step 6 and Step 7 and move to Step 8.

The example CLI output for a valid license follows:

```
switch# show license usage
Feature                               Ins  Lic  Status Expiry Date Comments
                                Count
-----
FM_SERVER_PKG                         No   -   Unused          -
MAINFRAME_PKG                         No   -   Unused          -
ENTERPRISE_PKG                       Yes  -   Unused never    -
-----
```

Step 6 Install licenses (if necessary) to ensure that the required features are available on the switch. Perform the following steps:

- Use the **show license host-id** command to obtain the serial number for your switch. The host ID is also referred to as the switch serial number.

```
switch# show license host-id
License hostid: VDH=JAF1721AEQG
```



Tip Use the entire ID that appears after the colon (:) sign. In this example, the host ID is VDH=JAF1721AEQG.

- Obtain your Claim Certificate or the Proof of Purchase document. This document accompanies every Cisco MDS switch.
- Locate the Product Authorization Key (PAK) from the Claim Certificate or Proof of Purchase document.
- Locate the website URL from the Claim Certificate or Proof of Purchase document.
- Access the specified URL that applies to your switch and enter the switch serial number and the PAK. The license key file is sent to you by email. The license key file is digitally signed to authorize its use only on the switch for which it was requested. The requested features are also enabled once the NX-OS software on the specified switch accesses the license key file.



Caution Install the license file in the specified Cisco MDS 9000 Family switch without making any modifications.

Step 7 Install the license key file when you receive it by email. Perform the following steps:

- a. Copy the license file to bootflash using TFTP or SCP.
- b. Perform the installation by issuing the **install license** command on the active supervisor module from the switch console.

```
switch# install license bootflash:license_file.lic
Installing license ..done
```



Note If you provide a target name for the license key file, the file is installed with the specified name. Otherwise, the file name specified in the license key file is used to install the license.

- c. Exit the switch console.

Step 8 Ensure that the required space is available in the bootflash: directory for the image file(s) to be copied using the **dir bootflash:** command. Use the **delete bootflash:filename** command to remove unnecessary files.



Note Before downloading and installing Cisco NX-OS software, verify that the release is supported by your Cisco System MDS reseller. If you purchased support through a Cisco Systems reseller, contact them directly for more information. Otherwise, contact Cisco Technical support at this URL: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.

```
switch# dir bootflash:
37011968   Apr 30 16:10:28 2014 m9700-sf4ek9-kickstart-mz-npe.8.4.2a.bin
195875124   Apr 30 12:55:14 2014 m9700-sf4ek9-mz-npe.8.4.2a.bin
Usage for bootflash://sup-local
  819736576 bytes used
  75313152 bytes free
  895049728 bytes total
```

Step 9 If you need more space on the active supervisor module bootflash, delete unnecessary files to make space available.

```
switch# delete m9700-sf4ek9-kickstart-mz-npe.8.4.2a.bin
switch# delete m9700-sf4ek9-mz-npe.8.4.2a.bin
```

Step 10 For switches with dual supervisor modules, verify that there is space available on the standby supervisor module bootflash on a switch.

```
switch# attach module x (where x is the module number of the standby supervisor)
switch(standby)# dir bootflash:
  12288     Aug 26 19:06:14 2011 lost+found/

16206848   Jul 01 10:54:49 2011 m9700-sf4ek9-kickstart-mz-npe.8.4.2a.bin
 78337129   Jul 01 10:33:52 2011 m9700-sf4ek9-mz-npe.8.4.2a.bin

Usage for bootflash://sup-local
 122811392 bytes used
 61748224 bytes free
 184559616 bytes total

switch(standby)# exit (to return to the active supervisor)
```

- Step 11** For switches with dual supervisor modules, if you need more space on the standby supervisor module bootflash on a switch, delete unnecessary files to make space available.

```
switch(standby)# delete bootflash:m9700-sf4ek9-kickstart-mz-npe.8.4.2a.bin
switch(standby)# delete m9700-sf4ek9-mz-npe.8.4.2a.bin
```

- Step 12** Access the Software Download Center using this URL:

<http://www.cisco.com/cisco/software/navigator.html>

If prompted to log in, use your Cisco system user ID and password.

- Step 13** Select the same version of the NPE image file or non-NPE image file that the switch is currently running. You see the Technical Support Encryption Software Export Distribution Authorization form.

- Step 14** Complete the required forms to obtain authorization.

- Step 15** Download the files to an FTP or TFTP server.

- Step 16** Copy the Cisco MDS NX-OS kickstart and system images to the active supervisor module bootflash using FTP or TFTP.



Note When you download an image file, change to your FTP environment IP address or DNS name and the path where the files are located.

```
switch# copy tftp://tftpserver.cisco.com/MDS/m9700-sf4ek9-kickstart-mz.8.4.2a.bin
bootflash:m9700-sf4ek9-kickstart-mz.8.4.2a.bin
switch# copy tftp://tftpserver.cisco.com/MDS/m9700-sf4ek9-mz-npe.8.4.2a.bin
bootflash:m9700-sf4ek9-mz-npe.8.4.2a.bin
```

- Step 17** Issue the **boot kickstart bootflash:filename** and **boot system bootflash:filename** commands to change the boot variables to point to the new image.

```
switch# configure terminal
switch(config)# boot kickstart bootflash:m9700-sf4ek9-kickstart-mz.8.4.2a.bin
Performing image verification and compatibility check, please wait...
switch(config)# boot system bootflash:m9700-sf4ek9-mz-npe.8.4.2a.bin
Performing image verification and compatibility check, please wait...
```

- Step 18** Issue the **show incompatibility-all system filename** command to verify any incompatible hardware.

```
switch(config-if)# show incompatibility-all system m9700-sf4ek9-mz-npe.8.4.2a.bin
Checking incompatible configuration(s)
No incompatible configurations

Checking dynamic incompatibilities:
-----
No incompatible configurations
```

- Step 19** Save the current running configuration to the startup configuration by issuing the **copy running-config startup-config** command.

```
switch(config)# copy running-config startup-config
[#####] 100%
Copy complete.
```

- Step 20** Issue the **show boot** command to check the current boot variable.

```
switch(config)# show boot

Current Boot Variables:
```

```

sup-1
kickstart variable = bootflash:/ m9700-sf4ek9-kickstart-mz.8.4.2a.bin
system variable = bootflash:/ m9700-sf4ek9-mz-npe.8.4.2a.bin
sup-2
kickstart variable = bootflash:/ m9700-sf4ek9-kickstart-mz.8.4.2a.bin
system variable = bootflash:/ m9700-sf4ek9-mz-npe.8.4.2a.bin
No module boot variable set

```

Boot Variables on next reload:

```

sup-1
kickstart variable = bootflash:/ m9700-sf4ek9-kickstart-mz.8.4.2a.bin
system variable = bootflash:/ m9700-sf4ek9-mz-npe.8.4.2a.bin
sup-2
kickstart variable = bootflash:/ m9700-sf4ek9-kickstart-mz.8.4.2a.bin
system variable = bootflash:/ m9700-sf4ek9-mz-npe.8.4.2a.bin
No module boot variable set

```

Step 21 Reload the switch by issuing the **reload** command.

```

switch(config)# reload
This command will reboot the system. (y/n)? [n]

```

You have now upgraded the Cisco MDS NX-OS software in your existing switch.

Supported Downgrade Paths for Cisco MDS NX-OS Releases

The following section describes how to downgrade from Cisco MDS NX-OS Release 8.x to an earlier Cisco MDS NX-OS Release.

- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.5\(1\), page 52](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(2d\), page 52](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(2c\), page 53](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(2b\), page 53](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(2a\), page 54](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(2\), page 55](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(1a\), page 55](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4\(1\), page 56](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.3\(2\), page 56](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.3\(1\), page 56](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.2\(2\), page 57](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.2\(1\), page 57](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1\(1b\), page 58](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1\(1a\), page 58](#)
- [Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1\(1\), page 59](#)

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.5(1)


Note

Before downgrading to releases prior to Cisco MDS NX-OS Release 8.5(1), ensure that you clear the OBFL log using the **clear logging onboard error-stats** command.

Table 26 *Nondisruptive Downgrade Paths from NX-OS Release 8.5(1)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
8.1(1) until 8.4(2b)	Downgrade to the target release
8.4(2c) ¹	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(2b) 2. Upgrade to MDS NX-OS Release 8.4(2c)
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
6.2(29) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b), Release 8.4(2), Release 8.4(2a), or Release 8.4(2b) 2. Downgrade to the target release
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

1. Downgrading from Cisco MDS NX-OS Release 8.5(1) directly to Cisco MDS NX-OS Release 8.4(2c) is not supported. To perform this downgrade, set the boot variables and reload the switch - this process is disruptive. To downgrade nondisruptively, first downgrade from Cisco MDS NX-OS Release 8.5(1) to Cisco MDS NX-OS Release 8.4(2b) and from there upgrade to Cisco MDS NX-OS Release 8.4(2c). For more information, see [CSCvx99164](#).

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(2d)

Table 27 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2d)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases except 8.5(1)	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
6.2(29) and above releases	Downgrade to the target release

Table 27 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2d)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(2c)

Table 28 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2c)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases except 8.5(1)	Downgrade directly from MDS NX-OS 8.4(2c)
MDS NX-OS Release 8.1(1a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
MDS NX-OS Release 6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release
MDS NX-OS Release 6.2(11d)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release
MDS NX-OS Release 6.2(11c)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(2b)

Table 29 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2b)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade directly from MDS NX-OS 8.4(2b)

Table 29 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2b)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
MDS NX-OS Release 8.1(1a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
MDS NX-OS Release 6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release
MDS NX-OS Release 6.2(11d)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release
MDS NX-OS Release 6.2(11c)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(2a)

Table 30 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2a)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
6.2(29) and above releases	Downgrade to the target release
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(2)

Table 31 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(2)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
6.2(29) and above releases	Downgrade to the target release
6.2(13a) until 6.2(27)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(1a)

Table 32 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(1a)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.4(1)

Table 33 *Nondisruptive Downgrade Paths from NX-OS Release 8.4(1)*

To MDS NX-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.3(2)

Table 34 *Nondisruptive Downgrade Paths from NX-OS Release 8.3(2)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.3(1)

Table 35 *Nondisruptive Downgrade Paths from NX-OS Release 8.3(1)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release

Table 35 *Nondisruptive Downgrade Paths from NX-OS Release 8.3(1)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.2(2)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before downgrading to Cisco MDS NX-OS Release 8.2(2).

Table 36 *Nondisruptive Downgrade Paths from NX-OS Release 8.2(2)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.2(1)

If you have the SAN analytics feature enabled, ensure that you disable the SAN analytics feature using the **no feature analytics** command before downgrading to Cisco MDS NX-OS Release 8.2(1).

Table 37 *Nondisruptive Downgrade Paths from NX-OS Release 8.2(1)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release

Table 37 *Nondisruptive Downgrade Paths from NX-OS Release 8.2(1)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
All 7.3(x) releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(13a) and above releases	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 6.2(13a) 3. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1(1b)

Table 38 *Nondisruptive Downgrade Paths from NX-OS Release 8.1(1b)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	Downgrade to the target release
All 6.2(13a) and above releases	Downgrade to the target release
All 6.2(x) releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 6.2(13a) 2. Downgrade to the target release

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1(1a)

Table 39 *Nondisruptive Downgrade Paths from NX-OS Release 8.1(1a)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
NX-OS:	
All 8.x releases	Downgrade to the target release
All 7.3(x) releases	Downgrade to the target release
All 6.2(13a) and above releases except 6.2(21)	Downgrade to the target release

Table 39 *Nondisruptive Downgrade Paths from NX-OS Release 8.1(1a)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Paths and Ordered Downgrade Steps
6.2(21) ¹	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 6.2(23) 2. Downgrade to the target release
All releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 6.2(13a) 2. Downgrade to the target release

1. Downgrading specifically from MDS NX-OS Release 8.1(1a) to MDS NX-OS Release 6.2(21) is disruptive. For more information, see [CSCvj40760](#).

Nondisruptive Downgrade Paths from Cisco MDS NX-OS Release 8.1(1)

Table 40 *Nondisruptive Downgrade Paths from NX-OS Release 8.1(1)*

To NX-OS or SAN-OS Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
All 7.3(x) releases	Downgrade to the target release
All 6.2(13a) and above releases	Downgrade to the target release
All releases prior to 6.2(13a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 6.2(13a) 2. Downgrade to the target release

Supported FICON Downgrade Paths for Cisco MDS NX-OS Releases

This section provides information on FICON downgrade paths that are supported for Cisco MDS NX-OS software Release 8.x. It includes the following topics:

- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4\(2e\)](#), page 60
- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4\(2c\)](#), page 60
- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4\(2b\)](#), page 61
- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4\(1a\)](#), page 61
- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1\(1b\)](#), page 61
- [FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1\(1a\)](#), page 62

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

Table 41 FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2e)

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.4(1a) and 8.4(2b) and 8.4(2e)	Downgrade directly to MDS NX-OS Release 8.4(2e)
8.1(1b)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) or 8.4(2e) 2. Downgrade to the target release
8.1(1a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) or 8.4(2e) 2. Downgrade to MDS NX-OS Release 8.1(1b) 3. Downgrade to the target release
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) or 8.4(2e) 2. Downgrade directly to MDS NX-OS Release 8.1(1a) 3. Downgrade directly to MDS NX-OS Release 8.1(1b) 4. Downgrade to the target release

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

Table 42 Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2c)

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.4(1a) and 8.4(2b)	Downgrade directly to MDS NX-OS Release 8.4(2c)
8.1(1b)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) 2. Downgrade to the target release
8.1(1a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) 2. Downgrade to MDS NX-OS Release 8.1(1b) 3. Downgrade to the target release
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.4(1a) or 8.4(2b) 2. Downgrade directly to MDS NX-OS Release 8.1(1a) 3. Downgrade directly to MDS NX-OS Release 8.1(1b) 4. Downgrade to the target release

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2b)

Table 43 *Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(2b)*

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.1(1b) and 8.4(1a)	Downgrade directly from MDS NX-OS 8.4(2b)
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(1a)

Table 44 *Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.4(1a)*

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.1(1b)	Downgrade directly to MDS NX-OS Release 8.4(1a)
8.1(1a)	<ol style="list-style-type: none"> 1. Downgrade directly to MDS NX-OS Release 8.1(1b) 2. Downgrade to the target release
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1(1b)

Table 45 *FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1(1b)*

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.1(1b)	Downgrade to the target release
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade to MDS NX-OS Release 8.1(1b) 2. Downgrade to MDS NX-OS Release 8.1(1a) 3. Downgrade to the target release

FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1(1a)

Table 46 FICON Nondisruptive Downgrade Paths to Cisco MDS NX-OS Release 8.1(1a)

Current Release	Nondisruptive Downgrade Path and Ordered Downgrade Steps
NX-OS:	
8.1(1a)	Downgrade to the target release
6.2(11e)	<ol style="list-style-type: none"> 1. Downgrade to MDS NX-OS Release 8.1(1a) 2. Downgrade to the target release

Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.x

This section includes the following topics:

- [Downgrade Guidelines for Cisco MDS 9396S Switch, page 63](#)
- [Downgrade Guidelines for Cisco MDS 9250i Switch, page 64](#)

Cisco MDS NX-OS Software Downgrade Guidelines

- Downgrading directly from Cisco MDS NX-OS Release 8.1(1) to releases before Cisco MDS NX-OS Release 6.2(9) is not supported. In such a scenario, we recommend that you first downgrade to Cisco MDS NX-OS Release 6.2(13a) or higher and then downgrade to the required release.
- Downgrading directly from Cisco MDS NX-OS Release 8.1(1) to Cisco MDS NX-OS Release 7.3(0)DY(1) is not supported. In such a scenario, we recommend that you first downgrade to Cisco MDS NX-OS Release 7.3(0)D1(1) and then upgrade to 7.3(0)DY(1).
- Downgrading directly from Cisco MDS NX-OS Release 8.1(1) to Cisco MDS NX-OS Release 7.3(1)DY(1) is not supported. In such a scenario, we recommend that you first downgrade to Cisco MDS NX-OS Release 7.3(0)D1(1) and then upgrade to 7.3(1)DY(1).
- Downgrading from Cisco MDS NX-OS Release 8.1(1) is not supported if the FLOGI Scale Optimization feature is enabled on Cisco MDS 9718 Switches.
- We do not recommend parallel In-Service Software Downgrade (ISSD) on Cisco MDS 9148S, Cisco MDS 9250i, and Cisco MDS 9396S fabric switches when these fabric switches are each other's peers.
- If you copy firmware using the SFTP or SCP clients after enabling the **feature scp-server** or **feature sftp-server** command on your switch, ensure that you close the SFTP or SCP connection using the **no feature scp-server** or **no feature sftp-server** command before performing ISSD. Otherwise, ISSD will be disruptive. To avoid this issue, we recommend that you transfer files to the switch using the **copy** command instead or using the DCNM client.
- Prior to upgrade or downgrade, reset the switch's logging levels to the system defaults via the **no logging level all** configuration command. If this is not done, the upgrade or downgrade may be disruptive due to excessive logging causing control plane downtime exceeding 80 seconds.

Before entering the **no logging level all** command, ensure that the switch's current logging configuration is saved. This will need to be restored after the upgrade or downgrade.

Follow these steps:

1. Enter the **show running-config | i "logging level"** command and save the output. These are the switch's current settings.
 2. Enter the **no logging level all** command in configuration mode.
 3. Perform upgrade or downgrade.
 4. Restore logging level configuration using the output that was saved from Step 1.
- To determine if high-bandwidth capability is enabled, use the **show hardware fabric-mode** command. The following example shows that the higher bandwidth capability is not activated:

```
switch# show hardware fabric-mode
Fabric mode supports only one configuration of 8G FC modules - 4/44 Host-Optimized 8G
FC module.
switch#
```

The following example shows that the higher bandwidth capability is activated:

```
switch# show hardware fabric-mode
fabric mode supports FCoE, Gen2 and above linecards
switch#
```

For information on supported chassis and modules, see the [Cisco MDS 9000 Series Compatibility Matrix](#). For information on the procedures for installing and upgrading software for Intelligent Storage Services on the Cisco MDS 9000 Series Storage Services Module (SSM), see the [Cisco MDS 9000 Series Storage Services Module Software Installation and Upgrade Guide](#).



Note

If you are downgrading from Cisco MDS NX-OS Release 9.2(1) or later releases to a release prior to Cisco MDS NX-OS Release 9.2(1), ensure that you use the clear logging onboard txwait command after downgrading. Otherwise, logging to the OBFL TxWait file may cease with an error. For more information, see the [Cisco MDS 9000 Series Interfaces Configuration Guide, Release 9.x](#).

Downgrade Guidelines for Cisco MDS 9396S Switch

- Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(0)D1(1) or Cisco MDS NX-OS Release 6.2(13a) is not supported on a Cisco MDS 9396S Switch which has DS-CAC-1200W as a power supply unit (PSU) and DS-C96S-FAN-I as port side intake fan tray.
- Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 6.2(13) is not supported on the Cisco MDS 9396S Multilayer Fabric Switch. The minimum recommended image for Cisco MDS 9396S Multilayer Fabric Switch is 6.2(13a).
- To downgrade from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(x) on a Cisco MDS 9396S Series switch, you must first disable the extended receive BB_credit configuration using the **no feature fcrxbbcredit extended** command. After the downgrade process is complete, enable the extended receive BB_credit configuration using the **feature fcrxbbcredit extended** command.
- If you are downgrading from Cisco MDS NX-OS 8.3(x) release to Cisco MDS NX-OS 8.2(x) release, disable the SAN analytics feature using the **no feature analytics** command.

Downgrade Guidelines for Cisco MDS 9250i Switch

- Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(0)D1(1), or 6.2(13a) and lower is not supported on a Cisco MDS 9250i Switch which has only one online PSU.
- Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(0)D1(1), or 6.2(13a) and lower on a Cisco MDS 9250i Switch with two online PSUs results in loss of N:N grid redundancy. The switch will run in non-redundant mode.
- Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(0)D1(1), or 6.2(13a) and lower on a Cisco MDS 9250i Switch with three online PSUs results in loss of N:N grid redundancy. The switch will run in N+1 power redundant mode.

Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.x

To downgrade from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 7.3(x) or an earlier release, perform the following steps:

- Step 1** Verify that the system image files for the downgrade are present in the active supervisor module bootflash:

```
switch# dir bootflash:

26126848   May 07 11:51:20 2019  m9250-s5ek9-kickstart-mz.8.4.1.bin
20090368   Apr 06 05:25:31 2001  m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
20044800   Mar 30 15:42:05 2014  m9250-s5ek9-kickstart-mz.6.2.7.bin
107197681  Apr 06 05:26:53 2001  m9250-s5ek9-mz.6.2.5.bin.S68
107587249  Mar 30 15:42:52 2014  m9250-s5ek9-mz.6.2.7.bin
```

- Step 2** If the software image file is not present, download it from an FTP or TFTP server to the active supervisor module bootflash. You can obtain the software image file from the Cisco.com Software Download Center:

<http://www.cisco.com/cisco/software/navigator.html>



Note If you need more space in the active supervisor module bootflash, use the **delete** command to remove the files that are not necessary, and perform [Step 3](#) and [Step 4](#).

```
switch# copy tftp://tftpserver.cisco.com/MDS/m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
bootflash:m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
switch# copy tftp://tftpserver.cisco.com/MDS/m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
bootflash:m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
```

- Step 3** Ensure that the required space is available in the active supervisor:

```
switch# dir bootflash:

26126848   May 07 11:51:20 2019  m9250-s5ek9-kickstart-mz.8.4.1.bin
12288     Aug 26 19:06:14 2011  lost+found/
18939904   Jul 01 10:54:49 2011  m9250-s5ek9-kickstart-mz.6.2.5.bin
101756072  Jul 01 10:33:52 2011  m9250-s5ek9-mz.6.2.5.bin

Usage for bootflash://sup-local
120695976 bytes used
63863640 bytes free
184559616 bytes total
```


- Step 4** If you need more space in the active supervisor module bootflash, delete the files that are not required, to make space available:

```
switch# delete bootflash: m9250-s5ek9-kickstart-mz.6.2.5.bin
switch# delete bootflash: m9250-s5ek9-kickstart-mz.6.2.5.bin
```

- Step 5** Run the **show incompatibility system *image-filename*** command to determine if you must disable the features not supported by a release earlier than release to be installed.

```
switch# show incompatibility system bootflash:m9250-s5ek9-mz.7.3.0.D1.1.bin
Checking incompatible configuration(s):
.
..
...
no incompatible configurations
switch#
```

- Step 6** Save the configuration using the **copy running-config startup-config** command:

```
switch# copy running-config startup-config
```

- Step 7** Run the **install all** command to downgrade the software:

```
switch# install all kickstart m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin
system m9250-s5ek9-mz.7.3.0.D1.1.bin
install all kickstart m9250-s5ek9-kickstart-mz.8.1.1b.bin system m9250-s5ek9-mz.8.1.1b.
bin
Installer will perform compatibility check first. Please wait.

Verifying image bootflash:/m9250-s5ek9-kickstart-mz.8.1.1b.bin for boot variable
"kickstart".
[#####] 100% -- SUCCESS

Verifying image bootflash:/m9250-s5ek9-mz.8.1.1b.bin for boot variable "system".
[#####] 100% -- SUCCESS

Performing module support checks.
[#####] 100% -- SUCCESS

Verifying image type.
[#####] 100% -- SUCCESS

Extracting "system" version from image bootflash:/m9250-s5ek9-mz.8.1.1b.bin.
[#####] 100% -- SUCCESS

Extracting "kickstart" version from image bootflash:/m9250-s5ek9-kickstart-mz.8.1.1b.bin.
[#####] 100% -- SUCCESS

Extracting "bios" version from image bootflash:/m9250-s5ek9-mz.8.1.1b.bin.
[#####] 100% -- SUCCESS

Performing Compact Flash and TCAM sanity test.
[#####] 100% -- SUCCESS

Notifying services about system upgrade.
[#####] 100% -- SUCCESS

Compatibility check is done:
Module bootable          Impact  Install-type  Reason
-----  -----  -
-----  -----  -
-----  -----  -
```

```
1      yes non-disruptive      reset
```

Other miscellaneous information for installation:

Module info

1 FC ports 1-40 and FCoE ports 1-8 are hitless, IPS 1-2 are hitful, and Intelligent Applications running are hitful

Images will be upgraded according to following table:

Module	Image	Running-Version(pri:alt)	New-Version	Upg-Required
1	system	8.4(1)	8.1(1b)	yes
1	kickstart	8.4(1)	8.1(1b)	yes
1	bios v2.1.17(01/08/14):v2.1.17(01/08/14)	v2.1.17(01/08/14):v2.1.17(01/08/14)	v2.1.17(01/08/14)	no

Do you want to continue with the installation (y/n)? [n] y

Install is in progress, please wait.

Performing runtime checks.

[#####] 100% -- SUCCESS

Notifying services about the upgrade.

[#####] 100% -- SUCCESS

Setting boot variables.

[#####] 100% -- SUCCESS

Performing configuration copy.

[#####] 100% -- SUCCESS

Module 1: Refreshing compact flash and Upgrading bios/loader/bootrom/power-seq.

Warning: please do not remove or power off the module at this time.

[#####] 100% -- SUCCESS

Converting startup config.

[#####] 100% -- SUCCESS

Upgrade can no longer be aborted, any failure will result in a disruptive upgrade.

Freeing memory in the file system.

[#####] 100% -- SUCCESS

Loading images into memory.

[#####] 100% -- SUCCESS

Saving linecard runtime state.

[#####] 100% -- SUCCESS

Saving supervisor runtime state.

[#####] 100% -- SUCCESS

Saving mts state.

[#####] 100% -- SUCCESS

Reloading the kernel to proceed with the upgrade.

All telnet and ssh connections will now be temporarily terminated.

alishan-241#

>> NX7--LC-loader-02.01.17 (Jan 8 2014 - 16:30:41), Build: 02.01.17

CPU0: 8572E, Version: 2.2, (0x80e80022)

```

Core: E500, Version: 3.0, (0x80210030)
Clock Configuration:
    CPU:1066.672 MHz, CCB:533.336 MHz,
    DDR:266.668 MHz (533.336 MT/s data rate), LBC:33.334 MHz
L1: D-cache 32 kB enabled
    I-cache 32 kB enabled
Board: 9044, IOFPGA: 0x0000001A, SPROM: 0xAB
Boot flash : Primary
I2C: ready
DRAM: Initializing
DDR: dimm type 10, registered 1
DDR: dimm type 10, registered 1
    DDR: 4 GB
L2: 1024 KB enabled
Using default environment

In: serial
Out: serial
Err: serial
Net: INFO: Net boot mode = 1
INFO: Net boot mode = 1
INFO: Board will come up MGMT interface
INFO: MAC address is: b8:38:61:4a:25:c0
eTSEC2 board phy 3
INFO: Net boot mode = 1
eTSEC2
IDE: Bus 0: OK
    Device 0: Model: UGB30STC4000Z4-EBY-ASD Firm: FW100511 Ser#: UNIGEN3 30009652
        Type: Hard Disk
        Capacity: 3907.9 MB = 3.8 GB (8003520 x 512)

Booting image bootflash://m9250-s5ek9-kickstart-mz.8.1.1b.bin
25012224 bytes read
NBI at 08000000 size 134217728

Booting image at addr 0x00800000 ...
Memory <- <0x0 0x0 0x1 0x0> (4096MB)
ethernet0: local-mac-address <- b8:38:61:4a:25:c0
ethernet1: local-mac-address <- 00:e0:0c:00:01:fd
ethernet2: local-mac-address <- 00:e0:0c:00:02:fd
CPU clock-frequency <- 0x3f941f80 (1067MHz)
CPU timebase-frequency <- 0x3f941f8 (67MHz)
CPU bus-frequency <- 0x1fca0fc0 (533MHz)

zImage starting: loaded at 0x00800000 (sp: 0x7fedc4c0)
Allocating 0x620d88 bytes for kernel ...
gunzipping (0x00000000 <- 0x00817000:0x00de3838)...done 0x5bc060 bytes
Using loader supplied ramdisk at 0x28000000-0x3cf1000
initrd head: 0x1f8b0808

Linux/PowerPC load: rw root=/dev/ram0 rdbase=0x70000000 card_index=9044 maxcpus=2 ip=off
ramdisk_size
=262144 noquiet obfl_type_ide=1 kgdboc=ttyS0,9600,B isanimg_loc=0x6000000
isanimg_size=0x400 console
=ttyS0,9600n8nn loader_ver="02.01.17" card_index=9044 quiet bootdev=ide0
server_ip=171.69.21.28 ksim
g=/m9250-s5ek9-kickstart-mz.8.1.1b.bin isanimg=/m9250-s5ek9-mz.8.1.1b.bin Finalizing
device tree...
flat tree at 0xdf0140

                                i¿½setup_arch: bootmem

mpc85xx_ds_setup_arch()
arch: exit

[ 0.060042] Host controller irq 26

```

```

[ 0.134632] Assign root port irq 26
[ 0.753013] physmap-flash physmap-flash.0: Could not reserve memory region
[ 1.032836] Enabling all PCI devices
INIT: version 2.88 booting
Checking all filesystems.....retval=[0]
done.
Loading system software
Uncompressing system image: bootflash:///m9250-s5ek9-mz.8.1.1b.bin
CCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCC
Load plugins that defined in image conf: /isan/plugin_img/img.conf
No Patching support on this platform
Loading plugin 0: core_plugin...
No Patching support on this platform
Enter pboot_chk_compatibility
num srgs 1
0: swid-core-s5ek9, swid-core-s5ek9
num srgs 1
0: swid-sup-ali-ks, swid-sup-ali-ks
INIT: Entering runlevel: 3

[ 95.008144] clpk_hw_init_1:Post ISSU instance 0 status 0x00000736 GOOD
[ 95.086952] clpk_hw_init_1:Post ISSU instance 1 status 0x00000536 GOOD
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...
System is coming up ... Please wait ...

Continuing with installation process, please wait.
The login will be disabled until the installation is completed.

Status for linecard upgrade.
[#####] 100% -- SUCCESS

Performing supervisor state verification.
[#####] 100% -- SUCCESS

Supervisor non-disruptive upgrade successful.

Install has been successful.
-----
8.1.1b -- 7.3.1.DY.1
*****

switch(config)# install all kickstart m9250-s5ek9-kickstart-mz.7.3.1.DY.1.bin system
m9250-s5ek9-mz.7.3.1.DY.1.bin
Installer will perform compatibility check first. Please wait.

Verifying image bootflash:/m9250-s5ek9-kickstart-mz.7.3.1.DY.1.bin for boot variable
"kickstart".
[#####] 100% -- SUCCESS

Verifying image bootflash:/m9250-s5ek9-mz.7.3.1.DY.1.bin for boot variable "system".
[#####] 100% -- SUCCESS

Performing module support checks.
[#####] 100% -- SUCCESS

Verifying image type.
[#####] 100% -- SUCCESS

```

Extracting "system" version from image bootflash:/m9250-s5ek9-mz.7.3.1.DY.1.bin.
 [#####] 100% -- SUCCESS

Extracting "kickstart" version from image
 bootflash:/m9250-s5ek9-kickstart-mz.7.3.1.DY.1.bin.
 [#####] 100% -- SUCCESS

Extracting "bios" version from image bootflash:/m9250-s5ek9-mz.7.3.1.DY.1.bin.
 [#####] 100% -- SUCCESS

Performing Compact Flash and TCAM sanity test.
 [#####] 100% -- SUCCESS

Notifying services about system upgrade.
 [#####] 100% -- SUCCESS

Compatibility check is done:

Module	bootable	Impact	Install-type	Reason
1	yes	non-disruptive	reset	

Other miscellaneous information for installation:

Module info

1 FC ports 1-40 and FCoE ports 1-8 are hitless, IPS 1-2 are hitful, and Intelligent Applications running are hitful

Images will be upgraded according to following table:

Module	Image	Running-Version	New-Version	Upg-Required
1	system	8.1(1b)	7.3(1)DY(1)	yes
1	kickstart	8.1(1b)	7.3(1)DY(1)	yes
1	bios v2.1.17(01/08/14):v2.1.17(01/08/14)	v2.1.17(01/08/14)	v2.1.17(01/08/14)	no

Do you want to continue with the installation (y/n)? [n] y

Install is in progress, please wait.

Performing runtime checks.
 [#####] 100% -- SUCCESS

Notifying services about the upgrade.
 [#####] 100% -- SUCCESS

Setting boot variables.
 [#####] 100% -- SUCCESS

Performing configuration copy.
 [#####] 100% -- SUCCESS

Module 1: Refreshing compact flash and Upgrading bios/loader/bootrom/power-seq.
 Warning: please do not remove or power off the module at this time.
 [#####] 100% -- SUCCESS

Converting startup config.
 [#####] 100% -- SUCCESS

Upgrade can no longer be aborted, any failure will result in a disruptive upgrade.

```

Freeing memory in the file system.
[#####] 100% -- SUCCESS

Loading images into memory.
[#####] 100% -- SUCCESS

Saving linecard runtime state.
[#####] 100% -- SUCCESS

Saving supervisor runtime state.
[#####] 100% -- SUCCESS

Saving mts state.
[#####] 100% -- SUCCESS

Reloading the kernel to proceed with the upgrade.
All telnet and ssh connections will now be temporarily terminated.

>> NX7--LC-loader-02.01.17 (Jan  8 2014 - 16:30:41), Build: 02.01.17

CPU0: 8572E, Version: 2.2, (0x80e80022)
Core: E500, Version: 3.0, (0x80210030)
Clock Configuration:
      CPU:1066.672 MHz, CCB:533.336 MHz,
      DDR:266.668 MHz (533.336 MT/s data rate), LBC:33.334 MHz
L1:   D-cache 32 kB enabled
      I-cache 32 kB enabled
Board: 9044, IOFPGA: 0x0000001A, SPROM: 0xAB
Boot flash : Primary
I2C:   ready
DRAM:  Initializing
DDR: dimm type 10, registered 1
DDR: dimm type 10, registered 1
      DDR: 4 GB
L2:   1024 KB enabled
Using default environment

In:   serial
Out:  serial
Err:  serial
Net:  INFO: Net boot mode = 1
INFO: Net boot mode = 1
INFO: Board will come up MGMT interface
INFO: MAC address is: b8:38:61:4a:25:c0
eTSEC2 board phy 3
INFO: Net boot mode = 1
eTSEC2
IDE:  Bus 0: OK
      Device 0: Model: UGB30STC4000Z4-EBY-ASD Firm: FW100511 Ser#: UNIGEN3      30009652
          Type: Hard Disk
          Capacity: 3907.9 MB = 3.8 GB (8003520 x 512)

Booting image bootflash://m9250-s5ek9-kickstart-mz.7.3.1.DY.1.bin
20824064 bytes read
NBI at 08000000 size 134217728

Booting image at addr 0x00800000 ...
Memory <- <0x0 0x0 0x1 0x0> (4096MB)
ethernet0: local-mac-address <- b8:38:61:4a:25:c0
ethernet1: local-mac-address <- 00:e0:0c:00:01:fd
ethernet2: local-mac-address <- 00:e0:0c:00:02:fd
CPU clock-frequency <- 0x3f941f80 (1067MHz)

```


Continuing with installation process, please wait.
The login will be disabled until the installation is completed.

Status for linecard upgrade.
[#####] 100% -- SUCCESS

Performing supervisor state verification.
[#####] 100% -- SUCCESS

Install has been successful.

Step 8 Run the **show version** command to verify the successful downgrade:

```
switch# show version

Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Documents: http://www.cisco.com/en/US/products/ps9372/tsd_products_support_series_home.html
Copyright (c) 2002-2016, Cisco Systems, Inc. All rights reserved.
The copyrights to certain works contained herein are owned by
other third parties and are used and distributed under license.
Some parts of this software are covered under the GNU Public
License. A copy of the license is available at
http://www.gnu.org/licenses/gpl.html.

Software
  BIOS:          version 2.1.17
  loader:        version N/A
  kickstart:     version 7.3(0)D1(1)
  system:        version 7.3(0)D1(1)
  BIOS compile time:    01/08/14
  kickstart image file is: bootflash:///m9250-s5ek9-kickstart-mz.7.3.0.D1.1.bin.S21
  kickstart compile time: 1/11/2016 16:00:00 [02/11/2016 10:35:42]
  system image file is:   bootflash:///m9250-s5ek9-mz.7.3.0.D1.1.bin.S21
  system compile time:   1/11/2016 16:00:00 [02/11/2016 13:08:53]

Hardware
  cisco MDS 9250i 40 FC 2 IPS 8 FCoE (2 RU) Chassis ("40FC+8FCoE+2IPS Supervisor
  ")
  Motorola, e500v2, core 0 with 4155752 kB of memory.
  Processor Board ID JAF1626BCQH

  Device name: alishan-dr
  bootflash:    4013856 kB

Kernel uptime is 0 day(s), 17 hour(s), 18 minute(s), 58 second(s)

Last reset at 443194 usecs after Wed Aug 31 10:58:41 2016

Reason: Reset due to upgrade
System version: 7.3(1)D1(1)
Service:

plugin
  Core Plugin
switch#
```

Step 9 Verify the status of the modules in the switch, using the **show module** command:

```
switch# show module
```



```

Mod  Ports  Module-Type                               Model                               Status
---  ---
1    50      40FC+8FCoE+2IPS Supervisor                      DS-C9250i-22PK9-SUP active *

Mod  Sw                               Hw                               World-Wide-Name(s) (WWN)
---  ---
1    7.3(0)D1(1)                      0.9                              20:01:54:7f:ee:1b:14:a0 to 20:28:54:7f:ee:1b:14:a0

Mod  MAC-Address(es)                               Serial-Num
---  ---
1    f0-f7-55-29-50-60 to f0-f7-55-29-50-6f      JAF1626BCQH

* this terminal session

switch#

```

Downgrading from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 6.2(x)

Cisco MDS 9700 Series Multilayer Director with a 48-Port 10-Gigabit FCoE Module and VLAN Configurations

To downgrade from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release, 6.2(9) and earlier release, perform the following steps:

- Step 1** Use the **purge module running-config** command to remove FCoE-related configurations, if any, from each 48-port 10-Gigabit FCoE module that is removed.
- Step 2** Remove all 48-port 10-Gigabit FCoE modules from the Cisco MDS 9710 chassis.
- Step 3** Remove all the VLANs that you have created and verify that no VLAN or VSAN mapping exists in the switch, using the **show vlan** and **show vlan fcoe** commands.
- Step 4** Remove all the Ethernet port channels and verify that no Ethernet port channel exists in the switch, using the **show interface brief** and **show ethernet-port-channel database** commands.
- Step 5** Remove all the virtual Fiber Channels (vFCs) and verify that no vFC exists in the switch, using the **show interface brief** command.

Cisco MDS 9700 Series Multilayer Director with a 24-Port 40-Gigabit FCoE Module and VLAN Configurations

To downgrade from Cisco MDS NX-OS Release 8.x to Cisco MDS NX-OS Release 6.2(9) and earlier releases, perform the following steps:

- Step 1** Remove all the 24-port 40-Gigabit FCoE modules from the Cisco MDS 9710 chassis.
- Step 2** Use the **purge module running-config** command to remove FCoE-related configuration, if any, from each 24-port 40-Gigabit FCoE module that is removed.
- Step 3** Remove all the VLANs that you have created and verify that no VLAN or VSAN mapping exists in the switch, using the **show vlan** and **show vlan fcoe** commands.



Note If a switch has 48-port 10-Gigabit FCoE modules and ISSD is performed in a version later than Cisco MDS NX-OS Release 6.2.7, skip [Step 3](#). This is because 10-Gigabit FCoE modules are supported from Cisco MDS NX-OS Release 6.2.7 and requires the VLANs for FCoE traffic to work in 10-Gigabit FCoE ports.

- Step 4** Remove all the Ethernet port channels and verify that no Ethernet port channel exists in the switch, using the **show interface brief** and **show ethernet-port-channel database** commands.
- Step 5** Remove all the virtual fibre channels (vFCs) and verify that no vFC exists in the switch, using the **show interface brief** command.

Cisco MDS 9700 Series Multilayer Director with Cisco MDS 24/10-Port SAN Extension Module

To downgrade from Cisco MDS NX-OS Release 8.x with Cisco MDS 24/10-port SAN extension module to Cisco MDS NX-OS Release 6.2(9) and earlier releases, perform the following steps:

-
- Step 1** Use the **poweroff module *number*** command to power off the module.
 - Step 2** Use the **purge module *slot* running-config** command for Cisco MDS 24/10-port SAN extension module to remove the configuration for the module from the running configuration.
 - Step 3** Use the **no feature fcip** command to disable Fibre Channel over IP (FCIP) on the switch.
 - Step 4** Remove the module and verify that the module does not exist in the switch, using the **show module** command.

Cisco MDS 9700 Series Multilayer Director with Cisco MDS 48-Port 32-Gbps Fibre Channel Switching Module

To downgrade from Cisco MDS NX-OS Release 8.x with MDS 48-port 32-Gbps Fibre Channel Switching Module to Cisco MDS NX-OS Release 6.2(x) and Cisco MDS NX-OS Release 7.3(x), perform the following steps:

-
- Step 1** Use the **poweroff module *number*** command to power off the module.
 - Step 2** Use the **purge module *slot* running-config** command in the switch for Cisco MDS 48-port 32-Gbps Fibre Channel Switching Module to remove the module's configuration from the running configuration.
 - Step 3** Remove the module and verify that the module does not exist on the switch, using the **show module** command.
-

Related Documentation

The documentation set for the Cisco MDS 9000 Series Multilayer switches is available at:

http://www.cisco.com/en/US/products/ps5989/tsd_products_support_series_home.html

The documentation set for Cisco Prime Data Center Network Manager is available at:

http://www.cisco.com/en/US/products/ps9369/tsd_products_support_series_home.html

Release Notes

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/products-release-notes-list.html>

Regulatory Compliance and Safety Information

<http://www.cisco.com/c/en/us/td/docs/switches/datacenter/mds9000/hw/regulatory/compliance/RCSI.html>

Compatibility Information

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/products-device-support-tables-list.html>

Installation and Upgrade

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/products-installation-guides-list.html>

Configuration Guides

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/products-installation-and-configuration-guides-list.html>

Command-Line Interface

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/products-command-reference-list.html>

Troubleshooting and Reference

<http://www.cisco.com/c/en/us/support/storage-networking/mds-9000-nx-os-san-os-software/tsd-products-support-troubleshoot-and-alerts.html>

Command-Line Interface

- *Cisco MDS 9000 Series Command Reference*

Intelligent Storage Networking Services Configuration Guides

- *Cisco MDS 9000 Series I/O Acceleration Configuration Guide*
- *Cisco MDS 9000 Series SANTap Deployment Guide*
- *Cisco MDS 9000 Series Data Mobility Manager Configuration Guide*
- *Cisco MDS 9000 Series Storage Media Encryption Configuration Guide*

Troubleshooting and Reference

- *Cisco MDS 9000 Series and Nexus 7000 Series System Messages Reference*
- *Cisco MDS 9000 Series SAN-OS Troubleshooting Guide*
- *Cisco MDS 9000 Series NX-OS MIB Quick Reference*
- *Cisco DCNM for SAN Database Schema Reference*

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly, *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2017 - 2024 Cisco Systems, Inc. All rights reserved.