



Configuring User Plane in CUPS

This section describes the CLI commands available to configure User Plane in CUPS.



- Important** For information related to following configurations, refer the *Ultra Packet Core CUPS Sx Interface Administration and Reference Guide*:
- *Configuring Sx Service for CUPS*
 - *Configuring Sx-u Interface for CUPS*
 - *Configuring Sx Demux for CUPS*
-



- Important**
- The following configuration limit applies in CUPS:
 - Rulebase - 512
 - Ruledef - 2500
 - Charging-action - 2048
 - The following CLI command is not recommended to be used, with active subscriber sessions, in production environment: **no active-charging service *service_name***
-
- [Configuring User Plane Service, on page 1](#)
 - [Associating GTP-U Service with User Plane Service, on page 2](#)
 - [Associating Sx Service to User Plane Service, on page 3](#)
 - [Recommended Timers, on page 3](#)

Configuring User Plane Service

Use the following CLI commands to configure the User Plane service.

```
configure
  context context_name
```

Associating GTP-U Service with User Plane Service

```
[ no ] user-plane-service service_name
end
```

NOTES:

- **user-plane-service** *service_name*: Creates the specified User Plane service name to allow configuration of User Plane service. The *service_name* is a mandatory parameter to define the User Plane service.
- [no] **user-plane-service** *service_name*: Removes the User Plane service from the particular context.
- By default, the CLI is disabled.

Starting a User Plane Service

The following minimum and critical parameters must be configured to start the User Plane service:

- One Sx-Service.
- Three GTP-U Services of interface type P-GW ingress, S-GW-ingress, and S-GW-egress.



Important

Removal or change of any critical parameters from User Plane service results in the User Plane service getting stopped.

The services that are associated with User Plane service should be in running mode. Else, stop in any associated service triggers stopping of User Plane service.

Associating GTP-U Service with User Plane Service

To associate the GTPU service with the User Plane service, execute the following CLI commands:

```
configure
context context_name
user-plane-service service_name
[ no ] associate gtpu-service gtpu_service_name { pgw-ingress |
sgw-ingress | sgw-egress }
end
```

NOTES:

- **no**: Removes association of GTP-U service with the specified interface type from User Plane service.
- **associate**: Associates User Plane service with GTP-U service.
- **gtpu-service** *gtpu_service_name*: Specifies the GTP-U service for the User Plane service.
- **pgw-ingress**: Configures the interface type as P-GW ingress.
- **sgw-ingress**: Configures the interface type as S-GW ingress.
- **sgw-egress**: Configures the interface type as S-GW egress.
- By default, this command is disabled.

Associating Sx Service to User Plane Service

Use the following CLI commands to associate Sx service with User Plane service.

```
configure
context context_name
user-plane-service service_name
associate sx-service sx_service_name
no associate sx-service
end
```

NOTES:

- **no** : Removes association of Sx service from User Plane service.
- Associating Sx service with User Plane service is a mandatory parameter.
- By default, this CLI command is disabled.

Recommended Timers

The following table provides the recommended timer values for CLI commands related to IPSEC, Sx, and SRP.

IPSEC	CP	UP
ikev2-ikesa max-retransmission	<i>3</i>	<i>3</i>
ikev2-ikesa retransmission-timeout	<i>1000</i>	<i>1000</i>
keepalive	interval <i>4</i> timeout <i>1</i> num-retry <i>4</i>	interval <i>5</i> timeout <i>2</i> num-retry <i>4</i>
Sx	CP	UP
sx-protocol heartbeat interval	<i>10</i>	<i>10</i>
sx-protocol heartbeat retransmission-timeout	<i>5</i>	<i>5</i>
sx-protocol heartbeat max-retransmissions	<i>4</i>	<i>4</i>
sxa max-retransmissions	<i>4</i>	<i>4</i>
sxa retransmission-timeout-ms	<i>5000</i>	<i>5000</i>
sxb max-retransmissions	<i>4</i>	<i>4</i>
sxb retransmission-timeout-ms	<i>5000</i>	<i>5000</i>
sxab max-retransmissions	<i>4</i>	<i>4</i>
sxab retransmission-timeout-ms	<i>5000</i>	<i>5000</i>

Recommended Configurations

IPSEC	CP	UP
sx-protocol association reattempt-timeout	60	60
SRP	CP	UP
hello-interval	3	3
dead-interval	15	15

Recommended Configurations

Following are the recommended configurations and restrictions related to Sx and SRP over IPsec:

- The multihop BFD timer between CP and UP must be seven seconds (for Data UPs).
- The singlehop BFD must be enabled on all the contexts (CP GW/Billing and UP Gn/Gi).
- Inter-chassis multihop BFD must be enabled for CP-CP ICSR and UP-UP ICSR (IMS UP).
- The SRP-IPsec ACL must be configured for TCP protocol instead of IP protocol.
- The Sx-IPsec ACL must be configured for UDP protocol instead of IP protocol.

Example Configurations in CP

Multihop BFD Configuration VPC-DI

The following is an example of multihop BFD configuration with seven seconds timer.

```
bfd-protocol
    bfd multihop-peer 209.165.200.226 interval 350 min_rx 350 multiplier 20
    bfd multihop-peer 209.165.200.227 interval 350 min_rx 350 multiplier 20
    bfd multihop-peer 209.165.200.225 interval 350 min_rx 350 multiplier 20
    bfd multihop-peer 209.165.200.230 interval 350 min_rx 350 multiplier 20
    bfd multihop-peer 209.165.200.228 interval 350 min_rx 350 multiplier 20
    bfd multihop-peer 209.165.200.229 interval 350 min_rx 350 multiplier 20
#exit
```

Multihop BFD Configuration VPC-SI

The following is an example of multihop BFD configuration with three seconds timer.

```
bfd-protocol
    bfd multihop-peer 209.165.200.226 interval 150 min_rx 150 multiplier 20
    bfd multihop-peer 209.165.200.227 interval 150 min_rx 150 multiplier 20
    bfd multihop-peer 209.165.200.225 interval 150 min_rx 150 multiplier 20
    bfd multihop-peer 209.165.200.230 interval 150 min_rx 150 multiplier 20
    bfd multihop-peer 209.165.200.228 interval 150 min_rx 150 multiplier 20
    bfd multihop-peer 209.165.200.229 interval 150 min_rx 150 multiplier 20
#exit
```

BGP Configuration

The following is an example of BGP configuration with recommended timers.

```
router bgp 1111
    router-id 209.165.200.225
    maximum-paths ebgp 15
```

```

neighbor 209.165.200.250 remote-as 1000
neighbor 209.165.200.250 ebgp-multipath
neighbor 209.165.200.250 update-source 209.165.200.225
neighbor 1111:2222::101 remote-as 1000
neighbor 1111:2222::101 ebgp-multipath
neighbor 1111:2222::101 update-source 1111:2222::1
bgp graceful-restart restart-time 120
bgp graceful-restart stalepath-time 300
timers bgp keepalive-interval 30 holdtime-interval 90 min-peer-holdtime-interval 0
server-sock-open-delay-period 10
address-family ipv4
    redistribute connected
#exit
address-family ipv6
    neighbor 1111:2222::101 activate
    redistribute connected
#exit
#exit
#exit

```

Singlehop BFD Configuration

The following is an example of singlehop BFD configuration with three seconds timer.

```

interface bgp-sw1-2161-10
    ip address 209.165.200.233 209.165.200.255
    ipv6 address 1111:222::9/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-11
    ip address 209.165.200.234 209.165.200.255
    ipv6 address 1111:222::10/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-12
    ip address 209.165.200.235 209.165.200.255
    ipv6 address 1111:222::11/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-3
    ip address 209.165.200.226 209.165.200.255
    ipv6 address 1111:222::2/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-4
    ip address 209.165.200.227 209.165.200.255
    ipv6 address 1111:222::3/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-5
    ip address 209.165.200.228 209.165.200.255
    ipv6 address 1111:222::4/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-6
    ip address 209.165.200.229 209.165.200.255
    ipv6 address 1111:222::5/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-7
    ip address 209.165.200.230 209.165.200.255
    ipv6 address 1111:222::6/112 secondary
    bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-8

```

Static Route for Multihop BFD Configuration

```

ip address 209.165.200.231 209.165.200.255
ipv6 address 1111:222::7/112 secondary
bfd interval 999 min_rx 999 multiplier 3
#exit
interface bgp-sw1-2161-9
  ip address 209.165.200.232 209.165.200.255
  ipv6 address 1111:222::8/112 secondary
  bfd interval 999 min_rx 999 multiplier 3
#exit

```

Static Route for Multihop BFD Configuration

The following is an example of static route multihop BFD configuration.

```

ip route static multihop bfd UP-5 209.165.200.240 209.165.200.245
  ip route static multihop bfd UP-6 209.165.200.240 209.165.200.246
  ip route static multihop bfd UP-9 209.165.200.240 209.165.200.247
  ip route static multihop bfd UP-10 209.165.200.240 209.165.200.248
  ip route static multihop bfd UP-7 209.165.200.240 209.165.200.249
  ip route static multihop bfd UP-8 209.165.200.240 209.165.200.250

```

Static Route for Singlehop BFD Configuration

The following is an example of static route singlehop BFD configuration.

```

ip route static bfd bgp-sw1-2161-3 209.165.200.230
  ip route static bfd bgp-sw1-2161-4 209.165.200.230
  ip route static bfd bgp-sw1-2161-5 209.165.200.230
  ip route static bfd bgp-sw1-2161-6 209.165.200.230
  ip route static bfd bgp-sw1-2161-7 209.165.200.230
  ip route static bfd bgp-sw1-2161-8 209.165.200.230
  ip route static bfd bgp-sw1-2161-9 209.165.200.230
  ip route static bfd bgp-sw1-2161-10 209.165.200.230
  ip route static bfd bgp-sw1-2161-11 209.165.200.230
  ip route static bfd bgp-sw1-2161-12 209.165.200.230

```

IPSec ACL Configuration

The following is an example IPSec ACL configuration in CP.

```

ip access-list UP-1
  permit udp host 209.165.200.225 host 209.165.200.226
#exit

```

IPSec Transform Set Configuration

The following is an example of IPSec Transform Set configuration in CP.

```

ikev2-ikesa transform-set ikesa-UP-1
  encryption aes-cbc-256
  group 14
  hmac sha2-256-128
  lifetime 28800
  prf sha2-256

ipsec transform-set A-UP-1
  encryption aes-cbc-256
  hmac sha2-256-128
  group 14

```

IPSec Crypto Map Configuration

The following is an example of IPSec Crypto Map configuration in CP.

```

crypto map UP-1 ikev2-ipv4
    match address UP-1
    authentication local pre-shared-key encrypted key secretkey
    authentication remote pre-shared-key encrypted key secretkey
    ikev2-ikesa max-retransmission 3
    ikev2-ikesa retransmission-timeout 1000
    ikev2-ikesa transform-set list ikesa-UP-1
    ikev2-ikesa rekey
    keepalive interval 4 timeout 1 num-retry 4
    control-dont-fragment clear-bit
    payload foo-sa0 match ipv4
        ipsec transform-set list A-UP-1
        lifetime 300
        rekey keepalive
    #exit
    peer 192.1.1.1
    ikev2-ikesa policy error-notification
#exit

```

Sx Configuration

The following is an example of Sx configuration in CP.

```

sx-service SX-1
    instance-type controlplane
    sxa max-retransmissions 4
    sxa retransmission-timeout-ms 5000
    sxb max-retransmissions 4
    sxb retransmission-timeout-ms 5000
    sxab max-retransmissions 4
    sxab retransmission-timeout-ms 5000
    n4 max-retransmissions 4
    n4 retransmission-timeout-ms 5000
    sx-protocol heartbeat interval 10
    sx-protocol heartbeat retransmission-timeout 5
    sx-protocol heartbeat max-retransmissions 4
    sx-protocol compression
    sx-protocol supported-features load-control
    sx-protocol supported-features overload-control
    exit
end

```

Example Router Configurations

Static Routes for Interface

The following is an example configuration of static route for interface.

```

ip route 209.165.200.224/27 Vlan1111 209.165.200.225
ip route 209.165.200.224/27 Vlan1111 209.165.200.226
ip route 209.165.200.224/27 Vlan1111 209.165.200.227
ip route 209.165.200.224/27 Vlan1111 209.165.200.228
ip route 209.165.200.224/27 Vlan1111 209.165.200.229
ip route 209.165.200.224/27 Vlan1111 209.165.200.230
ip route 209.165.200.224/27 Vlan1111 209.165.200.231
ip route 209.165.200.224/27 Vlan1111 209.165.200.232
ip route 209.165.200.224/27 Vlan1111 209.165.200.233
ip route 209.165.200.224/27 Vlan1111 209.165.200.234

```

Static Routes for Singlehop BFD

The following is an example configuration of static route for singlehop BFD.

Interface for Singlehop BFD

```
ip route static bfd Vlan1111 209.165.200.225
ip route static bfd Vlan1111 209.165.200.226
ip route static bfd Vlan1111 209.165.200.227
ip route static bfd Vlan1111 209.165.200.228
ip route static bfd Vlan1111 209.165.200.229
ip route static bfd Vlan1111 209.165.200.230
ip route static bfd Vlan1111 209.165.200.231
ip route static bfd Vlan1111 209.165.200.232
ip route static bfd Vlan1111 209.165.200.233
ip route static bfd Vlan1111 209.165.200.234
```

Interface for Singlehop BFD

The following is an example configuration of interface for singlehop BFD.

```
interface Vlan1111
  no shutdown
  bandwidth 10000000
  bfd interval 999 min_rx 999 multiplier 3
  no bfd echo
  ip address 209.165.200.224/27
  ipv6 address 1111:222::1/112
```

BGP Configuration

The following is an example of BGP configuration with recommended timers.

```
router bgp 1000
  router-id 209.165.200.226
  timers bgp 30 90
  timers bestpath-limit 300
  timers prefix-peer-timeout 30
  timers prefix-peer-wait 90
  graceful-restart
  graceful-restart restart-time 120
  graceful-restart stalepath-time 300
```

Example Configurations in UP**IPSec ACL Configuration**

The following is an example of IPSec ACL configuration in UP.

```
ip access-list CP-1
  permit udp host 209.165.200.225 host 209.165.200.226
#exit
```

IPSec Transform Set Configuration

The following is an example of IPSec Transform Set configuration in UP.

```
ipsec transform-set A-CP-1
  encryption aes-cbc-256
  hmac sha2-256-128
  group 14

  ikev2-ikesa transform-set ikesa-CP-1
    encryption aes-cbc-256
    group 14
    hmac sha2-256-128
    lifetime 28800
    prf sha2-256
```

IPSec Crypto Map Configuration

The following is an example of IPSec Crypto Map configuration in UP.

```
crypto map CP-1 ikev2-ipv4
    match address CP-1
    authentication local pre-shared-key encrypted key secretkey
    authentication remote pre-shared-key encrypted key secretkey
    ikev2-ikesa max-retransmission 3
    ikev2-ikesa retransmission-timeout 1000
    ikev2-ikesa transform-set list ikesa-CP-1
    ikev2-ikesa rekey
    keepalive interval 5 timeout 2 num-retry 4
    control-dont-fragment clear-bit
    payload foo-sa0 match ipv4
        ipsec transform-set list A-CP-1
    #exit
    peer 209.165.200.230
        ikev2-ikesa policy error-notification
    #exit
```

Sx Configuration

The following is an example of Sx configuration in UP.

```
sx-service SX-1
    instance-type userplane
    sxa max-retransmissions 4
    sxa retransmission-timeout-ms 5000
    sxb max-retransmissions 4
    sxb retransmission-timeout-ms 5000
    sxab max-retransmissions 4
    sxab retransmission-timeout-ms 5000
    n4 max-retransmissions 4
    n4 retransmission-timeout-ms 5000
    sx-protocol heartbeat interval 10
    sx-protocol heartbeat retransmission-timeout 5
    sx-protocol heartbeat max-retransmissions 4
    sx-protocol compression
exit
```

Example SRP Configurations

IPSec ACL Configuration

The following is an example of IPSec ACL configuration for SRP.

```
ip access-list SRP
    permit tcp host 209.165.200.227 host 209.165.200.228
    #exit
```

SRP Configuration

The following is an example of SRP configuration.

```
configure
    context srp
        bfd-protocol
            bfd multihop-peer 209.165.200.225 interval 999 min_rx 999 multiplier 3
        #exit
configure
    context srp
        service-redundancy-protocol
            chassis-mode primary
```

```
hello-interval 3
dead-interval 15
monitor bfd context srp 209.165.200.226 chassis-to-chassis
monitor bgp context gi-pgw 209.165.200.245
monitor bgp context gi-pgw 3333:888::1
monitor bgp context saegw 209.165.200.245
monitor bgp context saegw 3333:888::2
peer-ip-address 209.165.200.227
bind address 209.165.200.228
#exit
ip route static multihop bfd srp 209.165.200.229 209.165.200.245
ip route 209.165.201.1 209.165.202.129 209.165.200.230 SRP-Physical-2102
ip route 209.165.201.2 209.165.202.130 209.165.200.231 SRP-Physical-2102
ip route 209.165.201.3 209.165.202.131 209.165.200.232 SRP-Physical-2102
ip igmp profile default
#exit
#exit
end
```