

Sauvegarde et restauration de l'appareil Prime Infrastructure Gen1 avec clé USB

Contenu

[Introduction](#)

[Problème](#)

[Solution](#)

Introduction

Ce document décrit comment effectuer une sauvegarde depuis l'appareil Prime Infrastructure (PI) Gen 1 en externe avec l'utilisation d'un port USB de l'appareil et vice versa.

Problème

Dans de nombreux scénarios client, l'utilisation du protocole FTP/TFTP (File Transfer Protocol/Trivial File Transfer Protocol (**FTP/TFTP**)) est limitée dans leur centre de données et il est donc difficile pour le client de déplacer la sauvegarde de PI vers un point externe à l'aide de tout serveur **FTP/TFTP**. Comme Appliance est un serveur basé sur Linux, il est très difficile de déplacer la sauvegarde d'une autre manière vers le point externe car il pourrait y avoir une possibilité pour elle de corrompre la sauvegarde au moment d'un transfert incorrect.

Solution

Afin de surmonter cette situation, trouvez une autre solution pour déplacer la sauvegarde de Prime Server vers USB Stick avec l'utilisation du port USB de l'appareil. Un autre avantage est qu'il est beaucoup plus rapide et contribue à réduire le temps nécessaire à la copie par **FTP/TFTP/SFTP** et qu'il sera très utile de copier des données volumineuses également.

Sauvegarde de l'appliance PI Gen1 vers USB

Étape 1. Insérez une clé USB.

Étape 2. Créez un système de fichiers **ext4** pris en charge par une partition.

```
-bash-4.1# fdisk -l    n e l t 8e w
-bash-4.1# partprobe
-bash-4.1# mkfs.ext4 /dev/sdb1
-bash-4.1# mkdir /media/usb-drive/
-bash-4.1# mount -t ext4 /dev/sdb1 /media/usb-drive/
-bash-4.1# umount /media/usb-drive
```

Étape 3. Copiez la sauvegarde de **defaultRepo** vers le nouveau système de fichiers monté.

Étape 4. Validez le **md5** du fichier dans les deux emplacements.

Sauvegarde de l'appareil USB vers PI Gen1

Étape 1. Connectez-vous au PI.

```
pi/admin#
```

Étape 2. Accédez à **shell**.

```
pi/admin# shell
```

```
Enter shell access password :
```

```
Starting bash shell ...
```

```
ade #
```

```
ade #
```

```
ade # sudo su -
```

```
-bash-4.1#
```

Étape 3. Afficher toutes les partitions de disque dans PI.

```
-bash-4.1# fdisk -l
```

```
Disk /dev/sda: 897.0 GB, 896998047744 bytes
```

```
255 heads, 63 sectors/track, 109053 cylinders
```

```
Units = cylinders of 16065 * 512 = 8225280 bytes
```

```
Sector size (logical/physical): 512 bytes / 512 bytes
```

```
I/O size (minimum/optimal): 512 bytes / 512 bytes
```

```
Disk identifier: 0x000591be
```

Device	Boot	Start	End	Blocks	Id	System
/dev/sda1	*	1	64	512000	83	Linux
Partition 1 does not end on cylinder boundary.						
/dev/sda2		64	77	102400	83	Linux
Partition 2 does not end on cylinder boundary.						
/dev/sda3		77	109054	875359232	8e	Linux LVM

Disk /dev/mapper/smosvg-rootvol: 4194 MB, 4194304000 bytes

255 heads, 63 sectors/track, 509 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-swapvol: 16.8 GB, 16777216000 bytes

255 heads, 63 sectors/track, 2039 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-tmpvol: 2113 MB, 2113929216 bytes

255 heads, 63 sectors/track, 257 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-usrvol: 7348 MB, 7348420608 bytes

255 heads, 63 sectors/track, 893 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-varvol: 4194 MB, 4194304000 bytes

255 heads, 63 sectors/track, 509 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-optvol: 716.3 GB, 716252905472 bytes

255 heads, 63 sectors/track, 87079 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-home: 134 MB, 134217728 bytes

255 heads, 63 sectors/track, 16 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-recvol: 134 MB, 134217728 bytes

255 heads, 63 sectors/track, 16 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-altrootvol: 134 MB, 134217728 bytes

255 heads, 63 sectors/track, 16 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-localdiskvol: 134.6 GB, 134553272320 bytes

255 heads, 63 sectors/track, 16358 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/mapper/smosvg-storedatavol: 10.5 GB, 10502537216 bytes

255 heads, 63 sectors/track, 1276 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0x00000000

Disk /dev/sdb: 62.1 GB, 62075699200 bytes

255 heads, 63 sectors/track, 7546 cylinders

Units = cylinders of 16065 * 512 = 8225280 bytes

Sector size (logical/physical): 512 bytes / 512 bytes

I/O size (minimum/optimal): 512 bytes / 512 bytes

Disk identifier: 0xa5fe72c5

Device	Boot	Start	End	Blocks	Id	System
/dev/sdb1		1	7546	60613213+	8e	Linux LVM

Étape 4. Créez un nouveau répertoire et montez-le.

```
-bash-4.1# mkdir /media/usb-drive/
```

```
-bash-4.1# mount -t ext4 /dev/sdb1 /media/usb-drive/
```

```
-bash-4.1# ls -lv
```

```
total 60
```

```
-rw-----. 1 root root 8494 Aug 24 2018 anaconda-ks.cfg
```

```
drwxr-xr-x. 2 root root 4096 Aug 24 2018 bin
```

```
-rw-r--r--. 1 root root 18977 Aug 24 2018 install.log
```

```
-rw-r--r--. 1 root root 5646 Aug 24 2018 install.log.syslog
```

```
-rw-r--r--. 1 root root 5 Aug 24 2018 iso.ks.cfg
```

```
-rw-----. 1 root root 164 Aug 24 2018 ks-post.log
```

```
-rw-----. 1 root root 381 Aug 24 2018 ks-post-toinstall.log
```

```
-rw-rw-r--. 1 root root 120 Aug 23 17:47 test.log
```

```
-bash-4.1# cd /media/usb-drive/
```

```
-bash-4.1# pwd
```

```
/media/usb-drive
```

Étape 5. Avant de copier la sauvegarde, vérifiez le **md5** de la sauvegarde à partir d'USB.

```
-bash-4.1# ls -lv
```

```
total 21197320
```

```
-rw-r--r--. 1 root root 21706033973 Jun 28 14:57 pi-180419-  
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
drwx-----. 2 root root          16384 Jun 28 14:29 lost+found
```

```
-bash-4.1#
```

```
-bash-4.1#
```

```
-bash-4.1# md5sum pi-180419-
```

```
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
44daa932e7ca10fafe480302f7a17b6a pi-180419-
```

```
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
-bash-4.1#
```

```
-bash-4.1#
```

Étape 6. Copiez la sauvegarde dans le dossier **/localdisk/defaultRepo**.

```
-bash-4.1# cp pi-180419-
```

```
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg  
/localdisk/defaultRepo/
```

```
-bash-4.1#
```

```
-bash-4.1#
```

```
-bash-4.1# cd /localdisk/defaultRepo/
```

```
-bash-4.1# ls -lv
```

```
total 21218032
```

```
-rw-r--r--. 1 root root 21706033973 Aug 23 18:56 pi-180419-  
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
-bash-4.1#
```

```
-bash-4.1#
```

Étape 7. Vérifiez le **md5** de la sauvegarde copiée avec **md5** précédent.

```
-bash-4.1# md5sum pi-180419-
```

```
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
44daa932e7ca10fafe480302f7a17b6a pi-180419-
```

```
1332__VER3.1.0.0.132_BKSZ204G_CPU16_MEM3G_RAM15G_SWAP15G_APP_CK1589549125.tar.gpg
```

```
-bash-4.1#
```

```
-bash-4.1#
```

Étape 8. Démontez le répertoire.

```
-bash-4.1# umount /media/usb-drive
```

```
-bash-4.1#
```

```
-bash-4.1#
```

```
-bash-4.1#
```