

# Catalyst 스위치 구성 요소의 일련 번호 확인

## 목차

---

[소개](#)

[사전 요구 사항](#)

[요구 사항](#)

[사용되는 구성 요소](#)

[표기 규칙](#)

[배경 정보](#)

[Catalyst 6500](#)

[Catalyst 4500](#)

[Supervisor Engine 2가 포함된 Catalyst 4500](#)

[Catalyst 4500 Supervisor Engine II+/III/IV](#)

[Catalyst 3750](#)

[Catalyst 3560](#)

[Catalyst 3550](#)

[Catalyst 2950/2970/2940](#)

[Catalyst 2900XL/3500XL](#)

[Catalyst 2948GL3/4908G-L3/4980G-L3](#)

[Catalyst 9000](#)

[관련 정보](#)

---

## 소개

이 문서에서는 Cisco Catalyst 스위치에서 교체 가능한 다양한 구성 요소의 일련 번호를 확인하는 방법에 대해 설명합니다.

## 사전 요구 사항

### 요구 사항

이 문서에 대한 특정 요건이 없습니다.

### 사용되는 구성 요소

이 문서의 정보는 다음 소프트웨어 및 하드웨어 버전을 기반으로 합니다.

- 다양한 Catalyst 스위치
- 다양한 소프트웨어 버전

이 문서의 정보는 특정 랩 환경의 디바이스를 토대로 작성되었습니다. 이 문서에 사용된 모든 디바이스

이스는 초기화된(기본) 컨피그레이션으로 시작되었습니다. 현재 네트워크가 작동 중인 경우 모든 명령의 잠재적인 영향을 미리 숙지하시기 바랍니다.

## 표기 규칙


문서 규칙에 대한 자세한 내용은 [Cisco 기술 팁 표기 규칙을 참고하십시오.](#)

## 배경 정보

일련 번호는 네트워크에 있는 부품의 데이터베이스를 작성하는 데 필요합니다. [Cisco 기술](#) 지원에서 서비스 요청을 생성할 때, 영향을 받는 장비의 일련 번호가 있어야 합니다. 이러한 요구 사항은 교체 부품 또는 RMA(Return Materials Authorization)가 필요한 경우에 특히 그렇습니다.

Cisco Catalyst 스위치의 일련 번호는 수정할 수 없습니다. 관리를 위해 Cisco IOS® 소프트웨어를 실행하는 Cisco Catalyst 스위치에서 사용자 지정 문자열을 반환하도록 구성할 수 있습니다. 사용자 지정 문자열을 생성하려면 전역 컨피그레이션 모드에서 snmp-server chassis-id 명령을 실행합니다

---

 참고: show 명령에 대한 자세한 내용은 [Show Commands](#)를 [참조하십시오.](#)

---

## Catalyst 6500

새시 및 기타 구성 요소의 일련 번호를 확인하려면 `show idprom` 명령을 사용합니다:

```
<#root>
```

```
6506#
```

```
show idprom ?
```

```
all           selects all FRU-types
backplane     specify backplane
clock         specify clock <number>
earl          specify earl <slot>
fan-tray      specify fan-tray <number>
interface     interface name
module        specify module <slot>
power-supply  specify power-supply <number>
rp            specify RP (MSFC) <slot>
supervisor    specify supervisor <slot>
vtt           specify VTT <number>
```

새시 일련 번호를 가져오려면 `show idprom backplane` 명령을 실행합니다.

```
<#root>
```

```
6506#
```

show idprom backplane

IDPROM for backplane #0  
(FRU is 'Catalyst 6500 6-slot backplane')  
OEM String = 'Cisco Systems'

Product Number = 'WS-C6506'

Serial Number = 'TBA03270652'

Manufacturing Assembly Number = '73-3436-01'  
Manufacturing Assembly Revision = 'A0'  
Hardware Revision = 1.0  
Current supplied (+) or consumed (-) = -A

모듈 일련 번호를 얻으려면 show idprom module slot <slot number> 명령을 실행합니다. 또는 다음과 같이 show module 명령을 실행할 수 있습니다.

<#root>

6506#

show module

Mod	Ports	Card Type	Model
1	2	Catalyst 6000 supervisor 2 (Active)	WS-X6K-S2U-MSFC2
SAD055006NE			
3	0	2 port adapter FlexWAN	WS-X6182-2PA
SAD04350EEU			
4	48	SFM-capable 48-port 10/100 Mbps RJ45	WS-X6548-RJ-45
SAD055108C2			

Mod	MAC addresses	Hw	Fw	Sw	Status
1	0001.6415.a602 to 0001.6415.a603	3.2	6.1(3)	7.5(0.6)HUB6	Ok
3	0001.6413.c86b to 0001.6413.c8aa	1.5	12.1(13)E1	12.1(13)E1	Ok
4	0001.63d3.e77a to 0001.63d3.e7a9	4.0	6.3(1)	7.5(0.6)HUB6	Ok

Mod	Sub-Module	Model	Serial	Hw	Status
1	Policy Feature Card 2	WS-F6K-PFC2	SAD055004VA	3.0	Ok
1	Cat6k MSFC 2 daughterboard	WS-F6K-MSFC2	SAD055006VF	2.0	Ok

Mod Online Diag Status

-----  
1 Pass  
3 Not Supported

 참고: `show diagbus` 명령을 사용하여 Flex WAN 모듈의 포트 어댑터 일련 번호를 확인합니다.

## Catalyst 4500

### Supervisor Engine 2가 포함된 Catalyst 4500

Catalyst 4500/4000 Supervisor 2에서 새시 일련 번호는 버전 5.5(10), 6.3(2) 이상에서 CLI를 통해 사용할 수 있습니다. 이전 버전의 경우 `show version` 명령은 새시 일련 번호 대신 Supervisor Engine 일련 번호를 표시합니다. 이전 버전에서 새시의 일련 번호를 얻으려면 새시의 외부 스티커를 확인하십시오.

### Catalyst 4500 Supervisor Engine II+/III/IV

새시 및 기타 구성 요소의 일련 번호를 확인하려면 `show idprom` 명령을 사용합니다.

```
<#root>
```

```
Switch#
```

```
show idprom ?
```

```
all          show all non-interface IDPROMs
chassis      show IDPROM for chassis
fan-tray     show IDPROM for system fan tray
interface    show contents of gbic connected to this interface
module       show IDPROM for module
power-supply show IDPROM for power supply
supervisor   show IDPROM for supervisor
```

새시 일련 번호를 가져오려면 `show idprom chassis` 명령을 사용합니다:

```
<#root>
```

```
Switch#
```

```
show idprom chassis
```

```
Chassis Idprom :
```

```
Common Block Signature = 0xABAB
Common Block Version = 1
Common Block Length = 144
Common Block Checksum = 4081
Idprom Size = 256
Block Count = 2
FRU Major Type = 0x4001
FRU Minor Type = 37
OEM String = Cisco Systems, Inc.
```

Product Number = WS-C4506  
Serial Number = FOX0627A001  
Part Number = 73-8107-04  
Part Revision = 01  
Manufacturing Deviation String = 0  
Hardware Revision = 0.4  
Manufacturing Bits = 0x0000  
Engineering Bits = 0x0000  
Snmp OID = 0.0.0.0.0.0.0.0  
Power Consumption = 0  
RMA Failure Code = 0 0 0 0  
Chassis Block Signature = 0x4001  
Chassis Block Version = 1  
Chassis Block Length = 22  
Chassis Block Checksum = 628  
Feature Bits = 0x0000000000000000  
MAC Base = 000a.4172.df40  
MAC Count = 64

전원 공급 장치 일련 번호를 얻으려면 show idprom power-supply {1 | 2} 명령:

<#root>

Switch#

show idprom power-supply 1

Power Supply 1 Idprom :  
Common Block Signature = 0xABAB  
Common Block Version = 1  
Common Block Length = 144  
Common Block Checksum = 5857  
Idprom Size = 256  
Block Count = 2  
FRU Major Type = 0x4501  
FRU Minor Type = 1  
OEM String = Cisco Systems, Inc.

Product Number = PWR-C4K-1400AC

Serial Number = ABC06260005

Part Number = 34-1846-01  
Part Revision = 45  
Manufacturing Deviation String =  
Hardware Revision = 1.0  
Manufacturing Bits = 0x0000  
Engineering Bits = 0x0000  
Snmp OID = 22616.22616.22616.22616.22616.22616.22616.22616  
Power Consumption = 1400  
RMA Failure Code = 0 0 0 0  
Power Supply Block Signature = 0x4501  
PowerSupply Block Version = 1  
PowerSupply Block Length = 20  
PowerSupply Block Checksum = 293  
Feature Bits = 0x0000000000000000  
Current @ 110V = 17

Current @ 220V = 9  
StackMIB OID = 22616

모듈 일련 번호를 가져오려면 show idprom module slot <slot number> 명령을 사용합니다. 또는 show module 명령을 사용할 수 있습니다.

<#root>

Switch#

show module

Mod	Ports	Card Type	Model	Serial No.
1	2	1000BaseX (GBIC) Supervisor(active)	WS-X4014	

JAB054109H1

3	48	10/100BaseTX (RJ45)	WS-X4148	
---	----	---------------------	----------	--

JAB025202M6

4	6	1000BaseX (GBIC)	WS-X4306	
---	---	------------------	----------	--

JAB023403BG

M	MAC addresses	Hw	Fw	Sw	Status
1	000a.4172.df40 to 000a.4172.df41	0.5	12.1(12r)EW	12.1(13)EW(0.34)	Ok
3	0050.730b.2340 to 0050.730b.236f	1.0			Ok
4	0010.7bfa.7ca4 to 0010.7bfa.7ca9	2.0			Ok

## Catalyst 3750

여기 예와 같이 show version 명령을 사용하여 새시 일련 번호 및 스위치 모델 유형을 결정할 수 있습니다. 출력에서 모든 스위치 스택 멤버, 새시 및 일련 번호 정보를 찾을 수 있습니다.

<#root>

3750#

show version

```
Cisco Internetwork Operating System Software
Cisco IOS (tm) C3750 Software (C3750-I5-M), Version 12.1(14)EA1, RELEASE SOFTWARE (fc1
)
Copyright (c) 1986-2003 by cisco Systems, Inc.
Compiled Tue 22-Jul-03 13:17 by antonino
Image text-base: 0x00003000, data-base: 0x008F0CF8
```

ROM: Bootstrap program is C3750 boot loader  
BOOTLDR: C3750 Boot Loader (C3750-HB00T-M) Version 12.1(11r)AX, RELEASE SOFTWARE  
(fc1)

3750RJ uptime is 1 hour, 29 minutes  
System returned to ROM by power-on  
System image file is "flash:c3750-i5-mz.121.14-EA1/c3750-i5-mz.121.14-EA1.bin"

cisco WS-C3750-24TS (PowerPC405) processor (revision A0) with 120822K/10240K bytes of memory.

Processor board ID CAT0726R0ZU  
Last reset from power-on  
Bridging software.  
2 Virtual Ethernet/IEEE 802.3 interface(s)  
48 FastEthernet/IEEE 802.3 interface(s)  
16 Gigabit Ethernet/IEEE 802.3 interface(s)  
The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.

Base ethernet MAC Address : 00:0D:29:B4:18:00  
Motherboard assembly number : 73-7055-06  
Power supply part number : 341-0034-01  
Motherboard serial number : CAT0726043V  
Power supply serial number : PHI0708009K  
Model revision number : A0  
Motherboard revision number : A0

Model number : WS-C3750-24TS-E

System serial number : CAT0726R0ZU

Switch Ports Model SW Version SW Image

-----  
\* 1 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
2 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
3 12 WS-C3750G-12S 12.1(14)EA1 C3750-I5-M

Switch 02

-----  
Switch Uptime : 1 hour, 29 minutes  
Base ethernet MAC Address : 00:0D:29:B4:3F:00  
Motherboard assembly number : 73-7055-06  
Power supply part number : 341-0034-01  
Motherboard serial number : CAT07260438  
Power supply serial number : PHI0708008X  
Model revision number : A0  
Motherboard revision number : A0

Model number : WS-C3750-24TS-E

System serial number : CAT0726R10A

Switch 03

-----  
Switch Uptime : 1 hour, 29 minutes  
Base ethernet MAC Address : 00:0D:BD:6A:3E:00

Motherboard assembly number : 73-8307-06  
Power supply part number : 341-0048-01  
Motherboard serial number : CAT073205S2  
Power supply serial number : DTH0731055Z  
Model revision number : A0  
Motherboard revision number : A0

Model number : WS-C3750G-12S-E

System serial number : CAT0732R0M4

Top assembly part number : 800-23419-01  
Top assembly revision number : A0

Configuration register is 0xF

3750#

## Catalyst 3560

새시 일련 번호 및 스위치 모델 유형을 확인하려면 show version 명령을 사용합니다.

<#root>

3560#

show version

Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3560 Software (C3560-I5-M), Version 12.1(19)EA1c, RELEASE SOFTWARE (fc2)  
Copyright (c) 1986-2004 by cisco Systems, Inc.  
Compiled Tue 03-Feb-04 05:56 by yenanh  
Image text-base: 0x00003000, data-base: 0x0091D404

ROM: Bootstrap program is C3560 boot loader  
BOOTLDR: C3560 Boot Loader (C3560-HB00T-M) Version 12.1(19r)EA1b, RELEASE SOFTWARE (fc2)

3-8-03-CATS3560 uptime is 8 weeks, 4 days, 18 hours, 16 minutes  
System returned to ROM by power-on  
System image file is "flash:c3560-i5-mz.121-19.EA1c.bin"

cisco WS-C3560-24PS (PowerPC405) processor (revision D0) with 118776K/12288K bytes of memory.

Processor board ID CSG0802P0G4

Last reset from power-on

Bridging software.

1 Virtual Ethernet/IEEE 802.3 interface(s)

24 FastEthernet/IEEE 802.3 interface(s)

2 Gigabit Ethernet/IEEE 802.3 interface(s)

The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.

Base ethernet MAC Address : 00:0E:39:E9:32:80

Motherboard assembly number : 73-9299-01

Power supply part number : 341-0029-03

Motherboard serial number : CAT075108EK



Power supply serial number : LIT074900K3  
Model revision number : D0  
Motherboard revision number : C0

Model number : WS-C3560-24PS-E  
System serial number : CSG0802P0G4

Top Assembly Part Number : 800-24814-01  
Top Assembly Revision Number : D0  
Version ID : N/A  
Hardware Board Revision Number : 0x08

## Catalyst 3550

새시 일련 번호 및 스위치 모델 유형을 확인하려면 show version 명령을 사용합니다.

```
<#root>
```

```
Cat3550#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3550 Software (C3550-I5Q3L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Mon 25-Nov-02 00:07 by antonino  
Image text-base: 0x00003000, data-base: 0x0075FE48
```

```
ROM: Bootstrap program is C3550 boot loader
```

```
Cat3550 uptime is 4 days, 2 hours, 57 minutes  
System returned to ROM by power-on  
System image file is "flash:c3550-i5q3l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C3550-48 (PowerPC) processor (revision G0) with 65526K/8192K bytes of memory.  
Processor board ID CHK0642W02B  
Last reset from warm-reset  
Bridging software.  
Running Layer2/3 Switching Image
```

```
Ethernet-controller 1 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 2 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 3 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 4 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 5 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
Ethernet-controller 6 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
The password-recovery mechanism is enabled.  
384K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:0B:46:8A:2F:80
```

Motherboard assembly number: 73-5701-07  
Power supply part number: 34-0967-01  
Motherboard serial number: CAT0641027L  
Power supply serial number: DCA06392BU2  
Model revision number: G0  
Motherboard revision number: A0

Model number: WS-C3550-48-SMI

System serial number: CHK0642W02B

Configuration register is 0x10F

## Catalyst 2950/2970/2940

새시 일련 번호 및 스위치 모델 유형을 확인하려면 `show version` 명령을 사용합니다:

```
<#root>
```

```
Cat2950#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C2950 Software (C2950-I6Q4L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Sun 24-Nov-02 23:31 by antonino  
Image text-base: 0x80010000, data-base: 0x80562000
```

```
ROM: Bootstrap program is CALHOUN boot loader
```

```
Cat2950 uptime is 4 days, 2 hours, 52 minutes  
System returned to ROM by power-on  
System image file is "flash:c2950-i6q4l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C2950G-48-EI (RC32300) processor (revision C0) with 21002K bytes of memory.  
Processor board ID FHK0624W0HS  
Last reset from system-reset  
Running Enhanced Image  
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
32K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:09:E8:89:4A:40  
Motherboard assembly number: 73-7409-08  
Power supply part number: 34-0965-01  
Motherboard serial number: FOC06230ERQ  
Power supply serial number: DAB062143BP  
Model revision number: C0  
Motherboard revision number: B0
```

Model number: WS-C2950G-48-EI

System serial number: FHK0624W0HS

Configuration register is 0xF

# Catalyst 2900XL/3500XL

새시 일련 번호 및 스위치 모델 유형을 확인하려면 `show version` 명령을 사용합니다:

<#root>

Switch#

`show version`

```
Cisco Internetwork Operating System Software
Cisco IOS (tm) C3500XL Software (C3500XL-C3H2S-M), Version 12.0(5.2)XU, MAINTENANCE
INTERIM SOFTWARE
Copyright (c) 1986-2000 by cisco Systems, Inc.
Compiled Mon 17-Jul-00 18:29 by ayounes
Image text-base: 0x00003000, data-base: 0x00301F3C
```

ROM: Bootstrap program is C3500XL boot loader

```
Switch uptime is 4 days, 3 hours, 4 minutes
System returned to ROM by power-on
System image file is "flash:c3500XL-c3h2s-mz-120.5.2-XU.bin"
```

```
Cisco WS-C3548-XL (PowerPC403) processor (revision 0x01) with 16384K/1024K bytes
of memory. Processor board ID FOC0616X0RG, with hardware revision 0x00
Last reset from power-on
```

```
Processor is running Enterprise Edition Software
Cluster command switch capable
Cluster member switch capable
48 FastEthernet/IEEE 802.3 interface(s)
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
32K bytes of flash-simulated non-volatile configuration memory.
Base ethernet MAC Address: 00:09:7C:8E:78:80
Motherboard assembly number: 73-3903-09
Power supply part number: 34-0971-02
Motherboard serial number: FOC06160L07
Power supply serial number: APQ061200VZ
Model revision number: M0
Motherboard revision number: A0
```

**Model number: WS-C3548-XL-EN**

**System serial number: FOC0616X0RG**

Configuration register is 0xF

# Catalyst 2948GL3/4908G-L3/4980G-L3

새시 일련 번호를 확인하려면 `show hardware` 명령을 사용합니다:

<#root>

2948g-13#

**show hardware**

Model: Cat-2948G-L3 Date: 17:49:42 UTC Tue Mar 18 2003

XPIF FPGA File: xpif\_fpga\_0\_72b\_CClk.rbt  
XPIF FPGA Date: Wed Dec 8 17:05:42 1999

**Slot 0/0:**

Chip 0	Reset Count: 0	Chip 1	Reset Count: 0
Chip 2	Reset Count: 0	Chip 3	Reset Count: 0
Chip 4	Reset Count: 0	Chip 5	Reset Count: 0
Chip 6	Reset Count: 0	Chip 7	Reset Count: 0
Chip 8	Reset Count: 0	Chip 9	Reset Count: 0
Chip 10	Reset Count: 0	Chip 11	Reset Count: 0

EPIF Version : 0 CAM size: 32 KB

Ucode Version : 1.0

Ucode Image : EPIF\_UCODE\_RUNTIME

**Port Phy Setup**

Port1 :DONE	Port2 :DONE	Port3 :DONE	Port4 :DONE
Port5 :DONE	Port6 :DONE	Port7 :DONE	Port8 :DONE
Port9 :DONE	Port10:DONE	Port11:DONE	Port12:DONE
Port13:DONE	Port14:DONE	Port15:DONE	Port16:DONE
Port17:DONE	Port18:DONE	Port19:DONE	Port20:DONE
Port21:DONE	Port22:DONE	Port23:DONE	Port24:DONE
Port25:DONE	Port26:DONE	Port27:DONE	Port28:DONE
Port29:DONE	Port30:DONE	Port31:DONE	Port32:DONE
Port33:DONE	Port34:DONE	Port35:DONE	Port36:DONE
Port37:DONE	Port38:DONE	Port39:DONE	Port40:DONE
Port41:DONE	Port42:DONE	Port43:DONE	Port44:DONE
Port45:DONE	Port46:DONE	Port47:DONE	Port48:DONE

**Slot 0/1:**

XPIF Version : 0 CAM size: 128 KB

Ucode Version : 1.0

Ucode Image : XPIF\_UCODE\_RUNTIME

**Port Phy Setup**

Port49:DONE	Port50:DONE
-------------	-------------

**IDPROM Contents**

:  
FRU Type : 0x0.0x0  
OEM String : Cisco\_Systems

**Product Number** : WS-C2948G-L3

**Serial Number** : FOX05330ADH

Mfg. Assembly No. : 73-4083-07  
Mfg. Assembly Ver. : A0  
Hardware Version : 1.7  
FPGA Version : 0  
SNMP IOD : 9.5.1.3.1.1.2.275  
RMA Code : 0  
Feature Bits : 0x00000000  
MAC Address Base : 00:07:85:07:DC:00  
Total MAC Adrs. : 1024

# Catalyst 9000

새시 일련 번호를 확인하려면 show version 명령을 사용합니다. 또는 다음과 같이 show module 명령을 사용하여 더 작은 출력을 표시할 수 있습니다.

```
<#root>
```

```
C9300#
```

```
show version
```

```
Cisco IOS XE Software, Version 17.06.04  
Cisco IOS Software [Bengaluru], Catalyst L3 Switch Software (CAT9K_IOSXE), Version 17.6.4, RELEASE SOFTWARE  
Technical Support: http://www.cisco.com/techsupport  
Copyright (c) 1986-2022 by Cisco Systems, Inc.  
Compiled Sun 14-Aug-22 08:58 by mcpre
```

```
Cisco IOS-XE software, Copyright (c) 2005-2022 by cisco Systems, Inc.  
All rights reserved. Certain components of Cisco IOS-XE software are  
licensed under the GNU General Public License ("GPL") Version 2.0. The  
software code licensed under GPL Version 2.0 is free software that comes  
with ABSOLUTELY NO WARRANTY. You can redistribute and/or modify such  
GPL code under the terms of GPL Version 2.0. For more details, see the  
documentation or "License Notice" file accompanying the IOS-XE software,  
or the applicable URL provided on the flyer accompanying the IOS-XE  
software.
```

```
ROM: IOS-XE ROMMON
```

```
BOOTLDR: System Bootstrap, Version 17.8.1r[FC2], RELEASE SOFTWARE (P)
```

```
C9300 uptime is 1 week, 2 days, 17 hours, 51 minutes  
Uptime for this control processor is 1 week, 2 days, 17 hours, 54 minutes  
System returned to ROM by Reload Command at 07:14:20 jst Wed Aug 2 2023  
System restarted at 07:29:56 jst Wed Aug 2 2023  
System image file is "flash:packages.conf"  
Last reload reason: Reload Command
```

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at:  
<http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>

If you require further assistance please contact us by sending email to [export@cisco.com](mailto:export@cisco.com).

Technology Package License Information:

```

-----
Technology-package                Technology-package
Current                            Type                Next reboot
-----
network-advantage                Smart License        network-advantage
dna-advantage                    Subscription Smart License
AIR License Level: AIR DNA Advantage
Next reload AIR license Level: AIR DNA Advantage

```

Smart Licensing Status: Registration Not Applicable/Not Applicable

cisco C9300-24UX (X86) processor with 1317097K/6147K bytes of memory.  
 Processor board ID FJC2325E0HB  
 5 Virtual Ethernet interfaces  
 8 Gigabit Ethernet interfaces  
 64 Ten Gigabit Ethernet interfaces  
 4 TwentyFive Gigabit Ethernet interfaces  
 4 Forty Gigabit Ethernet interfaces  
 2048K bytes of non-volatile configuration memory.  
 8388608K bytes of physical memory.  
 1638400K bytes of Crash Files at crashinfo:.  
 11264000K bytes of Flash at flash:.

```

Base Ethernet MAC Address       : c4:c6:03:9a:bd:80
Motherboard Assembly Number     : 73-18276-03
Motherboard Serial Number       : FJZ23210BTF
Model Revision Number           : D0
Motherboard Revision Number     : B0

```

Model Number : C9300-24UX

System Serial Number : FJC2325E0HB

CLEI Code Number :

Switch	Ports	Model	SW Version	SW Image	Mode
*	1 41	C9300-24UX	17.06.04	CAT9K_IOSXE	INSTALL

C9300#

show module

Switch	Ports	Model	Serial No.	MAC address	Hw Ver.	Sw Ver.
1	41					

C9300-24UX

FJC2325E0HB

```

c4c6.039a.bd80 V02          17.06.04
C9300#

```

## 관련 정보

- [명령 표시](#)
- [Cisco 기술 지원 및 다운로드](#)

이 번역에 관하여

Cisco는 전 세계 사용자에게 다양한 언어로 지원 콘텐츠를 제공하기 위해 기계 번역 기술과 수작업 번역을 병행하여 이 문서를 번역했습니다. 아무리 품질이 높은 기계 번역이라도 전문 번역가의 번역 결과물만큼 정확하지는 않습니다. Cisco Systems, Inc.는 이 같은 번역에 대해 어떠한 책임도 지지 않으며 항상 원본 영문 문서(링크 제공됨)를 참조할 것을 권장합니다.