

访问SPA3102交互语音应答(IVR)菜单

目标

交互式语音响应提供设备内不同配置的说明。当电话连接到设备时，会获取这些指令。本文档加深了对SPA3102的交互式语音应答(IVR)菜单的了解。

适用设备

- SPA8000
- SPA3102
- SPA9000
- SPA2102
- SPA112
- PAP2T

软件版本

- v6.1.12

交互式语音应答(IVR)菜单

访问交互式语音应答菜单

步骤1.使用连接到语音网关的PHONE端口的电话。交互式语音响应菜单只能通过模拟电话访问。

步骤2.按四个星号(*)键。

步骤3.等到听到语音提示“Linksys配置菜单”。请输入选项，后跟#（井号）键或挂机退出。

步骤4.请参阅下表，其中列出了操作、命令、菜单选项和说明。选择选项后，按#（井）键。要退出菜单，请挂断电话。

交互式语音应答菜单

IVR Action	IVR Menu	Parameter(s)	Notes
Activate IVR Menu	****	None	Ignore SIT or other tones until you hear, "Sipura configuration menu. Please enter option followed by the pound key or hang-up to exit."
Check WAN IP Address	110	None	IVR will announce the IP address of the WAN port
Check WAN Network Mask	120	None	IVR will announce the network mask of the WAN port
Check WAN Gateway	130	None	IVR will announce the gateway of the WAN port
Check MAC Address	140	None	IVR will announce MAC address of the SPA-2100
Check Firmware Version	150	None	IVR will announce the firmware version running on SPA-2100
Check Primary DNS Server IP Address	160	None	IVR will announce the primary DNS server IP address
Check WAN Port Web Server Port	170	None	IVR will announce the WAN port web server port
Check LAN IP Address	210	None	IVR will announce the IP address of the LAN port
Check WAN Internet Connection Type	100	None	IVR will announce the WAN Internet Connection Type
Set WAN Internet Connection Type (see "Wan Setup" -> "Internet Connection Settings")	101	Enter 0 to use DHCP Enter 1 to use Static IP Enter 3 to use PPPoE	Requires Password
Set Static IP address (WAN Port)	111	Enter IP address using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Network Mask	121	Enter network mask using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Gateway	131	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set Primary DNS Server IP Address	161	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	Requires Password.
		Press 0 to select the router/NAT mode.	If the Voice Gateway acts as the router for your network, use the

注意：如果未设置管理员密码或允许用户更改密码，则标记为“需要密码”的项目将不需要密码

。