

# ل ك ش ب ي ئ ا ق ل ت ل ا ض و ا ف ت ل ا ن ي ك م ت F8 ن ي و ك ت ل ا ة د ع ا س م ل ا ة ا د ا ل ا ي ف ي ض ا ر ت ف ا CIMC

## ت ا ي و ت ح م ل ا

[ق م د ق م ل ا](#)

[ق ل ك ش م ل ا](#)

[ل ح ل ا](#)

[ر ا ر ق ل ا](#)

## ق م د ق م ل ا

ي ض ا ر ت ف ا ل ك ش ب ي ئ ا ق ل ت ل ا ض و ا ف ت ل ا ن ي ك م ت ر ا د ص ا ة ج ل ا ع م ة ي ف ي ك د ن ت س م ل ا ا ذ ه ح ض و ي Cisco ن م (CIMC) ق ل م ا ك ت م ل ا ة ر ا د ا ل ا ي ف م ك ح ت ل ا ة د ح و ة ك ب ش ا ض و ا ن ي ب ل ي د ب ت ل ا د ن ع ا ض و ل ا ي ف ا ل ا ي ئ ا ق ل ت ل ا ض و ا ف ت ل ا م ع د م ت ي ا ل F8 CIMC ن ي و ك ت ل ا ة د ع ا س م ل ا ة ا د ا ل ا م ا د خ ت س ا ب ا ل ا ي د و ي د ق ص ص خ م ع ض و ا ل ا ص ص خ م ر ي غ ع ض و ي ا ن م ل ي و ح ت ل ا ن ا ف ي ل ل ا ت ل ا ب و ، ص ص خ م ل ا ا ذ ه ك و ل س ل ا ا ذ ه

## ق ل ك ش م ل ا

ق ك ب ش ل ا ا ض و ا ة ص ا خ و ، CIMC ن ي و ك ت ل ج ا ن م F8 ة ي و ل و ا ي ل ع د م ت ع ت ا م د ن ع ق ل ك ش م ل ا ا ذ ه ر ث و ت ة .

ر ي ث ا ت ل ا / ا ل ا م ع ل ا ة ي و ر :

ن م ل ي د ب ت ل ا د ن ع ي ض ا ر ت ف ا ل ك ش ب ه ن ي ك م ت م ت ي ا ل ا ي ئ ا ق ل ت ل ا ض و ا ف ت ل ا د ا د ع ا ن ا ط ح ا ل ت د ق ق ك ب ش ع ض و ا ل ا (Shared-LOM/Cisco Card/Shared-LOM Ext) ة ص ص خ م ل ا ر ي غ ق ك ب ش ل ا ا ض و ا ص ص خ م .

F8 ن ي و ك ت ل ا ة د ع ا س م ل ا ة ا د ا ل ا م ا د خ ت س ا ب CIMC ت ا د ا د ع ا ث ي د ح ت د ن ع ا ل ا ا ذ ه ر ه ط ي ا ل : ة ط ح ا ل م ت ا د ا د ع ا ل ا ر ي غ ت ل WebUI م ا د خ ت س ا د ن ع ا ل ع ر ث و ي ا ل و ، CIMC .

## ل ح ل ا

م ا د خ ت س ا ب ص ص خ م ل ا ا ض و ل ا ي ل ا ك ر ت ش م ل ا LOM ع ض و ن م ل و ح ت ل ل ا ة م ز ا ل ل ا ت ا و ط خ ل ل ي ل ي ا م ي ف F8 ة د ع ا س م ل ا ة ا د ا ل ا

1. ة ر و ص ل ا ي ف ح ض و م و ه ا م ك ة د ع ا س م ل ا CIMC ن ي و ك ت ة ا د ا ل ا خ د ا ل F8 د ح و م د ا خ ل ا د ي ه م ت ب م ق .

Cisco IMC Configuration Utility Version 2.0 Cisco Systems, Inc.

\*\*\*\*\*

NIC Properties

NIC mode		NIC redundancy	
Dedicated:	<input type="checkbox"/>	None:	<input type="checkbox"/>
Shared LOM:	<input checked="" type="checkbox"/>	Active-standby:	<input type="checkbox"/>
Cisco Card:	<input type="checkbox"/>	Active-active:	<input checked="" type="checkbox"/>
Shared LOM Ext:	<input type="checkbox"/>		

IP (Basic)

IPV4:	<input checked="" type="checkbox"/>	IPV6:	<input type="checkbox"/>
DHCP enabled	<input type="checkbox"/>		
CIMC IP:	172.22.251.72		
Prefix/Subnet:	255.255.252.0		
Gateway:	172.22.248.1		
Pref DNS Server:	0.0.0.0		

VLAN (Advanced)

VLAN enabled:	<input type="checkbox"/>
VLAN ID:	1
Priority:	0

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit  
<F1>Additional settings

يذال CIMC رادصإ ىل ع دمت عي يذلاو ،F1 ىل ع طغضلا كىل ع ني ع تي دق :ةظحالم  
ةروصلال ي ف حضم وه امك ةيفاضإلا نيوكتلا تادادعإ ضرعل هم دختست

Cisco IMC Configuration Utility Version 2.0 Cisco Systems, Inc.

\*\*\*\*\*

Common Properties

Hostname:	<input type="checkbox"/> 240-FCH1612V0W4
Dynamic DNS:	<input checked="" type="checkbox"/>
DDNS Domain:	

FactoryDefaults

Factory Default:	<input type="checkbox"/>
------------------	--------------------------

Default User(Basic)

Default password:	
Reenter password:	

Port Properties

Auto Negotiation:	<input type="checkbox"/>
Speed[1000/100 Mbps]:	100
Duplex mode[half/full]:	full

Port Profiles

Reset:	<input type="checkbox"/>
Name:	

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit  
<F2>PreviousPage

ريغ يئاقلتلا ضوافتلا نأ ىرت نأ كنكمي و كرتشم لال LOM عضوي ف تنأ ،انه :ةظحالم

حلص ريغ دادعإ هنأل، نكمم

ةروصلإ يف حضوم وه امك أطخلل كيطعت اهناف، نيكمتللا ةلواحم دنع

```
Reenter password:
Port Properties
Auto Negotiation:      [ ]
Speed[1000/100 Mbps]: 100
Duplex mode[half/full]: full
Port Profiles
Reset:                  [ ]
Name:

*****
<Up/Down>Selection  <F10>Save  <Space>Enable/Disable  <F5>Refresh  <ESC>Exit
<F2>PreviousPage

Error: Port Properties SET operation is for Dedicated NIC mode only!
```

2. ف1ل ع طغضا، ةقباسللا ةحفصللا لىل ةدوعلل

صصخم عضو لىل CIMC ليوحتل تادادعإللا هذه ددح، كلذ دعب

- صصخم > (NIC) ةكبشللا ةهجاو ةقاطب عضو
- عيش ال > NIC راركت
- يكيتاتسإ نكاس ناووع ةجلاعم لىل ةفاضللاب IPv6 وأ IPv4، VLAN، ةكبش مادختسإ نإ كلحاتم رماً وه DHCP لباقم
- ةروصللا يف حضوم وه امك تادادعإللا ظفحل F10 لىل ع طغضا.

Cisco IMC Configuration Utility Version 2.0 Cisco Systems, Inc.

\*\*\*\*\*

NIC Properties

NIC mode		NIC redundancy	
Dedicated:	<input checked="" type="checkbox"/>	None:	<input checked="" type="checkbox"/>
Shared LOM:	<input type="checkbox"/>	Active-standby:	<input type="checkbox"/>
Cisco Card:	<input type="checkbox"/>	Active-active:	<input type="checkbox"/>
Shared LOM Ext:	<input type="checkbox"/>		

IP (Basic)

IPV4:	<input checked="" type="checkbox"/>	IPV6:	<input type="checkbox"/>
DHCP enabled	<input type="checkbox"/>		
CIMC IP:	172.22.251.72		
Prefix/Subnet:	255.255.252.0		
Gateway:	172.22.248.1		
Pref DNS Server:	0.0.0.0		

VLAN (Advanced)

VLAN enabled:	<input type="checkbox"/>
VLAN ID:	1
Priority:	0

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit  
<F1>Additional settings

Hit the Refresh key in 45 seconds to get the latest network settings.

وه امك ةكبشلا تادادع! شي دحتل F5 ىلع طغضا م ث ، ةلماك ةيئاث 45 ةدمل كراظتنا نم دكأت .  
ةروصلال يف حضوم .

Cisco IMC Configuration Utility Version 2.0 Cisco Systems, Inc.

\*\*\*\*\*

NIC Properties

NIC mode		NIC redundancy	
Dedicated:	<input checked="" type="checkbox"/>	None:	<input checked="" type="checkbox"/>
Shared LOM:	<input type="checkbox"/>	Active-standby:	<input type="checkbox"/>
Cisco Card:	<input type="checkbox"/>	Active-active:	<input type="checkbox"/>
Shared LOM Ext:	<input type="checkbox"/>		

IP (Basic)

IPv4:	<input checked="" type="checkbox"/>	IPv6:	<input type="checkbox"/>
DHCP enabled	<input type="checkbox"/>		
CIMC IP:	172.22.251.72		
Prefix/Subnet:	255.255.252.0		
Gateway:	172.22.248.1		
Pref DNS Server:	0.0.0.0		

VLAN (Advanced)

VLAN enabled:	<input type="checkbox"/>
VLAN ID:	1
Priority:	0

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit  
<F1>Additional settings

Network settings configured

وه امك يئاقللتلا ضوافتلا عبرم نآلا ضرعي وهو. ةيفاضإلا تادادعإلا ضرعل F1 لىع طغضا ددحم.

CIMC نيوكتل ةدعاسملا ةادألا نم مدقألا رادصإلا حضوت يتلا تاطقللا ضع ب يلي امي ف 1.5(4g) رادصإل تباثلا جم انربلاب ةطبترملا

ةروصلال ي ف حضوم وه امك كرتشملا LOM عضو نوكي

CIMC Configuration Utility Version 1.7 Cisco Systems, Inc.

\*\*\*\*\*

NIC Properties

NIC mode		NIC redundancy	
Dedicated:	<input type="checkbox"/>	None:	<input type="checkbox"/>
Shared LOM:	<input checked="" type="checkbox"/>	Active-standby:	<input type="checkbox"/>
Cisco Card:	<input type="checkbox"/>	Active-active:	<input checked="" type="checkbox"/>
Shared LOM Ext:	<input type="checkbox"/>		

IPV4 (Basic)

DHCP enabled:	<input type="checkbox"/>	Factory Defaults	
CIMC IP:	10.29.131.127	CIMC Factory Default:	<input type="checkbox"/>
Subnetmask:	255.255.255.0	Default User (Basic)	
Gateway:	10.29.131.1	Default password:	
		Reenter password:	

VLAN (Advanced)

VLAN enabled:	<input type="checkbox"/>	Port Profile	
VLAN ID:	1	Reset:	<input type="checkbox"/>
Priority:	0	Name:	

Port Properties

Auto Negotiation:	<input type="checkbox"/>
Speed[1000/100 Mbps]:	100
Duplex mode[half/full]:	full

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit

Network settings configured

ةروصلالاي حضورم وه امك ص صخ م ل ا عض و ل ا .

CIMC Configuration Utility Version 1.7 Cisco Systems, Inc.

\*\*\*\*\*

NIC Properties

NIC mode		NIC redundancy	
Dedicated:	<input checked="" type="checkbox"/>	None:	<input checked="" type="checkbox"/>
Shared LOM:	<input type="checkbox"/>	Active-standby:	<input type="checkbox"/>
Cisco Card:	<input type="checkbox"/>	Active-active:	<input type="checkbox"/>
Shared LOM Ext:	<input type="checkbox"/>		

IPV4 (Basic)

DHCP enabled:	<input type="checkbox"/>	Factory Defaults	
CIMC IP:	10.29.131.127	CIMC Factory Default:	<input type="checkbox"/>
Subnetmask:	255.255.255.0	Default User (Basic)	
Gateway:	10.29.131.1	Default password:	
		Reenter password:	

VLAN (Advanced)

VLAN enabled:	<input type="checkbox"/>	Port Profile	
VLAN ID:	1	Reset:	<input type="checkbox"/>
Priority:	0	Name:	

Port Properties

Auto Negotiation:	<input checked="" type="checkbox"/>
Speed[1000/100 Mbps]:	1000
Duplex mode[half/full]:	full

\*\*\*\*\*

<Up/Down>Selection <F10>Save <Space>Enable/Disable <F5>Refresh <ESC>Exit

Network settings configured

عقاولا يف ادحيم يئاقلتلا ضوافتلا عبرم نأ ىرت نأ كنكمي :ةظحالم

## رارقلا

املاط هسفن دادعإلا اذه نكمي .صصخملا عضولا يف ال يئاقلتلا ضوافتلا دادعإ رفوتي ال  
حل اص صصخم نيوكت نييعت مت

ةمچرتل هذه ل و ح

ةلأل تاي نقتل ن م ة و مچ م ادخت ساب دن تسم ل ا ذه Cisco ت مچرت  
م ل ا ل ا ا ن ا ع مچ ي ف ن م دخت س م ل ل م عد ي و ت م م م دقت ل ة يرش ب ل و  
امك ة ق ي ق د ن و ك ت ن ل ة ل ا ة مچرت ل ض ف ا ن ا ة ظ ح ال م ي ج ر ي . ة ص ا خ ل ا م ه ت غ ل ب  
Cisco ي ل خ ت . ف ر ت م م مچرت م ا م د ق ي ي ت ل ا ة ي ف ا ر ت ح ال ا ة مچرت ل ا م ل ا ح ل ا و ه  
ي ل ا م ا د ا د ع و ج ر ل ا ب ي ص و ت و ت ا مچرت ل ا هذه ة ق د ن ع ا ه ت ي ل و ئ س م Cisco  
Systems (ر ف و ت م ط ب ا ر ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا دن ت س م ل ا