

RV130 و RV130W ىلع ىسأسأل VPN دادعإ

فدهل

تاكبش عيسوتل ةلېسوك (VPN) ةيضا رتفا ةصاخ ةكبش تاكرشلل مدختست ام ابلاغ طقف ةكرشلل يفظوم لبق نم مادختسالل ةممصم عقاوم يهو، تاكرشلل ةصاخلل تنرتنلإ تاكرشلل ةئيب يف. ةماع ةكبشل ةيساسا ةينب نمض اهؤاشنإ مت ةصاخ ةكبش يه VPN، يفارغجلال اصلال عيسوت (VPN) ةيرهاظلا ةصاخلل تاكبشلل نكمي، ةيچذومنللا ةريغصلال نيسحتو، (WAN) ةيديلقتللا ةعسالل تاكبشلل لباقم ليغشتللا فيلكت ليلقتو نيفظوملل لمع ريس يف ةيحاتنللا.

ىلإ ةرابعلال نم VPN قفن دادعإ ةيناكلما ةيساسأل VPN ةكبش دادعإ ةحفص كل حيتت نيمدختستسملل VPN قفن حمسي امك. ىرخألل عقوملل ةرابع ةزهجأ مادختساب ةلوهسب ةباوبلل كب صاخلل هجوملل (LAN) ةيلحمللا ةقطنملا ةكبش ةكبش ىلإ لوصولاب نيديعبلل VPN ةكبش ليمع جم انرب مادختساب.

لوكوتورب معددي ةيچراخ ةهجاتنل نم VPN جم انرب RV130 و RV130W زارطلال معددي: **ةظحالم** جت نمللا ةرادا ليلد ىلإ عجرا، تامولعملال نم دي زمل IPSec.

ةيساسأل (VPN) ةيرهاظلا ةصاخلل ةكبشلل نيوكت ةيفيك حرش وه دننستسمللا اذه نم فدهللا RV130 ةزهجأ ىلع.

تباثلل جم انربلل رادصل | قي بطللل ةلباقللا ةزهجأ

- [\(ثدخالل لي زنت\) RV130 | v 1.0.3.28](#) زارطلال
- [\(ثدخالل لي زنت\) RV130W | v 1.0.3.28](#) زارطلال

ةيضا رتفال VPN تادادعإ ضرع

ىلإ عقوم نم VPN > IPSec VPN رايتخال هجوملل نيوكتل ةدعاسملا ةادألل مدختسأ 1. ةوطخللا: **ةيساسأل VPN دادعإ** ةحفص رهظت. **ةيساسأل VPN دادعإ** > عقوم

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

ةطساوب ةطوبضملا ةيضارتفالا ميقلا ىرتل ةيضارتفالا تادادعإلا ضرع رزرقنا 2. ةوطخلا
ي.ساسألا VPN

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Save

Cancel

ةيضا رتفال ا تاداعإل ا ةي س اسأل ا VPN دادعإ ةحفص ضرعت

Basic VPN Setup

Basic VPN Setup Default Values for IKE

Exchange Mode:	Main
Local WAN (Internet) ID:	Local WAN (Internet) IP Address
Remote WAN (Internet) ID:	Remote WAN (Internet) IP Address
Encryption Algorithm:	AES-128
Authentication Algorithm:	MD5
Authentication Method:	Pre-Shared Key
Diffie-Hellman (DH) Group:	Group2 (1024 bit)
SA-Lifetime:	8 Hours

Basic VPN Setup Default Values for VPN

Encryption Algorithm:	AES-128
Integrity Algorithm:	MD5
SA-Lifetime:	1 Hours
PFS Key Group:	Group 2(1024 bit)

Back

ي.س.اسأل VPN دادع| ةذفان ىلإ ةدوعلل فلخلل رز قوف رقنا. 3 ةوطخلل

Basic VPN Setup

Basic VPN Setup Default Values for IKE

Exchange Mode:	Main
Local WAN (Internet) ID:	Local WAN (Internet) IP Address
Remote WAN (Internet) ID:	Remote WAN (Internet) IP Address
Encryption Algorithm:	AES-128
Authentication Algorithm:	MD5
Authentication Method:	Pre-Shared Key
Diffie-Hellman (DH) Group:	Group2 (1024 bit)
SA-Lifetime:	8 Hours

Basic VPN Setup Default Values for VPN

Encryption Algorithm:	AES-128
Integrity Algorithm:	MD5
SA-Lifetime:	1 Hours
PFS Key Group:	Group 2(1024 bit)

Back

ي.س.اسأل VPN دادع|

سجل اء قوم نم VPN > IPSec VPN راى ء ءال هءوم لاء نى وءءل ءءءاس ملاء ءاءالاء مءءءءسأ. 1. ءو ءءال
ءى ساسال VPN ءاءءل ءءفص رهءء. ساسال VPN ءاءءل > ء قوم

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#) [Cancel](#)

ضارءال مءسال اءه مءءءءسأ مءس. ءىءءل لاء صءالاء مءسال لءء ف لاء صءاء مءسال لءء. 2. ءو ءءال
VPN ءءبش لىءءشء لىءء رىءاءء هل سىل وءءءال

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

cisco_sb

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

IP Address ▾

Remote WAN (Internet) IP Address:

(Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address:

(Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask:

(Hint: 255.255.255.0)

Local LAN (Local Network) IP Address:

(Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask:

(Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

ةكبش لي مع مزلي. اقبس م كرتشم حاتفم ل قح ي ف اقبس م كرتشم حاتفم لخدا 3. ةوطخل VPN. ةكبش لاصتا عاشنل حاتفم ل اذه ةباوبل و VPN.

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

عنوان FQDN أو IP ناووع رتخأ، ةديعب ل ةياهن ل ةطقن ل ةلدسنم ل ةمئاق ل ي ف 4 ةوطخ ل لاصتا عاشن ل ةديعب ل ةباوب ل هم دختست ي ذل ناووع ل

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

يلا تال وحننلا ىلع ةحاتملا تاراخيخلا دي دحت متي:

- مدختسي زاهج لك فرعت تارتفب ةلصفنم ماقرالآ نم ةديرف ةلسلس - IP ناونع ةكبش ربع لاصتالل تنرتنإلا لوكوتورب.
- وأ ددحم رتويبمك وأ تنرتنإلا لمالكلا لاجملا مسا - (لمالكلا لهؤملا لاجملا مسا) FQDN، لاثملا لىبس ىلع. لاجملا مسا او فيضملا مسا: نيأج نم FQDN نوكتي. ني عم فيضم وه فيضملا مسا *mymail.companyname.org* وه يضارتفا ديرب مداخل FQDN نوكتي دق *companyname.org* لاجملا لخاد دوجوم فيضملا او *myMail*.

ناونع لققح في 4، ةوطخلال في كب صاخلا دي دحتلا ىلع ءانب، FQDN وأ IP ناونع لخدا 5. ةوطخلال (تنرتنإلا) ةديعبلا WAN تاكبشلا IP.

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

IP ناوع يلقح يف ةديعبال LAN ةكبشلة يعرفال ةكبشلال انقو IP ناوع لخدأ 6. ةوطخال (ةلحمل ةكبشلال) ةديعبال LAN ةكبشو (ةلحمل ةكبشلال) ةديعبال LAN ةكبشلال ةعرفال.

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

عائق يلقح في إي لحملة كبل شلل إي عرف الة كبل شلل عائق و IP ناونع لخدأ 7. ووطخل
ة. إي عرف الة (ة لحملة كبل شلل) ة لحملة LAN كبل ش و IP (ة لحملة كبل شلل) ة لحملة كبل شلل

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

[Save](#)

[Cancel](#)

تادادعإل ظفحل ظفح يلع رقنا 8. ووطخل

Basic VPN Setup

About Basic VPN Setup

The basic VPN setup sets most parameters to defaults as proposed by the VPN Consortium (VPNC), and assumes a Pre-shared Key, which greatly simplifies setup. After creating the policies through the Basic VPN Setup, you can always update the parameters through the Policies menu

[View Default Settings](#)

Connection Name and Remote IP Type

New Connection Name:

Pre-Shared Key:

Endpoint Information

Remote Endpoint:

Remote WAN (Internet) IP Address: (Hint: 1.2.3.4 or abc.com)

Secure Connection Remote Accessibility

Remote LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Remote LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

Local LAN (Local Network) IP Address: (Hint: 1.2.3.4)

Local LAN (Local Network) Subnet Mask: (Hint: 255.255.255.0)

عرض فيديو متعلق بهذه المقالة...

[انقر هنا لعرض المحادثات التقنية الأخرى من Cisco](#)

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل