

Configure an Intel Wireless Network Card to Connect to a Management Frame Protection (MFP)-enabled Network

Objective

Management Frame Protection (MFP) is a wireless feature that increases the security of the management frames. Its wireless standard is IEEE 802.11w-2009 or Protected Management Frames (PMF) which aims to provide data confidentiality of the management frames and protect wireless connectivity. This feature only works if both the access point and the client have MFP enabled.

There are certain restrictions for some wireless clients to communicate with MFP-enabled infrastructure devices. MFP adds a long set of information elements to each probe request or SSID beacon. Some wireless clients such as Personal Digital Assistants (PDAs), smartphones, barcode scanners, and so forth have limited memory and CPU so you are not able to process these requests or beacons. As a result, you fail to see the Service Set Identifier (SSID) entirely, or you are not able to associate with these infrastructure devices due to mismatch of SSID capabilities. This issue is not specific to MFP. This also occurs with any SSID that has multiple information elements (IEs). It is always recommended to test MFP-enabled SSIDs on the environment with all your available client types before you deploy it in real time.

This article provides instructions on how to configure the Intel wireless network card on your Windows operating system to connect to your MFP-enabled access point.

Note: Your wireless client or operating system may or may not support this feature. Check with your wireless device or operating system manufacturer for more details. In this scenario, the wireless adapter used is Intel® Dual Band Wireless-N 7265 with version 17.13.0.9 on Windows 7 operating system.

Applicable Devices

- WAP300 Series – WAP361, WAP371
- WAP500 Series – WAP561, WAP571, WAP571E


Software Version

- 1.2.1.3 – WAP371, WAP561
- 1.0.0.17 – WAP571, WAP571E
- 1.0.1.6 – WAP361


Configure an Intel Wireless Network Card to Connect to an MFP-enabled Network

Important: Before proceeding with the configuration steps, make sure your wireless network card driver and operating system are updated.

Step 1. On your Windows-based wireless computer, go to **Start > Control Panel > Network and Internet > Network and Sharing Center > Manage wireless networks**.



Step 2. In the Manage Wireless Networks screen, click **Add**.



Step 3. Choose **Manually create a network profile**.

How do you want to add a network?



Manually create a network profile

This creates a new network profile or locates an existing network and saves a profile for the network on your computer. You need to know the network name (SSID) and security key (if applicable).



Create an ad hoc network

This creates a temporary network for sharing files or an Internet connection

Cancel

Step 4. Enter your SSID in the *Network name* field.

Enter information for the wireless network you want to add

Network name:

WAP2.4ghz

Security type:

[Choose an option]

Encryption type:

Security Key:

Hide characters

Start this connection automatically

Connect even if the network is not broadcasting

Warning: If you select this option, your computer's privacy might be at risk.

Next

Cancel

Step 5. Choose a security type from the Security type drop-down list.

Note: In this example, WPA2-Personal is chosen.

Manually connect to a wireless network

Enter information for the wireless network you want to add

Network name:

Security type:

Encryption type:

Security Key:

Start this connection at 802.1x

Connect even if the network is not broadcasting

Warning: If you select this option, your computer's privacy might be at risk.

Hide characters

Next Cancel

Step 6. (Optional) Choose an encryption type from the Encryption type drop-down list. The default value is AES.

Step 7. Enter your wireless network password in the *Security Key* field.

Enter information for the wireless network you want to add

Network name:

Security type:

Encryption type:

Security Key: Hide characters

Start this connection automatically

Connect even if the network is not broadcasting

Warning: If you select this option, your computer's privacy might be at risk.

Step 8. Click **Next**.


Step 9. Once you have successfully added your network, click **Close**.

Successfully added WAP2.4ghz


→ Change connection settings
Open the connection properties so that I can change the settings.

Close

Step 10. Right-click on the created network profile then click **Properties**.




Step 11. Click on the Security tab.




Step 12. Choose the 802.11w security type from the Security type drop-down list.

Note: In this example, Intel – WPA2/PSK – 802.11w is chosen.




Step 13. (Optional) Choose an encryption type from the Encryption type drop-down list. The default value is AES – CCMP.


Step 14. Click **Configure**.



Step 15. Once the Security window appears, enter the wireless network password then click **OK**.



Step 16. Click **OK**.



Step 17. Click on the wireless icon on your computer. It should show that you are already connected to the SSID that you have configured.



You should now have configured your Intel wireless network card to connect to your MFP-enabled access point.