



Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release 7.9.1

[Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release 7.9.1](#) 2

[What's New in Cisco IOS XR Release 7.9.1](#) 2

[Caveats](#) 10

[Supported Packages and System Requirements](#) 10

[Supported Hardware](#) 37

[Important Notes](#) 47

[Related Documentation](#) 48

Revised: February 15, 2024

Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release

IOS XR 64-bit on Cisco ASR 9000 Series is the next generation operating system running in a virtualized environment with an underlying 64-bit Linux kernel. Cisco IOS XR operating system delivers greater agility, automation, and simplicity while reducing the cost of operating the networks.

References

For more information about Cisco ASR 9000 Series, see:

- [Cisco ASR 9000 Data Sheet listing page](#)
- [Migration Guide for Cisco ASR 9000 Series Routers](#)

What's New in Cisco IOS XR Release 7.9.1

For more details on the Cisco IOS XR release model and associated support, see [Guidelines for Cisco IOS XR Software](#).

Software Features Introduced and Enhanced

To learn about features introduced in other Cisco IOS XR releases, select the release from the [Documentation Landing Page](#).

Feature	Description
Broadband Network Gateway	
Line Card based IPoE Subscriber Sessions on Cisco ASR 9000 5th Generation High Density Ethernet Line Cards	<p>We now support Line card based Internet over Ethernet (IPoE) subscriber sessions on the following :</p> <ul style="list-style-type: none">• Cisco ASR 9902 Router• Cisco ASR 9903 Router• Cisco ASR 9000 Series Route Switch Processor 5 (RSP5) <p>Also on the following Cisco ASR 9000 5th Generation High Density Ethernet line cards:</p> <ul style="list-style-type: none">• A99-32X100GE-X-SE• A9K-20HG-FLEX-SE• A9K-8HG-FLEX-SE

Feature	Description
Subscriber Redundancy Group on Cisco ASR 9903 Router, ASR 9902 Router, and Cisco ASR 9006 Route Switch Processor	<p>You can now configure subscriber redundancy group (SRG) for the IPoE subscribers over bundle and PWHE access interfaces on the following:</p> <ul style="list-style-type: none"> • Cisco ASR 9902 Router • Cisco ASR 9903 Router • Cisco ASR 9000 Series Route Switch Processor 5 (RSP5) <p>Also on the following Cisco ASR 9000 5th Generation High Density Ethernet line cards:</p> <ul style="list-style-type: none"> • A99-32X100GE-X-SE • A9K-20HG-FLEX-SE • A9K-8HG-FLEX-SE <p>SRG offers the advantage of enabling planned switch over or failover for all subscriber groups in case of a failure, proving especially advantageous for subscribers requiring high availability and geo-redundancy as part of their service level agreement (SLA).</p>
Interface and Hardware Component	
Exclude BNG interface statistics from show interface command	<p>The show interface command is modified to exclude the BNG interface statistics from the command output reduce the response time.</p> <p>Use the following keywords to exclude the BNG interface statistics.</p> <ul style="list-style-type: none"> • sparse • Non-dynamic
Support for 3x100G Muxponder Mode on A99-10X400GE-X-SE/A99-10X400GE-X-TR Line Cards	<p>QDD-400G-ZRP-S optical module operating in A99-10X400GE-X-SE/A99-10X400GE-X-TR Line Cards now supports 3x100G Muxponder Mode.</p>
oFEC Traffic Configuration for QDD-400G-ZRP-S	<p>QDD-400G-ZRP-S optical module can now support the following oFEC traffic configurations:</p> <ul style="list-style-type: none"> • 400G-TXP-1x1 DAC-16 QAM • 3x100G-MXP-1x1 DAC-8 QAM <p>This increases the interoperability of the QDD-400G-ZRP-S optical module across network components supporting these formats.</p>

Feature	Description
Support for DP04QSDD-HE0 Optical Module	<p>This release introduces support for the Cisco 400G QSFP-DD High-Power (Bright) Optical Module, Ethernet Variant.</p> <p>The Cisco 400G QSFP-DD High-Power (Bright) Optical module is an enhanced version of the currently available QSFP-DD ZR+ Optical Module, leveraging the same operational modes but providing as a major enhancement the increase of the Tx Optical Power up to +1dBm.</p> <p>DP04QSDD-HE0 optical module is supported in the following hardware:</p> <ul style="list-style-type: none"> • A9K-20HG-FLEX-SE/TR/FC • A9K-8HG-FLEX-SE/TR/FC
L2VPN and Ethernet Services	
Call Admission Control for L2VPN P2P Services over Circuit-Style SR-TE Policies	<p>This feature allows you to configure guaranteed bandwidth for Layer 2 P2P services steered over Circuit-Style SR-TE policies.</p> <p>This ensures that a Circuit-Style SR-TE policy has sufficient bandwidth to accommodate a Layer 2 P2P service, while also preventing a L2 P2P service from being steered over a Circuit-Style SR-TE policy when there is insufficient available bandwidth.</p>
Routing	
Enabling Flexible -Algorithm Redistribution in IP Networks	<p>This feature allows you to specify the Flex-Algorithm number during route redistribution via a route policy. You can also select or filter the prefix-matching algorithm number during route redistribution so that only the Flex-Algorithms that you configured for specific addresses are redistributed.</p> <p>This feature introduces the set algorithm command.</p>
Limiting LSA numbers in a OSPF Link-State Database	<p>The nonself-generated link-state advertisements (LSAs) for a given Open Shortest Path First (OSPF) process is limited to 500000. This protection mechanism prevents routers from receiving many LSAs, preventing CPU failure and memory shortages, and is enabled by default from this release onwards. If you have over 500000 LSAs in your network, configure the max-lsa command with the expected LSA scale before upgrading to this release or later.</p> <p>This feature modifies the following commands:</p> <ul style="list-style-type: none"> • show ospf to display the maximum number of redistributed prefixes. • show ospf database database-summary detail to display the number of LSA counts per router. • show ospf database database-summary adv-router router ID to display the router information and the LSAs received from a particular router.
Limiting the Maximum Redistributed Type-3 LSA Prefixes in OSPF	<p>By default, the maximum redistributed Type-3 LSA prefixes for a given OSPF process is now limited to 100000. This mechanism prevents OSPF from redistributing a large number of prefixes as Type-3 LSAs and therefore preventing high CPU utilization and memory shortages.</p> <p>Once the number of redistributed prefixes is reached or exceeds the threshold value, the system log message is generated, and no more prefixes are redistributed.</p>
Segment Routing	

Feature	Description
IS-IS: Flexible Algorithm Reverse Affinity	<p>This feature enhances the IS-IS Flexible Algorithm link admin group (affinity) constraint to include link colors on links in the reverse direction toward the calculating router.</p> <p>The ability to apply affinity constraints in the reverse direction provides additional control for IS-IS Flexible Algorithm path computation.</p>
Multicast: SR-PCE High Availability Support for Static Tree-SID	<p>This feature provides High Availability (HA) capability for static Tree-SID by using more than one Segment Routing Path Computation Elements (SR-PCE) in a multicast network.</p> <p>The feature helps in computing reliable paths for large and complex networks.</p>
SR-PCE: Stateful North-Bound API for Policies Containing IPv4 Unnumbered Interfaces	<p>The SR-PCE provides a north-bound HTTP-based API to allow communication between SR-PCE and external clients and applications. The Cisco Crosswork Optimization Engine is one of the applications that leverage the SR-PCE.</p> <p>This release adds support for the following:</p> <ul style="list-style-type: none"> • Reporting, provisioning, and updating of policies with IPv4 unnumbered interfaces in segment lists • Computing policy paths with IPv4 unnumbered interfaces in segment lists • Displaying IPv4 unnumbered hops in initiated tunnel database on PCE <p>For more information, refer to the Cisco Crosswork Optimization Engine User Guides.</p>
SR-TE Automated Steering Without Service Label	<p>This feature allows traffic to a BGP service route to be steered over an SR-TE policy using the AS principles, and without imposing the service route's prefix label.</p> <p>This feature enables use-cases such as centralized BGP EPE for 6PE in an SR-MPLS network.</p> <p>This feature introduces the following command:</p> <ul style="list-style-type: none"> • bgp prefix-label ignore
SR-TE Explicit Segment Lists with Mix of IPv4 and IPv6 Segments	<p>Explicit segment list can be configured to include IPv6 segments, for example IPv6 adjacency SIDs or IPv6 EPE SIDs.</p> <p>This feature enables use-cases such as Centralized BGP EPE for 6PE in an SR-MPLS Network.</p>
SRv6 Services: Services with Remote SIDs from W-LIB	<p>This feature enables an SRv6 headend node to receive and install remote SIDs with Wide (32-bit) functions (Remote W-LIB).</p> <p>There is no new CLI to enable this capability at the ingress PE.</p>
Support for L3 EVPN/SRv6 and L3 EVPN/MPLS Interworking Gateway	<p>This feature adds support for L3 EVPN interworking between SRv6 and MPLS.</p> <p>L3 EVPN/SRv6 and L3 EVPN/MPLS Interworking Gateway enables you to extend L3 services between MPLS and SRv6 domains by providing service continuity on the control plane and data plane.</p> <p>This feature allows for SRv6 L3 EVPN domains to interwork with existing MPLS L3 EVPN domains. The feature also allows a way to migrate from MPLS L3 EVPN to SRv6 L3 EVPN.</p>

Feature	Description
Support for L3 EVPN/SRv6 and L3VPN/MPLS Interworking Gateway	<p>This feature adds support for EVPN L3VPN interworking between SRv6 and MPLS.</p> <p>L3 EVPN/SRv6 and L3VPN/MPLS Interworking Gateway enables you to extend L3 services between MPLS and SRv6 domains by providing service continuity on the control plane and data plane.</p> <p>This feature allows for SRv6 L3 EVPN domains to interwork with existing MPLS L3VPN domains. The feature also allows a way to migrate from MPLS L3VPN to SRv6 L3 EVPN.</p>
Support for SRv6 Services: L3 EVPN	<p>This feature adds support for carrying L3VPN routes in L2VPN EVPN (AFI 25 SAFI 70) address-family RT5 instead of VPNv4 unicast and/or VPNv6 unicast address-family across SRv6 core (EVPN over SRv6 underlay).</p>
System Management	
1GbE Port Mode on SFP+ and SFP28 Ports	<p>It is now possible to use the 10GbE SFP+ and SFP28 ports to transmit 1GbE traffic on the routers or line cards. The number of ports on which you can enable 1GbE port mode has been increased from the previous releases.</p> <p>The details of the number of ports on which you can configure 1GbE port mode on the Cisco ASR 9000 Series routers, port expansion card, and line cards is as follows:</p> <ul style="list-style-type: none"> • Cisco ASR 9903 - 20 SFP+ ports • Cisco ASR 9902 - 24 SFP+ and 16 SFP28 ports • A9903-8HG-PEC - 40 SFP+ ports • A9K-4HG-FLEX-SE/TR - 24 SFP+ and 16 SFP28 ports • A99-4HG-FLEX-SE/TR - 24 SFP+ and 16 SFP28 ports • A9K-4HG-FLEX-FC - 24 SFP+ and 16 SFP28 ports • A99-4HG-FLEX-FC - 24 SFP+ and 16 SFP28 ports <p>Use the hw-module location breakout and hw-module location slice config mode commands to enable 1GbE port mode configuration.</p>
FQDN for NTP Server on Non-default VRF	<p>You can now specify a Fully Qualified Domain Name (FQDN) as the hostname for NTP server configuration over nondefault VRFs.</p> <p>FQDNs are easy to remember compared to numeric IP addresses. Service migration from one host to another can cause a change in IP address leading to outages.</p> <p>Prior releases allowed FQDN handling in only default VRFs.</p>
Optional RPM for Software Innovation Access Out-of-Compliance	<p>Now, you can do a major upgrade even when your SIA is Out-of-Compliance (OOC) by using the <i>license-util</i> optional rpm.</p> <p>Earlier, when your SIA is OOC, you weren't able to major upgrades. As a workaround, you were given a SMU, which disabled the SIA check.</p>

Feature	Description
New Cisco-NTP-MIB Traps to Monitor NTP server and Improve Timing Accuracy	<p>CiscoNtpMIB allows you to monitor NTP on the server and client using SNMP MIB. Support for new traps is added in this release that will help monitor the NTP server and improvise on timing accuracy. These traps act as synchronization source. These traps also display the current status of the NTP server, the stratum of the local clock, maximum error in seconds and the delay in round-trip in seconds. Use MIB Navigator to know more about the newly added traps . The following is the list of newly added traps:</p> <ul style="list-style-type: none"> • cntpSysPeer • cntpSysSrvStatus • cntpSysStratum • cntpSysRootDelay • cntpSysRootDispersion • cntpPeers
Onboard Failure Logs for show reboot history command	This feature now supports Onboard Failure logs (OBFL) when you use the show reboot history command. The logs are visible in the show output when you use this command.
General Administration	
Auto-Save with Secure File-Transfer and Additional Configurable Parameters	<p>Apart from automatically backing up the running configuration after every commit, you can also do the following with Auto-Save:</p> <ul style="list-style-type: none"> • Save running configurations to remote systems using Secure Copy Protocol (SCP) and Secure File Transfer Protocol (SFTP). • Configure wait-time between two subsequent auto-saves. • Append time-stamp to the file name of the saved configuration. • Save the encrypted password. • Specify the maximum number of files that you can auto-save. <p>The feature introduces these changes:</p> <p>CLI: Modified the configuration commit auto-save command</p> <p>Yang Data Model:</p> <ul style="list-style-type: none"> • New XPath for Cisco-IOS-XR-config-autosave-cfg • New XPath for Cisco-IOS-XR-um-config-commit-cfg
Secure File Transfer	<p>Now, you can securely transfer router files to an archive server. It's made possible because the copy command now supports SFTP (Secure File Transfer Protocol) and SCP (Secure Copy Protocol using the underlying SSH protocol implementation). Secure transfer of files from the router maintains the integrity, confidentiality, and availability of network configurations.</p> <p>This feature modifies the copy command.</p>
Programmability	

Feature	Description
Securely retrieve dynamic NACM with LDAP over TLS authentication	You can now securely retrieve the NETCONF Access Control Model (NACM) policies or rules on-demand from a remote Lightweight Directory Access Protocol (LDAP) server to validate each NETCONF operation using Transport Layer Security (TLS) authentication. Before this release, the policies or rules were not encrypted and posed security vulnerabilities. With TLS authentication, the communication between the router and the LDAP server is encrypted for security.
IP Addresses and Services	
Limit Address Resolution Protocol (ARP) Cache Entries per Interface	In this feature, you can configure the maximum limit for the number of entries of dynamic mapping between IP addresses and media addresses by ARP per interface. Limiting the number of entries provides overflow protections in ARP cache and protects the routers from DOS attacks by preventing memory overuse by cache entries. This feature introduces the arp cache-limit command.
System Security	
Securely retrieve NACM policies using LDAP over TLS connection	You can now securely retrieve the NETCONF Access Control Model (NACM) policies or rules from a remote Lightweight Directory Access Protocol (LDAP) server using Transport Layer Security (TLS) authentication. With TLS authentication, the communication between the router and the LDAP server is encrypted for security. Before this release, the communication between the LDAP server and the router was not secured.

YANG Data Models Introduced and Enhanced

This release introduces or enhances the following data models. For detailed information about the supported and unsupported sensor paths of all the data models, see the [Github](#) repository. To get a comprehensive list of the data models supported in a release, navigate to the Available-Content.md file for the release in the Github repository. The unsupported sensor paths are documented as deviations. For example, openconfig-acl.yang provides details about the supported sensor paths, whereas cisco-xr-openconfig-acl-deviations.yang provides the unsupported sensor paths for openconfig-acl.yang on Cisco IOS XR routers.

You can also view the data model definitions using the [YANG Data Models Navigator](#) tool. This GUI-based and easy-to-use tool helps you explore the nuances of the data model and view the dependencies between various containers in the model. You can view the list of models supported across Cisco IOS XR releases and platforms, locate a specific model, view the containers and their respective lists, leaves, and leaf lists presented visually in a tree structure.

To get started with using data models, see the *Programmability Configuration Guide for ASR 9000 Series Routers*.

Feature	Description
Programmability	
openconfig-isis.yang Version 1.0.0	The OpenConfig data model is revised from version 0.6.0 to 1.0.0 to simplify the authentication keychain nodes. With this feature, you can configure the authentication type to limit the establishment of adjacencies and the exchange of LSPs. You can also retrieve the operational state of the authentication nodes.

Feature	Description
openconfig-network-instance.yang	With this release, the OpenConfig data model is enhanced to view the number of routes that are routed through a specific neighbour for each peer and Subsequent Address Family Identifiers (SAFI) installed counter. The counter reflects the current state of Border Gateway Protocol (BGP) and Routing Information Base (RIB), and can be monitored to check the presence of stale routes, missing routes, and the current installed state of the BGP routes in RIB. The model supports a single instance of BGP with default VRF, and address family (IPv4, IPv6).
openconfig-network-instance.yang Version 0.2.3	In this release, the installed counter in the OpenConfig data model is enhanced to view the number of routes that are installed in Routing Information Base (RIB) from a specific neighbor per Address Family Identifiers (AFI) or Subsequent Address Family Identifiers (SAFI). The model supports a single instance of BGP with default VRF, and IPv4/IPv6 address family. Cross AFI where an IPv4 route learnt from an IPv6 neighbor, and vice versa, is not supported. You can stream Event-driven telemetry (EDT) and Model-driven telemetry (MDT) data.
Cisco-IOS-XR-config-autosave-cfg	This Cisco native yang data model enables you to automatically backup the running configuration files after every commit is made.
Cisco-IOS-XR-um-config-commit-cfg	This unified data model enables you to automatically backup the running configuration of the router after every commit is made.

Hardware Introduced

Cisco IOS XR Release 7.9.1 introduces the following hardware support:

Hardware Feature	Description
Optics	Note: Optics support varies across devices (routers, line cards, RPs, and so on). To know if an optics is compatible with a specific Cisco device, refer to the Transceiver Module Group (TMG) Compatibility Matrix . This release introduces the following optics: <ul style="list-style-type: none"> • Cisco 400GBASE Quad Small Form-Factor Pluggable Double Density (QSFP-DD) <ul style="list-style-type: none"> • DP04QSDD-HE0

Behavior Changes

- Prior to Cisco IOS XR release 7.2.1, a segment of an explicit segment list can be configured as an IPv4 address (representing a Node or a Link) using the **index indexaddress ipv4 address** command.

Starting with Cisco IOS XR release 7.2.1, an IPv4-based segment (representing a Node or a Link) can also be configured with the new **index index mpls adjacencyaddress** command. The configuration is stored in NVRAM in the same CLI format used to create it. There is no conversion from the old CLI to the new CLI.

Starting with Cisco IOS XR release 7.9.1, the old CLI has been deprecated. Old configurations stored in NVRAM will be rejected at boot-up.

As a result, explicit segment lists with IPv4-based segments using the old CLI must be re-configured using the new CLI.

There are no CLI changes for segments configured as MPLS labels using the **index index mpls label label** command.

- You must configure using the new CLI if you are using Cisco IOS XR Release 7.9.1 and above. In the updated CLI, the **sid-algorithm** is nested under **constraints | segments**.

```
segment-routing
traffic-eng
on-demand color 10
  dynamic
  metric
  type igp
  !
  !
constraints <----- New CLI
  segments
  sid-algorithm 131
  !
  !
  !
```

- If you are on a release before Cisco IOS XR Release 7.4.1, you can configure SR-ODN with Flexible Algorithm constraints using the **segment-routing traffic-eng on-demand color color dynamic sid-algorithm algorithm-number** command.

Starting with Cisco IOS XR release 7.4.1, you can also configure SR-ODN with Flexible Algorithm constraints using the new **segment-routing traffic-eng on-demand color color constraints segments sid-algorithm algorithm-number** command.

From Cisco IOS XR Release 7.9.1, the **segment-routing traffic-eng on-demand color color dynamic sid-algorithm algorithm-number** command is deprecated. Previous configurations stored in NVRAM will be rejected at boot-up.

Hence, for Cisco IOS XR Release 7.9.1, you must reconfigure all SR-ODN configurations with Flexible Algorithm constraints that use the [on-demand dynamic sid-algorithm](#) with the [on-demand constraints](#) command.

Caveats

There are no caveats in this release.

Supported Packages and System Requirements

Feature Set (Software Images)

Visit the [Cisco Software Download page](#) to download the Cisco IOS XR software.

Cisco IOS XR 64 bit

This table lists the feature set matrix (ISO and RPM files) and associated filenames available for the Cisco IOS XR 64 bit 7.9.1 Release supported on the Cisco ASR 9000 Series Aggregation Services Router.

Table 1: Cisco IOS XR 64 bit Software Release 7.9.1 TAR Files

Feature Set	Filename	Description
Cisco IOS XR IP/MPLS Core Software [for RSP and RP systems]	ASR9K-x64-iosxr-px-7.9.1.tar	<ul style="list-style-type: none">• Cisco IOS XR Manageability Package• Cisco IOS XR MPLS Package• Cisco IOS XR MPLS -TE and RSVP Package• Cisco IOS XR Multicast Package• Cisco IOS XR Optics Package• Cisco IOS XR BNG Package• Cisco IOS XR Lawful Intercept Package• Cisco IOS XR Satellite Package• Cisco IOS XR EIGRP Package• Cisco IOS XR ISIS Package• Cisco IOS XR OSPF Package• Cisco IOS XR Service Package

Feature Set	Filename	Description
Cisco IOS XR IP/MPLS Core Software 3DES [for RSP and RP systems]	ASR9K-x64-iosxr-px-k9-7.9.1.tar	<ul style="list-style-type: none"> • Cisco IOS XR Manageability Package • Cisco IOS XR MPLS Package • Cisco IOS XR MPLS -TE and RSVP Package • Cisco IOS XR Multicast Package • Cisco IOS XR Optics Package • Cisco IOS XR BNG Package • Cisco IOS XR Lawful Intercept Package • Cisco IOS XR Satellite Package • Cisco IOS XR Security Package • Cisco IOS XR EIGRP Package • Cisco IOS XR ISIS Package • Cisco IOS XR OSPF Package • Cisco IOS XR Service Package
Cisco IOS XR IP Unicast Routing Core Bundle and Migration to IOS XR 64 bit tar image	asr9k-mini-x64-migrate_to_eXR.tar-7.9.1	<p>Contains the required core packages, including OS, Admin, Base, Forwarding, Modular Services Card, Routing, FPD, SNMP Agent, and Alarm Correlation.</p> <p>Contains mini.iso file for XR 64 bit 7.9.1 and additional software for migration to 64 bit.</p>

Table 2: Cisco IOS XR 64 bit Software Release 7.9.1 ISO and RPM Files

Composite Package		
Feature Set	Filename	Description
Cisco IOS XR IP Unicast Routing Core Bundle	asr9k-mini-x64-7.9.1.iso	<p>Contains the required core packages, including OS, Admin, Base, Forwarding, Modular Services Card, Routing, FPD, SNMP Agent, and Alarm Correlation.</p> <p>The mini iso file is used for upgrading to the new release.</p>
Individually-Installable Optional Packages		
Feature Set	Filename	Description

Cisco IOS XR 64 bit EIGRP package	asr9k-eigrp-x64-1.0.0.0-r791.x86_64.rpm	Includes EIGRP protocol support software
Cisco IOS XR BNG Package	asr9k-bng-x64-1.1.0.0-r791.x86_64.rpm	Includes binaries to support BNG features.
Cisco IOS XR 64 bit ISIS package	asr9k-isis-x64-1.1.0.0-r791.x86_64.rpm	Includes IS-IS Link state protocol support software
Cisco IOS XR 64 bit OSPF package	asr9k-ospf-x64-1.1.0.0-r791.x86_64.rpm	Includes OSPF link state protocol support software
Cisco IOS XR Manageability Package	asr9k-mgbl-x64-3.0.0.0-r791.x86_64.rpm	CORBA2 agent, XML3 Parser, and HTTP server packages. This RPM also contains some SNMP MIB infrastructure. Certain MIBs won't work if this RPM is not installed. IPSLA and environment MIBs are part of the mgbl rpm.
Cisco IOS XR 64 bit MPLS-TE and RSVP package	asr9k-mpls-te-rsvp-x64-1.2.0.0-r791.x86_64.rpm	MPLS Traffic Engineering (MPLS-TE), Resource Reservation Protocol (RSVP).
Cisco IOS XR 64 bit MPLS Package	asr9k-mpls-x64-2.1.0.0-r791.x86_64.rpm	Label Distribution Protocol (LDP), MPLS Forwarding, MPLS Operations, Administration, and Maintenance (OAM), Link Manager Protocol (LMP), Optical User Network Interface (OUNI) and Layer-3 VPN.
Cisco IOS XR 64 bit Multicast Package	asr9k-mcast-x64-2.0.0.0-r791.x86_64.rpm	Multicast Routing Protocols (PIM, Multicast Source Discovery Protocol [MSDP], Internet Group Management Protocol [IGMP], Auto-RP), Tools (SAP, MTrace), and Infrastructure [(Multicast Routing Information Base [MRIB], Multicast-Unicast RIB [MURIB], Multicast forwarding [MFWD]), and Bidirectional Protocol Independent Multicast (BIDIR-PIM).
Cisco IOS XR 64 bit Optics Package	asr9k-optic-x64-1.0.0.0-r791.x86_64.rpm	Firmware for the optics feature for Cisco ASR 9000 Series Aggregation Services Router Chassis. It enables Transport / OTN feature under interfaces.
Cisco IOS XR 64 bit Lawful Intercept (LI) Package	asr9k-li-x64-1.1.0.0-r791.x86_64.rpm	Includes LI software images.
Cisco IOS XR Security Package	asr9k-k9sec-x64-3.1.0.0-r791.x86_64.rpm	Support for Encryption, Decryption,, Secure Shell (SSH), Secure Socket Layer (SSL), and Public-key infrastructure (PKI).

Cisco IOS XR Satellite Package -ASR9000v	asr9k-9000v-nV-x64-1.0.0.0-r791.x86_64.rpm	Includes RPM to support Cisco ASR9000v Series Router Software and to support Cisco ASR 9000v Series Router as a satellite for Cisco ASR 9000 Series Router
Cisco IOS XR 64 bit Services Package	asr9k-services-x64-1.0.0.0-r791.x86_64.rpm	Includes RPM to support Cisco IOS XR 64-bit inline MAP-T function

Memory



Caution If you remove the media in which the software image or configuration is stored, the router may become unstable and fail.

The available memory for Cisco ASR 9000 Series Aggregation Services Router running Cisco IOS XR Software Release consist of the following:

- 32 GB memory on the A99-RP-F
- 16 GB memory on the RSP880, RSP880-LT, RP2, A99-RSP-TR and A99-RSP-SE
- 16 GB memory on the RP2 transport optimised (TR) variant and 32 GB memory on the RP2 service edge (SE) variant
- 24 GB memory on the RP3 transport optimised (TR) variant and 40 GB memory on the RP3 service edge (SE) variant
- 24 GB memory on the RP3-X transport optimised (TR) variant and 48 GB memory on the RP3-X service edge (SE) variant
- 24 GB memory on the RSP5 transport optimised (TR) variant and 40 GB memory on the RSP5 service edge (SE) variant
- 24 GB memory on the RSP5-X transport optimised (TR) variant and 48 GB memory on the RSP5-X service edge (SE) variant
- 2 GB compact flash on route switch processors (RSPs)
- 8 GB memory on the line cards (LCs) running Cisco IOS XR 64-bit image

Software Compatibility

Cisco IOS XR Software Release is compatible with the following Cisco ASR 9000 Series Aggregation Services Router systems.

- Cisco ASR 9900 Series Chassis
 - Cisco ASR 9922 Chassis
 - Cisco ASR 9912 Chassis
 - Cisco ASR 9910 Chassis
 - Cisco ASR 9906 Chassis
 - Cisco ASR 9904 Chassis
 - Cisco ASR 9903 Chassis
 - Cisco ASR 9902 Chassis
 - Cisco ASR 9901 Chassis

- Cisco ASR 9000 Series Chassis
 - Cisco ASR 9010 Chassis
 - Cisco ASR 9006 Chassis

For Cisco license support, please contact your Cisco Sales Representative or Customer Service at 800- 553-NETS (6387) or 408-526-4000. For questions on the program other than ordering, please send e-mail to: cwm-license@cisco.com.

Determining Installed Packages

To determine the version of Cisco IOS XR Software packages installed on your router, log in to the router and enter the **show install active summary** command:

Cisco IOS XR 64 bit

```
Router# show install active summary
Label : 7.9.1
```

```
Active Packages: 16
  asr9k-xr-7.9.1 version=7.9.1 [Boot image]
  asr9k-li-x64-1.0.0.0-r791
  asr9k-mpls-x64-1.0.0.0-r791
  asr9k-services-x64-1.0.0.0-r791
  asr9k-mpls-te-rsvp-x64-1.0.0.0-r791
  asr9k-mcast-x64-1.0.0.0-r791
  asr9k-9000v-nV-x64-1.0.0.0-r791
  asr9k-cnbnng-x64-1.0.0.0-r791
  asr9k-eigrp-x64-1.0.0.0-r791
  asr9k-isis-x64-1.0.0.0-r791
  asr9k-m2m-x64-1.0.0.0-r791
  asr9k-optic-x64-1.0.0.0-r791
  asr9k-bng-supp-x64-1.0.0.0-r791
  asr9k-mgbl-x64-1.0.0.0-r791
  asr9k-k9sec-x64-1.0.0.0-r791
  asr9k-ospf-x64-1.0.0.0-r791
```

Firmware Support on Cisco IOS XR 64-bit

To check the firmware code running on the Cisco ASR 9000 Series Router, run the **show fpd package** command in admin mode:



Note

The show command output lists supported and EOL hardware PIDs. To know the PIDs that are supported in this release, see the Supported Hardware section in this Release Notes.

```
(sysadmin-vm)#show fpd package
```

```
=====
```

Field Programmable Device Package					
Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
A99-10X400GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-10X400GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-10X400GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-12X100GE	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Morra-1	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.34	9.34	0.1
	Sideswipe-0	YES	1.02	1.02	0.1
Sideswipe-1	YES	1.02	1.02	0.1	
A99-12X100GE-CM	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Morra-1	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.34	9.34	0.1
	Sideswipe-0	YES	1.02	1.02	0.1
Sideswipe-1	YES	1.02	1.02	0.1	

```
-----
```

A99-16X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A99-16X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A99-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A99-16X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0

A99-24HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
TAMFW-Sunstreaker	YES	2.65	2.65	0.0	

A99-24HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
TAMFW-Sunstreaker	YES	2.65	2.65	0.0	

A99-24HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-24X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-24X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-24X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	LeadFoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-32X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0

A99-32X100GE-DENS	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.12	0.12	0.0
	Grapple-1	YES	0.12	0.12	0.0
	IPU-DDR4	YES	1.08	1.08	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.08	0.08	0.0
	Skylynx-1	YES	0.08	0.08	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-32X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0

	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0

A99-32X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0

A99-32X100GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-32X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-32X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-48X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1

	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-48X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-48X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A99-4HG-FLEX-FC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-4HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-4HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A99-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-CM	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-SE	CBC	NO	38.23	38.23	0.0

	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99-RP-F	Aldrin-0-FPGA	YES	1.06	1.06	0.0
	CBC	NO	59.13	59.13	0.0

	Lionheart-FPGA	YES	0.30	0.30	0.0
	Longshot	YES	2.16	2.16	0.0
	Primary-BIOS	YES	33.30	33.30	0.0
	TamFW-Longshot	YES	2.65	2.65	0.0
	Wolfpack-FPGA	YES	0.19	0.19	0.0

A99-RP2-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC-0	NO	35.14	35.14	0.0
	CBC-1	NO	35.14	35.14	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	14.39	14.39	0.0

A99-RP2-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC-0	NO	35.14	35.14	0.0
	CBC-1	NO	35.14	35.14	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	14.39	14.39	0.0

A99-RP3-SE	Aldrin-0-FPGA	YES	1.03	1.03	0.0
	Aldrin-1-FPGA	YES	1.00	1.00	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC-0	NO	51.12	51.12	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	30.36	30.36	0.0
	Zenith-FPGA	YES	0.10	0.10	0.0

A99-RP3-TR	Aldrin-0-FPGA	YES	1.03	1.03	0.0
	Aldrin-1-FPGA	YES	1.00	1.00	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC-0	NO	51.12	51.12	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	30.36	30.36	0.0
	Zenith-FPGA	YES	0.10	0.10	0.0

A99-RP3-X-SE	Aldrin-0-FPGA	YES	1.00	1.00	0.0
	Aldrin-1-FPGA	YES	32.00	32.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC-0	NO	12.04	12.04	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	3.03	3.03	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.03	35.03	0.0
	Sigma	YES	3.33	3.33	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.07	2.07	0.0

A99-RP3-X-TR	Aldrin-0-FPGA	YES	1.00	1.00	0.0
	Aldrin-1-FPGA	YES	32.00	32.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC-0	NO	12.04	12.04	0.0

	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	3.03	3.03	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.03	35.03	0.0
	Sigma	YES	3.33	3.33	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.07	2.07	0.0

A99-RSP-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	43.03	43.03	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	16.18	16.18	0.0

A99-RSP-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	43.03	43.03	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	16.18	16.18	0.0

A99-SFC-S	CBC	NO	44.02	44.02	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0

A99-SFC-T	CBC	NO	44.02	44.02	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0

A99-SFC2	CBC	NO	37.20	37.20	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0

A99-SFC3	CBC	NO	49.03	49.03	0.0
	IPU-DDR4	YES	0.25	0.25	0.0

A99-SFC3-S	CBC	NO	44.02	44.02	0.0
	IPU-DDR4	YES	0.25	0.25	0.0

A99-SFC3-T	CBC	NO	44.02	44.02	0.0
	IPU-DDR4	YES	0.25	0.25	0.0

A99L-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99L-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0

	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99L-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99L-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99L-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A99L-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-1600W-AC	PO-PrimCU	NO	17.137	17.137	0.0

A9K-1600W-DC	PO-PrimCU	NO	1.09	1.09	0.0

A9K-16X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-16X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-20HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
	Windcharger-1	YES	0.08	0.08	0.0

A9K-20HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
	Windcharger-1	YES	0.08	0.08	0.0

A9K-20HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
	Windcharger-1	YES	0.08	0.08	0.0

A9K-24X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-24X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1

	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-24X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-400G-DWDM-TR	CBC	NO	42.04	42.04	0.0
	Doran	YES	1.05	1.05	0.0
	Frenzy	YES	49.00	49.00	0.0
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Martell	YES	1.03	1.03	0.0
	Meldun	YES	1.07	1.07	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-400GE-LSP	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-48X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-48X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-48X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.34	18.34	0.1

A9K-4HG-FLEX-FC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0

	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-4HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-4HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-4X100GE	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.34	9.34	0.1
	Sideswipe-0	YES	1.02	1.02	0.1

A9K-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0

	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-4X100GE-TR-V2	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-8HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0

A9K-8HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0

A9K-8HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0

A9K-8X100GE-CM	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-L-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-L-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-L-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0

	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-8X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-8X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-8X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

A9K-8X100GE-X2-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0

	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-8X100GE-X2-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-8X100GE-X2-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0

A9K-8X100GELSE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-8X100GELTR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9K-MOD200-CM	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-MOD200-SE	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-MOD200-TR	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-MOD400-CM	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1

	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-MOD400-SE	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-MOD400-TR	Blaster	YES	1.27	1.27	0.1
	CBC	NO	39.09	39.09	0.1
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Primary-BIOS	YES	8.51	8.51	0.1

A9K-RSP5-SE	Aldrin-0-FPGA	YES	1.06	1.06	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC	NO	53.10	53.10	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	31.36	31.36	0.0
	Zenith-FPGA	YES	0.10	0.10	0.0

A9K-RSP5-TR	Aldrin-0-FPGA	YES	1.06	1.06	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC	NO	53.10	53.10	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	31.36	31.36	0.0
	Zenith-FPGA	YES	0.10	0.10	0.0

A9K-RSP5-X-SE	Aldrin-0-FPGA	YES	51.00	51.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC	NO	14.04	14.04	0.0
	IPU-DDR4	YES	3.03	3.03	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.03	35.03	0.0
	Sigma	YES	3.33	3.33	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.07	2.07	0.0

A9K-RSP5-X-TR	Aldrin-0-FPGA	YES	51.00	51.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC	NO	14.04	14.04	0.0
	IPU-DDR4	YES	3.03	3.03	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.03	35.03	0.0
	Sigma	YES	3.33	3.33	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.07	2.07	0.0

A9K-RSP880-LT-SE	Aldrin-FPGA	YES	1.11	1.11	0.0
	Alpha-FPGA	YES	0.05	0.05	0.0
	CBC	NO	50.03	50.03	0.0
	IPU-FPGA	YES	0.20	0.20	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.07	0.07	0.0
	Optimus-FPGA	YES	0.05	0.05	0.0
	Primary-BIOS	YES	17.41	17.41	0.0

A9K-RSP880-LT-TR	Aldrin-FPGA	YES	1.11	1.11	0.0
	Alpha-FPGA	YES	0.05	0.05	0.0
	CBC	NO	50.03	50.03	0.0
	IPU-FPGA	YES	0.20	0.20	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.07	0.07	0.0
	Optimus-FPGA	YES	0.05	0.05	0.0
	Primary-BIOS	YES	17.41	17.41	0.0

A9K-RSP880-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	34.39	34.39	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	10.69	10.69	0.0

A9K-RSP880-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	34.39	34.39	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	10.69	10.69	0.0

A9K-TEST_LSQ_DX1	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.30	25.30	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0

A9KL-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9KL-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0

A9KL-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0

	Primary-BIOS	YES	8.51	8.51	0.0
ASR-9006-AC	CBC	NO	7.105	7.105	0.0
ASR-9006-AC-V2	CBC	NO	7.105	7.105	0.0
ASR-9006-FAN	CBC	NO	5.04	5.04	0.0
ASR-9006-FAN-V2	CBC	NO	5.05	5.05	0.0
ASR-9010-AC	CBC	NO	7.105	7.105	0.0
ASR-9010-AC-V2	CBC	NO	7.105	7.105	0.0
ASR-9010-FAN	CBC	NO	4.03	4.03	0.0
ASR-9010-FAN-V2	CBC	NO	29.12	29.12	0.0
ASR-9901-LC	CBC	NO	55.07	55.07	0.1
	Gamora-FPGA	YES	0.36	0.36	0.1
	IPU-FPGA	YES	1.10	1.10	0.1
	IPU-FSBL	YES	1.104	1.104	0.1
	IPU-Linux	YES	1.104	1.104	0.1
	Primary-BIOS	YES	23.23	23.23	0.1
ASR-9901-RP	CBC	NO	54.11	54.11	0.1
	Drax-FPGA	YES	0.38	0.38	0.1
	IPU-FPGA	YES	2.05	2.05	0.1
	IPU-FSBL	YES	1.104	1.104	0.1
	IPU-Linux	YES	1.104	1.104	0.1
	Primary-BIOS	YES	22.27	22.27	0.1
ASR-9902	FAN-CBC	NO	61.25	61.25	0.0
ASR-9902-LC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	17.03	17.03	0.0
	Chromia	YES	0.14	0.14	0.0
	IPU-DDR4	YES	1.17	1.17	0.0
	Primary-BIOS	YES	34.30	34.30	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.15	0.15	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
ASR-9903	FAN-CBC	NO	61.25	61.25	0.0
ASR-9903-LC	Aldrin-0-FPGA	YES	1.05	1.05	0.0
	CBC	NO	60.12	60.12	0.0
	Harpoon-0	YES	0.11	0.11	0.0
	Harpoon-1	YES	0.11	0.11	0.0
	IPU-DDR4	YES	1.25	1.25	0.0
	Metalmaster-0	YES	0.02	0.02	0.0
	Metalmaster-1	YES	0.02	0.02	0.0
	Primary-BIOS	YES	34.30	34.30	0.0
	Scattershot	YES	0.14	0.14	0.0
	Sunstreaker	YES	0.14	0.14	0.0
	Supernaut	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.65	2.65	0.0
	Warstar-0	YES	0.02	0.02	0.0
	Warstar-1	YES	0.02	0.02	0.0
ASR-9903-PXC800G-LC	Harpoon-0	YES	0.11	0.11	0.0
	Harpoon-1	YES	0.11	0.11	0.0

ASR-9904-AC	CBC	NO	7.105	7.105	0.0
ASR-9904-FAN	CBC	NO	31.06	31.06	0.0
ASR-9906	CBC	NO	7.105	7.105	0.0
ASR-9906-FAN	CBC	NO	56.01	56.01	0.0
	PSOC	NO	2.06	2.06	0.0
ASR-9910	CBC	NO	7.105	7.105	0.0
ASR-9910-FAN	CBC	NO	45.02	45.02	0.0
	PSOC	NO	2.06	2.06	0.0
ASR-9912-AC	CBC	NO	7.105	7.105	0.0
ASR-9912-FAN	CBC	NO	31.06	31.06	0.0
ASR-9912-SFC220	CBC	NO	37.20	37.20	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0
ASR-9922-AC	CBC-0	NO	7.105	7.105	0.0
	CBC-1	NO	7.105	7.105	0.0
ASR-9922-FAN	CBC	NO	29.12	29.12	0.0
ASR-9922-FAN-V2	CBC	NO	40.07	40.07	0.0
	PSOC	NO	2.06	2.06	0.0
ASR-9922-FAN-V3	CBC	NO	40.07	40.07	0.0
	PSOC	NO	2.06	2.06	0.0
PWR-1.6KW-AC	PrimMCU	NO	17.20	17.20	0.0
PWR-1.6KW-DC	PrimMCU	NO	1.03	1.03	0.0
PWR-2KW-DC-V2	DT-PrimMCU	NO	6.03	6.03	0.12
	DT-Sec54vMCU	NO	6.02	6.02	0.12

Supported Hardware

The following table lists the supported hardware components on the Cisco ASR 9000 Series Router and the minimum required software versions. For more information, see the *Firmware Support* section.

All hardware features are supported on Cisco IOS XR Software, subject to the memory requirements specified in the section.

For information on the end-of-sale and end-of-life dates for the Cisco ASR 9000 Series Router hardware, refer to the [End-of-Life and End-of-Sale Notices](#) page.

Table 3: Cisco ASR 9000 Series Aggregation Services Router Supported Hardware and Minimum Software Requirements

Cisco ASR 9000 Series Aggregation Services Router - Route Switch Processor Cards		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A9K-RSP5-X-SE	ASR 9000 Series Route Switch Processor 5 for Service Edge, Premium	Release 7.6.2

A9K-RSP5-X-TR	ASR 9000 Series Route Switch Processor 5 for Packet Transport, Premium	Release 7.6.2
A9K-RSP5-SE	ASR 9000 Route Switch Processor 5 for Service Edge	Release 6.5.15
A9K-RSP5-TR	ASR 9000 Route Switch Processor 5 for Packet Transport	Release 6.5.15
A9K-RSP880-LT-SE	Cisco ASR 9000 Series Aggregation Services Router RSP880-Lite, Service Edge Optimized	Release 6.4.1
A9K-RSP880-LT-TR	Cisco ASR 9000 Series Aggregation Services Router RSP880-Lite, Packet Transport Optimized	Release 6.4.1
A99-RSP-SE	Cisco ASR 9000 Series Aggregation Services Router RSP4-S, Service Edge Optimized for ASR 9910 from Release 6.0.1.	Release 6.2.1
A99-RSP-TR	Cisco ASR 9000 Series Aggregation Services Router RSP4-S, Packet Transport Optimized for ASR 9910 from Release 6.0.1.	Release 6.2.1
A99-RSP-SE	Cisco ASR 9000 Series Aggregation Services Router RSP4-S, Service Edge Optimized for ASR 9906 from Release 6.3.1.	Release 6.3.1
A99-RSP-TR	Cisco ASR 9000 Series Aggregation Services Router RSP4-S, Packet Transport Optimized for ASR 9906 supported from Release 6.3.1	Release 6.3.1
A9K-RSP880-SE	ASR9K Route Switch Processor with 880G/slot and 32 GB for Service Edge	Release 6.1.2
A9K-RSP880-TR	ASR9K Route Switch Processor with 880G/slot and 16 GB for Packet Transport	Release 6.1.2
Cisco ASR 9000 Series Aggregation Services Router - Route Processor Cards		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A99-RP3-X-SE	ASR 9900 Route Processor 3 for Service Edge, Premium	Release 7.6.2
A99-RP3-X-TR	ASR 9900 Route Processor 3 for Packet Transport, Premium	Release 7.6.2
A99-RP3-SE	ASR 9900 Route Processor 3 for Service Edge	Release 6.5.15
A99-RP3-TR	ASR 9900 Route Processor 3 for Packet Transport	Release 6.5.15
A99-RP2-SE	ASR Route Processor 32 GB for Service Edge	Release 6.1.2
A99-RP2-TR	ASR Route Processor 16 GB for Packet Transport	Release 6.1.2
Cisco ASR 9901 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9901	Cisco ASR 9000 Series Aggregation Services Router 2-RU Fixed Port	Release 6.4.1

ASR-9901-FAN	Cisco ASR 9000 Series Aggregation Services Router 2-RU Fixed Port Fan Tray	Release 6.4.1
A9K-1600W-AC	Cisco ASR 9000 Series Aggregation Services Router 2-RU 1600W AC Power Module	Release 6.4.1
A9K-1600W-DC	Cisco ASR 9000 Series Aggregation Services Router 2-RU 1600W DC Power Module	Release 6.4.1
Cisco ASR 9902 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9902	Cisco ASR 9902 2RU Chassis with fixed ports	Release 7.4.1
A99-RP-F	Cisco ASR 9900 Fixed Chassis Route Processor	Release 7.1.3
ASR-9902-4P-KIT	Cisco ASR 9902 4-Post Mounting Kit for 19-Inch and 23-Inch Rack	Release 7.4.1
ASR-9902-4P-KIT-L	ASR 9902 4-Post Mounting Kit for 19 & 23 inch Rack – Long	Release 7.4.1
ASR-9902-2P-KIT	Cisco ASR 9902 2-Post Mounting Kit for 19-Inch and 23-Inch Rack	Release 7.4.1
ASR-9902-CAB-MGMT	Cisco ASR 9902 Cable Management	Release 7.4.1
ASR-9902-FILTER	Cisco ASR 9902 Air Filter	Release 7.4.1
ASR-9902-FAN	Cisco ASR 9902 Fan Tray	Release 7.4.1
Cisco ASR 9903 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9903	Cisco ASR 9903 Compact High-Performance Router with fixed ports and PEC (Port Expansion Card) slot.	Release 7.1.3
A99-RP-F	Cisco ASR 9900 Fixed Chassis Route Processor	Release 7.1.3
ASR-9903-FAN	Cisco ASR 9903 Router Fan Tray	Release 7.1.3
ASR-9903-4P-KIT	ASR 9903 4-Post Mounting Kit for 19-inch Rack	Release 7.1.3
ASR-9903-CAB-MGMT	ASR 9903 Cable Management Brackets	Release 7.1.3
ASR-9903-FILTER	ASR 9903 Air Filter	Release 7.1.3
Cisco ASR 9904 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9904	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot Chassis, 6 RU	Release 6.1.2

ASR-9904-AC	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9904-DC	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2
ASR-9904-FAN	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Fan Tray	Release 6.1.2
ASR-9904-FILTER	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Filter	Release 6.1.2
ASR-9904-BAFFLE	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Baffle	Release 6.1.2
Cisco ASR 9912 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9912	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot Chassis	Release 6.1.2
ASR-9912-AC	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9912-DC	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2
A99-SFC3	Cisco ASR 9900 Switch Fabric Card 3	Release 6.5.15
A99-SFC2	Cisco ASR 9000 Fabric Card	Release 6.1.2
ASR-9912-FAN	Cisco ASR 9000 Series Aggregation Services Router 12-Slot Fan Tray	Release 6.1.2
Cisco ASR 9922 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9922	Cisco ASR 9922 20 Line Card Slot Chassis, 44 RU	Release 6.1.2
ASR-9922-AC	Cisco ASR 9000 Series Aggregation Services Router 22-Slot 20 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9922-DC	Cisco ASR 9000 Series Aggregation Services Router 22-Slot 20 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2
A99-SFC3	Cisco ASR 9900 Switch Fabric Card 3	Release 6.5.15
A99-SFC2	Cisco ASR 9000 Fabric Card	Release 6.1.2
ASR-9922-FAN-V3	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Fan Tray version 3	Release 6.5.15
ASR-9922-FLTR-CV2	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Air Filter with Media, Center	Release 6.1.2

ASR-9922-FLTR-LR	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Air Filter with Media, Left & Right	Release 6.1.2
ASR-9922-RP-FILR	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Route Processor Filler	Release 6.1.2
ASR-9922-FAN-V2	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Version 2 Fan Tray	Release 6.1.2
Cisco ASR 9006 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9006-SYS	Cisco ASR 9000 Series Aggregation Services Router 6-Slot System	Release 6.1.2
ASR-9006-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 6-Slot AC Chassis Version 2	Release 6.1.2
ASR-9006-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 6-Slot DC Chassis Version 2	Release 6.1.2
ASR-9006-FAN	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Tray	Release 6.1.2
ASR-9006-DOOR	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Door Kit	Release 6.1.2
ASR-9006-FILTER	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Air Filter	Release 6.1.2
Cisco ASR 9906 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9906	Cisco ASR 9000 Series Aggregation Services Router 6-Slot chassis	Release 6.3.1
ASR-9906-FAN	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Tray	Release 6.3.1
ASR-9906-FILTER	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Filter	Release 6.3.1
A99-SFC3-T	ASR 9906 Switch Fabric Card	Release 6.5.15
A99-SFC-T	ASR 9906 Switch Fabric Card 3	Release 6.3.1
Cisco ASR 9010 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9010-SYS	Cisco ASR 9000 Series Aggregation Services Router 10-Slot System	Release 6.1.2
ASR-9010-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 10-Slot AC Chassis Version 2	Release 6.1.2
ASR-9010-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 10-Slot DC Chassis Version 2	Release 6.1.2

ASR-9010-FAN	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Fan Tray	Release 6.1.2
ASR-9010-DOOR	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Door Kit	Release 6.1.2
ASR-9010-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 2 Post Mounting Kit	Release 6.1.2
ASR-9010-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 4 Post Mounting Kit	Release 6.1.2
ASR-9010-FILTER	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Air Filter	Release 6.1.2
Cisco ASR 9910 Router		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
ASR-9910	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) System	Release 6.2.1
ASR-9910-FAN	Cisco ASR 9000 Series Aggregation Services Router 10-Slot(9910) Fan Tray	Release 6.2.1
ASR-9910-ACC-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Accessory Kit	Release 6.2.1
ASR-9910-4P-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) 4 Post Rack Mounting Kit	Release 6.2.1
ASR-9910-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) 2 Post Rack Mounting Kit	Release 6.2.1
ASR-9910-AIRREF	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Air Reflector	Release 6.2.1
ASR-9910-FILTER	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Air Filter	Release 6.2.1
A99-SFC-S	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Switch Fabric Card	Release 6.2.1
A99-SFC3-S	ASR 9910 Switch Fabric Card 3	Release 6.5.15
Cisco ASR 9000 Series Aggregation Services Router - Power Modules		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
PWR-2KW-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 2KW DC Power Module, version 2	Release 6.1.2
PWR-3KW-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 3KW AC Power Module, version 2	Release 6.1.2

A9K-AC-PEM-V2	Cisco ASR 9000 Series Aggregation Services Router AC Power Entry Module Version 2	Release 6.1.2
A9K-DC-PEM-V2	Cisco ASR 9000 Series Aggregation Services Router DC Power Entry Module Version 2	Release 6.1.2
A9K-PEM-V2-FILR	Cisco ASR 9000 Series Aggregation Services Router Power Entry Module Version 2 Filler	Release 6.1.2
A9K-AC-PEM-V3	Cisco ASR 9000 Series Aggregation Services Router AC Power Enclosure Module Version 3	Release 6.1.2
A9K-DC-PEM-V3	Cisco ASR 9000 Series Aggregation Services Router DC Power Enclosure Module Version 3	Release 6.1.2
PWR-6KW-AC-V3	Cisco ASR 9000 Series Aggregation Services Router 6kW AC Power Module Version 3	Release 6.1.2
PWR-4.4KW-DC-V3	Cisco ASR 9000 Series Aggregation Services Router 4.4kW DC Power Module Version 3	Release 6.1.2
PWR-1.6KW-AC	ASR 9900 Fixed Chassis AC Power Supply	Release 7.1.25
PWR-1.6KW-DC	ASR 9900 Fixed Chassis DC Power Supply	Release 7.1.25
Cisco ASR 9000 Series Aggregation Services Router - Line Cards		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A9K-4HG-FLEX-SE	ASR 9000 400GE Combo Service Edge Line Card - 5th Generation	Release 7.4.1
A9K-4HG-FLEX-TR	ASR 9000 400GE Combo Packet Transport Line Card - 5th Generation	Release 7.4.1
A99-4HG-FLEX-SE	ASR 9900 400GE Combo Service Edge Line Card - 5th Generation	Release 7.4.1
A99-4HG-FLEX-TR	ASR 9900 400GE Combo Packet Transport Line Card - 5th Generation	Release 7.4.1
A9903-8HG-PEC	ASR 9903 800G Multi-rate Port Expansion Card	Release 7.4.1
A99-10X400GE-X-SE	ASR 9900 4T Service Edge Line Card - 5th Generation	Release 7.3.1
A99-10X400GE-X-TR	ASR 9900 4T Packet Transport Line Card - 5th Generation	Release 7.3.1
A9903-20HG-PEC	ASR 9903 2T Multi-rate Port Expansion Card	Release 7.1.3
A99-32X100GE-X-SE	ASR 9000 32-Port 100GE QSFP28/QSFP+ Service Edge optimized Line Card - 5th Generation	Release 7.1.15
A99-32X100GE-X-TR	ASR 9000 32-Port 100GE QSFP28/QSFP+ Packet Transport optimized Line Card - 5th Generation	Release 7.1.15
A9K-20HG-FLEX-SE A9K-20HG-FLEX-TR	ASR 9000 2T Combo Line Card - 5th Generation	Release 7.1.15

A9K-8HG-FLEX-SE A9K-8HG-FLEX-TR	ASR 9000 800G Combo Line Card - 5th Generation	Release 7.1.15
A9K-16X100GE-TR	ASR 9000 16-port 100GE QSFP TR line card	Release 6.5.15
A99-32X100GE-TR	ASR 9900 32-port 100GE QSFP TR line card	Release 6.5.15
A99-48X10GE-1G-SE	ASR 9000 48 port dual rate 10G/1G Service Edge line card	Release 6.5.2
A99-48X10GE-1G-TR	ASR 9000 48 port dual rate 10G/1G Transport Optimised line card	Release 6.5.2
A99-16X100GE-X-SE	ASR 9900 16-port 100GE QSFP SE	Release 6.5.3
A9K-48X10GE-1G-CM	ASR 9000 48-port dual-rate 10G/1G Consumption Model line card	Release 6.4.1
A9K-24X10GE-1G-CM	ASR 9000 24-port dual-rate 10G/1G Consumption Model line card	Release 6.4.1
A9K-4X100GE	ASR 9000 4-port 100-Gigabit Ethernet Line Card	Release 6.4.1
A9K-48X10GE-1G-SE	ASR9000 48-port dual-rate 10G/1G service edge-optimized line card	Release 6.3.2
A9K-48X10GE-1G-TR	ASR9000 48-port dual-rate 10G/1G packet transport-optimized line card	Release 6.3.2
A9K-24X10GE-1G-SE	ASR9000 24-port dual-rate 10G/1G service edge-optimized line card	Release 6.3.2
A9K-24X10GE-1G-TR	ASR9000 24-port dual-rate 10G/1G packet transport-optimized line card	Release 6.3.2
A99-8X100GE-SE	ASR 9900 8-port 100GE Service Edge optimized	Release 6.1.2
A99-8X100GE-TR	ASR 9900 8-port 100GE Packet Transport optimized	Release 6.1.2
A99-8X100GE-CM	ASR 9900 8-port 100GE Consumption Model	Release 6.1.2
A99-12X100GE	Cisco ASR 9000 Series Aggregation Services Router 12-Port 100-Gigabit Ethernet Line Card	Release 6.1.2
A99-12X100GE-CM	Cisco ASR 9000 Series Aggregation Services Router 12-port 100GE Ethernet Line card CM	Release 6.1.2
A9K-8X100GE-CM	Cisco ASR 9000 Series Aggregation Services Router 8-Port 100-Gigabit Ethernet, Consumption Model Optimized with CPAK	Release 6.1.2
A9K-8X100GE-SE	Cisco ASR 9000 Series Aggregation Services Router 8-Port 100-Gigabit Ethernet, Service Edge Optimized	Release 6.1.2
A9K-8X100GE-TR	Cisco ASR 9000 Series Aggregation Services Router 8-Port 100-Gigabit Ethernet, Packet Transport Optimized	Release 6.1.2
A9K-4X100GE-SE	Cisco ASR 9000 Series Aggregation Services Router 4--Port 100-Gigabit Ethernet, Service Edge Optimized	Release 6.1.2
A9K-4X100GE-TR	Cisco ASR 9000 Series Aggregation Services Router 4-Port 100-Gigabit Ethernet, Packet Transport Optimized	Release 6.1.2

Cisco ASR 9000 Series Aggregation Services Router - Modular Line Cards		
Part Number		Support Initially Provided in IOS XR 64 bit Release
	Cisco ASR 9000 Series Aggregation Services Router 200 Gigabit Modular Line Card, Packet Transport Optimized Cisco ASR 9000 Series Aggregation Services Router 200 Gigabit Modular Line Card, Service Edge Optimized	
A9K-MOD200-TR A9K-MOD200-SE	Cisco ASR 9000 Modular 400G Consumption Model Line Card	Release 6.3.1
A9K-MOD400-CM	Cisco ASR 9000 Series Aggregation Services Router 400 Gigabyte Modular Line Card, Service Edge Optimized	Release 6.2.1
A9K-MOD400-SE	Cisco ASR 9000 Series Aggregation Services Router 400 Gigabyte Modular Line Card, Packet Transport Optimized	Release 6.2.1
A9K-MOD400-TR	Cisco ASR 9000 Series Aggregation Services Router 200 Gigabit Modular Line Card, Packet Transport Optimized Cisco ASR 9000 Series Aggregation Services Router 200 Gigabit Modular Line Card, Service Edge Optimized	Release 6.2.1
Cisco ASR 9000 Series Aggregation Services Router - Modular Port Adapters (MPAs)		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A9K-MPA-1X200GE	Cisco ASR 9000 1-port 200-Gigabit Ethernet MPA, requires CFP2-DCO optics	Release 6.6.2
A9K-MPA-32X1GE	Cisco ASR 9000 32-port 1-Gigabit Ethernet MPA with MACSec	Release 6.6.2
A9K-MPA20X10GE-CM	Cisco ASR 9000 20x10GE Consumption Model MPA	Release 6.5.1
A9K-MPA2X100GE-CM	Cisco ASR 9000 2x100GE Consumption Model MPA	Release 6.5.1
A9K-MPA-1X100GE	Cisco ASR 9000 Series Aggregation Services Router 1-port 100-Gigabit Modular Port Adapter	Release 6.3.1
A9K-MPA-2X100GE	Cisco ASR 9000 Series Aggregation Services Router 2-port 100-Gigabit Modular Port Adapter	Release 6.2.2
A9K-MPA-20x10GE	20-Port 10-Gigabit Ethernet Modular Port Adapter with SFP+	Release 6.2.1
A9K-MPA-8X10GE	Cisco ASR 9000 Series Aggregation Services Router 8-port 10GE Modular Port Adapter	Release 6.3.2
A9K-MPA-4X10GE	Cisco ASR 9000 Series Aggregation Services Router 4-port 10GE Modular Port Adapter	Release 6.2.1
A9K-MPA-20X1GE	Cisco ASR 9000 Series Aggregation Services Router 20-port 1GE Modular Port Adapter	Release 6.2.1

A9K-MPA-2X40GE	Cisco ASR 9000 Series Aggregation Services Router 2-port 40GE Modular Port Adapter	Release 6.3.1
Cisco Digital Pluggable Optical Modules		
CFP2-WDM-DET-1HL=	200G, 100G, WDM Digital CFP2 pluggable Licensed for 100G only – TOF	Release 6.6.2
CFP2-WDM-D-1HL=	200G, 100G, WDM Digital CFP2 pluggable Licensed for 100G only – NON TOF	Release 6.6.2
Cisco ASR 9000v Satellite Shelf		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A9KV-V2-DC-A=	Cisco ASR 9000v Satellite Shelf Version 2 DC power ANSI chassis	Release 6.2.1
A9KV-V2-DC-E=	Cisco ASR 9000v Satellite Shelf Version 2 DC power chassis	Release 6.2.1
A9KV-V2-AC=	Cisco ASR 9000v Satellite Shelf AC power chassis	Release 6.2.1
A9KV-V2-FAN=	Cisco ASR 9000v Satellite Shelf Version 2 Fan Tray	Release 6.2.1
Cisco NCS 5000 Satellite Shelf		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
NCS-5001	Cisco NCS 5001 Series Router	Release 6.2.1
NCS-5002	Cisco NCS 5002 Series Router	Release 6.2.1
NCS-5001-ACSR	Cisco NCS 5001 Router Accessory Kit	Release 6.2.1
NCS-5002-ACSR	Cisco NCS 5002 Router Accessory Kit	Release 6.2.1
NCS-5001-FN-BK	Cisco NCS 5001 Router Fan Back to Front AirFlow	Release 6.2.1
NCS-5002-FN-BK	Cisco NCS 5002 Router Fan Back to Front AirFlow	Release 6.2.1
NCS-5001-FLT-BK	Cisco NCS 5001 Air Filter Back to Front Airflow	Release 6.2.1
NCS-5002-FLT-BK	Cisco NCS 5002 Air Filter Back to Front Airflow	Release 6.2.1
NCS-5001-FN-FR	Cisco NCS 5001 Fan Front to Back Airflow	Release 6.2.1
NCS-5002-FN-FR	Cisco NCS 5002 Fan Front to Back Airflow	Release 6.2.1
NCS-5001-FLT-FR	Cisco NCS 5001 Air Filter Front to Back Airflow	Release 6.2.1
NCS-5002-FLT-FR	Cisco NCS 5002 Air Filter Front to Back Airflow	Release 6.2.1

Important Notes

- Repetitive Smart Licensing evaluation expired warning messages are displayed on the console every hour, but no functionality impact is observed on the device. To stop these repetitive messages, you should register the device again with a new registration token.
- From IOS XR Release 7.0, 1st and 2nd generation of Ethernet ASR 9000 line cards are not supported.
- Country-specific laws, regulations, and licenses—In certain countries, use of these products may be prohibited and subject to laws, regulations, or licenses, including requirements applicable to the use of the products under telecommunications and other laws and regulations; customers must comply with all such applicable laws in the countries in which they intend to use the products.
- Exceeding Cisco testing—If you intend to test beyond the combined maximum configuration tested and published by Cisco, contact your Cisco Account Team or Technical Support representative to discuss how to engineer a large-scale configuration for your purpose.
- Installing a Line Card—For a fully populated Line Card with cable optics, maintenance time required for card replacement is higher. For more information about Line Card installation and removal, refer to the *Cisco ASR 9000 Aggregation Services Router Ethernet Line Card Installation Guide*.
- For ZTP, In Cisco IOS XR Release 7.3.1 and earlier, the system accepts the device sending **user-class = "exr-config"**; however starting Cisco IOS XR Release 7.3.2 and later, you must use only **user-class = "xr-config"**.

In Cisco IOS XR Release 7.3.2 and later, use:

```
host cisco-rp0 {
  hardware ethernet e4:c7:22:be:10:ba;
  fixed-address 172.30.12.54;
  if exists user-class and option user-class = "iPXE" {
    filename = "http://172.30.0.22/boot.ipxe";
  } elseif exists user-class and option user-class = "xr-config" {
    filename = "http://172.30.0.22/scripts/cisco-rp0_ztp.sh";
  }
}
```

Supported Transceiver Modules

To determine the transceivers that Cisco hardware device supports, refer to the [Transceiver Module Group \(TMG\) Compatibility Matrix](#) tool.

Supported Modular Port Adapters

For the compatibility details of Modular Port Adapters (MPAs) on the line cards, see the [datasheet](#) of that specific line card.

Production Software Maintenance Updates (SMUs)

A production SMU is a SMU that is formally requested, developed, tested, and released. Production SMUs are intended for use in a live network environment and are formally supported by the Cisco TAC and the relevant development teams. Software bugs identified through software recommendations or Bug Search Tools are not a basis for production SMU requests.

For information on production SMU types, refer the [Production SMU Types](#) section of the *IOS XR Software Maintenance Updates (SMUs)* guide.

Upgrading Cisco IOS XR Software

Cisco IOS XR Software is installed and activated from modular packages, allowing specific features or software patches to be installed, upgraded, or downgraded without affecting unrelated processes. Software packages can be upgraded or downgraded on all supported card types, or on a single card (node).

Software packages are installed from Route Processor Module (RPM) files that contain one or more software components.

The upgrade document is available along with the software images.



Note If you have mLACP/ICCP Redundancy Model setup, ensure that you upgrade the active and standby nodes to the same IOS XR version while upgrading to a newer version of the ASR 9000 router.

Cisco IOS XR Error messages

To view, search, compare, and download Cisco IOS XR Error Messages, refer to the [Cisco IOS XR Error messages](#) tool.

Cisco IOS XR MIBs

To determine the MIBs supported by platform and release, refer to the [Cisco IOS XR MIBs](#) tool.

Related Documentation

The most current Cisco ASR 9000 router documentation is located at the following URL:

<https://www.cisco.com/c/en/us/td/docs/iosxr/asr-9000-series-routers.html>



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA 95134-1706
USA

Asia Pacific Headquarters
CiscoSystems(USA)Pte.Ltd.
Singapore

Europe Headquarters
CiscoSystemsInternationalBV
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.