



Ultra Cloud Core 5G Session Management Function, Release 2024.01 - Statistics Reference

First Published: 2024-01-31

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2024 Cisco Systems, Inc. All rights reserved.



CONTENTS

PREFACE

[About this Guide](#) vii

CHAPTER 1

[SMF Interface for Metrics](#) 1

[Feature Description](#) 1

[How it Works](#) 2

[Configuring Metrics Collection](#) 2

[Configuration Example](#) 4

[Configuration Verification](#) 4

CHAPTER 2

[SMF Metrics](#) 7

[smf-service Metrics Reference](#) 7

[CHF Notification Statistics Category](#) 7

[Charging final unit indication statistics Category](#) 8

[Discover Messages Time statistics Category](#) 8

[Discover Messages statistics Category](#) 9

[Dropped Charging Data Requests Statistics Category](#) 9

[GTPC Message stats Category](#) 10

[Gy Online charging destination host change statistics Category](#) 12

[Gy Online charging reporting reason statistics Category](#) 12

[Gz Offline CDR drop statistics Category](#) 12

[Gz Offline CDR message statistics Category](#) 13

[Gz Offline SDF Containers statistics Category](#) 13

[Incoming Message Throttling Statistics Category](#) 14

[NF End point selections Category](#) 14

[NF failure handling stats Category](#) 15

[NF management message time statistics Category](#) 16

[NF management messages statistics Category](#) 16
[NRF Discovery Category](#) 17
[PDU UE Sync Procedure Category](#) 17
[Policy control ADC pcc rule statistics Category](#) 17
[Policy control NRF fail action statistics Category](#) 18
[Policy control PCF update statistics Category](#) 19
[Policy control active PCF statistics Category](#) 19
[Policy control current flow Category](#) 20
[Policy control dynamic pcc rule statistics Category](#) 21
[Policy control message statistics Category](#) 23
[Policy control pre-defined pcc rule statistics Category](#) 25
[Policy control rule report statistics Category](#) 27
[Policy control session rule statistics Category](#) 27
[Policy control static pcc rule statistics Category](#) 28
[Policy control total flow statistics Category](#) 30
[Policy destination host change statistics Category](#) 31
[Radius Authentication Message Stats Category](#) 31
[Radius Message stats Category](#) 32
[SLA Transaction Category](#) 33
[SMF ADC URR Statistics Category](#) 33
[SMF ALWAYS ON PDU SESSION Category](#) 34
[SMF Charging Descriptor Delete Stats Category](#) 34
[SMF Charging Descriptor Drop Stats Category](#) 35
[SMF Charging Failure Handling Stats Category](#) 36
[SMF Charging Message Stats Category](#) 37
[SMF Charging OOO Usage Report Stats Category](#) 38
[SMF Charging PFCP usage Report Stats Category](#) 38
[SMF Charging Quota Event Stats Category](#) 39
[SMF Charging Radius Accounting Message Stats Category](#) 40
[SMF Charging Session Limit Dynamic Stats Category](#) 40
[SMF Charging Usage Report Stats Category](#) 41
[SMF Charging Zero Usage Report Stats Category](#) 42
[SMF DB Marshal Category](#) 42
[SMF Data Consistency Check Category](#) 43

SMF Disconnect stats Category	43
SMF EBI stats Category	45
SMF IPAM Address Events Current Counter Category	46
SMF IPAM Address Events Total Counter Category	47
SMF IPAM Chunk Events Current Counter Category	48
SMF IPAM Address Events Total Counter Category	49
SMF N1 Message stats Category	50
SMF N2 Message stats Category	51
SMF Node Manager stats Category	53
SMF PCSCF Server Stats Category	54
SMF PDU Status Category	55
SMF Procedure Category	56
SMF Procedure Collision Category	59
SMF Procedure Total Time Statistics Category	60
SMF Protocol message counters Category	60
SMF RAN failed stats Category	61
SMF RSRA stats Category	61
SMF Secondary RAT Usage Report Stats Category	62
SMF Service Node Report Stats Category	63
SMF Service Resource Management Stats Category	63
SMF Service gtpc cache statistics Category	64
SMF Session counters Category	65
SMF Session stats Category	66
SMF Start Procedure Statistics Category	67
SMF Stop Procedure Statistics Category	68
SMF Timeout stats Category	68
SMF Total Timedout Procedure Count Category	69
SMF Total Timedout Procedure Count Category	69
SMF Total Timedout Procedure Time Category	70
SMF Total Unhandled Event Statistics Category	70
SMF Total Unhandled Transaction Statistics Category	71
SMF User Plane Session counters Category	71
UDM Message Failure Action Stats Category	72
UDP RPC message statistics Category	72

UDP Request Total Message Stats Category 73

UPF selection stats Category 74

CHAPTER 3 **Failure Disconnect Reasons Reference 77**

SMF Disconnect Reasons 77

CHAPTER 4 **MIB Reference 83**

CISCO-CNEE-MIB 83

CISCO-SMI 83



About this Guide



Note The documentation set for this product strives to use bias-free language. For purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. While any existing biased terms are being substituted, exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

This guide describes the metrics supported by 5G Session Management Function (SMF). This guide also provides information on how to gather the statistics or counters from its microservices.



CHAPTER 1

SMF Interface for Metrics

- [Feature Description, on page 1](#)
- [How it Works, on page 2](#)
- [Configuring Metrics Collection, on page 2](#)

Feature Description

You can monitor a wide range of application and system statistics, and key performance indicators (KPI) within the SMF infrastructure. KPIs are useful to gain insight into the overall health of the SMF environment. Statistics offer a simplified representation of the SMF configurations and utilization-specific data.

The SMF integrates with Prometheus, a third-party monitoring and alerting solution to capture and preserve the performance data. This data is reported as statistics and can be viewed in the web-based dashboard. Grafana provides a graphical or text-based representation of statistics and counters, which the Prometheus database collects. The Grafana dashboard projects a comprehensive set of quantitative and qualitative data that encourages you to analyze SMF metrics in the reporting tool of your choice and take informed decisions.

By default, the monitoring solution is enabled, which indicates that Prometheus continually monitors your SMF environment and the Prometheus data source is associated with Grafana. You must have the administrative privileges to access Grafana. However, to view a specific dashboard, run the Prometheus queries. The queries are available in the built-in and custom format.

The following snapshot is a sample of the Grafana dashboard.

Figure 1: Grafana Dashboard



How it Works

KPIs constitute of metrics, such as statistics and counters. These metrics represent the performance improvement or degradation. By default, Prometheus is enabled on the system where SMF is deployed, and configured with Grafana. Prometheus dynamically starts monitoring the data sources that are available on the system. For new dashboard panels, execute queries in Prometheus.

For more information about Prometheus, consult the Prometheus documentation at <https://prometheus.io/docs/introduction/overview/>.

Configuring Metrics Collection

The labels of each SMF metrics are classified into the following three categories:

- Production
- Debug
- Granular

All the SMF application metrics are controlled through the CLI command for performance optimization.

To collect the necessary SMF metrics and labels, use the following sample configuration:

```
config
  infra metrics verbose { service | protocol | load-balancer | application
  } [ level { debug | off | production | trace } | metrics metrics_name [
granular-labels label_name | level { debug | off | production | trace } |
pod pod_name | level { debug | off | production | trace } ] ]
end
```

NOTES:

- If the metrics verbosity is not configured, then the default verbosity level for pod type is as follows.
 - LoadBalancer = Production
 - Protocol = Trace
 - Service = Trace
 - Application = Debug
- The order of the level for verbose metrics is in the following priority order:
 - **metrics [[metrics_name] level [production|debug|trace|off]:** [Priority 1]
 - **pod [[pod_Name]] level [production | debug | trace | off]]** [Priority 2]
 - **level [production | debug | trace | off]** [Priority 3]
- **infra metrics verbose { service | protocol | load-balancer | application }**: Enable the metric collection. This configuration helps to collect the required application metrics and labels. By default, this command captures the debug labels of metrics.
- **level { debug | off | production | trace }**: Specify the application metrics category to capture the required application metrics and labels.
 - **debug**: Capture all the labels that are classified as production and debug categories. This option is the default configuration.
 - **off**: Disable the application level metrics collection.
For example, configuring the **infra metrics verbose application smf_service_stats level off** command disables the `smf_service_stats` application metrics.
 - **production**: Capture the labels that are classified as production category.
 - **trace**: This option is not supported for SMF application metrics. If this option is configured, the SMF treats this option as **debug**.
- If production and debug classification is empty for a metrics, then all the labels except granular-labels (if configured) are classified as debug.
- **metrics metrics_name**: Specify the metrics name to capture only the labels that correspond to the given metrics. The metric-level configuration takes precedence over the application-level configuration. If the metrics level is not configured, the labels are captured at the application level.
- **granular-labels**: Capture only the granular labels. By default, this option is disabled.
If a granular label is required for KPI, then that label must be configured. For example, to capture `dnn` labels of `smf_service_stats` metrics, you must configure the following CLI command:
infra metrics verbose application metrics smf_service_stats level debug granular-labels [dnn]

Configuration Example

The following is an example configuration to enable only production level for all the application metrics.

```
infra metrics verbose application level production
```

The following is an example configuration to enable production level for smf_service_stats application metrics and debug level for all other application metrics.

```
infra metrics verbose application smf_service_stats level production
```

The following is an example configuration to enable debug level for smf_service_stats application metrics along with granular labels and production level for all other application metrics.

```
infra metrics verbose application level production smf_service_stats level debug granular-labels [ dnn ]
```

The following is an example configuration to enable production level for smf_service_stats application metrics along with granular labels and debug level for all other application metrics.

```
infra metrics verbose application smf_service_stats level production granular-labels [ dnn ]
```

The following is an example configuration to disable smf_service_stats application metrics and debug level for all other application metrics.

```
infra metrics verbose application smf_service_stats level off
```

The following is an example configuration to configure NSSAI labels of smf_service_stats metrics.

```
infra metrics verbose application metrics smf_service_stats level debug granular-labels [ snssai ]
```



Note The NSSAI statistics are not pegged without configuring the NSSAI label in the granular-labels configuration.

Configuration Verification

To verify the configuration, use the following show command:

```
show running-config infra metrics verbose application
```

The following are example outputs of the **show running-config infra metrics verbose application** command.

```
[smf] smf# show running-config infra metrics verbose application
infra metrics verbose application
metrics smf_service_stats
  level production
  granular-labels [ dnn ]
exit
exit
```

The preceding output indicates that the configuration to capture production labels for smf_service_stats application metrics along with granular labels and debug levels of all other application metrics is enabled.

```
[smf] smf# show running-config infra metrics verbose application
infra metrics verbose application
  level production
metrics smf_service_stats
```

```
    level debug
    granular-labels [ [dnn] ]
  exit
exit
```

The preceding output indicates that the configuration to capture debug labels for smf_service_stats application metrics along with granular labels and production level of all other application metrics is enabled.

To verify the slice information on procedure and session statistics, use the following show command:

```
show running-config infra metrics verbose application
infra metrics verbose application
metrics smf_service_stats
  level debug
  granular-labels [ snssai ]
exit
```




CHAPTER 2

SMF Metrics

- [smf-service Metrics Reference, on page 7](#)

smf-service Metrics Reference

CHF Notification Statistics Category

smf_chf_notification_stats

Description: SMF Charging CHF Notification stats

Sample Query: 'smf_chf_notification_stats{notification_type="reauthorization"}'

Labels:

- Label: `notification_type`
Label Description: Type of notification request
Example: `reauthorization`, `abort_charging`
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: `cisco.com`
- Label: `status`
Label Description: Status of notify message processing
Example: `attempted`, `success`, `failures`
- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: `EUTRA`, `NR`, `WLAN`, `VIRTUAL`, `rat_type_unknown`
- Label: `reason`
Label Description: Reason for notify message failure
Example: `pdu_session_not_established`, `charging_failed`, `offline_converted`

Charging final unit indication statistics Category

chf_recieved_fui_stats

Description: Statistics for final unit indication with final unit action

Sample Query: 'sum (chf_recieved_fui_stats{interface_type="Gy"})'

Labels:

- Label: `chf_type`
Label Description: Type of CHF with which message is exchanged
Example: online, offline
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: N40, Gy
- Label: `fua_type`
Label Description: Type of final unit action
Example: FinalUnitActionType_TERMINATE", "FinalUnitActionType_REDIRECT", "FinalUnitActionType_RESTRICT_ACCESS

Discover Messages Time statistics Category

nf_discover_total_time

Description: Discover Messages Total time statistics

Sample Query: 'nf_discover_total_time{nf_type="amf", host="http://10.105.227.109:8082/nrf-nfm/v1", result="timeouOrRPCError"}'

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: http://10.105.227.109:8082/nrf-nfm/v1
- Label: `result`
Label Description: result of discover message
Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

Discover Messages statistics Category

nf_discover_messages_total

Description: Discover Messages statistics

Sample Query: 'nf_discover_messages_total{nf_type="amf", host="http://10.105.227.109:8082/nnrf-nfm/v1", result="timeouOrRPCError}"'

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: http://10.105.227.109:8082/nnrf-nfm/v1
- Label: `result`
Label Description: result of discover message
Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

Dropped Charging Data Requests Statistics Category

cdr_dropped_stats

Description: The current count for charging data requests dropped due to zero usage

Sample Query: 'cdr_dropped_stats{procedure_type="pdu_sess_create}"'

Labels:

- Label: `procedure_type`
Label Description: The procedure type associated with an call flow procedure
Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

GTPC Message stats Category

smf_gtpc_msg_stats

Description: Stats for GTPC interface messages

Sample Query: 'smf_gtpc_msg_stats{message_type="create_bearer_request"}'

Labels:

- Label: `message_type`

Label Description: GTPC Message Type

Example: `delete_bearer_request`, `create_bearer_request`, `delete_bearer_request_async`, `suspend_notification`, `resume_notification`, `change_notification`

- Label: `status`

Label Description: GTPC message status

Example: `attempted`, `success`, `failures`

- Label: `reason`

Label Description: The reason associated with failure

Example: `ipc_failed`, `sgw_failure`, `EGTP_CAUSE_LOCAL_DETACH`, `EGTP_CAUSE_RAT_CHANGED_FROM_3GPP_TO_NON_3GPP`, `EGTP_CAUSE_COMPLETE_DETACH`, `EGTP_CAUSE_ISR_DEACTIVATION`, `EGTP_CAUSE_ERROR_IND_RCVD_RNC_ENODE`, `EGTP_CAUSE_IMSI_DETACH_ONLY`, `EGTP_CAUSE_REACTIVATION_REQUESTED`, `EGTP_CAUSE_PDN_RECONNECTION_TO_THIS_APN_DISALLOWED`, `EGTP_CAUSE_ACCESS_CHANGED_FROM_NON_3GPP_TO_3GPP`, `EGTP_CAUSE_PDN_CONN_INACTIVITY_TIMER_EXPIRED`, `EGTP_CAUSE_PGW_NOT_RESPONDING`, `EGTP_CAUSE_NETWORK_FAILURE`, `EGTP_CAUSE_QOS_PARAMETER_MISMATCH`, `EGTP_CAUSE_REQ_ACCEPTED`, `EGTP_CAUSE_REQ_ACCEPTED_PARTIALLY`, `EGTP_CAUSE_NEW_PDN_TYPE_NETWORK_PREFERENCE`, `EGTP_CAUSE_NEW_PDN_TYPE_SINGLE_ADDR_BEARER_ONLY`, `EGTP_CAUSE_CONTEXT_NOT_FOUND`, `EGTP_CAUSE_INVALID_MESSAGE_FORMAT`, `EGTP_CAUSE_VERSION_NOT_SUPPORTED_BY_NEXT_PEER`, `EGTP_CAUSE_INVALID_LENGTH`, `EGTP_CAUSE_SERVICE_NOT_SUPPORTED`, `EGTP_CAUSE_MANDATORY_IE_INCORRECT`, `EGTP_CAUSE_MANDATORY_IE_MISSING`, `EGTP_CAUSE_SYSTEM_FAILURE`, `EGTP_CAUSE_NO_RESOURCES_AVAILABLE`, `EGTP_CAUSE_SEMANTIC_ERROR_IN_TFT_OPERATION`, `EGTP_CAUSE_SYNTACTIC_ERROR_IN_TFT_OPERATION`, `EGTP_CAUSE_SEMANTIC_ERROR_IN_PKT_FILTERS`, `EGTP_CAUSE_SYNTACTIC_ERROR_IN_PKT_FILTERS`, `EGTP_CAUSE_MISSING_OR_UNKNOWN_APN`, `EGTP_CAUSE_UNEXPECTED_REPEATED_IE`, `EGTP_CAUSE_GRE_KEY_NOT_FOUND`, `EGTP_CAUSE_REALLOCATION_FAILURE`, `EGTP_CAUSE_DENIED_IN_RAT`, `EGTP_CAUSE_PREFERRED_PDN_TYPE_UNSUPPORTED`, `EGTP_CAUSE_ALL_DYNAMIC_ADDR_OCCUPIED`, `EGTP_CAUSE_UE_CTX_WO_TFT_ALREADY_ACTIVATED`, `EGTP_CAUSE_PROTOCOL_TYPE_NOT_SUPPORTED`, `EGTP_CAUSE_UE_NOT_RESPONDING`, `EGTP_CAUSE_UE_REFUSES`, `EGTP_CAUSE_SERVICE_DENIED`,

EGTP_CAUSE_UNABLE_TO_PAGE_UE, EGTP_CAUSE_NO_MEMORY_AVAILABLE,
 EGTP_CAUSE_USER_AUTHENTICATION_FAILED,
 EGTP_CAUSE_APN_DENIED_NO_SUBSCRIPTION, EGTP_CAUSE_REQUEST_REJECTED,
 EGTP_CAUSE_PTMSI_SIGNATURE_MISMATCH, EGTP_CAUSE_IMSI_IMEI_NOT_KNOWN,
 EGTP_CAUSE_SEMANTIC_ERROR_IN_TAD_OPERATION,
 EGTP_CAUSE_SYNTACTIC_ERROR_IN_TAD_OPERATION,
 EGTP_CAUSE_RESERVED_MESSAGE_VALUE_RECEIVED,
 EGTP_CAUSE_PEER_NOT_RESPONDING,
 EGTP_CAUSE_COLLISION_WITH_NETWORK_INIT_REQUEST,
 EGTP_CAUSE_UNABLE_TO_PAGE_UE_DUE_TO_SUSPENSION,
 EGTP_CAUSE_CONDITIONAL_IE_MISSING, EGTP_CAUSE_INCOMPATIBLE_APN_REST_TYPE,
 EGTP_CAUSE_INVALID_LENGTH_WITH_PIGGYBACK_MSG,
 EGTP_CAUSE_DATA_FORWARDING_NOT_SUPPORTED,
 EGTP_CAUSE_INVALID_REPLY_FROM_REMOTE_PEER,
 EGTP_CAUSE_FALLBACK_TO_GTPV1, EGTP_CAUSE_INVALID_PEER,
 EGTP_CAUSE_TEMP_REJECTED_DUE_TO_HANOVER_IN_PROGRESS,
 EGTP_CAUSE_REQ_REJECTED_FOR_PMIPv6_REASON, EGTP_CAUSE_APN_CONGESTION,
 EGTP_CAUSE_BEARER_HANDLING_NOT_SUPPORTED,
 EGTP_CAUSE_UE_ALREADY_REATTACHED,
 EGTP_CAUSE_MULTI_PDN_CONNECTION_FOR_APN_NOT_ALLOWED,
 EGTP_CAUSE_MME_SGSN_REFUSES_DUE_TO_VPLMN_POLICY,
 EGTP_CAUSE_GTPC_ENTITY_CONGESTION,
 EGTP_CAUSE_TARGET_ACCESS_RESTRICTED_FOR_THE_SUBSCRIBER,
 EGTP_CAUSE_UE_TEMP_NOT_REACHABLE_DUE_TO_POWER_SAVING,
 EGTP_CAUSE_RELOC_FAILURE_DUE_TO_NAS_MSG_REDIRECTION,
 EGTP_CAUSE_MISSING_TIMESTAMP_OPTION,
 EGTP_CAUSE_MULTIPLE_HNP_NOT_ALLOWED, EGTP_CAUSE_SN_MALFORMED_MSG,
 EGTP_CAUSE_INT_TIMEOUT, cbr_fail_upstate_inactive, ubr_fail_upstate_inactive,
 mbc_retransmit_msg, change_notification_retransmit_msg

- Label: qos_5qi

Label Description: 5Qi applicable for the QoS flow

Example: 1, 2, 5

- Label: rat_type

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: smf_current_procedure

Label Description: Current Procedure Name for Message Level Stats

Example: nr_to_untrusted_wifi_handover, eps_fb_ded_brr, PdnDisconnectProcedure,
 enb_to_untrusted_wifi_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod,
 smf_initiated_pdn_detach, untrusted_wifi_to_enb_handover, upf_sess_report_srir_sess_rel,
 utn3gpp_to_5g_handover

Gy Online charging destination host change statistics Category

ocs_dest_host_change_stats

Description: Statistics for charging destination host change

Sample Query: 'sum (ocs_dest_host_change_stats)'

Gy Online charging reporting reason statistics Category

ocs_reporting_reason_stats

Description: Statistics for reporting reason to OCS

Sample Query: 'sum (ocs_reporting_reason_stats{Reporting_Reason="THRESHOLD"})'

Labels:

- Label: rating_group

Label Description: Rating Group for which usage is being reported

Example: Any string

- Label: service_identifier

Label Description: Service Identifier for which usage is being reported

Example: Any string

- Label: Reporting_Reason

Label Description: Type of 3GPP reporting reason from OCS

Example: THRESHOLD, QHT, FINAL, QUOTA_EXHAUSTED, VALIDITY_TIME, OTHER_QUOTA_TYPE, RATING_CONDITION_CHANGE, FORCED_REAUTHORISATION, POOL_EXHAUSTED

Gz Offline CDR drop statistics Category

ofcs_cdr_drop_stats

Description: Statistics for CDR drop with trigger reason

Sample Query: 'sum (ofcs_cdr_drop_stats{TriggerType="final-cdr"})'

Labels:

- Label: procedure_type

Label Description: The procedure name associated with a call flow procedure

Example: Any string

- Label: TriggerType

Label Description: Trigger reason

Example: final-cdr", "external-trigger-cdr", "internal-trigger-cdr

- Label: dnn

Label Description: DNN for which the flow is created

Example: cisco.com

Gz Offline CDR message statistics Category

ofcs_cdr_message_stats

Description: Statistics for CDR message with record closure reason to OFCS

Sample Query: 'sum (ofcs_cdr_message_stats{record_closure_reason="normalRelease"})'

Labels:

- Label: gtp_p_profile

Label Description: gtp profile name used for bearer

Example: Any string

- Label: ruleBase

Label Description: RuleBase name used for bearer

Example: Any string

- Label: record_closure_reason

Label Description: CDR closure reason

Example: normalRelease", "abnormalRelease", "cAMELInitCallRelease", "volumeLimit", "timeLimit", "servingNodeChange", "maxChangeCond", "managementIntervention", "intraSGSNIntersystemChange", "rATChange", "mSTimeZoneChange", "sGSNPLMNIDChange

- Label: dnn

Label Description: DNN for which the flow is created

Example: cisco.com

- Label: triggerType

Label Description: Trigger reason

Example: GZ_SECONDARY_RAT_USAGE_LIMIT_REACHED

Gz Offline SDF Containers statistics Category

ofcs_sdf_container_stats

Description: Statistics for SDF Container with service condition change to OFCS

Sample Query: 'sum (ofcs_sdf_container_stats{service_condition_change="PdpContextRelease"})'

Labels:

- Label: `service_condition_change`

Label Description: Service condition Change for SDF container

Example: QoSChange", "SgsnChange", "SgsnPlmnIdChange", "TariffTimeSwitch", "PdpContextRelease", "RatChange", "ServiceIdleOut", "ConfigurationChange", "ServiceStop", "DccaTimeThresholdReached", "DccaVolumeThresholdReached", "DccaServiceSpecificUnitThresholdReached", "DccaTimeExhausted", "DccaVolumeExhausted", "DccaValidityTimeout", "DccaReauthorisationRequest", "DccaContinueOngoingSession", "DccaRetryAndTerminateOngoingSession", "DccaTerminateOngoingSession", "CgiSaiChange", "RaiChange", "DccaServiceSpecificUnitExhausted", "RecordClosure", "TimeLimit", "VolumeLimit", "ServiceSpecificUnitLimit", "EnvelopeClosure", "EcgiChange", "TaiChange", "UserLocationChange

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

Incoming Message Throttling Statistics Category

smf_inc_msg_throttling_stats

Description: Stats of throttled incoming messages

Sample Query: 'smf_inc_msg_throttling_stats{message_type="S5S8CreateSessReq"}'

Labels:

- Label: `interface`

Label Description: Interface Type

Example: S5, S8, S2B

- Label: `message_type`

Label Description: Message type corresponding to given interface

Example: S5S8CreateSessReq, S5S8DeleteSessReq, S5S8ModifyBearerReq, S5S8ModifyBearerCmd, S5S8BearerResourceCmd, S5S8DeleteBearerCmd

- Label: `Cause`

Label Description: Cause of Message Throttling

Example: EGTP_CAUSE_GTPC_ENTITY_CONGESTION

NF End point selections Category

nf_endpoint_selections_total

Description: NF End Point Selection Statistics

Sample Query: 'nf_endpoint_selections_total{nf_type="amf", host="http://10.105.227.109:8082/nrf-nfm/v1", req="initial"}'

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: `http://10.105.227.109:8082/nrf-nfm/v1`
- Label: `req`
Label Description: req type
Example: initial, fallback,

NF failure handling stats Category

`nf_failure_handling_stats_total`

Description: NF Failure handling stats

Sample Query: `'nf_failure_handling_stats_total{nf_type="amf", host="http://10.105.227.109:8082/nrf-nfm/v1", req="initial", response="202", status="final"}'`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: `http://10.105.227.109:8082/nrf-nfm/v1`
- Label: `req`
Label Description: Request type
Example: initial, fallback,
- Label: `response`
Label Description: Response from the server
Example: 200, 201, 204, `timeout_rpc_error`,
- Label: `status`
Label Description: Status from the server
Example: retry, final

NF management message time statistics Category

nf_management_total_time

Description: NF management messages total time taken

Sample Query: 'nf_management_total_time{host="http://10.105.227.109:8082/nnrf-nfm/v1", direction="outbound", message_type="registration", result="timeouOrRPCError" }'

Labels:

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nnrf-nfm/v1`

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: `inbound`, `outbound`

- Label: `message_type`

Label Description: Type of Message

Example: `registration`, `heartbeat`, `subscription`, `notification`

- Label: `result`

Label Description: result of discover message

Example: `200`, `201`, `204`, `success`, `timeout_rpc_error`, `response_parse_failure`, `request_parse_failure`, `invalid_notify_event`, `invalid_nf_instance_uri`, `internal_error`

NF management messages statistics Category

nf_management_stats_total

Description: NF management messages statistics

Sample Query: 'nf_management_stats_total{host="http://10.105.227.109:8082/nnrf-nfm/v1", direction="outbound", message_type="registration", result="timeouOrRPCError" }'

Labels:

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nnrf-nfm/v1`

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: `inbound`, `outbound`

- Label: `message_type`

Label Description: Type of Message

Example: registration, heartbeat, subscription, notification

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

NRF Discovery Category

nf_discover_events_total

Description: NF Discover Stats

Sample Query: `'nf_discover_events_total{nf_type="pcf", response_type="local"}'`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `response_type`

Label Description: Discovery response choosen from

Example: local, cache, expired-cache

PDU UE Sync Procedure Category

pdu_ue_sync_proc

Description: PDU UE Sync Procedure counter

Sample Query: `'pdu_ue_sync_proc{status="attempted"}'`

Labels:

- Label: `status`

Label Description: call flow procedure status counter

Example: attempted, success, failures, suspend, resume, abort

Policy control ADC pcc rule statistics Category

policy_adc_total

Description: PCC Rule total statistics for ADC

Sample Query: `'sum (policy_adc_total{app_id="abc"})'`

Labels:

- Label: `app_id`
Label Description: ADC Application ID for pcc rule
Example: Any string
- Label: `mute`
Label Description: Mute for ADC rule
Example: true, false
- Label: `operation`
Label Description: Operation performed on the ADC pcc rule
Example: install, modify, remove
- Label: `event`
Label Description: Event associated with the operation performed on the ADC pcc rule
Example: attempted, success, failure, abort
- Label: `gr_instance_id`
Label Description: GR instance ID
Example: Any string
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: pcf, pcrf

Policy control NRF fail action statistics Category

policy_msg_nrf_fail_action

Description: NRF fail action stats for policy messages

Sample Query: `'sum (policy_msg_nrf_fail_action{policy_control_msg="SmPolicyCreate"})'`

Labels:

- Label: `policy_control_msg`
Label Description: Type of policy control message
Example: SmPolicyCreate, SmPolicyUpdate, SmPolicyDelete
- Label: `policy_nrf_action`
Label Description: NRF failure action
Example: ignore, continue, terminate
- Label: `pcf_end_point`
Label Description: PCF IP Address

Example: 10.84.17.11

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

Policy control PCF update statistics Category

policy_pcf_updates_total

Description: Statistics for triggers sent to PCF in SmPolicyUpdate Request to PCF

Sample Query: `'sum (policy_pcf_updates_total{trigger="rat_change"})'`

Labels:

- Label: `trigger`

Label Description: Trigger sent in the policy update request sent to PCF

Example: `ue_ip_change`, `plmn_change`, `res_mod_req`, `access_type_change`, `ue_ip_change`, `credit_mon_sess_fail`, `def_qos_change`, `sess_ambr_change`, `no_credit`, `serving_area_change`, `revalidation_timeout`, `resoure_release`, `resource_alloc`, `rat_change`

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `smf_initiated_pdn_detach`, `disc_pdurel_smf_init_release`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

Policy control active PCF statistics Category

session_policy_type_total

Description: Stats for PCF active Sessions

Sample Query: `'sum (session_policy_type_total{policy_type="local"})'`

Labels:

- Label: `policy_type`

Label Description: Policy type

Example: `local`, `pcf`

- Label: `pcf_address`

Label Description: PCF IP Address

Example: 10.84.17.11

- Label: `access_type`

Label Description: Access type

Example: Ipv4PduSession, Ipv6PduSession, Ipv4V6PduSession

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control current flow Category

policy_pdu_flows_current

Description: QoS flow current counts

Sample Query: 'sum (policy_pdu_flows_current{flow_type="gbr"}) by(qos_5qi, arp)'

Labels:

- Label: `rat_type`

Label Description: RAT type on which the flow is created

Example: nr, WLAN, EUTRA

- Label: `ssc_mode`

Label Description: SSC mode for the session which created the QoS flow

Example: one, two, three

- Label: `pdn_type`

Label Description: PDN type of the session which created the QoS flow

Example: v4, v6, v4v6

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

- Label: `flow_type`

Label Description: Flow type for the QoS flow

Example: gbr, non_gbr

- Label: `qos_5qi`

Label Description: 5Qi applicable for the QoS flow

Example: 1, 2, 5

- Label: `arp`

Label Description: Priority level of ARP applicable for the QoS flow

Example: 10, 20

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

- Label: `mapped_flow`

Label Description: flow has mapped 5Qi or not

Example: `true` , `false`

- Label: `policy_type`

Label Description: policy type for the subscriber session

Example: `pcrf`,`pcf`,`optimized`,`local_policy`

Policy control dynamic pcc rule statistics Category

policy_dynamic_pcc_rules_total

Description: PCC Rule total statistics for dynamic rules pushed from PCF

Sample Query: `'sum (policy_dynamic_pcc_rules_total{rule_id="Rule-1"}) by(qos_5qi, arp)'`

Labels:

- Label: `rule_id`

Label Description: Rule Id for the received dynamic pcc rule

Example: `PccRule-1`

- Label: `operation`

Label Description: Operation performed on the dynamic pcc rule

Example: `install`, `modify`, `remove`

- Label: `event`

Label Description: Event associated with the operation performed on the pcc rule

Example: `attempted`, `success`, `failure`, `abort`

- Label: `qos_5qi`

Label Description: 5Qi applied on the dynamic pcc rule

Example: 1, 2, 5

- Label: `arp`

Label Description: Priority level of ARP applied on the dynamic pcc rule

Example: 10, 20

- Label: `tc_event`

Label Description: Traffic Control event applied on the dynamic pcc rule

Example: `enabled_ul`, `enabled_dl`, `enabled`, `disabled`, `removed`

- Label: `charging_type`

Label Description: Charging type applied on the dynamic pcc rule

Example: `online`, `offline`, `online-offline`

- Label: `charging_method`

Label Description: Charging method applied on the dynamic pcc rule

Example: `volume`, `time`, `vol_time`

- Label: `details`

Label Description: Details on the operation applied on the dynamic pcc rule

Example: `success`, `failed`, `validation_failed`

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `pccrule_change_type`

Label Description: pcc rule parameter change type

Example: `NA`, `binding_param_change`, `no_binding_param_change`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

- Label: `rule_fail_reason`

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid

charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received existing Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID inforamtion for Charging Desc, Missing Service ID inforamtion for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic chargng descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to Ref TC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-Gbr Flow with GBR value, Received Std-QCI Gbr Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule revd with missing rule name, PCC Rule revd with invlaid Flow Description, PCC Rule revd with Invalid ToS Traffic Class, PCC Rule revd with Invalid SecurityParameterIndex, PCC Rule revd with Invalid Flow Label, PCC Rule revd with missing precedence, PCC Rule revd with missing QoS Information, PCC Rule revd with missing QCI in QoS Information, PCC Rule revd with invalid or unsupported QCI in QoS Information, PCC Rule revd with missing ARP priority level in QoS Information, PCC Rule revd with invalid ARP priority level, PCC Rule revd with invalid reporting level, PCC Rule revd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received

Policy control message statistics Category

policy_msg_processing_status

Description: Policy message handling Stats

Sample Query: 'sum
(policy_msg_processing_status{policy_notification_msg="SmPolicyUpdateNotify"})'

Labels:

- Label: `policy_notification_msg`
Label Description: Policy message type
Example: SmPolicyUpdateNotify, SmPolicyTerminate, SmPolicyCreate, SmPolicyUpdate, SmPolicyDelete
- Label: `msg_status`
Label Description: Policy processing message status
Example: accepted, rejected, skipped, attempted, failed, exp_attempted, exp_accepted, exp_rejected, exp_failed
- Label: `pcf_end_point`
Label Description: PCF IP Address
Example: 10.84.17.11
- Label: `rat_type`
Label Description: RAT type of the flow
Example: nr, WLAN, EUTRA
- Label: `result`
Label Description: result of policy message processing
Example: cfg_issue, max_outstanding, send_failure, timeout, proc_timeout, rc_with_err, ex_rc_with_err, none
- Label: `policy_fh_action`
Label Description: Policy CHF action
Example: continue, terminate, none
- Label: `policy_fh_subaction`
Label Description: Policy CHF subaction
Example: discard_traffic, local_fallback, retryserver_on_event, sendccrt_call_term, with_term_req, without_term_req, none
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: pcf, pcrf
- Label: `sess_rel_cause`
Label Description: Session release cause received from policy server in policy response or policy request
Example: unspecified, ue_subscription, insuff_server_res, ip_can_sess_term, ue_ip_addr_rel
- Label: `termination_cause`
Label Description: Termination cause sent in terminate request towards policy server

Example: logout, service_not_provided, bad_answer, administrative, link_broken, auth_expired, user_moved, session_timeout

Policy control pre-defined pcc rule statistics Category

policy_predefined_pcc_rules_total

Description: PCC Rule total statistics for pre-defined rules activated by PCF

Sample Query: 'sum (policy_predefined_pcc_rules_total{rule_id="Rule-1"}) by(event, operation)'

Labels:

- Label: `rulebase`
Label Description: Rulebase to which this pre-defined rule belongs
Example: Rulebase-1
- Label: `operation`
Label Description: Operation performed on the pre-defined pcc rule
Example: install, modify, remove
- Label: `event`
Label Description: Event associated with the operation performed on the pre-defined rule
Example: attempted, success, failure
- Label: `qos_5qi`
Label Description: 5Qi applied on the pre-defined pcc rule
Example: 1, 2, 5
- Label: `arp`
Label Description: Priority level of ARP applied on the pre-defined pcc rule
Example: 10, 20
- Label: `charging_type`
Label Description: Charging type applied on the pre-defined pcc rule
Example: online, offline, online-offline
- Label: `charging_method`
Label Description: Charging method applied on the pre-defined pcc rule
Example: volume, time, vol_time
- Label: `smf_current_procedure`
Label Description: Current procedure associated with the operation performed on the pcc rule
Example: pdn_sess_create, pdu_sess_create, smf_initiated_pdn_detach, disc_pdurel_smf_init_release, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover,

untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

- Label: `rule_fail_reason`

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received existing Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID inforamtion for Charging Desc, Missing Service ID inforamtion for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic chargng descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to RefTC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-Gbr Flow with GBR value, Received Std-QCI Gbr Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule recvd with missing rule name, PCC Rule recvd with invlaid Flow Description, PCC Rule recvd with Invalid ToS Traffic Class, PCC Rule recvd with Invalid SecurityParameterIndex, PCC Rule recvd with Invalid Flow Label, PCC Rule recvd with missing precedence,

PCC Rule recvd with missing QoS Information, PCC Rule recvd with missing QCI in QoS Information, PCC Rule recvd with invalid or unsupported QCI in QoS Information, PCC Rule recvd with missing ARP priority level in QoS Information, PCC Rule recvd with invalid ARP priority level, PCC Rule recvd with invalid reporting level, PCC Rule recvd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received

Policy control rule report statistics Category

pcf_rule_report_stats

Description: Statistics for Rule Report sent to PCF

Sample Query: 'sum (pcf_rule_report_stats{pcf_rule_report_fail_code="INCOR_FLOW_INFO"})'

Labels:

- Label: `pcf_rule_report_fail_code`
Label Description: Failure code sent in RuleReport
Example: INCOR_FLOW_INFO
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: pcf, pcrf

Policy control session rule statistics Category

policy_session_rules_total

Description: Session total statistics for session rules applied

Sample Query: 'sum (policy_session_rules_total{rule_id="SessRule-1"})'

Labels:

- Label: `rule_id`
Label Description: Rule Id for the received session rule from PCF
Example: SessRule-1
- Label: `operation`
Label Description: Operation performed on the session rule
Example: install, modify, remove
- Label: `event`
Label Description: Event associated with the operation performed on the rulebase

Example: attempted, success, failure

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `smf_initiated_pdn_detach`, `disc_pdurel_smf_init_release`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

Policy control static pcc rule statistics Category

`policy_static_pcc_rules_total`

Description: PCC Rule total statistics for static rules activated via rulebase

Sample Query: `'sum (policy_static_pcc_rules_total{rulebase="Rulebase-1"})'`

Labels:

- Label: `rulebase`

Label Description: Rulebase to which the static rules belong

Example: `Rulebase-1`

- Label: `operation`

Label Description: Operation performed on the rulebase

Example: `install`, `remove`

- Label: `event`

Label Description: Event associated with the operation performed on the rulebase

Example: attempted, success, failure

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `smf_initiated_pdn_detach`, `disc_pdurel_smf_init_release`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

- Label: `rule_fail_reason`

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received existing Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID inforamtion for Charging Desc, Missing Service ID inforamtion for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic chargng descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to Ref TC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-Gbr Flow with GBR value, Received Std-QCI Gbr Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule recvd with missing rule name, PCC Rule recvd with invlaid Flow Description, PCC Rule recvd with Invalid ToS Traffic Class, PCC Rule recvd with Invalid SecurityParameterIndex, PCC Rule recvd with Invalid Flow Label, PCC Rule recvd with missing precedence, PCC Rule recvd with missing QoS Information, PCC Rule recvd with missing QCI in QoS Information, PCC Rule recvd with invalid or unsupported QCI in QoS Information, PCC Rule recvd with missing ARP priority level in QoS Information, PCC Rule recvd with invalid ARP priority level, PCC Rule recvd with invalid reporting level, PCC Rule recvd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received

Policy control total flow statistics Category

policy_pdu_flows_total

Description: QoS flow total statistics

Sample Query: 'sum (policy_pdu_flows_total{flow_type="gbr"}) by(qos_5qi, arp) '

Labels:

- Label: `operation`
Label Description: Operation performed on the QoS flow
Example: install, modify, remove
- Label: `event`
Label Description: Event associated with the operation performed on QoS flow
Example: attempted, success, failure, abort
- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: nr, WLAN, EUTRA
- Label: `ssc_mode`
Label Description: SSC mode for the session which created the QoS flow
Example: one, two, three
- Label: `pdn_type`
Label Description: PDN type of the session which created the QoS flow
Example: v4, v6, v4v6
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: cisco.com
- Label: `flow_type`
Label Description: Flow type for the QoS flow
Example: gbr, non_gbr
- Label: `init_or_ho`
Label Description: Flow operation phase
Example: initial, ho
- Label: `qos_5qi`
Label Description: 5Qi applicable for the QoS flow
Example: 1, 2, 5
- Label: `arp`

Label Description: Priority level of ARP applicable for the QoS flow

Example: 10, 20

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

- Label: `mapped_flow`

Label Description: flow has mapped 5Qi or not

Example: `true` , `false`

- Label: `policy_type`

Label Description: policy type for the subscriber session

Example: `pcrf`,`pcf`,`optimized`,`local_policy`

Policy destination host change statistics Category

policy_pcrf_dest_host_change

Description: Statistics for Policy destination host change

Sample Query: `'sum (policy_pcrf_dest_host_change{gr_instance_id="1"})'`

Labels:

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: Any string

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

Radius Authentication Message Stats Category

radius_authentication_message_stats

Description: Stats for Radius Authentication messages

Sample Query:

`'radius_authentication_message_stats{radius_auth_algorithm="radius_auth_algorithm_pap}'`

Labels:

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `radius_auth_algorithm`

Label Description: Radius Authentication Algorithm used

Example: `radius_auth_algorithm_pap`, `radius_auth_algorithm_chap`, `radius_auth_algorithm_mschap`, `radius_auth_algorithm_default`

- Label: `status`

Label Description: Radius Auth message status

Example: `attempted`, `success`, `encode_failed`, `decode_failed`, `failed`

- Label: `reason`

Label Description: The reason associated with failure

Example: `timeout`, `parse_error`, `invalid_code`, `invalid_pco`, `invalid_apco`, `invalid_epco`, `write_error`

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`

Radius Message stats Category

smf_radius_message_stats

Description: Stats for Radius interface messages

Sample Query: `'smf_radius_message_stats{message_type="radius_access_request}'`

Labels:

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: `inbound`, `outbound`

- Label: `message_type`

Label Description: Radius Message Type

Example: `radius_access_request`, `radius_access_accept`

- Label: `radius_avp_type`

Label Description: Radius AVP Type

Example: `radius_avp_pap_username`, `radius_avp_pap_user_password`, `radius_avp_chap_challenge`, `radius_avp_chap_response`, `radius_avp_mschap_challenge`, `radius_avp_mschap_response`, `radius_avp_idle_timeout`, `radius_avp_session_timeout`

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`

SLA Transaction Category

smf_sla_transaction_stats

Description: Transaction SLA stats

Sample Query: `sum(smf_sla_transaction_stats) by (smf_sla_transaction_stats,smf_proc_type,status, message_type)`

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `status`

Label Description: gives status of the procedure

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, Unknown

- Label: `message_type`

Label Description: gives the message type received during sla transaction

Example: IntSelfTxnSla

SMF ADC URR Statistics Category

smf_pfcpc_adc_report_stats

Description: The current count of PFCPC adc reports towards PCF

Sample Query: `'smf_pfcpc_adc_report_stats{adc_report_type="async"}'`

Labels:

- Label: `adc_report_type`

Label Description: Synchronous adc report or Asynchronous adc report

Example: async, sync

- Label: `status`

Label Description: ADC report status

Example: dropped, processed

SMF ALWAYS ON PDU SESSION Category

smf_always_on_session_stats

Description: Always On Pdu Session Statistics

Sample Query: 'smf_always_on_session_stats{status="pdusetup_req_alwayson_requested"}'

Labels:

- Label: `status`

Label Description: always on status statistics

Example: `pdusetup_req_alwayson_requested`, `pdusetup_acc_alwayson_allowed`, `pdusetup_acc_alwayson_not_allowed`, `pdumod_req_alwayson_requested`, `pdumod_cmd_alwayson_allowed`, `pdumod_cmd_alwayson_not_allowed`, `pdumod_cmd_nw_init_alwayson_allowed`, `pdu_utwifit_to_nr_alwayson_requested`, `pdu_utwifit_to_nr_alwayson_allowed`, `pdu_utwifit_to_nr_alwayson_not_allowed`

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: `EUTRA`, `NR`, `WLAN`, `VIRTUAL`, `rat_type_unknown`

- Label: `pdu_type`

Label Description: pdu connection type

Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `ssc_mode`

Label Description: Type of ssc mode associated with the request

Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`

SMF Charging Descriptor Delete Stats Category

smf_chrg_desc_del_stats

Description: The current count of charging descriptors deleted because of all associate Rule Ids are deleted

Sample Query: 'smf_chrg_desc_del_stats{rating_group="10"}'

Labels:

- Label: `charging_id`

Label Description: Charging Descriptor Identifier

Example: Any string

- Label: `rating_group`
Label Description: Rating Group for which charging descriptors is dropped
Example: Any string
- Label: `configured`
Label Description: Configured signifies if a Rule Id is configured or is dynamic
Example: true, false
- Label: `reason`
Label Description: Reason for the charging descriptor delete
Example: Error string value

SMF Charging Descriptor Drop Stats Category

smf_chrg_desc_drop_stats

Description: The current count of charging descriptors dropped due to validation error on Rule Id

Sample Query: `'smf_chrg_desc_drop_stats{rating_group="10"}'`

Labels:

- Label: `rating_group`
Label Description: Rating Group for which charging descriptors is dropped
Example: Any string
- Label: `service_identifier`
Label Description: Service Identifier for which charging descriptors is dropped
Example: Any string
- Label: `action`
Label Description: Action with respect to Rule Id
Example: add, mod, del
- Label: `configured`
Label Description: Configured signifies if Rule Id is configured or is dynamic
Example: true, false
- Label: `reason`
Label Description: Reason for the charging descriptor drop
Example: Error string value

SMF Charging Failure Handling Stats Category

chf_failure_handling_stats

Description: Statistics for application error received from CHF

Sample Query: 'chf_failure_handling_stats(appl_err_code="HTTP_STATUS_CODE_403_FORBIDDEN")'

Labels:

- Label: `http2_err_code`
Label Description: HTTP2 error code received from CHF
Example: HTTP_STATUS_CODE_403_FORBIDDEN
- Label: `appl_err_code`
Label Description: Application error code received from CHF
Example: END_USER_REQUEST_REJECTED, QUOTA_LIMIT_REACHED, CHARGING_FAILED, USER_UNKNOWN, END_USER_REQUEST_DENIED, QUOTA_LIMIT_REACHED, CHARGING_NOT_APPLICABLE
- Label: `fh_action`
Label Description: Action taken on failure from CHF
Example: Terminate, Drop Traffic, Disable Charging
- Label: `fh_exchg_type`
Label Description: CHF Exchange in which failure occurred
Example: update, initial
- Label: `disposition`
Label Description: SMF action on failure
Example: disable-charging, drop-traffic, terminate, convert-offline, allocate-max-quota
- Label: `procedure_type`
Label Description: The procedure type associated with an call flow procedure
Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

SMF Charging Message Stats Category

chf_message_stats

Description: Charging Message Statistics

Sample Query: 'chf_message_stats{procedure_type="charging_initial"}'

Labels:

- Label: `procedure_type`

Label Description: Charging message type

Example: `charging_initial`, `charging_update`, `charging_terminate`

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: `cisco.com`

- Label: `status`

Label Description: Status of OOO usage report processing

Example: `attempted`, `success`, `timeout`

- Label: `rat_type`

Label Description: RAT type on which the flow is created

Example: `EUTRA`, `NR`, `WLAN`, `VIRTUAL`, `rat_type_unknown`

- Label: `chf_type`

Label Description: Type of CHF with which message is exchanged

Example: `online`, `offline`

- Label: `smf_current_procedure`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`, `nw_req_service_active`, `upf_notify_downlink_data`, `xn_path_switch`, `pdn_sess_create`, `pdn_5g_4g_handover`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `n2_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `n26_4g_to_5g_im_mobility`, `pdu_im`, `pdn_sess_create`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `pcf_initiated_pdn_detach`, `smf_initiated_pdn_detach`, `upf_initiated_pdn_detach`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `N40`, `Gy`

SMF Charging OOO Usage Report Stats Category

smf_ooo_usage_report

Description: The current count for OOO usage report

Sample Query: 'smf_ooo_usage_report{procedure_type="pdu_sess_create"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

- Label: `status`

Label Description: Status of OOO usage report processing

Example: attempted, success, timeout

SMF Charging PFCP usage Report Stats Category

smf_pfcf_usage_report_stats

Description: The current count of PFCP usage reports towards CHF

Sample Query: 'smf_pfcf_usage_report_stats{usage_report_type="async"}'

Labels:

- Label: `usage_report_type`

Label Description: Synchronous usage report or Asynchronous usage report

Example: async, sync

- Label: `status`

Label Description: Usage report status

Example: recieved, dropped, ignored, processed

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

- Label: usage_report_discard_reason

Label Description: Reason for usage report rejection

Example: uuc_endc_cond_not_met, charg_parm_not_found, start_of_traffic_rcvd, ignore_rule_base_urr, no_valid_trgr_present, ignore_immd_trgr, urr_not_present, no_term_and_drop_traffic, onlinrpt_false_or_drop_traffic, mandatory_ie_incorrect, session_ctxt_not_found, radius_accounting, radius_accounting_not_enabled, urr_or_radius_accounting_missing

SMF Charging Quota Event Stats Category

chf_quota_event_stats

Description: The current count for quota event received from CHF

Sample Query: 'chf_quota_event_stats{quota_type="initial"}'

Labels:

- Label: rating_group

Label Description: Rating group for which quota is received from CHF

Example: Any string

- Label: quota_type

Label Description: Quota type as received from CHF

Example: initial, update, initial_final, update_final, fail

- Label: quota_method

Label Description: Quota method received from CHF

Example: time, volume, time_volume

- Label: quota_status

Label Description: Result for the quota received from CHF

Example: SUCCESS, END_USER_SERVICE_DENIED, QUOTA_MANAGEMENT_NOT_APPLICABLE, QUOTA_LIMIT_REACHED, END_USER_SERVICE_REJECTED, RATING_FAILED

- Label: quota_fail_action

Label Description: Action on quota failure

Example: No Action , Disable charging, Drop Traffic, Offline Converted

- Label: `service_identifier`

Label Description: Service Identifier for CHF quota event

Example: Any string

SMF Charging Radius Accounting Message Stats Category

radius_accounting_message_stats

Description: SMF Radius accounting message stats

Sample Query: `'radius_accounting_message_stats{procedure_type="radius_initial"}'`

Labels:

- Label: `procedure_type`
Label Description: Charging Radius message type
Example: `radius_initial`, `radius_update`, `radius_terminate`
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: `cisco.com`
- Label: `status`
Label Description: Status of Radius charging message processing
Example: `attempted`, `success`, `failures`
- Label: `reason`
Label Description: Reason for Radius message failure
Example: `error`, `reject`, `timeout`, `invalid_arg`
- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: `EUTRA`, `NR`, `WLAN`, `VIRTUAL`, `rat_type_unknown`

SMF Charging Session Limit Dynamic Stats Category

chf_sess_limit_dynamic_stats

Description: SMF Charging Session Limit stats

Sample Query:

`'chf_sess_limit_dynamic_stats{chf_sess_limit_dyn_reason="chf_sess_limit_dyn_del_all_trig_disabled"}'`

Labels:

- Label: `chf_sess_limit_dyn_reason`

Label Description: Reason for Charging session limit stats

Example: `chf_sess_limit_dyn_del_all_trig_disabled`, `chf_sess_limit_dyn_del_vol_time_nil`, `chf_sess_limit_dyn_add_in_cdru`

SMF Charging Usage Report Stats Category

`chf_usage_report_stats`

Description: The current count for usage reports towards CHF

Sample Query: `'chf_usage_report_stats(charging_method="offline")'`

Labels:

- Label: `rating_group`

Label Description: Rating Group for which usage is being reported

Example: Any string

- Label: `service_identifier`

Label Description: Service Identifier for which usage is being reported

Example: Any string

- Label: `charging_method`

Label Description: Metering method for the PDU Session

Example: `online`, `offline`, `online_offline`

- Label: `charging_trigger_type`

Label Description: Trigger for usage report

Example: `QUOTA_THRESHOLD`, `QHT`, `FINAL`, `QUOTA_EXHAUSTED`, `VALIDITY_TIME`, `OTHER_QUOTA_TYPE`, `FORCED_REAUTHORISATION`, `UNIT_COUNT_INACTIVITY_TIMER`, `ABNORMAL_RELEASE`, `QOS_CHANGE`, `VOLUME_LIMIT`, `TIME_LIMIT`, `EVENT_LIMIT`, `PLMN_CHANGE`, `USER_LOCATION_CHANGE`, `RAT_CHANGE`, `UE_TIMEZONE_CHANGE`, `TARIFF_TIME_CHANGE`, `MAX_NUMBER_OF_CHANGES_IN_CHARGING_CONDITIONS`, `MANAGEMENT_INTERVENTION`, `CHANGE_OF_UE_PRESENCE_IN_PRESENCE_REPORTING_AREA`, `CHANGE_OF_3GPP_PS_DATA_OFF_STATUS`, `SERVING_NODE_CHANGE`, `REMOVAL_OF_UPF`, `ADDITION_OF_UPF`, `START_OF_SERVICE_DATA_FLOW`, `AMBR_CHANGE`

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`,

nw_req_service_active, upf_notify_downlink_data,
 xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete,
 pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility,
 pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod,
 pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

SMF Charging Zero Usage Report Stats Category

chf_zero_usage_report_stats

Description: The current count for usage reports dropped due to zero usage

Sample Query: 'chf_zero_usage_report_stats{measurement_type="volume"}'

Labels:

- Label: measurement_type

Label Description: Measurement type

Example: volume, duration, duration-volume

- Label: charging_trigger_type

Label Description: Trigger for usage report

Example: QUOTA_THRESHOLD, QHT, FINAL, QUOTA_EXHAUSTED, VALIDITY_TIME,
 OTHER_QUOTA_TYPE, FORCED_REAUTHORISATION, UNIT_COUNT_INACTIVITY_TIMER,
 ABNORMAL_RELEASE, QOS_CHANGE, VOLUME_LIMIT, TIME_LIMIT, EVENT_LIMIT,
 PLMN_CHANGE, USER_LOCATION_CHANGE, RAT_CHANGE, UE_TIMEZONE_CHANGE,
 TARIFF_TIME_CHANGE, MAX_NUMBER_OF_CHANGES_IN_CHARGING_CONDITIONS,
 MANAGEMENT_INTERVENTION,
 CHANGE_OF_UE_PRESENCE_IN_PRESENCE_REPORTING_AREA,
 CHANGE_OF_3GPP_PS_DATA_OFF_STATUS, SERVING_NODE_CHANGE, REMOVAL_OF_UPF,
 ADDITION_OF_UPF, START_OF_SERVICE_DATA_FLOW, AMBR_CHANGE

SMF DB Marshal Category

smf_db_marshall_stats

Description: SMF DB marshal stats

Sample Query: sum(smf_db_marshall_stats) by (module)

Labels:

- Label: module

Label Description: module type counter

Example: policy, charging, upserv, access, generic

SMF Data Consistency Check Category

smf_datacheck_stats

Description: Total number of sessions checked for consistency

Sample Query: 'smf_datacheck_stats{rat_type="NR", status="failed"}'

Labels:

- Label: `procedure_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `rat_type`

Label Description: Type of the radio access associated

Example: EUTRA, NR, WLAN, VIRTUAL, rat_type_unknown

- Label: `pdu_type`

Label Description: Type of PDU session

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `status`

Label Description: Procedure status after data consistency check

Example: success, failed

- Label: `reason`

Label Description: Failure reason of data inconsistency

Example: invalid_n4_data_in_txn_start, invalid_n4_data_in_txn_end, invalid_n7_data_in_txn_start, invalid_n7_data_in_txn_end, invalid_n40_data_in_txn_start, invalid_n40_data_in_txn_end

SMF Disconnect stats Category

smf_disconnect_stats

Description: SMF Disconnect stats counters

Sample Query: 'smf_disconnect_stats{reason="disc_pdu_rel_amf_init_detach"}'

Labels:

- Label: `rat_type`

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: `reason`

Label Description: The reason associated with an call disconnect

Example: disc_pdusetup_create_over_create, disc_pdusetup_release_over_create, disc_pdusetup_admin_clear, disc_pdusetup_n1_decode_failure, disc_pdusetup_n1_content_not_found, disc_pdusetup_sess_abs_timeout, disc_pdusetup_sess_idle_timeout, disc_pdusetup_sess_cp_idle_timeout, disc_pdusetup_sess_default_flow_only_timeout, disc_pdusetup_ssc_mode_not_supported, disc_pdusetup_ssc_mode_denied, disc_pdusetup_identity_conflict, disc_pdusetup_pdtype_unsupported, disc_pdusetup_pdtype_denied, disc_pdusetup_snsai_denied, disc_pdusetup_dnn_denied, disc_pdusetup_iwf_denied, disc_pdusetup_subscription_denied, disc_pdusetup_dnn_not_supported, disc_pdusetup_dnn_not_supported_in_slice, disc_pdusetup_network_failure, disc_pdusetup_pdu_sess_does_not_exist, disc_init_chg_data_err, disc_pdusetup_ip_alloc_failed, disc_pdusetup_static_ip_alloc_failed, disc_pdusetup_pdu_fetch_failure, disc_pdusetup_udm_reg_failed, disc_pdusetup_udm_sub_fetch_failure, disc_pdusetup_udm_sub_fetch_resp_failed, disc_pdusetup_udm_sub_notify_failed, disc_pdusetup_upf_setup_cause_not_accepted, disc_pdusetup_secondary_auth_failed, disc_pdusetup_secondary_auth_resp_failed, disc_pdusetup_sm_cxt_invalid, disc_pdusetup_sm_cxt_invalid_ie, disc_pdusetup_sm_cxt_sess_id_err, disc_pdusetup_sm_cxt_invalid_json, disc_pdusetup_sm_cxt_n1_process_failed, disc_pdusetup_sm_cxt_man_param_missing, disc_pdusetup_pcf_create_exchg_failure, disc_pdusetup_pcf_create_rsp_failure, disc_pdusetup_rm_exchg_failure, disc_pdusetup_rm_rsp_failure, disc_pdusetup_pcf_update_exchg_failure, disc_pdusetup_pcf_update_rsp_failure, disc_chf_data_exchg_failure, disc_chf_data_rsp_failure, disc_pdusetup_upf_setup_exchg_failure, disc_pdusetup_upf_setup_rsp_failure, disc_pdusetup_n1n2_transfer_exchg_failure, disc_pdusetup_n1n2_transfer_rsp_failure, disc_pdusetup_n2_setup_failed, disc_pdusetup_ue_init_release, disc_pdusetup_amf_assign_ebi_failure, disc_pdusetup_upf_modify_exchg_failure, disc_pdusetup_upf_modify_rsp_failure, disc_pdusetup_upf_modify_failed, disc_pdusetup_upf_serv_data_nill, disc_pdusetup_upf_dl_tunnel_info_not_found, disc_pdusetup_upf_tunnel_id_not_found, disc_pdusetup_upf_mod_gnb_tun_params_failed, disc_pdusetup_upf_mod_rsra_tun_params_failed, disc_pdusetup_upf_mod_tun_param_tos_failed, disc_pdusetup_smf_mop_offline, disc_pdusetup_sm_context_nssai_not_supported, disc_pdusetup_sm_context_network_failure, disc_pdusetup_lbo_rejected, disc_pdusetup_home_route_not_supported, disc_pdusetup_internal_error, disc_pdusetup_plmn_not_supported, disc_pdurel_amf_sends_ue_not_found, disc_pdusetup_dnn_missing, disc_pdusetup_udm_dnn_missing, disc_pdusetup_resource_mgr_rsp_failed, disc_pdusetup_apply_wps_failed, disc_pdurel_ue_init_release, disc_pdurel_amf_init_release, disc_pdurel_amf_init_release_404, disc_pdurel_amf_init_release_mod_req, disc_pdurel_pcf_reconciliation, disc_rel_chf_err, disc_pdurel_pcf_init_release, disc_pdurel_udm_init_release, disc_pdurel_gnb_init_release, disc_pdurel_smf_init_release, disc_pdurel_upf_init_association_release, disc_pdurel_radius_init_release, disc_pdurel_upf_init_path_failure, disc_pdurel_upf_recovered, disc_pdurel_config_change, disc_db_conflict_release, disc_pdurel_pcf_reconciliation, disc_n2ho_n4_modify_failed, disc_n2ho_failure, disc_n2ho_guard_timer_expiry, disc_n2ho_idft_timer_expiry, disc_n26_4g_5g_ho_n4_modify_failed, disc_n26_4g_5g_im_mobility_n4_modify_failed, disc_pdumodify_context_not_found, disc_pdumodify_invalid_pdu_sess_identity, disc_pdurelease_invalid_pdu_sess_identity, disc_pduim_context_not_found, disc_n26_4g_5g_ho, disc_n26_5g_4g_ho, disc_n26_5g_4g_ho_timer_expired_post_exec, disc_n26_4g_5g_ho_udm_reg_failed, disc_n26_5g_4g_ho_mbr_failed, disc_pdusetup_upf_rule_creation_mod_failure, disc_non3gpp_utn_5g_ho, disc_5gtonon3gpp_utn_ho, disc_4g_non3gpp_utn_ho, disc_non3gpp_utn_4g_ho, disc_enb_wifi_ho_failed, disc_utn3gpp_5g_ho_failed, disc_sess_report_srsr_pdu_sess_rel, disc_pdn_ue_init_release, disc_pdn_mme_init_release, disc_pdn_chf_reconciliation, disc_pdn_pcf_reconciliation, disc_pdn_pcf_init_release, disc_pdn_pcf_fallback, disc_pdn_udm_init_release, disc_pdn_chf_init_release, disc_pdn_upf_init_release, disc_admin_init_release, disc_sess_time_exp_release, disc_sess_cp_idle_time_exp_release,

disc_session_recreate, disc_gtpc_peer_pathfail, disc_gtpc_peer_restart, disc_upf_init_path_failure, disc_transaction_timedout, disc_upf_recovered, disc_sgw_ctx_failure, disc_pdn_internal_release, disc_reason_unknown,, disc_pdnsetup_iwk_5gs_flag_false, disc_pdnsetup_pduid_init_failed, disc_pdnsetup_csr_invalid, disc_pdnsetup_udm_reg_failed, disc_pdnsetup_udm_reg_req_create_failed, disc_pdnsetup_udm_rpc_failed, disc_pdnsetup_udm_dnn_missing, disc_pdnsetup_udm_reg_resp_failed, disc_pdnsetup_udm_sub_fetch_failed, disc_pdnsetup_udm_sub_fetch_resp_failed, disc_pdnsetup_udm_sub_notify_failed, disc_pdnsetup_udm_sub_notify_resp_failed, disc_pdnsetup_udm_sgw_u_teid_missing, disc_pdnsetup_secondary_auth_failed, disc_pdnsetup_secondary_auth_resp_failed, disc_pdnsetup_secondary_auth_ip_addr_conflict, disc_pdnsetup_pcf_create_failed, disc_pdnsetup_pcf_create_resp_failed, disc_pdnsetup_pcf_update_req_create_failed, disc_pdnsetup_pcf_update_exchg_failed, disc_pdnsetup_pcf_update_resp_failed, disc_pdnsetup_resource_mgr_exchg_failed, disc_pdnsetup_resource_mgr_resp_failed, disc_pdnsetup_upf_sess_setup_exchg_failed, disc_pdnsetup_upf_sess_setup_resp_failed, disc_pdnsetup_upf_sgw_tunnelid_error, disc_pdnsetup_upf_local_fteid_error, disc_pdnsetup_ssc_mode_denied, disc_pdnsetup_pdu_type_denied, disc_pdnsetup_pdu_type_not_supported, disc_pdnsetup_ssc_mode_not_supported, disc_pdnsetup_subscription_denied, disc_pdnsetup_smf_mop_offline, disc_pdnsetup_plmn_not_supported, disc_pdnsetup_non5gcapableue_not_allowed, disc_pdnsetup_default_flow_only_timeout, disc_affinity_add_error, disc_pdnsetup_sgwctx_brr_data_invalid, disc_ue_int_n1_5g_sm_status, disc_pdu_ctx_not_found, disc_internal_affinity_add_error, upf_sess_report_gter_pdn_sess_rel, upf_sess_report_srir_pdn_sess_rel, upf_sess_report_spter_pdn_sess_rel, upf_sess_report_srsr_pdn_sess_rel, upf_sess_report_erir_pdn_sess_rel, upf_sess_report_upir_pdn_sess_rel, disc_sess_report_srsr_pdn_sess_rel, disc_originatingEntity_request_timed_out, disc_new_pdn_type_due_to_single_addr_bearer_only, disc_new_pdn_type_due_to_network_preference, disc_pdnsetup_dnn_missing_or_unknown, disc_request_timeout_at_originating_entry, disc_pdusetup_integrity_protected_mdr_not_acceptable, disc_pdnsetup_upip_status_req_denied_in_rat, disc_pdn_pcrf_init_release, disc_pdnsetup_pcrf_create_resp_failed, disc_pdnsetup_charging_create_resp_failed, disc_vsmf_insert_dtssa_acscr_not_configured, disc_vsmf_insert_interplmn_ho_not_configured, disc_vsm_insert_hsmf_retrieve_failure, disc_ro2ho_n2ho_interplmn_ho_not_configured, disc_ro2ho_n4_modify_failed, disc_ho2ro_n4_modify_failed, disc_ho2ro_failure disc_ro2ho_failure, disc_ro2ho_guard_timer_expiry, disc_ho2ro_guard_timer_expiry

SMF EBI stats Category

smf_ebi_stats

Description: Stats for the EBI Assignment

Sample Query: 'smf_ebi_stats{status="success"}'

Labels:

- Label: procedure_type

Label Description: The procedure type associated with an call flow procedure

Example: pdusetup_ebi_assignment

- Label: status

Label Description: status of EBI Assignment

Example: attempted, success, failures

SMF IPAM Address Events Current Counter Category

IPAM_address_allocations_current

Description: Current state of SMF IPAM Address allocations

Sample Query:

```
'IPAM_address_allocations_current(dnn='dnn',servingArea='area1',nssai='slice1',pool='p1',allocationType='dynamic',addressType='IPv4',upf='upf1',grInstId='1')
```

Labels:

- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `servingArea`
Label Description: name of the serving area associated with the request
Example: Any string
- Label: `nssai`
Label Description: name of the nssai associated with the request
Example: Any string
- Label: `pool`
Label Description: name of the pool associated with the request
Example: Any string
- Label: `allocationType`
Label Description: type of allocation associated with the request
Example: static/dynamic
- Label: `addressType`
Label Description: address type associated with the request
Example: IPv4/IPv6PD
- Label: `upf`
Label Description: upf identifier associated with the request
Example: Any string
- Label: `grInstId`
Label Description: GR Instance ID
Example: 1 or 2

SMF IPAM Address Events Total Counter Category

IPAM_address_events_total

Description: Total number of SMF IPAM Address events

Sample Query:

```
'IPAM_address_events_total(dn='dn1',servingArea='area1',nssai='slice1',pool='pl',eventType='Allocation',allocationType='dynamic',addressType='IPv4',upf='up1',grInstId='1')
```

Labels:

- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `servingArea`
Label Description: name of the serving area associated with the request
Example: Any string
- Label: `nssai`
Label Description: name of the nssai associated with the request
Example: Any string
- Label: `pool`
Label Description: name of the pool associated with the request
Example: Any string
- Label: `eventType`
Label Description: type of event associated with the request
Example: Allocation/Release
- Label: `allocationType`
Label Description: type of allocation associated with the request
Example: static/dynamic
- Label: `addressType`
Label Description: address type associated with the request
Example: IPv4/IPv6PD
- Label: `upf`
Label Description: upf identifier associated with the request
Example: Any string
- Label: `grInstId`
Label Description: GR Instance ID
Example: 1 or 2

SMF IPAM Chunk Events Current Counter Category

IPAM_chunk_allocations_current

Description: Current state of SMF IPAM Address Chunk allocations

Sample Query:

```
'IPAM_chunk_allocations_current(dn='dn1',servingArea='areal',nssai='slicel',pool='pl',addressType='IPv4',upf='upl',grInstId='1',forRemoteSmf='true)'
```

Labels:

- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `servingArea`
Label Description: name of the serving Area associated with the request
Example: Any string
- Label: `nssai`
Label Description: name of the nssai associated with the request
Example: Any string
- Label: `pool`
Label Description: name of the pool associated with the request
Example: Any string
- Label: `addressType`
Label Description: address type associated with the request
Example: IPv4/IPv6PD
- Label: `upf`
Label Description: upf identifier associated with the request
Example: Any string
- Label: `grInstId`
Label Description: GR Instance ID
Example: 1 or 2
- Label: `forRemoteSmf`
Label Description: Indicates if chunk is reserved for Remote SMF
Example: true/false

SMF IPAM Address Events Total Counter Category

IPAM_address_events_total

Description: Total number of SMF IPAM Address events

Sample Query:

```
'IPAM_address_events_total(dn='dn1',servingArea='area1',nssai='slice1',pool='pl',eventType='Allocation',allocationType='dynamic',addressType='IPv4',upf='upf1',grInstId='1')
```

Labels:

- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `servingArea`
Label Description: name of the serving area associated with the request
Example: Any string
- Label: `nssai`
Label Description: name of the nssai associated with the request
Example: Any string
- Label: `pool`
Label Description: name of the pool associated with the request
Example: Any string
- Label: `eventType`
Label Description: type of event associated with the request
Example: Allocation/Release
- Label: `allocationType`
Label Description: type of allocation associated with the request
Example: static/dynamic
- Label: `addressType`
Label Description: address type associated with the request
Example: IPv4/IPv6PD
- Label: `upf`
Label Description: upf identifier associated with the request
Example: Any string
- Label: `grInstId`
Label Description: GR Instance ID
Example: 1 or 2

SMF N1 Message stats Category

smf_n1_message_stats

Description: Stats for N1 Messages

Sample Query: 'smf_n1_message_stats{procedure_type="pcf_req_pdu_sess_mod"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`, `nw_req_service_active`, `upf_notify_downlink_data`, `xn_path_switch`, `pdn_sess_create`, `pdn_5g_4g_handover`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `n2_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `n26_4g_to_5g_im_mobility`, `pdu_im`, `pdn_sess_create`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `pcf_initiated_pdn_detach`, `smf_initiated_pdn_detach`, `upf_initiated_pdn_detach`, `smf_eps_fb`

- Label: `direction`

Label Description: Direction of N1 message

Example: `outbound`, `inbound`

- Label: `message_type`

Label Description: The N1 message type

Example: `pdu_session_establishment_reject`, `pdu_session_release_request`, `pdu_session_modification_command_reject`, `pdu_session_modification_reject`, `pdu_session_release_reject`, `5g_sm_status_msg_release`, `5g_sm_status_msg_no_action`, `5g_sm_status_msg_invalid_pti`

- Label: `n1_cause`

Label Description: N1 cause associated with the message

Example: `OPERATOR_DETERMINED_BARRING`, `INSUFFICIENT_RESOURCES`, `MISSING_OR_UNKNOWN_DNN`, `UNKNOWN_PDU_SESSION_TYPE`, `USER_AUTHENTICATION_OR_AUTHORIZATION_FAILED`, `REQUEST_REJECTED_UNSPECIFIED`, `SERVICE_OPTION_NOT_SUPPORTED`, `REQUESTED_SERVICE_OPTION_NOT_SUBSCRIBED`, `SERVICE_OPTION_TEMPORARILY_OUT_OF_ORDER`, `PTI_ALREADY_IN_USE`, `REGULAR_DEACTIVATION`, `NETWORK_FAILURE`, `REACTIVATION_REQUESTED`, `SEMANTIC_ERROR_IN_THE_TFT_OPERATION`, `SYNTACTICAL_ERROR_IN_THE_TFT_OPERATION`, `INVALID_PDU_SESSION_IDENTITY`, `SEMANTIC_ERRORS_IN_PACKET_FILTER`, `SYNTACTICAL_ERROR_IN_PACKET_FILTER`, `OUT_OF_LADN_SERVICE_AREA`, `PTI_MISMATCH`, `PDU_SESSION_TYPE_IPV4_ONLY_ALLOWED`, `PDU_SESSION_TYPE_IPV6_ONLY_ALLOWED`, `PDU_SESSION_DOES_NOT_EXIST`, `INSUFFICIENT_RESOURCES_FOR_SPECIFIC_SLICE_AND_DNN`, `NOT_SUPPORTED_SSC_MODE`, `INSUFFICIENT_RESOURCES_FOR_SPECIFIC_SLICE`, `MISSING_OR_UNKNOWN_DNN_IN_A_SLICE`, `INVALID_PTIValue`

MAXIMUM_DATA_RATE_PER_UE_FOR_USER_PLANE_INTEGRITY_PROTECTION_IS_TOO_LOW,
 SEMANTIC_ERROR_IN_THE_QOS_OPERATION,
 SYNTACTICAL_ERROR_IN_THE_QOS_OPERATION,
 INVALID_MAPPED_EPS_BEARER_IDENTITY, SEMANTICALLY_INCORRECT_MESSAGE,
 INVALID_MANDATORY_INFORMATION,
 MESSAGE_TYPE_NON_EXISTENT_OR_NOT_IMPLEMENTED,
 MESSAGE_TYPE_NOT_COMPATIBLE_WITH_THE_PROTOCOL_STATE,
 INFORMATION_ELEMENT_NON_EXISTENT_OR_NOT_IMPLEMENTED,
 CONDITIONAL_IE_ERROR, MESSAGE_NOT_COMPATIBLE_WITH_THE_PROTOCOL_STATE,
 PROTOCOL_ERROR_UNSPECIFIED

SMF N2 Message stats Category

smf_n2_message_stats

Description: Stats for N2 Messages

Sample Query: 'smf_n2_message_stats{procedure_type="pcf_req_pdu_sess_mod"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod,
 udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel,
 pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel,
 chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active,
 nw_req_service_active, upf_notify_downlink_data,
 xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete,
 pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility,
 pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod,
 pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb

- Label: `direction`

Label Description: Direction of N2 message

Example: outbound, inbound

- Label: `n2_Ngap_ie_type`

Label Description: The N2 Ngap IE type

Example: N2_PDU_SESSION_RESOURCE_RELEASE_COMMAND_TRANSFER,
 N2_PDU_SESSION_PATH_SWITCH_REQUEST_TRANSFER,
 N2_INVALID_OR_UNSUPPORTED_NGAP_IE_TYPE,
 N2_PDU_SESSION_PATH_SWITCH_REQUEST_SETUP_FAILED_TRANSFER,
 N2_PDU_SESSION_RESOURCE_SETUP_UNSUCCESS_TRANSFER,
 N2_PDU_SESSION_RESOURCE_NOTIFY_RELEASED_TRANSFER,
 N2_PDU_SESSION_RESOURCE_MODIFY_UNSUCCESS_TRANSFER,
 N2_PDU_SESSION_HANDOVER_REQUEST_ACK_TRANSFER,
 N2_PDU_SESSION_HANDOVER_RESOURCE_ALLOC_UNSUCCESS_TRANSFER,

N2_INVALID_OR_UNSUPPORTED_NGAP_TYPE,
N2_PDU_SESSION_RESOURCE_SETUP_RESPONSE_TRANSFER

- Label: n2_cause_group

Label Description: The N2 Cause Group

Example: NgapCauseGroupEnum_RadioNetworkCause, NgapCauseGroupEnum_TransportLayerCause,
NgapCauseGroupEnum_NASCause, NgapCauseGroupEnum_ProtocolCause,
NgapCauseGroupEnum_MiscCause, NgapCauseGroupEnum_NgapCauseGroupDummy

- Label: n2_cause

Label Description: N2 cause associated with the message

Example: NgapCauseEnum_RadioNetwork_DummyEnum, NgapCauseEnum_RadioNetwork_Unspecified,
NgapCauseEnum_RadioNetwork_TXnRELOCoverall_expiry,
NgapCauseEnum_RadioNetwork_Successful_handover,
NgapCauseEnum_RadioNetwork_Release_due_to_NG_RAN_generated_reason,
NgapCauseEnum_RadioNetwork_Release_due_to_5GC_generated_reason,
NgapCauseEnum_RadioNetwork_Handover_cancelled,
NgapCauseEnum_RadioNetwork_Partial_handover,
NgapCauseEnum_RadioNetwork_Handover_failure_in_target_5GC_NG_RAN_node_or_target_system,
NgapCauseEnum_RadioNetwork_Handover_target_not_allowed,
NgapCauseEnum_RadioNetwork_TNGRELOCoverall_expiry,
NgapCauseEnum_RadioNetwork_TNGRELOCprep_expiry,
NgapCauseEnum_RadioNetwork_Cell_not_available,
NgapCauseEnum_RadioNetwork_Unknown_target_ID,
NgapCauseEnum_RadioNetwork_No_radio_resources_available_in_target_cell,
NgapCauseEnum_RadioNetwork_Unknown_local_UE_NGAP_ID,
NgapCauseEnum_RadioNetwork_Inconsistent_remote_UE_NGAP_ID,
NgapCauseEnum_RadioNetwork_Handover_desirable_for_radio_reasons,
NgapCauseEnum_RadioNetwork_Time_critical_handover,
NgapCauseEnum_RadioNetwork_Resource_optimisation_handover,
NgapCauseEnum_RadioNetwork_Reduce_load_in_serving_cell,
NgapCauseEnum_RadioNetwork_User_inactivity,
NgapCauseEnum_RadioNetwork_Radio_connection_with_UE_lost,
NgapCauseEnum_RadioNetwork_Radio_resources_not_available,
NgapCauseEnum_RadioNetwork_Invalid_QoS_combination,
NgapCauseEnum_RadioNetwork_Failure_in_the_radio_interface_procedure,
NgapCauseEnum_RadioNetwork_Interaction_with_other_procedure,
NgapCauseEnum_RadioNetwork_Unknown_PDU_Session_ID,
NgapCauseEnum_RadioNetwork_Unknown_QoS_Flow_ID,
NgapCauseEnum_RadioNetwork_Multiple_PDU_Session_ID_Instances,
NgapCauseEnum_RadioNetwork_Multiple_QoS_Flow_ID_Instances,
NgapCauseEnum_RadioNetwork_Encryption_and_or_integrity_protection_algorithms_not_supported,
NgapCauseEnum_RadioNetwork_NG_intra_system_handover_triggered,
NgapCauseEnum_RadioNetwork_NG_inter_system_handover_triggered,
NgapCauseEnum_RadioNetwork_Xn_handover_triggered,
NgapCauseEnum_RadioNetwork_Not_supported_5QI_value,
NgapCauseEnum_RadioNetwork_UE_context_transfer,
NgapCauseEnum_RadioNetwork_IMS_voice_EPS_fallback_or_RAT_fallback_triggered,
NgapCauseEnum_RadioNetwork_UP_integrity_protection_not_possible,
NgapCauseEnum_RadioNetwork_UP_confidentiality_protection_not_possible,

NgapCauseEnum_RadioNetwork_Slice_not_supported,
 NgapCauseEnum_RadioNetwork_UE_in_RRC_INACTIVE_state_not_reachable,
 NgapCauseEnum_RadioNetwork_Redirection,
 NgapCauseEnum_RadioNetwork_Resources_not_available_for_the_slice,
 NgapCauseEnum_RadioNetwork_UE_maximum_integrity_protected_data_rate_reason,
 NgapCauseEnum_RadioNetwork_Release_due_to_CN_detected_mobility,
 NgapCauseEnum_RadioNetwork_N26_Interface_Not_Available,
 NgapCauseEnum_RadioNetwork_Release_Due_To_Pre_Emption,
 NgapCauseEnum_Transport_resource_unavailable, NgapCauseEnum_Transport_Unspecified,
 NgapCauseEnum_Nas_Normal_release, NgapCauseEnum_Nas_Authentication_failure,
 NgapCauseEnum_Nas_Deregister, NgapCauseEnum_Nas_Nas_Unspecified,
 NgapCauseEnum_Protocol_Transfer_syntax_error,
 NgapCauseEnum_Protocol_Abstract_syntax_error_reject,
 NgapCauseEnum_Protocol_Abstract_syntax_error_ignore_and_notify,
 NgapCauseEnum_Protocol_Message_not_compatible_with_receiver_state,
 NgapCauseEnum_Protocol_Semantic_error,
 NgapCauseEnum_Protocol_Abstract_syntax_error_falsely_constructed_message,
 NgapCauseEnum_Protocol_Proto_Unspecified, NgapCauseEnum_Misc_Control_processing_overload,
 NgapCauseEnum_Misc_Not_enough_user_plane_processing_resources,
 NgapCauseEnum_Misc_Hardware_failure, NgapCauseEnum_Misc_O_M_intervention,
 NgapCauseEnum_Misc_Unknown_PLMN, NgapCauseEnum_Misc_Unspecified,
 NgapCauseEnum_UP_integrity_protection_not_possible,
 NgapCauseEnum_Encryption_and_or_integrity_protection_algorithms_not_supported

- Label: `n2_fail_reason`

Label Description: N2 failure reason

Example: None, N2 Decode Failed, Invalid N2 Container, upfServData is Nil, DL TunnelInfo is Not Found, UPF Tunnel ID lookup Failed, UPF MOD GNB Tunnel Params Failed, UPF MOD RSRA Tunnel Params Failed, UPF MOD Apply WPS Failed, MOD Tunnel LI Params Failed, Qos Mod Info Failed, Missing N2 SM Info, PDU Context Not Found, Default QFI (1) present in failed QosFlowList, RSRA Tunnel Recreation Failed For HO, Update QER Rule Map Failed, Rollback N2 Failed, Invalid Cause N2 SM Info, Mandatory IE incorrect in N2 SM Info, Xn HO Tobe Switch Flag Is Not Set in SmContextUpdateData, Invalid QFI List in PathSwitchRequest, QoS Flow Accepted List not found in XnHO, at least one Qfi to be accepted, PDU Session is Not Established, Missing T-gNB DL UP TunnelInfo, Missing S-gNB DL UP TunnelInfo, Default QFI is present in the Failed QFI List, N4 Session Modification failed, SLA Timeout

SMF Node Manager stats Category

smf_service_node_mgr_stats

Description: Stats for SMF Node Manager

Sample Query: `'smf_service_node_mgr_stats{ip_req_type="ip-alloc}'`

Labels:

- Label: `upf_ep_key`

Label Description: UPF Endpoint Key

Example: IP String Value

- Label: `first_nodemgr_inst`
Label Description: First Nodemgr instance ID
Example: unsigned integer
- Label: `second_nodemgr_inst`
Label Description: Second Nodemgr instance ID
Example: unsigned integer
- Label: `error`
Label Description: Error in case of Node Mgr failure
Example: None, Both associated nodemgr instances are down, Second nodeMgr down and First NodeMgr responded with SmfRspFailure, Second nodeMgr down and First NodeMgr failed with IpcError, First NodeMgr responded with SmfRspFailure, First NodeMgr failed with IpcError, Second NodeMgr failed with IpcError, Second NodeMgr responded with SmfRspFailure
- Label: `retransmit`
Label Description: Is retransmit message
Example: true, false
- Label: `ip_req_type`
Label Description: Type of IP request
Example: ip-alloc, ip-dealloc, ip-static, ip-static-subscription, ip-static-radius
- Label: `pdu_type`
Label Description: pdu connection type
Example: ipv4, ipv6, ipv4v6, unknown

SMF PCSCF Server Stats Category

smf_pcscf_server_stats

Description: Stats for SMF PCSCF Server

Sample Query: `'smf_pcscf_server_stats{PrimaryIPv4="1.2.3.4"}'`

Labels:

- Label: `PrimaryIPv4`
Label Description: Primary PCSCF IPV4 address
Example: 1.2.3.4
- Label: `SecondaryIPv4`
Label Description: Secondary PCSCF IPV4 address
Example: 1.2.3.4
- Label: `TertiaryIPv4`

Label Description: Tertiary PCSCF IPV4 address

Example: 1.2.3.4

- Label: `PrimaryIPv6`

Label Description: Primary PCSCF IPV6 address

Example: IPv6 IP

- Label: `SecondaryIPv6`

Label Description: Secondary PCSCF IPV6 address

Example: IPv6 IP

- Label: `TertiaryIPv6`

Label Description: Tertiary PCSCF IPV6 address

Example: IPv6 IP

- Label: `ResolvedFrom`

Label Description: Info used to resolve PCSCF Address

Example: DNS, LocalConfig

SMF PDU Status Category

smf_service_counters

Description: The current count of SMF pdu sessions

Sample Query: `'smf_service_counters{pdu_state="all_pdu"}'`

Labels:

- Label: `pdu_state`

Label Description: PDU session status indicated by N3 UPF tunnel status

Example: `all_pdu`, `idle`, `connected`

- Label: `rat_type`

Label Description: RAT Type of the Session

Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`

- Label: `dnn`

Label Description: Dnn configured in dnn-policy, also can have `virtual_dnn` if configured, separated by #

Example: `intershat`, `intershat#cisco.com`

- Label: `roaming_status`

Label Description: Roaming status of the subscriber session

Example: `visitor-lbo`, `visitor-hr`, `roamer`, `homer`, `none`

- Label: `ssc_mode`

Label Description: SSC Mode of the session

Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`

- Label: `flow_type`

Label Description: Indicates whether it's total bearer or dedicated bearer

Example: `dedicated_bearer`, `total_bearer`

SMF Procedure Category

smf_service_stats

Description: SMF call flow procedure counters

Sample Query: `'smf_service_stats{procedure_type="pdu_sess_create"}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`, `nw_req_service_active`, `upf_notify_downlink_data`, `xn_path_switch`, `pdn_sess_create`, `pdn_5g_4g_handover`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `n2_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `n26_4g_to_5g_im_mobility`, `pdu_im`, `pdn_sess_create`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `pcf_initiated_pdn_detach`, `smf_initiated_pdn_detach`, `upf_initiated_pdn_detach`, `smf_eps_fb`, `misc_pdu_sess_rel`, `pcrf_req_ded_brr_mod`, `pcrf_req_ded_brr_create`, `pcrf_req_ded_brr_delete`, `suspend_notification`, `resume_notification`, `change_notification`, `gx_validation_failure_pdn_sess_rel`, `smf_inter_plmn_ro2ho_n2ho`, `smf_inter_plmn_ho2ro_n2ho`, `smf_idft_inter_plmn_ro2ho_n2ho`, `smf_dft_inter_plmn_ro2ho_n2ho`, `smf_idft_inter_plmn_ho2ro_n2ho`, `smf_dft_inter_plmn_ho2ro_n2ho`

- Label: `status`

Label Description: call flow procedure counter

Example: `attempted`, `success`, `failures`, `pcrf_failure`

- Label: `pdu_type`

Label Description: pdu connection type

Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`

- Label: `dnn`

Label Description: Dnn configured in dnn-policy, also can have `virtual_dnn` if configured, separated by #

Example: `intershat`, `intershat#cisco.com`

- Label: `reason`

Label Description: Reason for failure status. For success and attempted it will be Empty

Example: `proc_pdu_not_established, proc_pdu_ctx_not_found, n2ho_ie_validation_failed, n2ho_n4_ho_preparing_failed, n2ho_n4_ho_prepared_failed, n2ho_n4_ho_completed_failed, n2ho_ho_cancelled, n2ho_resource_alloc_unsuccess_transfer, n2ho_invalid_state, n2ho_preparation_unsuccess_transfer, n2ho_n1n2_transfer_failure, n2ho_dft_intra_amf, n2ho_dft_inter_amf, n2ho_idft_intra_amf, n2ho_idft_inter_amf, n2ho_default_flow_failed, n2ho_n2_decode_failiure, n2ho_chf_update_failure, n2ho_invalid_response, xnho_tobe_switched_flag_not_set, xnho_dl_tunnel_info_not_found, xnho_invalid_accepted_qfi_list, xnho_n4_modification_failed, xnho_n1n2_transfer_failure//NotUsedtoberemoved, xnho_n2_decode_failiure, xnho_pdu_state_error, n26ho_4g_5g_n1n2_transfer_failure, n26ho_4g_5g_invalid_state, n26ho_4g_5g_n4_failed_prepared_state, n26ho_4g_5g_resource_alloc_unsuccess_transfer, n26ho_4g_5g_timedout_in_post_exec_state, n26ho_4g_5g_n4_failed_completed_state, n26ho_4g_5g_handover_cancelled, n26ho_4g_5g_send_n4mod_failed_preparing_state, n26ho_4g_5g_n4mod_rsp_failed_preparing_state, n26ho_4g_5g_n4mod_rsp_timeout_preparing_state, n26ho_4g_5g_im_mobility_send_n4mod_failed, n26ho_4g_5g_im_mobility_n4mod_rsp_failed, n26ho_4g_5g_im_mobility_n4mod_rsp_timeout, n26ho_4g_5g_invalid_eps_pdn_connlist, n26ho_4g_5g_udm_reg_failed, n26ho_4g_5g_dft, n26ho_4g_5g_idft, n26ho_5g_4g_dft, n26ho_5g_4g_idft, n26ho_5g_4g_ctxrtrive_rec_for_4g_session, n26ho_5g_4g_handover_cancel, n26ho_4g_5g_no_eps_5gs_continuity, n26ho_default_flow_failed, n26ho_n2_decode_failiure, n26ho_chf_update_failure, n26im_mobility_4g_5g_no_eps_5gs_continuity, n26im_mobility_4g_5g_default_eps_bearer_inactive, pduim_n1n2_transfer_failure, pduim_n2_setup_response_failure, pduim_n1n2_txfr_failure_notification, pduim_n4_modification_failed, pduim_misc_error, pduim_n1n2ack_decode_error, pduim_n1n2ack_unhndl_cause, pduim_n1n2ack_unhndl_rsp_code, pduim_n1n2ack_unhndl_prb_cause, pduim_suspended_procedure, pduim_amf_ctx_not_found, pduim_internal_error, pduim_upstate_not_in_deactivated_state, pduim_pdu_access_type_mismatch, pduim_pdu_gnb_tunnel_not_available, pduim_pdu_n4_deactivated_state, pduim_sla_timer_expired, pduim_temp_reject_max_retry, upf_failure, pcf_failure, idft_release_failure, access_4g_already, idft_setup_failure, mbr_setup_failure, sgw_failure, udm_registration_failure, udm_subscription_fetch_failure, udm_subscribe_notify_failure, udm_update_notify_failure, aaa_subscribe_auth_failure, aaa_framed_ip_addr_conflict, pcf_create_failure, pcf_update_failure, charging_data_failure, no_rule_matched, invalid_protocol, invalid_dst_mask, invalid_src_mask, invalid_5qi, invalid_arp, invalid_other, internal_error, invalid_ebi, invalid_framed_ipv6_pfx_length, invalid_acct_sess_id_radius_dm, reason_unknown, invalid_rat_type, session_associated_to_online_chf, session_not_in_state, unknown, n4_release_failed, gtpu_peer_path_failed, rel_received_for_non_5g_session, qfi_failed_to_setup, utn3gppto5gho_n4_failed_completed_state, utn3gppto5gho_n4_failed_prepared_state, utn3gppto5gho_resource_alloc_unsuccess_transfer, utn3gppto5gho_invalid_state, utn3gppto5gho_policy_update_failure, utn3gppto5gho_charging_update_failure, utn3gppto5gho_n1n2_transfer_failure, utn3gppto5gho_pcf_update_failed_post_ho, utn3gppto5gho_chf_update_failed_post_ho, utn3gppto5gho_n4_failed_post_ho, utn3gppto5gho_del_bearer_failed, utn3gppto5gho_partial_flow_failure, utn3gppto5gho_default_flow_failed, utn3gppto5gho_eps_fallback, utn3gppto5gho_setup_unsuccess_transfer, utn3gppto5gho_fail_due_n2msg_rsp_not_rcvd, utn3gppto5gho_ctxt_create_res_failure, utn3gppto5gho_invalid_ctxt_create_req, utn3gpp_epsfallback_failed_during_5g_4g_ho, utn3gpp_epsfallback_failed_guard_timer_expiry, nr_to_untrusted_wifi_invalid_sess_state, nr_to_untrusted_wifi_invalid_json, nr_to_untrusted_wifi_invalid_paa, nr_to_untrusted_wifi_invalid_msg, nr_to_untrusted_wifi_pcf_failed, nr_to_untrusted_wifi_n40_failed, nr_to_untrusted_wifi_n4_failed, nr_to_untrusted_wifi_pcf_failed_post_cb, nr_to_untrusted_wifi_n40_failed_post_cb,`

nr_to_untrusted_wifi_n4_failed_post_cb, nr_to_untrusted_wifi_cbr_failed,
 nr_to_untrusted_wifi_ubr_failed, nr_to_untrusted_wifi_cb_res_failed,
 nr_to_untrusted_wifi_n1n2_release_failed, nr_to_untrusted_wifi_n4_failed_post_ho,
 nr_to_untrusted_wifi_pcf_update_failed_post_ho, nr_to_untrusted_wifi_chf_update_failed_post_ho,
 nr_to_untrusted_wifi_sla_timer_expired, nr_to_untrusted_wifi_dbr_failed,
 enb_to_untrusted_wifi_to_enb_ho_reject, enb_to_untrusted_wifi_to_enb_invalid_sess_state,
 enb_to_untrusted_wifi_to_enb_invalid_json, enb_to_untrusted_wifi_to_enb_invalid_paa,
 enb_to_untrusted_wifi_to_enb_invalid_msg, enb_to_untrusted_wifi_to_enb_udm_failed,
 enb_to_untrusted_wifi_to_enb_pcf_failed, enb_to_untrusted_wifi_to_enb_n40_failed,
 enb_to_untrusted_wifi_to_enb_n4_failed, enb_to_untrusted_wifi_to_enb_pcf_failed_post_cb,
 enb_to_untrusted_wifi_to_enb_mbr_failed, enb_to_untrusted_wifi_to_enb_n4_failed_post_mbr,
 enb_to_untrusted_wifi_to_enb_n40_failed_post_cb, enb_to_untrusted_wifi_to_enb_n4_failed_post_cb,
 enb_to_untrusted_wifi_to_enb_n40_failed_post_db, enb_to_untrusted_wifi_to_enb_pcf_failed_post_db,
 enb_to_untrusted_wifi_to_enb_cbr_failed, enb_to_untrusted_wifi_to_enb_dbr_failed,
 enb_to_untrusted_wifi_to_enb_ubr_failed, dsr_target_rat_rejected, upip_req_denied_in_rat,
 nr_to_untrusted_wifi_upip_status_req_denied_in_rat, pcrf_create_failure, cbr_fail_upstate_inactive,
 ubr_fail_upstate_inactive, pdnrel_conditional_ie_missing, pdn_create_over_created_pdn,
 interplmn_ho_not_configured, dtssa_acscr_not_supported, ho2ro_invalid_state, ro2ho_invalid_state,
 mbc_retransmit_msg, change_notification_retransmit_msg

- Label: emergency_call

Label Description: Flag indicating if it is an emergency call

Example: true, false

- Label: rat_type

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: roaming_status

Label Description: Roaming status of the subscriber session

Example: visitor-lbo, visitor-hr, roamer, homer, none

- Label: up_state

Label Description: Userplane connection status of the session

Example: UpState_None, UpState_Establishing, UpState_Activating, UpState_Activated,
 UpState_Deactivating, UpState_Deactivated, UpState_Modifying, UpState_Deleting, UpState_Deleted

- Label: qos_5qi

Label Description: 5Qi applicable for the QoS flow

Example: 1, 2, 5

- Label: always_on

Label Description: always on status

Example: enable, disable

- Label: dcnr

Label Description: UE DCNR status

Example: enable, disable

- Label: `smf_current_procedure`

Label Description: Current Procedure Name for Message Level Stats

Example: DedBearerProc, eps_fb_ded_brr, ue_req_ded_brr_mod, udm_req_ded_brr_mod, smf_req_ded_brr_del, upf_req_ded_brr_del, mme_req_ded_brr_del, mme_req_ded_brr_mod, pcf_req_ded_brr_mod, pcf_req_ded_brr_create, pcf_req_ded_brr_delete

- Label: `fourg_only_ue`

Label Description: Only 4g capable UE flag

Example: true, false

- Label: `pra`

Label Description: Presence Reporting Area Information

Example: enable, none

- Label: `uipip_active`

Label Description: UPIP activated for the session or not

Example: true, false

- Label: `local_policy`

Label Description: Flows or Bearers created based on local policy config

Example: true, false

SMF Procedure Collision Category

smf_procedure_collision

Description: Total number of procedures collided

Sample Query: `sum(smf_procedure_collision) by (smf_current_procedure, smf_current_state, smf_new_procedure, smf_current_procedure_action)`

Labels:

- Label: `smf_current_procedure`

Label Description: Current Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_current_state`

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: `smf_new_procedure`

Label Description: New Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_current_procedure_action`

Label Description: Current Procedure Action on Collision

Example: Ignore, Suspend, Resume, Abort, Cleanup, Continue, Ready, INVALID ACTION

SMF Procedure Total Time Statistics Category

smf_procedure_seconds

Description: Total number of seconds taken to complete the procedure

Sample Query: `'smf_procedure_seconds{smf_proc_status="Aborted"}'`

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Protocol message counters Category

smf_proto_udp_msg_total

Description: SMF Protocol message statistics

Sample Query: `'smf_proto_udp_msg_total{message_direction="inbound",nf_type="amf"}'`

Labels:

- Label: `message_name`

Label Description: name of N4 interface message

Example: `n4_session_establishment_req`, `n4_session_establishment_res`, `n4_session_modification_req`, `n4_session_modification_res`, `n4_session_report_req`, `n4_session_report_res`, `n4_session_deletion_req`, `n4_session_deletion_res`, `n4_association_setup_req`, `n4_association_setup_res`, `n4_association_update_req`, `n4_association_update_res`, `n4_association_release_req`, `n4_association_release_res`,

n4_prime_pfd_management_req, n4_prime_pfd_management_res, n4_heartbeat_req, n4_heartbeat_res, n4_node_report_req, n4_node_report_res

- Label: `message_direction`

Label Description: direction of message from SMF perspective

Example: inbound, outbound

- Label: `status`

Label Description: status of message processing

Example: accepted, denied, discarded

SMF RAN failed stats Category

`smf_ran_failed_flows`

Description: Stats for the failed QFIs sent in UE Sync

Sample Query: `'smf_ran_failed_flows{procedure_type="pdu_ue_sync_proc}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_ue_sync_proc

- Label: `reason`

Label Description: The reason associated with failure

Example: qfi_failed_to_setup

SMF RSRA stats Category

`smf_service_rsra_stats`

Description: Stats for SMF Service RSRA

Sample Query: `'smf_service_rsra_stats{rat_type="NR}'`

Labels:

- Label: `procedure_type`

Label Description: The RSRA procedure type

Example: router_advt_solicit_request, router_advt_unsolicit_request, router_solicit_request

- Label: `status`

Label Description: status of RSRA

Example: failed, sent, retransmit, received

- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, `rat_type_unknown`
- Label: `upf_ep_key`
Label Description: UPF Endpoint Key
Example: IP String Value
- Label: `reason`
Label Description: reason for the failed status
Example: `userplane_error`, `ho_in_progress`, `ipc_failed`, `userplane_error`, `encode_failed`, `decode_failed`

SMF Secondary RAT Usage Report Stats Category

`smf_secondary_rat_usage_report_stats`

Description: Stats for SMF Secondary RAT Usage Report

Sample Query: `'smf_secondary_rat_usage_report_stats{rat_type="NR"}'`

Labels:

- Label: `status`
Label Description: Status of Sec RAT Usage Report
Example: `ReceivedFromSgw`
- Label: `reason`
Label Description: The reason associated with status
Example: `success`
- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: `NR`
- Label: `ebi`
Label Description: ebi number as string
Example: `unsigned int as string or NA`
- Label: `qfi`
Label Description: qfi number as string
Example: `unsigned int as string or NA`

SMF Service Node Report Stats Category

smf_service_node_report_stats

Description: Stats for SMF Service Node Report

Sample Query: 'smf_service_node_report_stats{procedure_type="upf_node_report_pdu_sess_rel"}'

Labels:

- Label: `procedure_type`
Label Description: The SMF procedure type
Example: `upf_node_report_pdu_sess_rel`, `upf_node_report_pdn_sess_rel`
- Label: `status`
Label Description: Status of SMF Service Node Report
Example: `attempted`, `failures`, `success`
- Label: `pdu_type`
Label Description: pdu connection type
Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`
- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`
- Label: `up_state`
Label Description: Userplane connection status of the session
Example: `UpState_None`, `UpState_Establishing`, `UpState_Activating`, `UpState_Activated`, `UpState_Deactivating`, `UpState_Deactivated`, `UpState_Modifying`, `UpState_Deleting`, `UpState_Deleted`
- Label: `peer_gtpu_ep_key`
Label Description: GTP Peer
Example: IP String
- Label: `upf_endpoint`
Label Description: UPF Endpoint
Example: IP String Value

SMF Service Resource Management Stats Category

smf_service_resource_mgmt_stats

Description: SMF Service Resource Management Stats

Sample Query:

'smf_service_resource_mgmt_stats{ip_req_type="ip-alloc",pdu_type="ipv4",dnn="dnn1"}'

Labels:

- Label: `ip_req_type`

Label Description: Type of IP request

Example: ip-alloc, ip-dealloc, ip-static, ip-static-subscription, ip-static-radius

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb, Cleanuplocal

- Label: `status`

Label Description: status of resource management request

Example: attempted, success, failures

- Label: `pdu_type`

Label Description: pdu connection type

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `emergency_call`

Label Description: Flag indicating if it is an emergency call

Example: true, false

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

SMF Service gtpc cache statistics Category

`smf_service_gtpc_cache_stats`

Description: SMF Service gtpc cache counters

Sample Query: `'smf_service_gtpc_cache_stats{gr_instance_id="1"}'`

Labels:

- Label: `smf_proc_type`

Label Description: The procedure type associated with an call flow procedure

Example: `eps_fb_ded_brr`, `ue_req_ded_brr_mod`, `udm_req_ded_brr_mod`, `smf_req_ded_brr_del`, `mme_req_ded_brr_del`, `mme_req_ded_brr_mod`, `mme_req_ded_brr_del`, `pcrf_req_ded_brr_create`, `pcf_req_ded_brr_create`, `pcrf_req_ded_brr_delete`, `pcf_req_ded_brr_delete`, `pcrf_req_ded_brr_mod`, `pcf_req_ded_brr_mod`, `ProcessNoStateMBR`, `suspend_acknowledgement`

- Label: `message_type`

Label Description: GTPC Message Type

Example: `CreateBearerReq`, `UpdateBearerReq`, `DeleteBearerReq`, `ModifyBearerResp`, `DeleteSessionResp`, `ModifyBearerResp`, `CreateSessionResp`, `SuspendAck`,

- Label: `gtpc_cache_operation`

Label Description: GTPC cache operation

Example: `add`, `delete`

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: Any string

SMF Session counters Category

smf_session_counters

Description: SMF current active Session counters

Sample Query:

```
'smf_session_counters{rat_type="NR",pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1"}'
```

Labels:

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`

- Label: `pdu_type`

Label Description: pdu connection type

Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`

- Label: `dnn`

Label Description: Dnn configured in dnn-policy, also can have `virtual_dnn` if configured, separated by #

Example: `intershat`, `intershat#cisco.com`

- Label: `ssc_mode`

Label Description: Type of ssc mode associated with the request

Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`

- Label: `always_on`
Label Description: always on status
Example: enable, disable
- Label: `dcnr`
Label Description: UE DCNR status
Example: enable, disable
- Label: `emergency_call`
Label Description: Flag indicating if it is an emergency call
Example: true, false
- Label: `fourg_only_ue`
Label Description: Only 4g capable UE flag
Example: true, false
- Label: `unauthenticated_supi`
Label Description: indicates if SUPI is unauthenticated
Example: true, false
- Label: `pra`
Label Description: Presence Reporting Area Information
Example: enable, none
- Label: `roaming_status`
Label Description: Roaming status of the subscriber session
Example: visitor-lbo, visitor-hr, roamer, homer, none
- Label: `policy_type`
Label Description: Policy type of the subscriber session
Example: pcf, pcrf, none
- Label: `local_policy`
Label Description: Flows or Bearers created based on local policy config
Example: true, false

SMF Session stats Category

smf_session_stats

Description: SMF Session stats counters

Sample Query:

```
'smf_session_stats(rat_type="NR",pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1",status="attempted")'
```

Labels:

- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, `rat_type_unknown`
- Label: `pdu_type`
Label Description: pdu connection type
Example: ipv4, ipv6, ipv4v6, unknown
- Label: `dnn`
Label Description: Dnn configured in dnn-policy, also can have `virtual_dnn` if configured, separated by #
Example: intershat, intershat#cisco.com
- Label: `ssc_mode`
Label Description: Type of ssc mode associated with the request
Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`
- Label: `status`
Label Description: PDU session status indicated at SMF
Example: attempted, success, setup
- Label: `roaming_status`
Label Description: Roaming status of the subscriber session
Example: visitor-lbo, visitor-hr, roamer, homer, none
- Label: `policy_type`
Label Description: Policy type of the subscriber session
Example: pcf, pcrf, none

SMF Start Procedure Statistics Category

smf_procedure_start

Description: Total number of procedures started

Sample Query: `'smf_procedure_start(smf_proc_type="PDN Connect")'`

Labels:

- Label: `smf_proc_type`
Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

SMF Stop Procedure Statistics Category

smf_procedure_stop

Description: Total number of procedures stopped

Sample Query: 'smf_procedure_stop{smf_proc_type="PDU Session Establishment"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete

SMF Timeout stats Category

smf_timeout_stats

Description: SMF Timeout stats

Sample Query: 'smf_timeout_stats{timeout_type="SessionSetupTimeout"}'

Labels:

- Label: timeout_type

Label Description: SMF Timeout type

Example: SessionSetupTimeout, SessionCallflowTimeout, SessionEpsFbTimeout, SessionPolicyRevalTimeout, SessionRsRaAdvTime, SessionModifyTimeout, SessionReleaseTimeout, SessionN2HoTimeout, SessionImTimeout, SessionDedBearerTimeout, SessionPdnSetupTimeout, SessionPdnDisconnectTimeout, SessionPdnModifyTimeout, SessionPduIdftTimeout, SessionPdu5G4GHandover, SessionNrToUnTrustWifiHOTOTimeout, Session4GWifi4GHOTOTimeout, SessionWifiTo4GHoMBReqTimeout, SessionRouterSolicitTimeout, SessionUsageReportTimeout, SessionPathSwitchTimeout, SessionN1N2RetryAfter, SessionPDUIMN1N2RetryAfter, SessionN2HoIdftTimeout, SessionN26HoIdftTimeout, SessionAbsoluteTimeout, SessionIwfN26IdftTimeout, SessionDedBrrReEstTimer, SessionDedBrrDelayTimer, Session4G5GN26Timeout, SessionN1N2RetryTimeout, SessionN1N2RetransTimeout, SessionPDUIMResumeTimeout, SessionUrrOutOfOrderWaitTimeout, SessionPduRelCmdRetryTimeout, SessionUnTrustWifiToNrHOTOTimeout, SessionUbrRetryTimer, SessionDbrRetryTimer,

SessionPduUeSyncTimeout, SessionAmfChangeGuardTimeout, SessionPduSetupProcSLA, SessionPduImProcSLA, ProcedureSlaTimeout, SessionN2HOProcSLA, SessionCatchAllTimeout, SessionIdleTimeout, SessionCpIdleTimeout, SessionTempRejectHoTimeout, SessionDefaultFlowOnlyTimeout, SessionErirDelayTimeout

SMF Total Timedout Procedure Count Category

smf_procedure_timeout

Description: Total number of procedures executed more than 10sec

Sample Query: 'smf_procedure_timeout{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Timedout Procedure Count Category

smf_procedure_timeout

Description: Total number of procedures executed more than 10sec

Sample Query: 'smf_procedure_timeout{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Timedout Procedure Time Category

smf_procedure_timeout_seconds

Description: Total number of seconds taken by procedures executed more than 10sec

Sample Query: 'smf_procedure_timeout_seconds{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Unhandled Event Statistics Category

smf_procedure_unhndl_event

Description: Total number of unhandled events per procedure type

Sample Query: 'smf_procedure_unhndl_event{smf_proc_type="PDU Session Release - SMF initiated"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: message_type

Label Description: Type of Request/Response Message associated with Unhandled Event

Example: N11SmContextUpdateSuccess, N11EbiAssignmentReq, N4HeartBeatFailure, S5CreateSessRsp, NLiSubscriberQueryReq, RadiusCoaDisconnectReq, N7SmPolicyUpdateSuccess

- Label: smf_current_state

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: guard_timer

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

SMF Total Unhandled Transaction Statistics Category

smf_procedure_unhndl_trans

Description: Total number of unhandled transactions per procedure type

Sample Query: 'smf_procedure_unhndl_trans{message_type="RadiusCoaDisconnectReq}'

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `message_type`

Label Description: Type of Request/Response Message associated with Unhandled Transaction

Example: N11SmContextUpdateSuccess, N11EbiAssignmentReq, N4HeartBeatFailure, S5CreateSessRsp, NLiSubscriberQueryReq, RadiusCoaDisconnectReq, N7SmPolicyUpdateSuccess

- Label: `smf_current_state`

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: `guard_timer`

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

SMF User Plane Session counters Category

smf_up_session_counters

Description: SMF current active User Plane Sessions

Sample Query: 'smf_up_session_counters{pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1}'

Labels:

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: `pdu_type`
Label Description: pdu connection type
Example: ipv4, ipv6, ipv4v6, unknown
- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `ssc_mode`
Label Description: Type of ssc mode associated with the request
Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`

UDM Message Failure Action Stats Category

`smf_udm_msg_fail_action`

Description: Stats for UDM Message Failure Action

Sample Query: `'smf_udm_msg_fail_action{udm_msg="UdmRegistration"}'`

Labels:

- Label: `udm_msg`
Label Description: Type of UDM Message
Example: `UdmRegistration`, `UdmDeregistration`, `UdmSmSubscription`, `UdmSubscribeToNotify`, `UdmUnSubscribeToNotify`
- Label: `udm_failure_action`
Label Description: Action taken on UDM Message failure
Example: `ignore`, `continue`, `terminate`
- Label: `udm_end_point`
Label Description: UDM Endpoint
Example: IP String

UDP RPC message statistics Category

`udp_rpc_msg_stats`

Description: Statistics for UDP RPC

Sample Query: `'sum (udp_rpc_msg_stats{gr_instance_id="1"})'`

Labels:

- Label: `msgtype`
Label Description: message Type

Example: MessageNone, PfcPProxyMsg, UdpProxyMsg, UnknownMsg

- Label: `direction`

Label Description: Direction of UDP RPC message

Example: inbound, outbound

- Label: `status`

Label Description: status of message processing

Example: success, failures

- Label: `transport_type`

Label Description: Transport type of message

Example: original, asyncmessage, retransmitted,

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: Any string

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

UDP Request Total Message Stats Category

smf_service_udp_req_msg_total

Description: Stats for Total UDP Request Messages

Sample Query: `'smf_service_udp_req_msg_total{status="attempted"}'`

Labels:

- Label: `message_type`

Label Description: Type of UDP Message

Example: N4SessionEstablishmentReq

- Label: `upf_endpoint`

Label Description: UPF Endpoint

Example: IP String Value

- Label: `status`

Label Description: Status of UDP Message

Example: attempted, success, failures

- Label: `trans_type`

Label Description: Transmission type of UDP Message

Example: `trans_type_origin`, `trans_type_reselected`

- Label: `cause_code`

Label Description: Causecode of UDP Message

Example: `Reserved`, `Request_Accepted`, `Request_Rejected_Unspecified`, `Session_Ctx_Not_Found`, `Mandatory_IE_Missing`, `Cond_IE_Missing`, `Invalid_Length`, `Mandatory_IE_Incorrect`, `Invalid_FW_Policy`, `Invalid_FTEID_Alloc_Opt`, `No_Established_PFCP_Assc`, `Rule_Creation_Mod_Failure`, `PFCP_Entity_In_Congestion`, `No_Resource_Available`, `Service_Not_Supported`, `System_failure`, `No_Response`, `Duplicate_Userplane_Id`, `OutOfRange_Userplane_Id`

UPF selection stats Category

upf_selection_stats

Description: Stats for the UPF Selection

Sample Query: `'upf_selection_stats{upf_selection_type="preferred"}'`

Labels:

- Label: `upf_selection_type`

Label Description: Type of UPF Selection

Example: `preferred`

- Label: `upf_fqdn`

Label Description: FQDN of the UPF selected

Example: `string`

- Label: `status`

Label Description: Status the UPF selected

Example: `attempted`, `failed`

- Label: `reason`

Label Description: Reason for status of the UPF selected

Example: `upf_not_associated`, `upf_profile_not_found`, `upf_not_active`

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: `EUTRA`, `NR`, `WLAN`, `rat_type_unknown`

- Label: `pdu_session_type`

Label Description: PDU Session type

Example: ip-alloc, ip-dealloc, ip-static

- Label: pdu_subscription_type

Label Description: PDU Subscription type

Example: ip-alloc, ip-dealloc, ip-static

- Label: snssai

Label Description: SNSSAI of the session having sd and sst

Example: sd:<string> sst:<uint>



CHAPTER 3

Failure Disconnect Reasons Reference

- [SMF Disconnect Reasons](#), on page 77

SMF Disconnect Reasons

This section describes the procedure failure disconnect reasons supported on SMF.

The following table provides the descriptions for the key failure disconnect reasons.

Table 1: Failure Disconnect Reasons

Disconnect Reason	Description
disc_chf_reconciliation	The total number of sessions released by the SMF due to CHF reconciliation.
disc_sess_report_erir_pdn_sess_rel	The total number of 4G or Wi-Fi sessions released by the SMF due to N4 Session Report Request from UPF with ERIR report type. If the ERIR delay timer is configured under access profile, the configured value delays the N4 Session Report Request handling.
disc_pdusetup_create_over_create	The total number of ongoing 5G sessions rejected by the SMF when 5G session establishment is received while handling N11SmContextCreateRequest for 5G session establishment (Create over Create case).
disc_pdurel_amf_init_release_404	The total number of 5G sessions released by the SMF due to 404 response from AMF for N1N2Transfer Request during 5G session modification.
disc_sess_report_erir_pdn_sess_rel	The total number of 4G or Wi-Fi sessions released by the SMF due to N4 Session Report Request from UPF with ERIR report type. If the ERIR delay timer is configured under access profile, the configured value delays the N4 Session Report Request handling.

Disconnect Reason	Description
disc_pdusetup_create_over_create	The total number of ongoing 5G sessions rejected by the SMF when 5G session establishment is received while handling N11SmContextCreateRequest for 5G session establishment (Create over Create case).
disc_pdurel_amf_init_release_404	The total number of 5G sessions released by the SMF due to 404 response from AMF for N1N2Transfer Request during 5G session modification.
disc_pduim_context_not_found	The total number of 5G sessions released by the SMF due to 404 response from AMF for N1N2Transfer Request during idle to active mobility and vice versa.
disc_pdnsetup_smf_mop_offline	The total number of 4G or Wi-Fi sessions rejected by the SMF due to Session Create received when SMF is in maintenance mode and when the offline mode configuration is set in the SMF profile or specifically for a DNN in the DNN profile.
disc_pdusetup_n2_setup_failed	The total number of 5G sessions rejected by the SMF when N2_PDU_SESSION_RESOURCE_SETUP_UNSUCCESS_TRANSFER is received from AMF indicating the N2 failure during 5G session establishment.
disc_pdusetup_n1n2_transfer_rsp_failure	The total number of 5G sessions rejected by the SMF due to N11N1N2MessageTransferFailure response from AMF during 5G session setup.
disc_pdnsetup_non5gcapableue_not_allowed	The total number of 4G or Wi-Fi sessions rejected by the SMF due to Session Create received without 5G InterWorking (IWK_5GS) indication and when the DNN profile is configured to support only NR capable UE by setting only-nr-capable-ue to true.
disc_pdnsetup_udm_sub_fetch_failed	<p>The total number of sessions rejected by the SMF due to failure in fetching the session management subscription data (sm-data) from UDM during 4G or Wi-Fi session establishment time.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF request to UDM for fetching the session management subscription data (sm-data) fails. • SMF receives failure response from UDM for SM data request. • Validation of request from UE (SSC mode, PDU session type and Snsai) fails against the subscription allowed based on UDM response.

Disconnect Reason	Description
disc_pdnsetup_udm_sub_fetch_resp_failed	<p>The total number of sessions rejected by the SMF due to failure in fetching the session management subscription data (sm-data) from UDM during 4G or Wi-Fi session establishment time.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF receives failure response from UDM for session management subscription data (sm-data) request. • Validation of request from UE (SSC mode, PDU session type, and Snsai) fails against the subscription allowed based on UDM response.
disc_pdusetup_release_over_create	The total number of 5G sessions rejected by the SMF due to 5G session release event during ongoing 5G session establishment.
disc_pdusetup_pdu_sess_does_not_exist	The total number of 5G sessions rejected by the SMF when SmContextCreateRequest is received with RequestType as EXISTING_PDU_SESSION during Wi-Fi to 5G handover, but the session doesn't exist with SMF.
disc_sess_cp_idle_time_exp_release	The total number of 4G or Wi-Fi sessions released by the SMF due to Control Plane (CP) idle timeout that started on successful session establishment. The idle timeout is configured in the DNN profile.
disc_sgw_ctx_failure	The total number of 4G or Wi-Fi sessions rejected by the SMF due to default flow failure caused by S-GW.
disc_pdnsetup_pcf_create_resp_failed	The total number of 4G or Wi-Fi sessions rejected by the SMF due to PCF Create Failure during 4G or Wi-Fi session establishment.
disc_gtpc_peer_pathfail	The total number of 4G or Wi-Fi sessions released by the SMF due to GTPC path failure in the network.
disc_pdusetup_rm_exchg_failure	The total number of 5G sessions rejected by the SMF due to IP allocation failure for the PDU session during 5G session setup.
disc_rel_chf_err	The total number of sessions released by the SMF due to CHF-initiated session release.
disc_pdnsetup_udm_reg_resp_failed	<p>The total number of sessions rejected by the SMF due to SMF registration failure with UDM during 4G or Wi-Fi session establishment time. The SMF sends registration request to UDM for storing UE context management information.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF registration request to UDM fails. • SMF receives failure response from UDM for registration request.

Disconnect Reason	Description
disc_pdumodify_context_not_found	The total number of 5G sessions released by the SMF due to 404 response from AMF for N1N2Transfer Request during 5G session modification.
disc_pdusetup_sm_cxt_sess_id_err	<p>The total number of sessions rejected by the SMF when pduSessionId in 5G PDU Session Establishment Request (N11SmContextCreate Request) is either zero or not in the expected format.</p> <p>This disconnect reason is also pegged when there is no subscriber ID (SUPI or PEI) but the ueEpsPdnConnection parameter is present in the request.</p>
disc_pdusetup_upf_setup_rsp_failure	The total number of sessions rejected by the SMF when N4 session establishment with UPF fails during 5G session establishment time.
disc_pdusetup_sess_cp_idle_timeout	The total number of PDN sessions released by the SMF due to Control Plane (CP) idle timer expiry. The CP idle timer expires when there is no control plane activity within the CP idle timeout.
disc_pdusetup_ip_alloc_failed	<p>The total number of sessions rejected by the SMF or PGW-C when IP address allocation fails.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF service (node manager) which handles IP address allocation is down. • SMF service (node manager) couldn't allocate the IP address of the requested PDU session type.
disc_pdusetup_n1n2_transfer_exchg_failure	The total number of sessions rejected by the SMF when there is failure in N1N2 Transfer Request with AMF during 5G PDU session establishment.
disc_pdnsetup_resource_mgr_exchg_failed	The total number of sessions rejected by the SMF or PGW-C when resource manager exchange fails due to IP address allocation failure during 4G or Wi-Fi PDN connection time.
disc_pdusetup_pcf_create_rsp_failure	<p>The total number of sessions rejected by the SMF due to Policy Create Failure.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF receives failure from PCF for Policy Create Request during 5G session establishment. • No response from PCF for Policy Create Failure.

Disconnect Reason	Description
disc_pdsetup_csr_invalid	<p>The total number of Create Session Requests rejected by the SMF when Create Session Request includes invalid parameters.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • Create Session Request with invalid parameters for new PDN connection (4G or Wi-Fi). • Create Session Request with invalid parameters in handover requests—5G to Wi-Fi HO, 4G to Wi-Fi HO, and Wi-Fi to 4G HO.
disc_n26_4g_5g_ho_n4_modify_failed	<p>The total number of sessions released by the SMF or PGW-C when N4 modification with UPF fails in the execution phase of 4G to 5G N26 handover.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • N4 Modification Request failure in the execution phase of N26 HO. • SMF receives failure response from UPF for N4 modification in the execution phase of N26 HO. • SLA timeout at SMF during N4 modification in the execution phase of N26 HO.
disc_sess_cp_idle_time_exp_release	<p>The total number of PDN sessions released by the SMF or PGW-C due to Control Plane (CP) idle timer expiry. The CP idle timer expires when there is no control plane activity within the CP idle timeout.</p>
disc_pdsetup_dnn_not_supported_in_slice	<p>The total number of sessions rejected by the SMF where the 5G PDU Session Establishment Request (N11smContextCreate) received from AMF contains DNN which is not supported in the requested network slice.</p>
disc_pdsetup_udm_reg_failed	<p>The total number of sessions rejected by the SMF due to SMF registration failure with UDM during 5G session establishment time. The SMF sends registration request to UDM for storing UE context management information.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF registration request to UDM fails. • SMF receives failure response from UDM for registration request.
disc_pdurel_db_conflict	<p>The total number of sessions released by the SMF due to internal issue related to the database conflict.</p>

Disconnect Reason	Description
disc_pdusetup_udm_sub_fetch_resp_failed	<p>The total number of sessions rejected by the SMF due to failure in fetching the session management subscription data (sm-data) from UDM during 5G session establishment time.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF receives failure response from UDM for session management subscription data (sm-data) request. • Validation of request from UE (SSC mode, PDU session type and Snsai) fails against the subscription allowed based on UDM response.
disc_pdusetup_udm_sub_fetch_failure	<p>The total number of sessions rejected by the SMF due to failure in fetching the session management subscription data (sm-data) from UDM during 5G session establishment time.</p> <p>This disconnect reason is pegged in the following scenarios:</p> <ul style="list-style-type: none"> • SMF request to UDM for fetching the session management subscription data (sm-data) fails. • SMF receives failure response from UDM for SM data request. • Validation of request from UE (SSC mode, PDU session type, and Snsai) fails against the subscription allowed based on UDM response.



CHAPTER 4

MIB Reference

- [CISCO-CNEE-MIB, on page 83](#)
- [CISCO-SMI, on page 83](#)

CISCO-CNEE-MIB

This is the MIB module for the Cisco Cloud Native Execution Environment (CNEE) platform. This MIB only handles notifications from the CNEE.



Note The Cisco Cloud Native Execution Environment (CNEE) MIB (CISCO-CNEE-MIB.my) uses definitions that are defined in the Cisco Enterprise Structure of Management Information (SMI) MIB (CISCO-SMI.my).

For more information, see the "*UCC Subscriber Microservice Infrastructure - Operations Guide*" > *SMI MIB Reference* chapter.

CISCO-SMI

This is the Structure of Management Information for the Cisco Enterprise.



Note The Cisco Cloud Native Execution Environment (CNEE) MIB (CISCO-CNEE-MIB.my) uses definitions that are defined in the Cisco Enterprise Structure of Management Information (SMI) MIB (CISCO-SMI.my).

For more information, see the "*UCC Subscriber Microservice Infrastructure - Operations Guide*" > *SMI MIB Reference* chapter.

