



# Unified Personal Communicator の設定

Unified Personal Communicator の設定のウィンドウを使用して、すべての Cisco Unified Personal Communicator ユーザに適用する設定値を設定します。

## Cisco Unified Personal Communicator 設定値の設定

Unified Personal Communicator 設定値を設定するには、次の手順に従います。

### 手順

**ステップ 1** [アプリケーション] > [Unified Personal Communicator] > [設定] の順に選択します。

[Unified Personal Communicator の設定 (Unified Personal Communicator Settings)] ウィンドウが表示されます。

**ステップ 2** 表 23-1 の説明に従って適切な設定値を入力します。

**ステップ 3** Cisco Unified Personal Communicator のアトリビュート名にマッピングする、自分の環境に適切な LDAP アトリビュート名を入力します。Cisco Unified Personal Communicator のアトリビュート名とそれに対応するデフォルトの LDAP 名のリストについては、表 23-2 を参照してください。

**ステップ 4** データを保存するには、ウィンドウの左上隅のツールバーに表示される [保存] アイコンをクリックします (または、ウィンドウの下部に表示される [保存] ボタンをクリックします)。

表 23-1 Cisco Unified Personal Communicator の設定値

フィールド	説明
プライマリ TFTP サーバ (Primary TFTP Server)	このパラメータは、プライマリ TFTP サーバのアドレスを、完全修飾ドメイン名または IP アドレスのいずれかで指定します。  最大文字数：128
バックアップ TFTP サーバ (Backup TFTP Server)	このパラメータは、バックアップ TFTP サーバのアドレスを、完全修飾ドメイン名または IP アドレスのいずれかで指定します。  最大文字数：128

表 23-2 LDAP アトリビュートマッピング

Unified Personal Communicator のアトリビュート名	デフォルトの LDAP アトリビュート名
UID	employeenumber
LastName	sn
Nickname	nickname
Photo	jpegPhoto
DisplayName	displayName
NameSuffix	
BusinessEMail	mail
BusinessPhoneNumber	telephoneNumber
BusinessMobilePhone	mobile
BusinessFax	facsimileTelephoneNumber
HomeEMail	
HomeFax	
FirstName	givenName
MiddleName	initials
UserID	uid
Title	title
NamePrefix	
Gender	
IM	
BusinessVoiceMail	voicemail
BusinessPager	pager
BusinessOtherPhone	
HomeMobilePhone	
URL	labeledURI