

Cisco ESA, WSA 및 SMA에 기능 키를 설치하는 방법

목차

[소개](#)

[Cisco ESA, WSA 및 SMA에 기능 키를 설치하는 방법](#)

[CLI에 기능 키 설치](#)

[GUI에 기능 키 설치](#)

[설치 성공](#)

[설치 실패](#)

소개

이 문서에서는 물리적 Cisco ESA(Email Security Appliances), WSA(Web Security Appliances) 및 SMA(Security Management Appliances)에 기능 키를 설치하는 방법에 대해 설명합니다.

Cisco ESA, WSA 및 SMA에 기능 키를 설치하는 방법

기능 키는 do-not-reply@cisco.com에서 기능 키 구매 또는 갱신의 지정된 이메일 주소로 전송됩니다. 이메일에는 구매 또는 갱신에 적용할 수 있는 기능 키가 포함된 첨부 파일이 포함되어 있습니다.

기능 키의 샘플 출력은 첨부 파일에 있습니다.

```
Serial Number : XXXXXXXXXXXX-AAAAAAAAA
```

```
Type: Sophos Anti-Virus, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-d-dddd-xxxxx-aaaaa-bbbbb-cccc-d-dddd-ffff-eeee
```

```
Type: Webroot, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-d-dddd-xxxxx-aaaaa-bbbbb-cccc-d-dddd-ffff-eeee
```

```
Type: IronPort Web Reputation Filters, apply by: <year>/<month>/<date>,
```

```
expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-d-dddd-xxxxx-aaaaa-bbbbb-cccc-d-dddd-ffff-eeee
```

CLI에 기능 키 설치

```
CLI> featurekey
```

```
Enter feature key, or press Enter to go to the main prompt.
```

```
[ ]>
```

GUI에 기능 키 설치

1. System Administration(시스템 관리)>Feature Keys(기능 키)로 이동합니다.
2. Feature Key(기능 키): 필드의 Feature Activation(기능 활성화) 섹션에 키를 붙여넣습니다.
3. 이미지에 표시된 대로 Submit Key(키 제출)를 클릭합니다.

Feature Keys

Feature Keys for Serial Number: 423F4E7150C767600ADB-2806218F46F3

Description	Status	Time Remaining
Cisco L4 Traffic Monitor	Active	317 days
Cisco HTTPS Proxy	Active	317 days
File Reputation	Active	73 days
Cisco Web Usage Controls	Active	317 days
Sophos	Active	317 days
File Analysis	Active	73 days
Webroot	Active	317 days
Cisco Web Proxy & DVS Engine	Active	317 days
Cisco AnyConnect Secure Mobility	Dormant	317 days
Cisco Web Reputation Filters	Active	317 days

Pending Activation

No feature key activations are pending.

Feature Activation

Feature Key:

설치 성공

- 라이선스 계약 페이지가 표시됩니다.계약을 검토하고 동의.
- 계약에 동의하면 기능 키가 이미지에 표시된 대로 제공된 출력과 함께 설치됩니다.

Feature Keys

Success — Feature key accepted for host

Automatically checking for additional updates.
No new feature keys are available.

설치 실패

- 오류 메시지가 생성됩니다. 이 메시지는 이미지에 표시된 대로 설치에 실패한 이유를 제공합니다.
(예:"기능 키의 형식이 잘못되었습니다." 또는 "기능 키가 호스트에서 이미 사용되었습니다.")

Feature Keys

Error — Errors have occurred. Please see below for details.

Feature Keys for Serial Number: 423F4E7150C767600ADB-280621BF46F3

Description	Status	Time Remaining	Expiration Date
Cisco L4 Traffic Monitor	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco HTTPS Proxy	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Usage Controls	Dormant	227 days	Sat Dec 10 13:59:59 2016
Sophos	Dormant	227 days	Sat Dec 10 13:59:59 2016
Webroot	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Proxy & DVS Engine	Active	227 days	Sun Dec 11 11:29:20 2016
Cisco AnyConnect Secure Mobility	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Reputation Filters	Dormant	227 days	Sat Dec 10 13:59:59 2016

Note: The Cloud Web Security authorization key (or license key) is separate from the appliance feature keys. See Network > Cloud Connector to enter the authorization key.

Pending Activation

No feature key activations are pending.

[Check for New Keys](#)

Feature Activation

Feature Key:

Feature key is malformed.

[Submit Key](#)

참고: Cisco 라이선싱 팀(licensing@cisco.com)에 문의하거나 [지원 사례](#)를 열어 추가 지원을 요청하십시오.