

RV130W의 SSID에 대한 일일 액세스 시간

목표

관리자는 특정 SSID(Service Set Identifier)에 대해 Time of Day Access(일일 액세스 시간)를 구성하여 네트워크의 보안을 강화할 수 있습니다. SSID는 무선 네트워크와 연결된 고유 식별자입니다. 관리자는 Time of Day Access를 통해 사용자가 네트워크에 액세스할 수 있는 시기와 사용자가 제한된 시기를 지정할 수 있습니다.

이 문서의 목적은 RV130W에서 SSID에 대한 Time of Day Access 설정을 구성하는 방법을 설명하는 것입니다.

적용 가능한 디바이스

·RV130W

절차 단계

1단계. 웹 구성 유틸리티에 로그인하고 무선 > 기본 설정을 선택합니다. Basic Settings 페이지가 열립니다.

The screenshot shows the 'Basic Settings' page. Under the 'Radio' section, 'Enable' is checked. 'Wireless Network Mode' is set to 'B/G/N-Mixed', 'Wireless Band Selection' is '20MHz', and 'Wireless Channel' is 'Auto'. Below this is a 'Wireless Table' with columns: Enable SSID, SSID Name, SSID Broadcast, Security Mode, MAC Filter, VLAN, Wireless Isolation with SSID, WMM, Max Associated clients, WPS, and Captive Portal (Portal Profile, Enable). The first row for 'SSIDName1' has 'Enable SSID' checked and 'Time of Day Access' button highlighted. Other rows for 'ciscosb2', 'ciscosb3', and 'ciscosb4' have 'Enable SSID' unchecked. At the bottom are 'Save' and 'Cancel' buttons.

2단계. 수정할 SSID(Service Set Identifier)의 확인란을 선택한 다음 Time of Day Access(일일 액세스 시간) 버튼을 클릭하여 SSID에 대한 Time of Day Access(일일 액세스 시간)를 구성합니다.

Basic Settings

Radio: Enable

Wireless Network Mode: B/G/N-Mixed

Wireless Band Selection: 20MHz 20/40MHz

Wireless Channel: Auto

AP Management VLAN: 1

U-APSD (WMM Power Save): Enable

Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
										Portal Profile	Enable
<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

Buttons: Edit, Edit Security Mode, Edit MAC Filtering, Time of Day Access, Edit WPS, Save, Cancel

Time of Day Access 페이지가 열립니다.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Buttons: Save, Cancel, Back

3단계. Active Time 필드에서 **Enable** 확인란을 선택하여 Time of Day Access를 활성화합니다

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Buttons: Save, Cancel, Back

4단계. Start Time 필드에서 제공된 드롭다운 목록을 사용하여 사용자가 네트워크에 액세스할 수 있게 되는 요일을 지정합니다.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Save Cancel Back

5단계. *Stop Time*(중지 시간) 필드에서 제공된 드롭다운 목록을 사용하는 사용자로 네트워크가 제한되는 요일을 지정합니다.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 05 Hours 08 Minutes PM

Stop Time: 12 Hours 0 Minutes AM

Save Cancel Back

6단계. 설정을 저장하려면 **저장**을 클릭합니다.

06		28		50	
07		29		51	
08		30		52	
09		31		53	
10		32		54	
11		33		55	
12		34		56	
13		35		57	
14		36		58	
15		37		59	
16		38		60	
17		39		61	
18		40		62	
19		41		63	
20		42		64	
21		43			
22		44			

Save Cancel Back