

Solucionar problemas de reinicialização do servidor C-Series

Contents

[Introduction](#)

[Prerequisites](#)

[Componentes Utilizados](#)

[Informações de Apoio](#)

[Reinicializações esperadas](#)

[Reinicializações inesperadas](#)

[Principais pontos](#)

[Reunir pacotes de log para análise](#)

[Saída esperada para diferentes condições de reinicialização e desligamento](#)

[Reinicialização do SO - ESXi, RHEL e Windows](#)

[Log OBFL](#)

[RHEL - /var/log/messages](#)

[Windows - Log de Eventos](#)

[Desligamento do SO - ESXi, RHEL e Windows](#)

[Log OBFL:](#)

[ESXi - /var/log/hostd.log](#)

[RHEL - /var/log/messages](#)

[Windows - Log de Eventos](#)

[Ligar do CIMC](#)

[Log OBFL:](#)

[Ciclo de energia do CIMC](#)

[Log OBFL](#)

[Desligar do CIMC](#)

[Log OBFL](#)

[Perda de energia devido a falha na PSU](#)

[Log OBFL](#)

[Botão frontal desligado](#)

[Log OBFL](#)

[Botão frontal ligado](#)

[Log OBFL](#)

[Informações Relacionadas](#)

Introduction

Este documento descreve como determinar se uma reinicialização ou desligamento foi iniciada no hardware ou no sistema operacional (SO).

Há vários bons locais de log para se concentrar quando você determina por que um servidor foi reinicializado ou desligado. Ao pesquisar no Suporte técnico do Cisco Integrated Management

Controller (CIMC), consulte os registros `/var/log/messages` ou Onboard Failure Logging (OBFL).

O exemplo de saída fornecido neste documento é de `/var/log/messages` ou OBFL, assim como registros de SO para ESXi, RHEL e Windows.

Prerequisites

Não existem requisitos específicos para este documento.

Componentes Utilizados

As informações neste documento são baseadas nestas versões de software e hardware:

- Firmware do Cisco Unified Computing System (UCS) C200-M1 versão 1.4(3w)
- Firmware Cisco UCS C210-M2 versão 1.4(3w)
- Firmware Cisco UCS C220-M3 versão 2.0(3d)
- Firmware Cisco UCS C220-M4 versão 2.0(3f)
- ESXi 5.0 U2
- RHEL 6.6
- Windows 2008 R2

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. If your network is live, make sure that you understand the potential impact of any command.

Informações de Apoio

Uma reinicialização pode ser esperada ou inesperada. Quando uma reinicialização é esperada, pode ser que nem todas as partes interessadas a esperem. É importante ter um processo de controle de alterações em vigor para qualquer tarefa de manutenção de reinicialização ou desligamento para garantir que todos estejam cientes da ação.

Reinicializações esperadas

Este é qualquer evento de reinicialização ou desligamento iniciado por uma pessoa, processo ou script intencionalmente. Isso pode ser iniciado de várias maneiras. Esses trechos de log podem ajudar a identificar qual cenário de reinicialização ocorreu, para que você possa rastrear quem ou o que tomou a ação:

- Através da GUI do CIMC
- Do SO
- Quando você pressiona o botão do painel frontal na parte frontal do servidor

Reinicializações inesperadas

Esta é qualquer reinicialização que não é planejada ou esperada, mas ainda pode ser esperada pela pessoa ou processo que iniciou a ação. Além disso, pode ter havido uma falha de hardware, como uma falha de PSU ou perda de energia no data center. Eles podem ser iniciados de várias maneiras.

Se for determinado que o botão do painel frontal foi pressionado, você poderá saber quem tinha acesso físico ao data center no momento da reinicialização. Se for um problema de energia, entre em contato com a equipe do data center para ver se houve uma falha de energia no momento.

- Através da GUI do CIMC
- Do SO
- Quando você pressiona o botão do painel frontal na parte frontal do servidor
- De falha de hardware, como falha de PSU ou cabo de alimentação defeituoso
- Falha da unidade de distribuição de energia (PDU) no data center
- Falha na fonte de alimentação ininterrupta (UPS) ou queda de energia ou queda de energia no data center

Principais pontos

- O CIMC iniciado reinicializa, desliga e liga sempre inclui a palavra-chave "do_power" nos registros.
- As teclas do painel frontal incluem "passthrough_pin2_isr" quando você executa versões mais recentes do firmware. Além disso, é provável que não haja correlação entre eventos em nível de SO a partir disso.
- As reinicializações e desligamentos iniciados pelo SO têm um evento associado no nível do SO. Observe também que "do_power" não está registrado e, em vez disso, o "High Voltage Mode" pode ser registrado.

Reunir pacotes de log para análise

Antes de revisar os registros relevantes, primeiro é necessário gerar os pacotes de log. Use estes recursos para criar os registros necessários para referência quando você comparar com os exemplos de saída neste documento:

Suporte técnico CIMC série C

[Guia visual para coletar arquivos de suporte técnico \(séries B e C\)](#)

ESXi

[base de conhecimento vmware](#)

RHEL

[O que é um relatório de eventos e como criar um no Red Hat Enterprise Linux 4.6 e posterior?](#)

Windows

[Arquivar um registro de eventos do Windows](#)

Saída esperada para diferentes condições de reinicialização e desligamento

Reinicialização do SO - ESXi, RHEL e Windows

Log OBFL

```
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[readPostData]:525:BIOS_POST_CMPLT Asserted --> BIOS has
completed
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4740 : Filename =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4740 : FName =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:129:[lpc_reset_seen]
LPC Reset Count is Different [0x77:0x78] Asserted LPC Reset Seen
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:200:[transition_function]
Starting Transition to [High Voltage Mode] from [Unknown Mode]
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:220:[transition_function]
Transition to [High Voltage Mode] Success
...
5:2017 Mar 2 09:47:01:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/DimmTempOffset
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/se_pilot2_udc_usb1_1.c:2290:
USB FS: VDD Power WAKEUP- Power Good = OFF
5:2017 Mar 2 09:47:06:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = OFF
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4756 : FName =
BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:IPMI:1497: Rack_FanCtrl.c:1183:fscUpdateActualFanPolicyFile:
Applied Policy: N/A, Configuration Status: PENDING - Host powered off
5:2017 Mar 2 09:47:06:BMC:IPMI:1466: Pilot2SrvPower.c:466:Blade Power Changed To: [ OFF ]
5:2017 Mar 2 09:47:06:BMC:selparser:1547: selparser.c:710:
# 7E 03 00 00 01 02 00 00 6A 30 B8 58 20 00 04 25 05 00 00 00 08 00 FF FF # 37e | 03/02/2017
09:47:06
| CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Absent | Asserted
...
```

```

5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = ON
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:2685:Failed USB2.0 register
test
5:2017 Mar  2 09:47:12:BMC:kernel:-:last message repeated 2 times
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4778 : Filename =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4778 : FName =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:selparser:1547: selparser.c:710:
# 7F 03 00 00 01 02 00 00 6F 30 B8 58 20 00 04 25 05 00 00 00 08 01 FF FF # 37f
| 03/02/2017 09:47:11 | CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Present | Asserted
5:2017 Mar  2 09:47:12:BMC:IPMI:1495: Pilot2SrvPower.c:466:Blade Power Changed To: [ ON ]

```

Verifique os registros do ESXi para obter mais informações sobre por que o SO iniciou esse evento.

- /var/log/vmksuSummary.log
- /var/log/vmkernel.log
- /var/log/hostd.log
- /var/log/shell.log

[KB do VMware](#)

RHEL - /var/log/messages

```

May 12 12:55:00 localhost rtkit-daemon[10450]: Demoting known real-time threads.
May 12 12:55:00 localhost rtkit-daemon[10450]: Successfully demoted thread
10987 of process 10987 (/usr/bin/pulseaudio).
May 12 12:55:00 localhost console-kit-daemon[10311]: WARNING: no sender#012
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoted 1 threads.
May 12 12:55:00 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w" May 12 12:55:00 localhost init:
Disconnected from system bus
May 12 12:55:00 localhost auditd[3587]: The audit daemon is exiting.
May 12 12:55:00 localhost kernel: type=1305 audit(1431453300.949:33):
audit_pid=0 old=3587 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditd_t:s0 res=1
May 12 12:55:01 localhost kernel: type=1305 audit(1431453301.053:34):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditctl_t:s0 res=1
May 12 12:55:01 localhost kernel: Kernel logging (proc) stopped.
May 12 12:55:01 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3617" x-info="http://www.rsyslog.com"] exiting on signal 15.
May 12 12:58:27 localhost kernel: imklog 5.8.10, log source = /proc/kmsg started.
May 12 12:58:27 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3631" x-info="http://www.rsyslog.com"] start
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpuset
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpu
May 12 12:58:27 localhost kernel: Linux version 2.6.32-504.el6.x86_64
(mockbuild@x86-023.build.eng.bos.redhat.com) (gcc version 4.4.7 20120313
(Red Hat 4.4.7-11) (GCC) ) #1 SMP Tue Sep 16 01:56:35 EDT 2014
May 12 12:58:27 localhost kernel: Command line:
ro root=/dev/mapper/VolGroup-lv_root rd_NO_LUKS LANG=en_US.UTF-8

```

```
rd_NO_MD rd_LVM_LV=VolGroup/lv_swap SYSFONT=latarcyrheb-sun16 crashkernel=auto
rd_LVM_LV=VolGroup/lv_root KEYBOARDTYPE=pc KEYTABLE=us rd_NO_DM rhgb quiet
```

Para obter mais dicas sobre como solucionar problemas de reinicializações RHEL, consulte este artigo do KB [da Red Hat](#).

Windows - Log de Eventos

Event 1074

The process **Explorer.EXE has initiated the restart** of computer WIN-5JPBKNNMRRNF on behalf of user WIN-5JPBKNNMRRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: restart
Comment: C-Series Test

Event 1074

The **process C:\Windows\system32\winlogon.exe (WIN-5JPBKNNMRRNF) has initiated the restart** of computer WIN-5JPBKNNMRRNF on behalf of user WIN-5JPBKNNMRRNF\Administrator for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: restart Comment:

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:26:32.778837300Z.

Event 12

The operating system started at system time ?2015?-?05?-?18T08:28:28.610798500Z.

Para obter mais dicas sobre os registros de eventos do Windows, consulte este [artigo da TechNet](#).

Desligamento do SO - ESXi, RHEL e Windows

Log OBFL:

```
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs
Fn:0x6 Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC
Reset ISR -> ResetState: 1
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[readPostData]:519:BIOS_POST_
CMPLT Asserted --> BIOS has completed
5:2015 May 12 18:03:38:BMC:kernel:-:<5>drivers/bmc/usb/usbl.1/se_pilot2_udc_
usb1_1.c:2288:USB FS:
VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 18:03:38:BMC:IPMI:1563: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 18:03:38:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
```

```
# 11 04 00 00 01 02 00 00 7A 40 52 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 411 | 05/12/2015 18:03:38 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 12 04 00 00 01 02 00 00 7A 40 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF # 412 |
05/12/2015 18:03:38 | CIMC | Entity presence MAIN_POWER_PRS #0xa9 | Device Absent | Asserted
```

ESXi - /var/log/hostd.log

```
2015-05-15T00:46:01.809Z [28B69B90 info 'TaskManager'] Task Created :
    haTask--vim.host.AutoStartManager.autoPowerOff-245137084
2015-05-15T00:46:01.810Z [28AE7B90 info 'TaskManager'] Task Completed :
haTask--vim.host.AutoStartManager.autoPowerOff-245137084 Status success
2015-05-15T00:46:01.814Z [28AE7B90 verbose 'Default']
CloseSession called for session id=526869fe-3f96-f54a-4bb6-41250fa3242b
2015-05-15T00:46:01.814Z [28AE7B90 info 'ha-eventmgr'] Event 107 : User dcui logged out
2015-05-15T00:46:01.822Z [28AA6B90 verbose 'Proxysvc Req00060'] New proxy client SSL
(TCP(local=127.0.0.1:0, peer=127.0.0.1:58274))
2015-05-15T00:46:01.822Z [28AA6B90 warning 'Proxysvc Req00060'] Error reading from
client while waiting for header: N7Vmacore15SystemExceptionE(Connection reset by peer)
2015-05-15T00:46:02.077Z [29441B90 verbose 'Proxysvc Req00061'] New proxy client
SSL(TCP(local=127.0.0.1:443, peer=127.0.0.1:58877))
2015-05-15T00:46:02.088Z [28AE7B90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket issued for dcui
2015-05-15T00:46:02.090Z [2930AB90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket used
Accepted password for user dcui from 127.0.0.1
2015-05-15T00:46:02.090Z [2930AB90 info 'Vimsvc'] [Auth]: User dcui
2015-05-15T00:46:02.091Z [2930AB90 info 'ha-eventmgr'] Event 108 :
User dcui@127.0.0.1 logged in
2015-05-15T00:46:02.093Z [29366B90 info 'InternalServiceInstance'] Shutting down service
2015-05-15T00:46:22.104Z [FFAB2AD0 error 'Default'] SSLStreamImpl::
BIORead (291a1000) timed out
Section for VMware ESX, pid=2882, version=5.0.0, build=build-914586, option=Release
```

RHEL - /var/log/messages

```
May 12 13:03:24 localhost init: tty (/dev/tty2) main process
(10152) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty3) main process
(10154) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty4) main process
(10156) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty5) main process
(10158) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty6) main process
(10162) killed by TERM signal
May 12 13:03:25 localhost abrttd: Got signal 15, exiting
May 12 13:03:29 localhost acpid: exiting
May 12 13:03:30 localhost NetworkManager[9732]: <info>
    caught signal 15, shutting down normally.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): taking down device.
```

```

May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> exiting (success)
May 12 13:03:31 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w"
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoting known real-time threads.
May 12 13:03:31 localhost rtkit-daemon[10367]: Successfully demoted thread 1
0365 of process 10365 (/usr/bin/pulseaudio).
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoted 1 threads.
May 12 13:03:31 localhost console-kit-daemon[10228]: WARNING: no sender#012
May 12 13:03:31 localhost init: Disconnected from system bus
May 12 13:03:31 localhost auditd[3601]: The audit daemon is exiting.
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.355:22):
audit_pid=0 old=3601 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditd_t:s0 res=1
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.459:23):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditctl_t:s0 res=1
May 12 13:03:31 localhost kernel: Kernel logging (proc) stopped.
May 12 13:03:31 localhost rsyslogd: [origin software="rsyslogd"
swVersion="5.8.10" x-pid="3631" x-info="http://www.rsyslog.com"] exiting on signal 15.

```

Windows - Log de Eventos

Event 1074

The process C:\Windows\system32\winlogon.exe (WIN-5JPBKNMMRNF) **has initiated the power off of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator** for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: power off
Comment

Event 1074

The **process Explorer.EXE has initiated the shutdown** of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: shutdown
Comment: Shut down Test

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:38:13.237425300Z.

Ligar do CIMC

Log OBFL:

```

5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 18:08:31:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0 Cmd:0x2
Data&colon; 0x1
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:345:Power Driver:
Power On Logic Pulse for 250ms @ 25164275955:2015 May 12 18:08:31:BMC:IPMI:

```



```

1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:08:31:BMC:AUDIT:20723: Server power state modify (op:power-on)
5:2015 May 12 18:08:31:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]
:2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:484:Blade
Power Changed To: [ ON ]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 18:08:31:BMC:IPMI:1566: Pilot3SrvPower.c:191:Pilot2SrvPowerOn
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:375:
Power Driver: Power On Logic Done @ 2516427846
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1406 : Filename = BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1406 : FName = BiosTech_7.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1408 : Filename = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1408 : FName = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:262:Sending
event_ipmi_power_state_change (ON) ..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:137:Sending
event_server_boot_start..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:148:
Will be able to send event_server_crash..
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 13 04 00 00 01 02 00 00 A0 41 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 413 | 05/12/2015 18:08:32 | Unknown
#0x602c | Unknown #0x1a |
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 14 04 00 00 01 02 00 00 A0 41 52 55 20 00 04 25 00 00 00 00 08 00 FF FF
# 414 | 05/12/2015 18:08:32 | CIMC | Entity presence BIOS_POST_CMPLT
#0x00 | Device Absent | Asserted
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1410 : Filename = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1410 : FName = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt

```

Ciclo de energia do CIMC

Log OBFL

```
5:2015 May 12 19:18:45:BMC:kernel:--<5>[do_cycle]:560:do_cycle
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x2
5:2015 May 12 19:18:45:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 19:18:45:BMC:kernel:--<5>[__do_power_off]:300:Power Driver:
Power Off Logic @ 2520641182
5:2015 May 12 19:18:45:BMC:IPMI:1566: Pilot3SrvPower.c:539:
Pilot2SrvPowerCycle
5:2015 May 12 19:18:45:BMC:AUDIT:20723: Server power state modify
(op:power-cycle)
5:2015 May 12 19:18:49:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 19:18:49:BMC:kernel:--<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 12 19:18:49:BMC:kernel:--<5>drivers/bmc/usb/
usb1.1/se_pilot2_udc_usb1.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 19:18:49:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 19:18:49:BMC:video_trigger:-- video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 19:18:49:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 12 19:18:49:BMC:selparser:1602: selparser.c:678:
# 1A 04 00 00 01 02 00 00 19 52 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 41a | 05/12/2015 19:18:49 | CIMC | Entity presence MAIN_POWER_PRS #0xa9
| Device Absent | Asserted
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
# 1B 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 DC 1A 00 00 00 74 03 00 00
# 41b | 05/12/2015 19:18:54 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
# 1C 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 16 16 00 00 00 0A 00 00 00
# 41c | 05/12/2015 19:18:54 | Unknown
#0x602c | Microcontroller/Coprocessor
#0x16 | Transition to Running | Asserted
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]:345:
Power Driver: Power On Logic Pulsefor 250ms @ 2520661694
5:2015 May 12 19:19:05:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 19:19:05:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:542:Pilot2SrvPowerCycle
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]
:375:Power Driver: Power On Logic Done @ 2520661945
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:481:
-> Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:242:
File Open : BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:748:
```

```
File Close : /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1466 : Filename = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1944:block_transfer_fetch_host_request_for_app :
BT_FILE_CLOSE : HostBTDescr = 1466 : FName = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:selparser:1602: selparser.c:678:
# 1D 04 00 00 01 02 00 00 29 52 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 41d | 05/12/2015 19:19:05 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:19:06:BMC:video_trigger:--: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 12 19:19:06:BMC:video_trigger:--: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 12 19:19:06:BMC:video_trigger:--: video_trigger.c:148:
Will be able to send event_server_crash ..
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1468 : Filename = BiosTech_6.txt
```

Desligar do CIMC

Log OBFL

```
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x0
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:300:Power Driver:
Power Off Logic@ 2524221543
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 20:18:25:BMC:AUDIT:20723: Server power state modify (op:power-off)
5:2015 May 12 20:18:30:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 20:18:30:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 12 20:18:30:BMC:kernel:--<5>drivers/bmc/usb/usbl1.1/se_pilot2_udc_
usbl_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 20:18:30:BMC:IPMI:1567: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 20:18:30:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 12 20:18:30:BMC:selparser:1602: selparser.c:678:
# 24 04 00 00 01 02 00 00 16 60 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 424 | 05/12/2015 20:18:30 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:2015 May 12 20:18:30:BMC:video_trigger:--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 20:18:31:BMC:vkcs_mux:1582: vkcs_mux.c:76:[REQ] 00 01
5:2015 May 12 20:18:36:BMC:IPMI:1566: Pilot3SrvPower.c:348:Pilot2SrvPowerOff
5:2015 May 12 20:18:37:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:37:BMC:blade-power:11311: host-power.c:53:POWER Off
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:511:Run-update Process Starting.
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:44:Setting FP Button Lock: current state 0
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1373:Front Panel Power Button is now permanently locked.
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1378:Front Panel Reset Button is now permanently locked.
```

Perda de energia devido a falha na PSU

Log OBFL

```
5:2015 May 15 14:29:12:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:29:12:BMC:kernel:--<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 15 14:29:12:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:29:12:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 15 14:29:12:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:29:12:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 33 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 27 00 00 00 03 00 FF FF
# 433 | 05/15/2015 14:29:12 | CIMC | Power supply PSU1_AC_OK
#0x27 | State Deasserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 34 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 42 00 00 00 04 01 FF FF
# 434 | 05/15/2015 14:29:12 | CIMC | Power supply PMBUS_ALERT #0x42
| Predictive Failure asserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 35 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 435 | 05/15/2015 14:29:12 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:1970 Jan 1 00:02:48:BMC:kernel:--<5>Linux version 2.6.35.10
(buildsa@savbu-swbmc-vb1) (gcc version 3.4.5)
#2 Tue Nov 18 07:09:13 PST 2014 Unversioned directory
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: ARM926EJ-S [41069265]
revision 5 (ARMv5TEJ), cr=00053177
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: VIVT data cache, VIVT instruction cache
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Machine: ServerEngines PILOT3 Hornet Board
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Memory policy: ECC disabled, Data cache writeback
```

Botão frontal desligado

Log OBFL

```
5:2015 May 15 14:50:19:BMC:kernel:--<5>[passthrough_pin2_isr]:158:x86
Host Power Button Press
5:2015 May 15 14:50:19:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:50:19:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:
USB HS: VDD Power = ON
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1478:audit from:kcs Fn:0x6
Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1484:audit Resp:0x0
5:2015 May 15 14:50:35:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:50:35:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 15 14:50:35:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:50:35:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:50:35:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:50:35:BMC:IPMI:1531: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
```

```
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A2 04 00 00 01 02 00 00 BB 07 56 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 4a2 | 05/15/2015 14:50:35 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A3 04 00 00 01 02 00 00 BB 07 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 4a3 | 05/15/2015 14:50:35 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
```

Botão frontal ligado

Log OBFL

```
5:2015 May 15 14:51:18:BMC:kernel:--<5>[passthrough_pin2_isr]
:158:x86 Host Power Button Press
5:2015 May 15 14:51:18:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/se_pilot2
_udc_usbl.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:51:18:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:51:19:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/se_pilot2_
_udc_usbl.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 0
5:2015 May 15 14:51:19:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCoff[0]
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 118 : Filename = BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 119 : Filename = BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 120 : Filename = BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 121 : Filename = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 121 : FName = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:video_trigger:--: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 15 14:51:19:BMC:video_trigger:--: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 15 14:51:19:BMC:video_trigger:--: video_trigger.c:148
:Will be able to send event_server_crash ..
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
```

```
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:  
HostDescriptor = 123 : Filename = BiosTech_3.txt  
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_3.txt  
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]  
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :  
HostBTDescr = 123 : FName = BiosTech_3.txt  
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:  
File Close : /var/nuova/BIOS/BiosTech_3.txt
```

Informações Relacionadas

- [Solução de problemas de reinicialização C-Series](#)
- [Suporte Técnico e Documentação - Cisco Systems](#)