

Acesso por hora do dia para um SSID no RV130W

Objetivo

Os administradores podem aumentar a segurança de uma rede configurando o Acesso por Hora do Dia para um SSID (Service Set Identifier) específico. Um SSID é o identificador exclusivo associado a uma rede sem fio. O acesso por horário permite que um administrador especifique quando os usuários podem acessar a rede e quando os usuários são restritos.

O objetivo deste documento é explicar como configurar as definições de Acesso por Hora do Dia para um SSID no RV130W.

Dispositivos aplicáveis

RV130W

Etapas do procedimento

Etapa 1. Faça login no utilitário de configuração da Web e escolha **Wireless > Basic Settings**. A página *Configurações básicas* é aberta:

The screenshot shows the 'Basic Settings' page for wireless configuration. It includes several configuration options and a table for SSID settings.

Configuration options:

- Radio: Enable
- Wireless Network Mode: B/G/N-Mixed
- Wireless Band Selection: 20MHz 20/40MHz
- Wireless Channel: Auto
- AP Management VLAN: 1
- U-APSD (WMM Power Save): Enable

Wireless Table												
<input type="checkbox"/>	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

Buttons below the table: Edit, Edit Security Mode, Edit MAC Filtering, Time of Day Access, Edit WPS.

Buttons at the bottom: Save, Cancel.

Etapa 2. Marque a caixa de seleção do SSID (Service Set Identifier, Identificador do conjunto de serviços) que deseja editar e clique no botão **Time of Day Access** para configurar o *Time of Day Access* para um SSID.

Basic Settings

Radio: Enable

Wireless Network Mode: B/G/N-Mixed

Wireless Band Selection: 20MHz 20/40MHz

Wireless Channel: Auto

AP Management VLAN: 1

U-APSD (WMM Power Save): Enable

Wireless Table												
<input type="checkbox"/>	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

Buttons: Edit, Edit Security Mode, Edit MAC Filtering, Time of Day Access, Edit WPS

Buttons: Save, Cancel

A página *Acesso no Horário do Dia* é aberta:

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Buttons: Save, Cancel, Back

Etapa 3. No campo *Tempo de atividade*, marque a caixa de seleção **Habilitar** para habilitar o Acesso por horário.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Buttons: Save, Cancel, Back

Etapa 4. No campo *Hora de início*, especifique a hora durante o dia em que a rede se torna acessível aos usuários com as listas suspensas fornecidas.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Save Cancel Back

Etapa 5. No campo *Hora de parada*, especifique a hora durante o dia em que a rede se torna restrita aos usuários com as listas suspensas fornecidas.

Time of Day Access

Add / Edit Access Point Configuration

Active Time: Enable

Start Time: 05 Hours 08 Minutes PM

Stop Time: 12 Hours 0 Minutes AM

Save Cancel Back

Etapa 6. Clique em **Salvar** para salvar suas configurações.

06		28		50	
07		29		51	
08		30		52	
09		31		53	
10		32		54	
11		33		55	
12		34		56	
13		35		57	
14		36		58	
15		37		59	
16		38		60	
17		39		61	
18		40		62	
19		41		63	
20		42		64	
21		43			
22		44			

Save Cancel Back