

跨多個ESA共用許可證

目錄

[簡介](#)

[跨多個ESA共用許可證](#)

簡介

本文描述如何在多個思科電子郵件安全裝置(ESA)之間成功共用現有許可證。

跨多個ESA共用許可證

使用購買的許可證產品啟用金鑰(PAK)，可以在多個ESA之間共用許可證。

在[產品授權註冊](#)入口中，完成以下步驟：

1. 在門戶中，按一下**Licenses > Move Licenses**
2. 在下拉選單中，選擇**Share licenses... > Get activation code...**
3. 在「共用許可證流程」彈出視窗中，對於「產品」，請選擇**Iron Port Product - SW捆綁包**
4. 在Source Serial Number / Virtual Device Identifier欄位中，輸入源序列號 **提示**：您只需輸入完整序列號的結尾。例如，如果完整序列號為888869E737F5-33NPP11，請輸入33NPP11。
5. 在Target Serial Number / Virtual Device Identifier欄位中，輸入目標序列號 **提示**：您只需輸入完整序列號的結尾。例如，如果完整序列號為999969E748G65-44MQQ22，請輸入44MQQ22。
6. 在「傳送至」欄位中輸入有效的電子郵件地址
7. 按一下**請求代碼**

成功完成後，將向輸入的電子郵件地址傳送電子郵件。在電子郵件中有用於訪問和驗證的超連結。最多可能需要一個小時才能收到許可證註冊電子郵件。

以下是將會接收的電子郵件範例：

```
From: "do-not-reply@cisco.com" <do-not-reply@cisco.com>
Date: Tuesday, October 31, 2017 at 12:59 PM
To: Joe User <joe_user@example.com>
Subject: Device Registration
```

PLEASE DO NOT DISCARD THIS EMAIL.

You have received this email because your email address was provided to Cisco Systems during the registration process and you are requesting to copy the shared licenses from an existing device to new device. Please contact Cisco Systems if you are not requesting to copy the shared licenses during device registration process.

Below, you will find the Activation Code:

Activation Code : LUY3012Z

Here is the device registration information:

Existing Device Serial # : 33NPP11

New Device Serial # : 44MQQ22

Please click the below link and follow the instructions given below to continue the registration process:

<https://slexui.cloudapps.cisco.com/SWIFT/LicensingUI/Quickstart>

- 1) Click on Other Licenses drop down and Select 'Share License Process' option.
- 2) Select 'Use Activation code' option and Enter the above activation code in 'Specify Activation Code' tab and click on Next button to register the activation code.

然後，您將再次訪問產品許可證註冊門戶。

1. 按一下**Licenses > Move Licenses**
2. 在下拉選單中，選擇**Share licenses... > Use activation code...**
3. 輸入電子郵件中提供的啟用碼，然後點選下一步
4. 確認啟用代碼、源串列和目標串列，然後按一下下一步
5. 完成審閱即可完成

然後，在裝置GUI中選擇**System Administration > Feature Keys > Check for New Keys**，以檢查金鑰和啟用。或者，在CLI中輸入**featurekey**和**checknow**。對於ESA的新增任何/所有功能，需要閱讀並接受終端使用者許可協定(EULA)才能啟用該功能。

如果許可證共用有任何問題，您需要直接聯絡全球許可證運營(GLO)、開啟支援案例或閱讀常見問題解答：

- 免費電話：1-800-553-2447或思科全球**聯絡人**
- 電子郵件:licensing@cisco.com
- **思科支援個案管理器：開啟思科支援問題單**
- **思科全球許可運營(GLO):常見問題**