

如何在Cisco ESA、WSA和SMA上安裝功能金鑰？

目錄

[簡介](#)

[如何在Cisco ESA、WSA和SMA上安裝功能金鑰？](#)

[在CLI上安裝功能金鑰](#)

[在GUI上安裝功能金鑰](#)

[成功安裝](#)

[安裝失敗](#)

簡介

本檔案介紹如何在實體思科電子郵件安全設備(ESA)、網路安全裝置(WSA)和安全管理裝置(SMA)上安裝功能金鑰的過程。

如何在Cisco ESA、WSA和SMA上安裝功能金鑰？

功能金鑰從do-not-reply@cisco.com傳送到功能金鑰購買或續訂的指定電子郵件地址。該電子郵件包含一個附件，其中包含適用於購買或續訂的功能金鑰。

功能鍵的輸出示例在附件中：

```
Serial Number : XXXXXXXXXXXX-AAAAAAAAA
```

```
Type: Sophos Anti-Virus, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-dddd-xxxx-aaaaa-bbbbb-cccc-dddd-ffff-eeee
```

```
Type: Webroot, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-dddd-xxxx-aaaaa-bbbbb-cccc-dddd-ffff-eeee
```

```
Type: IronPort Web Reputation Filters, apply by: <year>/<month>/<date> ,
```

```
expires: <year>/<month>/<date>
```

```
Key : xxxxx-aaaaa-bbbbb-cccc-dddd-xxxx-aaaaa-bbbbb-cccc-dddd-ffff-eeee
```

在CLI上安裝功能金鑰

```
CLI> featurekey
```

```
Enter feature key, or press Enter to go to the main prompt.
```

```
[ ]>
```

在GUI上安裝功能金鑰

1. 導覽至System Administration> Feature Keys。
2. 在Feature Key:欄位中貼上Feature Activation部分中的Key。
3. 按一下「Submit Key」，如下圖所示。

Feature Keys

Feature Keys for Serial Number: 423F4E7150C767600ADB-2806218F46F3

Description	Status	Time Remaining
Cisco L4 Traffic Monitor	Active	317 days
Cisco HTTPS Proxy	Active	317 days
File Reputation	Active	73 days
Cisco Web Usage Controls	Active	317 days
Sophos	Active	317 days
File Analysis	Active	73 days
Webroot	Active	317 days
Cisco Web Proxy & DVS Engine	Active	317 days
Cisco AnyConnect Secure Mobility	Dormant	317 days
Cisco Web Reputation Filters	Active	317 days

Pending Activation

No feature key activations are pending.

Feature Activation

Feature Key:

成功安裝

- 系統將顯示License Agreement頁面。檢查協定並接受。
- 接受協定後，系統會使用提供的輸出安裝功能金鑰，如下圖所示。

Feature Keys

Success — Feature key accepted for host

Automatically checking for additional updates.
No new feature keys are available.

安裝失敗

- 生成錯誤消息。該消息提供安裝失敗的原因，如下圖所示。
(示例：「功能金鑰格式不正確」或「功能金鑰已在主機上使用」)

Feature Keys

Error — Errors have occurred. Please see below for details.

Feature Keys for Serial Number: 423F4E7150C767600ADB-280621BF46F3

Description	Status	Time Remaining	Expiration Date
Cisco L4 Traffic Monitor	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco HTTPS Proxy	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Usage Controls	Dormant	227 days	Sat Dec 10 13:59:59 2016
Sophos	Dormant	227 days	Sat Dec 10 13:59:59 2016
Webroot	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Proxy & DVS Engine	Active	227 days	Sun Dec 11 11:29:20 2016
Cisco AnyConnect Secure Mobility	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Reputation Filters	Dormant	227 days	Sat Dec 10 13:59:59 2016

Note: The Cloud Web Security authorization key (or license key) is separate from the appliance feature keys. See Network > Cloud Connector to enter the authorization key.

Pending Activation

No feature key activations are pending.

Check for New Keys

Feature Activation

Feature Key:

xxxx-aaaaa-bbbbb-ccccc-xxxx-ffff-nnnnnn-mmmmm-qqqqqq-ddddd

Feature key is malformed.

Submit Key

附註：建議通過licensing@cisco.com與思科許可團隊聯絡，或開啟支援案例以獲得進一步幫助。